# R6511Q • R6500/13

R6500 Microcomputer System



# R6511Q One-Chip Microprocessor and R6500/13 One-Chip Microcomputer

# SECTION 1 INTRODUCTION

## **1.1 FEATURES**

- Enhanced 6502 CPU
  - -Four new bit manipulation instructions
    - Set Memory Bit (SMB)
    - Reset Memory Bit (RMB)
    - Branch on Bit Set (BBS)
    - Branch on Bit Reset (BBR)
  - Decimal and binary arithmetic modes
  - —13 addressing modes
  - —True indexing
- 256-byte mask-programmable ROM or no ROM\*
- 192-byte static RAM
- 32 bidirectional, TTL-compatible I/O lines (four ports)
- One 8-bit port may be tri-stated under software control
- One 8-bit port may have latched inputs under software control
- Two 16-bit programmable counter/timers, with latches --Pulse width measurement
  - -Asymmetrical pulse generation
  - Pulse generation
  - Interval timer
  - -Event counter
  - -Retriggerable interval timer
- Serial port
  - -Full-duplex asynchronous operation mode
  - -Selectable 5- to 8-bit characters
  - -Wake-up feature
  - -Synchronous shift register mode
  - Standard programmable bit rates programmable
  - up to 62.5K bits/sec @ 1 MHz
- Ten interrupts
  - —Four edge-sensitive lines; two positive, two negative —Reset
  - ---Non-maskable
  - --- Two counter underflows
  - -Serial data received
  - -Serial data transmitted
- Bus expandable to 64K bytes of external memory \*R6511Q has no ROM.

- Flexible clock circuitry
  - -2-MHz or 1-MHz internal operation
  - ---Internal clock with external XTAL at two or four times internal frequency
- -External clock input divided by one, two or four
- 1µs minimum instruction execution time @ 2 MHz
- NMOS-3 silicon gate, depletion load technology
- Single +5V power supply
- 12 mW stand-by power for 32 bytes of the 192-byte RAM
- 64-pin QUIP

#### NOTE

This document uses the term R6500/13 to describe both parts. See section 1.3 for a description of the options available when using the R6500/13 and the fixed features of the R6511Q.

## 1.2 SUMMARY

The Rockwell R6500/13 is a complete, high-performance 8-bit NMOS-3 microcomputer on a single chip and is compatible with all members of the R6500 family.

The R6500/13 consists of an enhanced 6502 CPU, an internal clock oscillator, an optional 256 bytes of Read-Only Memory, 192 bytes of Random Access Memory (RAM) and versatile interface circuitry. The interface circuitry includes two 16-bit programmable timer/counters, 32 bidirectional input/output lines (including four edge-sensitive lines and input latching on one 8-bit port), a full-duplex serial I/O channel, ten interrupts and bus expandability.

The innovative architecture and the demonstrated high performance of the R6502 CPU, as well as instruction simplicity, results in system cost-effectiveness and a wide range of computational power. These features make the R6500/13 a leading candidate for microcomputer applications.

The R6511Q contains all the features of the R6500/13 except it has no ROM and is thus intended as a high feature microprocessor with full 65K address bus.

To allow prototype circuit development, Rockwell offers a PROM-compatible 64-pin extended microprocessor device. This device, the R6511Q, provides all R6500/11 interface lines, plus the address bus, data bus and control lines to interface with external memory. The R6511Q also can be used to emulate the R6500/13. With the addition of external circuits it can also emulate the R6500/12.

Rockwell supports development of the R6500/13 with the Low Cost Emulator (LCE) Development System and the R6500/\* Family of Personality Modules. Complete in-circuit emulation with the R6500/\* Family of Personality Modules allows total system test and evaluation.

This product description assumes that the reader is familiar with the R6502 CPU hardware and programming capabilities. A detailed description of the R6502 CPU hardware is included in the R6500 Microcomputer System Hardware Manual (Document Number 29650N31). A description of the instruction capabilities of the R6502 CPU is contained in the R6500 Microcomputer System Programming Manual (Document Number 29650N30).

### **1.3 CUSTOMER OPTIONS**

The R6500/13 microcomputer is available with the following customer specified mask options.

- Option 1 Crystal or RC oscillator
- Option 2 Clock divide by 2 or 4
- Option 3 Clock MASTER Mode or SLAVE Mode
- Option 4 with or without a 256 byte ROM
- Option 5 Reset Vector at FFFC or 7FFF
- Option 6 Port A with or without internal pull-up resistors
- Option 7 Port B with or without internal pull-up resistors
- Option 8 Port C with or without internal pull-up resistors

All options should be specified on an R6500/13 order form.

The R6511Q has no customer specified mask options. It has the following characteristics.

- Crystal Oscillator
- Clock Divide by 2
- Clock MASTER Mode
- Without ROM
- Reset Vector at FFFC
- No internal pull-up resistors on any Port (PA, PB, or PC)



Figure 2-1. Mechanical Outline & Pin Out Configuration

# SECTION 2 INTERFACE REQUIREMENTS

This section describes the interface requirements for the R6511Q and R6500/13. Figure 2-1 and 2-2 show the Interface Diagram and the pin out configuration for both devices. Table 2-1 describes the function of each pin. Figure 3-1 has a detailed block diagram of the R6500/13 ports which illustrates the internal function of the device.

Table	2-1.	R6500/13	Pin	Description
Iavie	2-1.	10300/13	F 101	Description

XTLO -			
			1
	CLOCK OSCILLATOR	EDGE DETECT	
		[	0 8 PAO-PA7 (PAO, PA1,
	INTERRUPT	PORT A	PACPA7 (PAU, PAI, PA2, PA3: EDGE DETECTS)
V <sub>CC</sub>	Louio	L	Ebde Derecta)
v <sub>ss</sub>			BO-PB7 (LATCHED INPUTS)
33	CPU	PORT B	DS (PA0) (DATA STROBE)'
<b>d</b> 2		·	08 PC0-PC7/(A13, A14
	192 · 8 RAM	PORT C	(Full address mode)
080-D87 (18C)			
12, A15 (14)	BUS CONTROL	PORT D	D0-PD7/ (DATA/ADDR BUS (A4-A11))
SYNC	BUS CONTROL	PORTO	
R/W 🖛		16 BIT	
	CONTROL REGISTERS	COUNTER/LATCH	
			CB (PA5)
	16 BIT COUNTER/LATCH	SERIAL RECEIVE,	SO (PA6)*
	B	TRANSMIT REGISTERS	SI (PA7)
	R6511Q	R6500/13	

Figure 2-2. Interface Diagram

Vss11 <t< th=""><th colspan="8">Table 2-1. R6500/13 Pin Descriptions</th></t<>	Table 2-1. R6500/13 Pin Descriptions							
Vna43Separate power pin for RAM In the event that Vcc power is off, this power retains RAM data.Vss44Signal and power ground (O Crystal or clock input for in ternal clock oscillator. Als allows input of X1 clock sig nal if XTL0 is connected to Vss, or X2 or X4 clock if XTL0 is floated.XTLO41Crystal output from internat clock oscillator.RES6The Reset input is used to initialize the device. This sig nal must not transition from low to high for at least eigt cycles after Vcc reaches op erating range and the inter- nal secillator has stabilizedØ245Clock signal output at inter- nal frequency.NMI23A negative going edge on th Non-Maskable interrupt sig nal requests that a non maskable interrupt sig nal requests that a non maskable interrupt seg en- erated with the CPU.PA0-PA739-32Four 8-bit ports used fo eration with the cPU.PA0-PA739-32Four 8-bit ports used fo eration with the cPU.PA0-PD752-64.of an active transistor to Vs and an optional passive puli up to vcc. In the abbreviate or multiplexed modes of op eration Port C has an active puli-up transistors.A0-A12, A1520-7Fourteen address ines used to address space. The full clock cycle whenever the CPU is per forming an OP CODE fetch Controls the direction of data transfer between the CPU and the external 65K ad dress space. The signal id high when reading and low	Signal Name	Pin No.	Description					
Vna43Separate power pin for RAM In the event that Vcc power is off, this power retains RAM data.Vss44Signal and power ground (O Crystal or clock input for in ternal clock oscillator. Als allows input of X1 clock sig nal if XTL0 is connected to Vss, or X2 or X4 clock if XTL0 is floated.XTLO41Crystal output from internat clock oscillator.RES6The Reset input is used to initialize the device. This sig nal must not transition from low to high for at least eigt cycles after Vcc reaches op erating range and the inter- nal secillator has stabilizedØ245Clock signal output at inter- nal frequency.NMI23A negative going edge on th Non-Maskable interrupt sig nal requests that a non maskable interrupt sig nal requests that a non maskable interrupt seg en- erated with the CPU.PA0-PA739-32Four 8-bit ports used fo eration with the cPU.PA0-PA739-32Four 8-bit ports used fo eration with the cPU.PA0-PD752-64.of an active transistor to Vs and an optional passive puli up to vcc. In the abbreviate or multiplexed modes of op eration Port C has an active puli-up transistors.A0-A12, A1520-7Fourteen address ines used to address space. The full clock cycle whenever the CPU is per forming an OP CODE fetch Controls the direction of data transfer between the CPU and the external 65K ad dress space. The signal id high when reading and low	V <sub>cc</sub>	21	Main power supply +5V					
Vss44Signal and power retains RAM data.XTLI42Signal and power ground (0) Crystal or clock input for in ternal clock oscillator. Als allows input of X1 clock sig nal if XTLO is connected t Vss. or X2 or X4 clock if XTLG is floated.XTLO41Crystal output from interma clock oscillator.RES6The Reset input is used th initialize the device. This sig nal must not transition from low to high for at least eig cycles after Vcc reaches op erating range and the inter- nal oscillator has stabilizedØ245Clock signal output at inter- nal oscillator has stabilized interrupt be gen erated with the CPU.PA0-PA739-32Four 8-bit ports used fo either input/output. Each lind of an active transistor to Vs and an optional passive pull up to Vcc. In the abbreviated or multiplexed modes of op eration Port C has an active pull-up transistors. Port 0 functions as either an 8-bi input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Foureen address lines used to functions as either an 8-bi input or 8-bit output port. I has active pull-up and pull down transistors.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external address space. Note: A13 & A14 are source through PC6 & PC7 WeahSYNC22SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch controls the direction of data transfer between the CPL and the external 65K ad dress space. The signal ide high when reading and low		43	Separate power pin for RAM.					
Vss44Signal and power ground (0X Crystal or clock input for in ternal clock oscillator. Als allows input of X1 clock sig nal if XTLO is connected th Vss. or X2 or X4 clock if XTLO is floated.XTLO41Crystal output from interna clock oscillator.RES6The Reset input is used to initialize the device. This sig nal must not transition from low to high for at least eigf cycles after Vcc reaches op erating range and the inter- nal oscillator has stabilizedØ245Clock signal output at inter- nal oscillator has stabilizedØ245Clock signal output at inter- nal requests that a non maskable interrupt be gen- erated with the CPU.PA0-PA739-32Four 8-bit ports used fo either input/output. Each lim of PB0-PB7PB0-PB731-24of an active transistor to Vs- and an optional passive puli up to Vcc In the abbreviate or multiplexed modes of op eration Port C has an activi pull-up transistor.A0-A12, A1520-7Fourteen address lines used to input or 8-bit output port. I has active pull-up and pull down transistors.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external address mode.SYNC22SYNC is a positive going sign nal for the full clock cycle whenever the CPU is per forming an OF CODE fetch controls the direction of data transfer between the CPL and the external 65K ad dress space. The signal id high when reading and low			In the event that Vcc power					
Vss44Signal and power ground (0VXTLI42Crystal or clock input for in ternal clock oscillator. Als allows input of X1 clock sig nal if XTLO is connected to Vss. or X2 or X4 clock if XTL0 is floated.XTLO41Crystal output from interna clock oscillator.RES6The Reset input is used to initialize the device. This sig nal must not transition from low to high for at least eigf cycles after Vcc reaches op erating range and the inter- nal socillator has stabilized per atting range and the inter- nal requests that a non maskable interrupt sig nal requests that a non of Pors A, B and C consist of an active transistor. Port D functions as either an 8-bi input or 8-bit output port. I has active pull-up and pull down transistor. Port D functions as either an 8-bi input or 8-bit output port. I has active pull-up and pull down transistor.A0-A12, A1520-7Fourteen address space Note: A13 & A14 are source through PC6 & PC7 when in the Full Address Mode.DB0-DB753-46								
XTLI42Crystal or clock input for ir ternal clock oscillator. Als allows input of X1 clock sig nal if XTLO is connected to Vss. or X2 or X4 clock if XTLO is floated.XTLO41Crystal output from interna clock oscillator.RES6The Reset input is used to initialize the device. This sig nal must not transition from low to high for at least eigt cycles after V <sub>cc</sub> reaches op erating range and the inter- nal oscillator has stabilizedØ245Clock signal output at inter- nal oscillator has stabilized core stabilizedØ245Clock signal output at inter- nal frequency.NMI23A negative going edge on th Nor-Maskable interrupt be gen- erated with the CPU.PA0-PA7 PB0-PB739-32Four 8-bit ports used fo of Ports A, B and C consisti of an active transistor to V_s and an optional passive pull- up transistor. Port C functions as either an 8-bi input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourfeen address lines used to address a complete 65K external address space hote: A13 & A14 are source to ransmit data to and for mexternal memory SYNC22B0-DB753-46Eight bidirectional data bus lines used to transmit data to and for the full clock cycle whenever the CPU is per forming an OF CODE fetch controls the direction of data transfer between the CPU and the external 65K ad dress space. The signal id high when reading and low	v							
XTLO41ternal clock oscillator. Als allows input of X1 clock sig nal if XTLO is connected th Vs., or X2 or X4 clock if XTLO is floated.RES6The Reset input is used th initialize the device. This sig nal must not transition from low to high for at least eigh cycles after Vcc reaches op erating range and the inter- nal oscillator has stabilized Clock signal output at inter- nal oscillator has stabilized Clock signal output at inter- nal frequency.MMI23A negative going edge on th Non-Maskable Interrupt be gen- erated with the CPU.PA0-PA7 PB0-PB739-32Four 8-bit ports used fo of Ports A, B and C consist of an active transistor to Vs and an optional passive pull up to Vcc. In the abbreviated or multiplexed modes of op eration Port C has an active pull-up transistors. Port C functions as either an 8-bi input or 8-bit output port.A0-A12, A1520-7Fourteen address lines used to input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-77Fourteen address lines used to input or 8-bit output port. I has active pull-up and pull down transistors.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external address space. Note: A13 & A14 are sourced through PC6 & PC7 when it mermal memory SYNC22SYNC22R/W40A0-A12, A15Cortors the direction of data transfer between the CPU and the external 65K ad dress space. The signal id high when reading and low								
XTLO41allows input of X1 clock sig nal if XTLO is connected th Vs.s. or X2 or X4 clock if XTLO is floated.RES6The Reset input is used to initialize the device. This sig nal must not transition for low to high for at least eigf cycles after Vcc reaches op erating range and the inter nal oscillator.Ø245Clock signal output at inter nal oscillator has stabilizedØ245Clock signal output at inter nal requency.NMI23A negative going edge on th Non-Maskable interrupt be gen erated with the CPU.PA0-PA739-32Four 8-bit ports used fo either input/output. Each lim of PB0-PB7PB0-PB731-24either input/output. Each lim optional passive pull up to Vcc. In the abbreviate or multiplexed modes of op eration Port C has an active pull-up transistor.A0-A12, A1520-7Fourteen address lines used to address a complet 65K external address space hote: A13 & A14 are sourced through PC6 & PC Or when it the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external address space through PC6 & PC Or when it and for mexternal memory SYNC22R/W40Controls the direction of data transfer between the CPU and the external 65K ad dress space. The signal id high when reading and low		42						
XTLO41Vss. or X2 or X4 clock if XTLG is floated.RES61Crystal output from interna clock oscillator.RES6The Reset input is used th initialize the device. This sig nal must not transition from low to high for at least eight cycles after V <sub>cc</sub> reaches op erating range and the inter- nal oscillator has stabilizedØ245Clock signal output at inter- nal frequency.NMI23A negative going edge on th Non-Maskable interrupt be gen erated with the CPU.PA0-PA739-32Four 8-bit ports used fo of PB0-PB7PB0-PB731-24either input/output. Each line of an active transistor to Vs and an optional passive pull up to V <sub>cc</sub> . In the abbreviate or multiplexed modes of op eration Port C has an active pull-up transistor. Port C functions as either an 8-bi input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address lines used to transmit data to and from external address space Note: A13 & A14 are source to rough PC6 & PC7 when in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external address Mode.DB0-DB7SYNC22SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch or the space. The signal is high when reading and low			allows input of X1 clock sig-					
XTLO41is floated. Crystal output from internat clock oscillator.RES6The Reset input is used to initialize the device. This signal must not transition for low to high for at least eigh cycles after V <sub>cc</sub> reaches op erating range and the inter nal oscillator has stabilized (clock signal output at inter nal frequency.NMI23A negative going edge on th Non-Maskable interrupt be gen erated with the CPU.PA0-PA739-32Four 8-bit ports used fo of PB0-PB7PB0-PB731-24either input/output. Each line of an active transistor to Vs and an optional passive pull up to Vcc. In the abbreviate or multiplexed modes of op eration Port C has an active pull-up transistor. Port L functions as either an 8-bi input or 8-bit output port.A0-A12, A1520-7Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are sourced through PC6 & PC Or yhen it merong SYNC22SYNC22SYNC is a positive going signal nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch contols the direction of data transfer between the CPU and the external 65K add dress space. The signal is high when reading and low			nal if XTLO is connected to					
XTLO41Crystal output from internat clock oscillator.RES6The Reset input is used th initialize the device. This sig nal must not transition from low to high for at least eight cycles after V <sub>cc</sub> reaches op erating range and the inter- nal oscillator has stabilized (ycles after V <sub>cc</sub> reaches op erating range and the inter- nal socillator has stabilized tock signal output at inter- nal requeets that a non- maskable interrupt sig nal requests that a non- maskable interrupt be gen- erated with the CPU.PA0-PA739-32PB0-PB731-24PB0-PD762-64, 1-5PD0-PD762-64, 1-5and an optional passive pull up to V <sub>cc</sub> . In the abbreviate or multiplexed modes of op eration Port C has an active pull-up transistor. Port D functions as either an 8-bi input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address ines used to address a complete 65K external address space Note: A13 & A14 are sourced through PC6 & PC7 when in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external memory SYNC22SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch or forming an OP CODE fetch or forming an OP coDE fetch or forming and OF comparison and the external 65K ad dress space. The signal is high when reading and low								
RES6Clock oscillator.RES6The Reset input is used th initialize the device. This sig nal must not transition from low to high for at least eiglicycles after Vice reaches op erating range and the inter nal oscillator has stabilized (yce reaches op erating range and the inter nal oscillator has stabilized to clock signal output at inter nal frequency.NMI23A negative going edge on th Non-Maskable interrupt be gen erated with the CPU.PA0-PA739-32Four 8-bit ports used fo either input/output. Each line of Para A, B and C consist of an active transistor. To Vg and an optional passive pull up to Vice. In the abbreviate or multiplexed modes of op eration Port C has an active pull-up transistor. Port D functions as either an 8-bit input or 8-bit output part 1 has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are source through PC6 & PC7 when in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external memory SYNC22SYNC22R/W40Controls the direction of data transfer between the CPU and the external 65K ad dress space. The signal is high when reading and low								
RES6The Reset input is used to initialize the device. This signal mal must not transition from low to high for at least eigh cycles after V <sub>cc</sub> reaches op erating range and the inter- nal oscillator has stabilized cycles after V <sub>cc</sub> reaches op erating range and the inter- nal oscillator has stabilized nal requests that a non- maskable interrupt be gen erated with the CPU.PA0-PA739-32 PB0-PB739-32 sinal requests that a non- maskable interrupt be gen erated with the CPU.PA0-PA739-32 PB0-PB754-61 of Ports A, B and C consist of an active transistor to V_s and an optional passive pull up to V <sub>cc</sub> . In the abbreviated or multiplexed modes of op eration Port C has an active pull-up transistor. Port 0 functions as either an 9-bit input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address lines used to address space though PC6 & PC7 when in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external address space through PC6 & PC0 When in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external memory SYNCSYNC22SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch controls the direction of data transfer between the CPL and the external 65K ad dress space. The signal in high when reading and low	XILO	41						
\$\psi2\$initialize the device. This signal must not transition for low to high for at least eigit cycles after V_c_ reaches op erating range and the inter nal oscillator has stabilized Clock signal output at inter nal requercy.NMI23A negative going edge on th Non-Maskable interrupt signal requests that a non maskable interrupt be gen erated with the CPU.PA0-PA739-32Four 8-bit ports used fo either input/output. Each lim of PB0-PB7PB0-PB731-24Four 8-bit ports used fo either input/output. Each lim of Ports A, B and C consist and an optional passive pull up to V_cc. In the abbreviate or multiplexed modes of op eration Port C has an active pull-up transistor. Port I functions as either an 8-bi input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address lines used to address a complete 65K external address space hote: A13 & A14 are sourced through PC6 & PC7 when it the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external memory SYNCSYNC22SYNC is a positive going signal ran for the full clock cycle whenever the CPU is per forming an OP CODE fetch Controls the direction of data transfer between the CPL and the external 65K ad dress space. The signal is high when reading and low	BES	6						
Ø2Anal must not transition from low to high for at least eight cycles after V <sub>CC</sub> reaches op erating range and the inter nal oscillator has stabilized Clock signal output at inter nal frequency.NMI23A negative going edge on the Non-Maskable Interrupt sig nal requests that a non maskable interrupt be gen erated with the CPU.PA0-PA739-32Four 8-bit ports used fo of P07 S4-61PC0-PC754-61of Ports A, B and C consist of an active transistor to Vs and an optional passive pull up to V <sub>CC</sub> . In the abbreviate or multiplexed modes of op eration Port C has an active pull-up transistors.A0-A12, A1520-7Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are source through PC6 & PC7 Wen in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and for the full clock cycle whenever the CPU is positive going sig nal for the full clock cycle whenever the CPU is positive going sign al for the full clock cycle whenever the CPU is positive going sign al for the full clock cycle whenever the CPU is positive going sign al for the full clock cycle whenever the CPU is positive going sign al for the full clock cycle whenever the CPU is positive going sign al for the full clock cycle whenever the CPU is positive going sign al for the full clock cycle and the external 65K ad dress space. The signal is high when reading and low	1120	Ŭ						
Ø245cycles after V <sub>cc</sub> reaches op erating range and the inter nal oscillator has stabilized clock signal output at inter nal frequency.NMI23A negative going edge on the Non-Maskable interrupt be gen erated with the CPU.PA0-PA739-32PB0-PB731-24PC0-PC754-61PD0-PD762-64, 1-51-5and an optional passive pull up to V <sub>cc</sub> . In the abbreviate or multiplexed modes of op eration Port C has an active pull-up transistor. Port C functions as either an application of an active pull-up and pull down transistors.A0-A12, A1520-7DB0-DB753-46DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external address Mode.DB0-DB753-46VW40KWW40Controls the direction of data transfer between the CPU and the external address space (controls the direction of data transfer between the CPU and the external address for proming an OP CODE fetch controls the direction of data transfer between the CPU and the external address for proming an OP code fetch controls the direction of data transfer between the CPU and the external address for proming an OF code fetch controls the direction of data transfer between the CPU and the external address for proming an OF code fetch controls the direction of data transfer between the CPU and the external address for proming an OF code fetch controls the direction of data transfer between the CPU and the external address proming an OF code fetch controls the direction of data transfer between the CPU and the external address proming and			nal must not transition from					
Ø245erating range and the internal oscillator has stabilized (Clock signal output at inter- nal frequency.NMI23A negative going edge on the Non-Maskable interrupt signal erated with the CPU.PA0-PA739-32Four 8-bit ports used for erated with the CPU.PA0-PD752-64.of an active transistor to Vs and an optional passive pull up to Vcc. In the abbreviated or multiplexed modes of op eration Port C has an active pull-up transistor. Port I functions as either an 8-bit input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are sourced through PC6 & PC7 when it memoryDB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external memory SYNCSYNC22SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch Controls the direction of data transfer between the CPL and the external 65K ad dress space. The signal is high when reading and low			low to high for at least eight					
Ø2All oscillator has stabilized Cicck signal output at inter nal frequency.NMI23A negative going edge on the Non-Maskable Interrupt sig nal requests that a non maskable interrupt be gen erated with the CPU.PA0-PA739-32Four 8-bit ports used for either input/output. Each lim of Ports A, B and C consist PD0-PD7PA0-PD752-64. 52-64. 1-5for active transistor to Vs and an optional passive pull up to Vcc. In the abbreviate or multiplexed modes of op eration Port C has an active pull-up transistor. Port C functions as either an 8-bit input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are sourced time SPNCDB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external memory SYNCSYNC22SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch and the external 65K ad dress space. The signal is high when reading and low			cycles after V <sub>cc</sub> reaches op-					
\$\verline{\\verline{\verline{\verline{\\verlin{\\verline{\\verline{\\verline{\\verline{\\verline{\\verline{\\verline{\\verline{\\verline{\\verline{\\\verline{								
NMI23nal frequency. A negative going edge on th Non-Maskable Interrupt sig nal requests that a non maskable interrupt be gen erated with the CPU.PA0-PA739-32Four 8-bit ports used to erated with the CPU.PB0-PB731-32Four 8-bit ports used to of Ports A, B and C consist of an active transistor to Vs and an optional passive pull up to Vcc. In the abbreviated or multiplexed modes of op eration Port C has an active pull-up transistor. Port D functions as either an 8-bi input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address lines used to address space Note: A13 & A14 are sourced through PC6 & PC7 When i the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external address ging is nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch Controls the direction of data transfer between the CPU and the external 65K ad dress space. The signal is high when reading and low	da	45						
NMI23A negative going edge on the Non-Maskable Interrupt sig nal requests that a non maskable interrupt be gen erated with the CPU.PA0-PA739-32Four 8-bit ports used for either input/output. Each lim of Ports A, B and C consist of an active transistor to Vs and an optional passive pull up to Vcc. In the abbreviated or multiplexed modes of op eration Port C has an active pull-up transistors.A0-A12, A1520-7Foureen address lines used to address a complete 65K external address space Note: A13 & A14 are sourced through PC6 & PC7 when in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and for the full clock cycle whenever the CPU is positive going sig nal for the full clock cycle whenever the CPU is positive going sig nal for the full clock cycle whenever the CPU is positive going sig nal for the full clock cycle and the external 65K address space. The signal is high when reading and low	ΨZ	40						
PA0-PA739-32Non-Maskable Interrupt sig nal requests that a non maskable interrupt be gen erated with the CPU.PB0-PB731-24Four 8-bit ports used for either input/output. Each lim of Ports A, B and C consist ports and an optional passive pull up to V <sub>cc</sub> . In the abbreviate or multiplexed modes of op eration Port C has an active pull-up transistor. Port C functions as either an 8-bit input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are sourced through PC6 & PC7 when in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and form external memory SYNCSYNC22SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch and the external 65K add dress space. The signal is high when reading and low	NMI	23						
PA0-PA739-32 Four 8-bit ports used for erated with the CPU.PB0-PB731-32 Four 8-bit ports used for either input/output. Each line of an active transistor to Vs and an optional passive pull up to Vcc. In the abbreviated or multiplexed modes of op eration Port C has an active pull-up transistor. Port I functions as either an 8-bi input or 8-bit output port.A0-A12, A1520-7B0-DB753-46DB0-DB753-46EB0-DB753-46EB0-DB753-46EIG0-DB753-46EIG0-DB753-46FVW40A0-A12, A1520-77Fourteen address space trough PC6 & PC7 when it and from external address space to ransmit data to and from external memory SYNCSYNC22SYNC24A0-A19, A1040A0-A19, A11A0-A12, A1553-46B0-DB753-46B0			Non-Maskable Interrupt sig-					
PA0-PA739-32erated with the CPU.PB0-PB731-32Four 8-bit ports used for either input/output. Each lim of Ports A, B and C consist of an active transistor to Vs and an optional passive pull up to Vcc. In the abbreviated or multiplexed modes of op eration Port C has an active pull-up transistor. Port D functions as either an 8-bit input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are sourced through PC6 & PC7 when in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and for the full clock cycle whenever the CPU is positive going sig nal for the full clock cycle whenever the CPU is positive going sig nal for the direction of data transfer between the CPU and the external 65K add dress space. The signal is high when reading and low			nal requests that a non-					
PA0-PA7 PB0-PB739-32 31-24Four 8-bit ports used for either input/output. Each lim of Ports A, B and C consist of an active transistor to Vg and an optional passive pull up to Vcc In the abbreviate or multiplexed modes of op eration Port C has an active pull-up transistor. Port D functions as either an 8-bi input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are source through PC6 & PC7 when in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and for the full clock cycle whenever the CPU is per forming an OP CODE fetch Controls the direction of data transfer between the CPU and the external aSK ad dress space. The signal is high when reading and low								
PB0-PB7 PC0-PC731-24 54-61 62-64, 1-5either input/output. Each line of Ports A, B and C consist of an active transistor to Vs and an optional passive pull up to Vcc. In the abbreviated or multiplexed modes of op eration Port C has an active pull-up transistor. Port C functions as either an 8-bi input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address lines used to address pace Note: A13 & A14 are sourced the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external memory SYNCSYNC22SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch Controls the direction of data transfer between the CPU and the external aSK and dress space. The signal is high when reading and low	<b>D1</b> 0 <b>D1</b> 7		1					
PC0-PC754-61of Ports A, B and C consist: of an active transistor to Vg and an optional passive pull up to Vgc. In the abbreviated or multiplexed modes of op eration Port C has an active pull-up transistor. Port C functions as either an 8-bi input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are sourced through PC6 & PC7 when in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and form external memory SYNCSYNC22SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch address space. The signal is high when reading and low								
PD0-PD762-64, 1-5of an active transistor to Vs and an optional passive pull up to Vcc In the abbreviated or multiplexed modes of op eration Port C has an active pull-up transistor. Port D functions as either an 8-bi input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are source through PC6 & PC7 when in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and form external memory SYNCSYNC22SYNC is a positive going sig nal for the full clock cycle whenever the CPU is positive going sig nal for the direction of data transfer between the CPU and the external 65K ad dress space. The signal is high when reading and low								
1-5and an optional passive pull up to V <sub>cc</sub> . In the abbreviate or multiplexed modes of op eration Port C has an active pull-up transistor. Port I functions as either an 8-bi input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are sourced through PC6 & PC7 when in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external memory SYNCSYNC22SYNC22R/W40Controls the direction of data transfer between the CPU and the external 65K ad dress space. The signal is high when reading and low			of an active transistor to V <sub>ss</sub>					
A0-A12, A1520-7B0-DB753-46Firw40Controls the functions are static or and the external address space through PC6 & PC7 when it the space of the difference of difference of difference through PC6 & PC7 when it the Full Address Mode.B0-DB753-46Eight bidirectional data bus ins used to transmit data to and form external memory forming an OP CODE fetch dress space. The Signal is high when reading and lowR/W40A0-A12, A1520-7Fourteen address to address a complete 65K external address space through PC6 & PC7 when it the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external memory forming an OP CODE fetch forming an OP CODE fetch and the external 65K ad dress space. The signal is high when reading and low		1-5	and an optional passive pull-					
Provide R/W20-7For the second seco			up to V <sub>cc</sub> . In the abbreviated					
A0-A12, A1520-7Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are sourced through PC6 & PC7 when in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external memory SYNCSYNC22SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch drass space. The signal is high when reading and low								
A0-A12, A1520-7Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are sourced through PC6 & PC7 when in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and form external memory SYNCSYNC22SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch and the external 65K ad dress space. The signal is high when reading and low								
A0-A12, A1520-7input or 8-bit output port. I has active pull-up and pull down transistors.A0-A12, A1520-7Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are sourced through PC6 & PC7 when in the Full Address Mode.DB0-DB753-46Eight bidirectional data bus lines used to transmit data to and from external memory SYNCSYNC22SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch and the external 65K ad dress space. The Signal is high when reading and low								
A0-A12, A15     20-7     Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are sourced through PC6 & PC7 when the Full Address Mode.       DB0-DB7     53-46     Eight bidirectional data bus lines used to transmit data to and from external memory SYNC       SYNC     22     SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch Controls the direction of data transfer between the CPU and the external 65K ad dress space. The signal is high when reading and low			input or 8-bit output port. It					
A0-A12, A15     20-7     Fourteen address lines used to address a complete 65K external address space Note: A13 & A14 are sourced through PC6 & PC7 when in the Full Address Mode.       DB0-DB7     53-46     Eight bidirectional data bus lines used to transmit data to and from external memory SYNC       SYNC     22     SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch and the external 65K ad dress space. The signal is high when reading and low			has active pull-up and pull-					
toaddressa complete65K external addressspaceNote: A13 & A14 are sourcedthrough PC6 & PC7 when inthe Full Address Mode.DB0-DB753-46Eight bidirectional data buslines used to transmit data to and from external memorySYNC22SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch forms between the CPU and the external 65K ad dress space. The Signal is high when reading and low								
BB0-DB7     53-46     53-46       DB0-DB7     53-46     Eight bidirectional data bus lines used to transmit data to and from external memory SYNC       22     SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch forming the direction of data transfer between the CPU and the external 65K ad dress space. The signal is high when reading and low	A0-A12, A15	20-7						
Note: A13 & A14 are sourced through PC6 & PC7 when in the Full Address Mode.       DB0-DB7     53-46       Eight bidirectional data bus lines used to transmit data to and from external memory SYNC       22     SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch Controls the direction of data transfer between the CPL and the external 65K ad dress space. The signal is high when reading and low								
DB0-DB7       53-46       Eight bidirectional data bus lines used to transmit data ta and from external memory SYNC         SYNC       22       SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch forming an OP CODE fetch and the external 65K ad dress space. The signal is high when reading and low								
DB0-DB7     53-46     Eight bidirectional data bus lines used to transmit data to and from external memory SYNC       SYNC     22     SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch Controls the direction of data transfer between the CPL and the external 65K ad dress space. The signal is high when reading and low			through PC6 & PC7 when in					
SYNC       22       SYNC is a positive going signation of the full clock cycle whenever the CPU is per forming an OP CODE fetch forming an OP CODE fetch and the external 65K ad dress space. The signal is high when reading and low			1					
SYNC     22     and from external memory SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch Controls the direction of data transfer between the CPU and the external 65K ad dress space. The signal is high when reading and low	DB0-DB7	53-46	Eight bidirectional data bus					
SYNC     22     SYNC is a positive going sig nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch       R/W     40     Controls the direction of data transfer between the CPU and the external 65K ad dress space. The signal is high when reading and low								
<ul> <li>nal for the full clock cycle whenever the CPU is per forming an OP CODE fetch Controls the direction of data transfer between the CPL and the external 65K ad dress space. The signal is high when reading and low</li> </ul>	SVNC	22						
R/W 40 Controls the direction of data transfer between the CPU is per forming an OP CODE fetch Controls the direction of data transfer between the CPU and the external 65K ad dress space. The signal is high when reading and low	SHIC	22						
F/W 40 forming an OP CODE fetch Controls the direction of data transfer between the CPU and the external 65K ad dress space. The signal is high when reading and low			whenever the CPU is per-					
transfer between the CPU and the external 65K ad- dress space. The signal is high when reading and low			forming an OP CODE fetch.					
and the external 65K ad dress space. The signal is high when reading and low	R/W	40	Controls the direction of data					
dress space. The signal is high when reading and low			transfer between the CPU					
high when reading and low								

# SECTION 3 SYSTEM ARCHITECTURE

This section provides a functional description of the R6500/ 13. Functionally the R6500/13 consists of a CPU, both RAM and optional ROM memories, four 8-bit parallel I/O ports, a serial I/O port, dual counter/latch circuits, a mode control register, and an interrupt flag/enable dual register circuit. A block diagram of the system is shown in Figure 3-1.

#### NOTE

Throughout this document, unless specified otherwise, all memory or register address locations are specified in hexadecimal notation.

### 3.1 CPU LOGIC

The R6500/13 internal CPU is a standard 6502 configuration with an 8-bit Accumulator register, two 8-bit Index Registers (X and Y); an 8-bit Stack Pointer register, an ALU, a 16-bit Program Counter, and standard instruction register/decode and internal timing control logic.

#### 3.1.1 Accumulator

The accumulator is a general purpose 8-bit register that stores the results of most arithmetic and logic operations. In addition, the accumulator usually contains one of the two data words used in these operations.

#### 3.1.2 Index Registers

There are two 8-bit index registers, X and Y. Each index register can be used as a base to modify the address data program counter and thus obtain a new address—the sum of the program counter contents and the index register contents.

When executing an instruction which specifies indirect addressing, the CPU fetches the op code and the address and modifies the address from memory by adding the index register to it prior to loading or storing the value of memory.

Indexing greatly simplifies many types of programs, especially those using data tables.

#### 3.1.3 Stack Pointer

The Stack Pointer is an 8-bit register. It is automatically incremented and decremented under control of the microprocessor to perform stack manipulation in response to either user instructions, an internal  $\overline{IRQ}$  interrupt, or the external interrupt line  $\overline{NMI}$ . The Stack Pointer must be initialized by the user program.

The stack allows simple implementation of multiple level interrupts, subroutine nesting and simplification of many types of data manipulation. The JSR, BRK, RTI and RTS instructions use the stack and Stack Pointer.

The stack can be envisioned as a deck of cards which may be accessed only from the top. The address of a memory location is stored (or "pushed") onto the stack. Each time data are to be pushed onto the stack, the Stack Pointer is placed on the Address Bus, data are written into the memory location addressed by the Stack Pointer, and the Stack Pointer is decremented by 1. Each time data are read (or "pulled") from the stack, the Stack Pointer is incremented by 1. The Stack Pointer is then placed on the Address Bus and data are read from the memory location addressed by the Pointer.

The stack is located on zero page, i.e., memory locations 00FF-0040. After reset, which leaves the Stack Pointer indeterminate, normal usage calls for its initialization at 00FF.

#### 3.1.4 Arithmetic And Logic Unit (ALU)

All arithmetic and logic operations take place in the ALU, including incrementing and decrementing internal registers (except the Program Counter). The ALU cannot store data for more than one cycle. If data are placed on the inputs to the ALU at the beginning of a cycle, the result is always gated into one of the storage registers or to external memory during the next cycle.

Each bit of the ALU has two inputs. These inputs can be tied to various internal buses or to a logic zero; the ALU then generates the function (AND, OR, SUM, and so on) using the data on the two inputs.

## 3.1.5 Program Counter

The 16-bit Program Counter provides the addresses that are used to step the processor through sequential instructions in a program. Each time the processor fetches an instruction from program memory, the lower (least significant) byte of the Program Counter (PCL) is placed on the low-order bits of the Address Bus and the higher (most significant) byte of the Program Counter (PCH) is placed on the high-order 8 bits of the Address Bus. The Counter is incremented each time an instruction or data is fetched from program memory.

## 3.1.6 Instruction Register and Instruction Decode

Instructions are fetched from ROM or RAM and gated onto the Internal Data Bus. These instructions are latched into the Instruction Register, then decoded along with timing and interrupt signals to generate control signals for the various registers.

#### 3.1.7 Timing Control

The Timing Control Logic keeps track of the specific instruction cycle being executed. This logic is set to T0 each time an instruction fetch is executed and is advanced at the beginning of each Phase One clock pulse for as many cycles as are required to complete the instruction. Each data transfer which takes place between the registers is caused by decoding the contents of both the instruction register and timing control unit.





#### 3.1.8 Interrupt Logic

Interrupt logic controls the sequencing of three interrupts; RES, NMI and IRQ. IRQ is generated by any one of eight conditions: 2 Counter Overflows, 2 Positive Edge Detects, 2 Negative Edge Detects, and 2 Serial Port Conditions.

### 3.2 NEW INSTRUCTIONS

In addition to the standard R6502 instruction set, four new bit manipulation instructions have been added to the R6500/ 13. The added instructions and their format are explained in the following paragraphs. Refer to Appendix A for the Op Code mnemonic addressing matrix for these added instructions. The four added instructions do not impact the CPU processor status register.

#### 3.2.1 Set Memory Bit (SMB m, Addr.)

This instruction sets to "1" one of the 8-bit data field specified by the zero page address (memory or I/O port). The first byte of the instruction specifies the SMB operation and one of eight bits to be set. The second byte of the instruction designates address (0-255) of the byte to be operated upon.

#### 3.2.2 Reset Memory Bit (RMB m, Addr.)

This instruction is the same operation and format as SMB instruction except a reset to "0" of the bit results.

# 3.2.3 Branch On Bit Set Relative (BBS m, Addr, DEST)

This instruction tests one of eight bits designated by a 3-bit immediate field within the first byte of the instruction. The second byte is used to designate the address of the byte to be tested within the zero page address range (memory or I/O ports). The third byte of the instruction is used to specify the 8-bit relative address to which the instruction branches if the bit tested is a "1". If the bit tested is not set, the next sequential instruction is executed.

# 3.2.4 Branch On Bit Reset Relative (BBR m, Addr, DEST)

This instruction is the same operation and format as the BBS instruction except that a branch takes place if the bit tested is a "0".

### 3.3 READ-ONLY-MEMORY (ROM)

The optional ROM consists of 256 bytes mask programmable memory with an address space from 7F00 to 7FFF. ROM locations FFFA to FFFF are assigned for interrupt vectors. The reset vector can be optionally at 7FFE or FFFC.

The R6511Q has no ROM and its Reset vector is at FFFC.

### 3.4 RANDOM ACCESS MEMORY (RAM)

The RAM consists of 192 bytes of read/write memory with an assigned page zero address of 0040 through 00FF. The R6500/13 provides a separate power pin (V<sub>RR</sub>) which may be used for standby power for 32 bytes located at 0040-005F. In the event of the loss of V<sub>cc</sub> power, the lowest 32 bytes of RAM data will be retained if standby power is supplied to the V<sub>RR</sub> pin. If the RAM data retention is not required then V<sub>RR</sub> must be connected to V<sub>cc</sub>. During operation V<sub>RR</sub> must be at the V<sub>cc</sub> level.

For the RAM to retain data upon loss of V<sub>cc</sub>, V<sub>RR</sub> must be supplied within operating range and RES must be driven low at least eight Ø2 clock pulses before V<sub>cc</sub> falls out of operating range. RES must then be held low while V<sub>cc</sub> is out of operating range and until at least eight Ø2 clock cycles after V<sub>cc</sub> is again within operating range and the internal Ø2 oscillator is stabilized. V<sub>RR</sub> must remain within V<sub>cc</sub> operating range during normal operation. When V<sub>cc</sub> is out of operating range, V<sub>RR</sub> must remain within the V<sub>RR</sub> retention range in order to retain data. Figure 3.2 shows typical waveforms.





### 3.5 CLOCK OSCILLATOR

The R6511Q has been configured for a crystal oscillator, a divide by 2 countdown network, and for Master Mode Operation.

Three customer selectable mask options are available for controlling the R6500/13 timing. The R6500/13 can be ordered with a *crystal* oscillator, a *divide by 2 or divide by 4* countdown network and for *clock master mode or clock slave mode* operation.

For 2MHz interval operation the divide-by-2 options must be specified.

The on-chip oscillator is designed for a parallel resonant crystal connected between XTLI and XTLO pins. The equivalent oscillator circuit is shown in Figure 3-3.

A parallel resonant crystal is specified by its load capacitance and series resonant resistance. For proper oscillator operation, the load capacitance ( $C_L$ ), series resistance ( $R_s$ ) and the crystal resonant frequency (F) must meet the following two relations:

$$(C + 27) = 2C_L$$
 or  $C = 2C_L - 27 \text{ pF}$   
 $R_s \le R_{smax} = \frac{2 \times 10^6}{(FC_s)^2}$ 

where: F is in MHz; C and C<sub>L</sub> are in pF; R is in ohms.

To select a parallel resonant crystal for the oscillator, first select the load capacitance from a Crystal Manufacturer's catalog. Next, calculate  $R_{smax}$  based on F and  $C_L$ . The selected crystal must have a  $R_s$  less than the  $R_{smax}$ .



Figure 3-3. Clock Oscillator Input Options

For example, if  $C_{\text{L}}$  = 22 pF for a 4 MHz parallel resonant crystal, then

$$C = (2 \times 22) - 27 = 17 \text{ pF}$$
  
(use standard value of 18 pF)

The series resistance of the crystal must be less than

$$R_{smax} = \frac{2 \times 10^6}{(4 \times 22)^2} = 258 \text{ ohms}$$

Internal timing can also be controlled by driving the XTLI pin with an external frequency source. Figure 3-3b shows typical connections. If XTLO is left floating, the external source is divided by the internal countdown network. However, if XTLO is tied to V<sub>ss</sub>, the internal countdown network is bypassed causing the chip to operate at the frequency of the external source.

The operation described above assumed a CLOCK MASTER MODE mask option. In this mode a frequence source (crystal or external source) must be applied to the XTLI and XTLO pins.

Ø2 is a buffered output signal which closely approximates the interal timing. When a common external source is used to drive multiple devices the internal timing between devices as well as their Ø2 outputs will be skewed in time. If skewing represents a system problem it can be avoided by the Master/Slave connection and options shown in Figure 3-4.

One R6500/13 is operated in the CLOCK MASTER MODE and a second in the CLOCK SLAVE MODE. Mask options in the SLAVE unit convert to Ø2 signal into a clock input pin which is tightly coupled to the internal timing generator. As a result the internal timing of the MASTER and SLAVE units are synchronized with minimum skew. If the Ø2 signal to the SLAVE unit is inverted, the MASTER and SLAVE UNITS WILL OPER-ATE OUT OF PHASE. This approach allows the two devices to share external memory using cycle stealing techniques.



Figure 3-4. Master/Slave Connections

## 3.6 MODE CONTROL REGISTER (MCR)

The Mode Control Register contains control bits for the multifunction I/O ports and mode select bits for Counter A and Counter B. Its setting, along with the setting of the Serial Communications Control Register (SCCR), determines the basic configuration of the R6500/13 in any application. Initializing this register is one of the first actions of any software program. The Mode Control Register bit assignment is shown in Figure 3-5.



Figure 3-5. Mode Control Register

The use of Counter A Mode Select is shown in Section 6.1.

The use of Counter B Mode Select is shown in Section 6.2.

The use of Port B Latch Enable is shown in Section 4.4.

The use of Port D in Tri-State Enable is shown in Section 4.6.

The use of Bus Mode Select is shown in Section 4.5 and 4.6.

## 3.7 INTERRUPT FLAG REGISTER (IFR) AND INTERRUPT ENABLE REGISTER (IER)

An IRQ interrupt request can be initiated by any or all of eight possible sources. These sources are all capable of being enabled or disabled by the use of the appropriate interrupt enabled bits in the Interrupt Enable Register (IER). Multiple simultaneous interrupts cause the IRQ interrupt request to remain active until all interrupting conditions have been serviced and cleared.

The Interrupt Flag Register contains the information that indicates which I/O or counter needs attention. The contents of the Interrupt Flag Register may be examined at any time by reading at address: 0011. Edge detect IFR bits may be cleared by executing a RMB instruction at address location 0010. The RMB X, (0010) instruction reads FF, modifies bit X to a "0", and writes the modified value at address location 0011. In this way IFR bits set to a "1" after the read cycle of a Read-Modify-Write instruction (such as RMB) are protected from being cleared. A logic "1" is ignored when writing to edge detect IFR bits.

Each IFR bit has a corresponding bit in the Interrupt Enable Register which can be set to a "1" by writing a "1" in the respective bit position at location 0012. Individual IER bits may be cleared by writing a "0" in the respective bit position, or by RES. If set to a "1", an IRQ will be generated when the corresponding IFR bit becomes true. The Interrupt Flag Register and Interrupt Enable Register bit assignments are shown in Figure 3-6 and the functions of each bit are explained in Table 3-1.





Figure 3-6. Interrupt Enable and Flag Registers

Table 3-1.	Interrupt	Flag	Register	Bit Codes
------------	-----------	------	----------	-----------

Bit Code	Function
IFR 0:	PA0 Positive Edge Detect Flag—Set to a "1" when a positive going edge is detected on PA0. Cleared by RMB O (0010) instruction or by RES.
IFR 1:	PA1 Positive Edge Detect Flag—Set to a 1 when a positive going edge is detected on PA1. Cleared by RMB 1 (0010) instruction or by RES.
IFR 2:	PA2 Negative Edge Detect Flag—Set to a 1 when a negative going edge is detected on PA2. Cleared by RMB 2 (0010) instruction or by RES.
IFR 3:	PA3 Negative Edge Detect Flag—Set to 1 when a negative going edge is detected on PA3. Cleared by RMB 3 (0010) instruction or by RES.
IFR 4:	Counter A Underflow Flag—Set to a 1 when Counter A underflow occurs. Cleared by reading the Lower Counter A at location 0018, by writing to address location 001A, or by RES.
IFR 5:	Counter B Underflow Flag—Set to a 1 when Counter B underflow occurs. Cleared by reading the Lower Counter B at location 001C, by writing to address location 001E, or by RES.
IFR 6:	Receiver Interrupt Flag—Set to a 1 when any of the Serial Communication Status Register bits 0 through 3 is set to a 1. Cleared when the Receiver Status bits (SCSR 0-3) are cleared or by RES.
IFR 7:	Transmitter Interrupt Flag—Set to a 1 when SCSR 6 is set to a 1 while SCSR 5 is a 0 or SCSR 7 is set to a 1. Cleared when the Transmitter Status bits (SCSR 6 & 7) are cleared or by RES.

### 3.8 PROCESSOR STATUS REGISTER

The 8-bit Processor Status Register, shown in Figure 3-7, contains seven status flags. Some of these flags are controlled by the user program; others may be controlled both by the user's program and the CPU. The R6502 instruction set contains a number of conditional branch instructions which are designed to allow testing of these flags. Each of the eight processor status flags is described in the following sections.

#### 3.8.1 Carry Bit (C)

The Carry Bit (C) can be considered as the ninth bit of an arithmetic operation. It is set to logic 1 if a carry from the eighth bit has occurred or cleared to logic 0 if no carry occurred as the result of arithmetic operations.

The Carry Bit may be set or cleared under program control by use of the Set Carry (SEC) or Clear Carry (CLC) instruction, respectively. Other operations which affect the Carry Bit are ADC, ASL, CMP, CPX, CPY, LSR, PLP, ROL, ROR, RTI, and SBC.

#### 3.8.2 Zero Bit (Z)

The Zero Bit (Z) is set to logic 1 by the CPU during any data movement or calculation which sets all 8 bits of the result to

zero. This bit is cleared to logic 0 when the resultant 8 bits of a data movement or calculation operation are not all zero. The R6500 instruction set contains no instruction to specifically set or clear the Zero Bit. The Zero Bit is, however, affected by the following instructions; ADC, AND, ASL, BIT, CMP, CPX, CPY, DEC, DEX, DEY, EOR, INC, INX, INY, LDA, LDX, LDY, LSR, ORA, PLA, PLP, ROL, ROR, RTI, SBC, TAX, TAY, TXA, TSX, and TYA.

#### 3.8.3 Interrupt Disable Bit (I)

The Interrupt Disable Bit (I) is used to control the servicing of an interrupt request ( $\overline{IRQ}$ ). If the I Bit is reset to logic 0, the  $\overline{IRQ}$  signal will be serviced. If the bit is set to logic 1, the  $\overline{IRQ}$  signal will be ignored. The CPU will set the Interrupt Disable Bit to logic 1 if a RESET ( $\overline{RES}$ ),  $\overline{IRQ}$ , or Non-Maskable Interrupt ( $\overline{NM}$ ) signal is detected.

The I bit is cleared by the Clear Interrupt Mask Instruction (CLI) and is set by the Set Interrupt Mask Instruction (SEI). This bit is set by the BRK Instruction. The Return from Interrupt (RTI) and Pull Processor Status (PLP) instructions will also affect the I bit.



Figure 3-7. Processor Status Register

#### 3.8.4 Decimal Mode Bit (D)

The Decimal Mode Bit (D) is used to control the arithmetic mode of the CPU. When this bit is set to logic 1, the adder operates as a decimal adder. When this bit is cleared to logic 0, the adder operates as a straight binary adder. The adder mode is controlled only by the programmer. The Set Decimal Mode (SED) instruction will set the D bit; the Clear Decimal Mode (CLD) instruction clears it. The PLP and RTI instructions also affect the Decimal Mode Bit.

#### CAUTION

The Decimal Mode Bit will either set or clear in an unpredictable manner upon power application. This bit must be initialized to the desired state by the user program or erroneous results may occur.

#### 3.8.5 Break Bit (B)

The Break Bit (B) is used to determine the condition which caused the  $\overline{IRQ}$  service routine to be entered. If the  $\overline{IRQ}$  service routine was entered because the CPU executed a BRK command, the Break Bit will be set to logic 1. If the  $\overline{IRQ}$  routine was entered as the result of an  $\overline{IRQ}$  signal being generated, the B bit will be cleared to logic 0. There are no instructions which can set or clear this bit.

#### 3.8.6 Overflow Bit (V)

The Overflow Bit (V) is used to indicate that the result of a signed, binary addition, or subtraction, operation is a value that cannot be contained in seven bits ( $-128 \le n \le 127$ ).

This indicator only has meaning when signed arithmetic (sign and seven magnitude bits) is performed. When the ADC or SBC instruction is performed, the Overflow Bit is set to logic 1 if the polarity of the sign bit (bit 7) is changed because the result exceeds +127 or -128; otherwise the bit is cleared to logic 0. The V bit may also be cleared by the programmer using a Clear Overflow (CLV) instruction.

The Overflow Bit may also be used with the BIT instruction. The BIT instruction—which may be used to sample interface devices—allows the overflow flag to reflect the condition of bit 6 in the sampled field. During a BIT instruction the Overflow Bit is set equal to the content of the bit 6 on the data *tested with BIT instruction. When used in this mode, the* overflow has nothing to do with signed arithmetic, but is just another sense bit for the microprocessor. Instructions affecting the V flag are ADC, BIT, CLV, PLP, RTI and SBC.

#### 3.8.7 Negative Bit (N)

The Negative Bit (N) is used to indicate that the sign bit (bit 7) in the resulting value of a data movement or data arithmetic operation is set to logic 1. If the sign bit is set to logic 1, the resulting value of the data movement or arithmetic operation is negative; if the sign bit is cleared, the result of the data movement or arithmetic operation is positive. There are no instructions that set or clear the Negative Bit since the Negative Bit represents only the status of a result. The instructions that effect the state of the Negative Bit are: ADC, AND, ASL, BIT, CMP, CPX, CPY, DEC, DEX, DEY, CPA, ROR, RTI, SBC, TAX, TAY, TSX, TXA, and TYA.

# SECTION 4 PARALLEL INPUT/OUTPUT PORTS & BUS MODES

The devices have 32 I/O lines grouped into four 8-bit ports (PA, PB, PC, and PD). Ports A through C may be used either for input or output individually or in groups of any combination. Port D may be used as all inputs or all outputs.

Multifunction I/O's such as Port A and Port C are protected from normal port I/O instructions when they are programmed to perform a multiplexed function.

Internal pull-up resistors (FET's with an impedance range of  $3K \le R_{\rm L} \le 12K$  ohm) are optional on all port pins except Port D (R6500/13 only).

The direction of the 32 I/O lines are controlled by four 8-bit port registers located in page zero. This arrangement provides quick programming access using simple two-byte zero page address instructions. There are no direction registers associated with the I/O ports, thus simplifying I/O handling. The I/O addresses are shown in Table 4-1. Appendix E.6 shows the I/O Port Timing.

#### Table 4-1. I/O Port Addresses

Port	Address
A	0000
В	0001
С	0002
D	0003

### 4.1 INPUTS

Inputs for Ports A, B, and C are enabled by loading logic 1 into all I/O port register bit positions that are to correspond to I/O input lines. A low (<0.8V) input signal will cause a logic 0 to be read when a read instruction is issued to the port register. A high (>2.0V) input will cause a logic 1 to be read. An RES signal forces all I/O port registers to logic 1 thus initially treating all I/O lines as inputs.

Port D may only be all inputs or all outputs. All inputs is selected by setting bit 5 of the Mode Control Register (MCR5) to a "0".

The status of the input lines can be interrogated at any time by reading the I/O port addresses. Note that this will return the actual status of the input lines, not the data written into the I/O port registers.

Read/Modify/Write instructions can be used to modify the operation of PA, PB, PC, & PD. During the Read cycle of a Read/Modify/Write instruction the Port I/O register is read. For all other read instructions the port input lines are read. Read/Modify/Write instructions are: ASL, DEC, INC, LSR, RMB, ROL, ROR, and SMB.

### 4.2 OUTPUTS

Outputs for Ports A thru D are controlled by writing the desired I/O line output states into the corresponding I/O port register bit positions. A logic 1 will force a high (>2.4V) output while a logic 0 will force a low (<0.4V) output.

Port D all outputs is selected by setting MCR5 to a "1".

#### 4.3 Port A (PA)

Port A can be programmed via the Mode Control Register (MCR) and the Serial Communications Control Register (SCCR) as a standard parallel 8-bit, bit independent, I/O port or as serial channel I/O lines, counter I/O lines, or an input data strobe for the Port B input latch option. Table 4-2 tabulates the control and usage of Port A.

In addition to their normal I/O functions, PA0 and PA1 can detect positive going edges and PA2 and PA3 can detect negative going edges. A proper transition on these pins will set a corresponding status bit in the IFR and generate an interrupt request if the respective Interrupt Enable Bit is set. The maximum rate at which an edge can be detected is one-half the p2 clock rate. Edge detection timing is shown in Appendix E.5.

				Tour Mont	-	
		NO 1/O		ATCH MODE		
		R4 = 0		34 = 1		
		GNAL		SNAL		
PA0 (2)	PA0	1/O	PORT B	TYPE INPUT (1)		
PIN 39			LATCH STROBE	L		
PA1 (2)		PA3 I/O				
PIN 38		GNAL				
PA2 (3) PIN 37	NAME	TYPE				
PA3 (3) PIN 36	PA1 PA2 PA3	1/O 1/O 1/O				
	PA	4 I/O		COUNTE	R A I/O	
PA4 PIN 35	MCR0 = 0 MCR1 = 0 SCCR7 = 0 RCVR S/R MODE	= 0 (4) (5)	MCR0 = 1 MCR1 = 0 SCCR7 = 0 RCVR S/R MODE	= 0 4)	SCCR7 = 0 SCCR6 = 0 MCR1 = 1	
	SIG	BNAL	SIG	NAL		SIGNAL
	NAME	TYPE	NAME	TYPE	NAME	TYPE
	PA4	I/O	CNTA	OUTPUT	CNTA	INPUT (1)
			SERIAL I/O SHIFT	REGISTER CLOC	ĸ	
		SCCR7 = 1 SCCR5 = 1		RCVF	R S/R MODE = 1 (4)	
		SIGNAL			SIGNAL	
	NAME		TYPE			TYPE
	XMTR CLO	СК	OUTPUT	RCVR CLC	ОСК	INPUT (1)
	PA	5 I/O		COUNTE	R B I/O	
PA5	MCR: MCR:	3 = 0 2 = 0	MCR3 MCR2			CR3 = 1 CR2 = X
PIN 34	SIG	NAL	SIG	NAL		SIGNAL
	NAME	TYPE	NAME	TYPE	NAME	TYPE
	PA5	I/O	CNTB	OUTPUT	CNTB	INPUT (1)
	PAG	6 I/O	SERIA XMTR C		(1) Hardware E	Buffer Float
		R7 = 0	SCCR		(2) Positive Ed	ge Detect
PA6 PIN 33		NAL	SIGI			Node = 1 when SCCF
	NAME	TYPE	NAME	TYPE	• $\overline{\text{SCCR5}}$ • $\overline{\text{SCCR4}} = 1$	
	PA6	I/O	XMTR	OUTPUT	(5) For the following mode control tions PA4 is available as a second	
					only pin: SCCR7•SC	CR6+SCCR5+MCR1
	PA7	' I/O	SERIA RCVR		+ SCCR7•S + SCCR7•S	CCR6•7SCCR4•MCF SCCR6•SCCR5
PA7	SCCR	16 = 0	SCCR	6 = 1	+ SCCR7•8	SCCR5C+SCCR4.
PIN 32	SIG	NAL	SIGN	NAL		
	NAME	TYPE	NAME	TYPE		

### Table 4-2. Port A Control & Usage

### 4.4 PORT B (PB)

Port B can be programmed as an 8-bit, bit-independent I/O port. It has a latched input capability which may be enabled or disabled via the Mode Control Register (MCR). Table 4-3 tabulates the control and usage of Port B. An Input Data Strobe signal must be provided thru PA0 when Port B is programmed to be used with latched input option. Input data latch timing for Port B is shown in Appendix E.5.

		I/O Mode MCR4 = 0		MCR	itch ode 4 = 1 2)
		Signal		Sig	gnal
Pin #	Pin Name	Name	Type (1)	Name	Туре
31	PB0	PB0	I/O	PB0	INPUT
30	PB1	PB1	I/O	PB1	INPUT
29	PB2	PB2	I/O	PB2	INPUT
28	PB3	PB3	1/0	PB3	INPUT
27	PB4	PB4	1/0	PB4	INPUT
26	PB5	PB5	1/0	PB5	INPUT
25	PB6	PB6	1/0	PB6	INPUT
24	PB7	PB7	I/O	PB7	INPUT

Table 4-3. Port B Control & Usage

(1) Resistive Pull-Up, Active Buffer Pull-Down

(2) Input data is stored in Port B latch by PA0 Pulse

### 4.5 PORT C (PC)

Port C can be programmed as an I/O port, as part of the full address bus, and, in conjunction with Port D, as an abbreviated bus, or as a multiplexed bus. When operating in the Full Address Mode PC6 and PC7 serve as A13 and A14 with PC0-PC5 operating as normal I/O pins. When used in the abbreviated or multiplexed bus modes, PC0-PC7 function as A0-A3, A12, R/W, A13, and EMS, respectively, as shown in Table 4-4. EMS (External Memory Select) is asserted (low) whenever the internal processor accesses memory area between 0100 and 3FFF. (See Memory Map, Appendix B). The leading edge of EMS may be used to strobe the eight address lines multiplexed on Port D in the Multiplexed Bus Mode. See Appendices E.3 through E.5 for Port C timing.

### 4.6 PORT D (PD)

Port D can be programmed as an I/O Port, an 8-bit tri-state data bus, or as a multiplexed bus. Mode selection for Port D is made by the Mode Control Register (MCR). The Port D output drivers can be selected as tri-state drivers by setting bit 5 of the MCR to 1 (one). Table 4-5 shows the necessary settings for the MCR to achieve the various modes for Port D. When Port D is selected to operate in the Abbreviated Mode PD0–PD7 serves as data register bits D0–D7. When Port D is selected to operate in the Multiplexed Mode data bits D0 through D7 are time multiplexed with address bits A4 through A11, respectively. Refer to the Memory Maps (Appendix C) for Abbreviated and Multiplexed memory assignments. See Appendices E.3 through E.5 for Port D timing.

#### 4.7 BUS MODES

A special attribute of Port C and Port D is their capability to be configured via the Mode Control Register (see Section 3.6) into four different modes.

In the Full Address Mode, the separate address and data bus are used in conjunction with PC6 and PC7, which automatically provide A13 and A14. The remaining ports perform the normal I/O function.

In the I/O Bus Mode all ports serve as I/O. The address and data bus are still functional but without A13 and A14. Since the internal RAM and registers are in the 00XX location, A15 can be used for chip select and A0–A12 used for selecting 8K of external memory. Thus, the device can be used to emulate the R6500/11 in the Normal Bus Mode.

In the Abbreviated Bus Mode, the address and data lines can be used as in the I/O Bus Mode to emulate the R6500/11. Port C and Port D are automatically transformed into an abbreviated address bus and control signals (Port C) and a bidirectional data bus (Port D). 64 Peripheral addresses can be selected. In general usage, these 64 addresses would be distributed to several external I/O devices such as R6522 and R6520, etc., each of which may contain more than one unique address.

In the Multiplexed Bus Mode, the operation is similar to the Abbreviated Mode except that a full 16K of external addresses are provided. Port C provides the lower addresses and control signals. Port D multiplexes functions. During the first half of the cycle it contains the remaining necessary 8 address bits for 16K; during the second half of the cycle it contains a bidirectional data bus. The address bits appearing on Port D must be latched into an external holding register. The leading edge of EMS, which indicates that the bus function is active, may be used for this purpose.

MCR5 must be a logic 1 in the Abbreviated and Multiplexed Bus Modes.

Figures 4-1a through 4-1d show the possible configurations of the four bus modes. Figure 4-2 shows a memory map of the part as a function of the Bus Mode and further shows which adddresses are active or inactive on each of the three possible buses.

			Address Mode	Normal	Mode		reviated Node	1	tiplexed lode
	MCR7 = 0 MCR6 = 0			MCR7 = 0 MCR6 = 1			R7 = 1 R6 = 0	MCR7 = 1 MCR6 = 1	
		Signal		Sig	nal	S	ignal	I S	
Pin #	Pin Name	Name	Туре	Name	Туре (1)	Name	Туре (2)	Name	Type (2)
54	PC0	PC0	I/O (1)	PC0	I/O	AO	OUTPUT	A0	OUTPUT
55	PC1	PC1	I/O (1)	PC1	1/0	A1	OUTPUT	A1	OUTPUT
56	PC2	PC2	I/O (1)	PC2	I/O	A2	OUTPUT	A2	OUTPUT
57	PC3	PC3	I/O (1)	PC3	1/0	A3	OUTPUT	A3	OUTPUT
58	PC4	PC4	1/O (1)	PC4	1/0	A12	OUTPUT	A12	OUTPUT
59	PC5	PC5	I/O (1)	PC5	I/O	RW	OUTPUT	RŴ	OUTPUT
60	PC6	A13	OUTPUT (2)	PC6	I/O	A13	OUTPUT	A13	OUTPUT
	PC7	A14	OUTPUT (2)	PC7	I/O	EMS	OUTPUT	EMS	OUTPUT

#### Table 4-4. Port C Control & Usage

(2) Active Buffer Pull-Up and Pull-Down

Table 4-5.	Port	D Control	&	Usage
------------	------	-----------	---	-------

		Normal Modes				Abbreviated Normal Modes Mode						Multiple	xed Mode	
		MCR7 = 0 MCR6 = X MCR5 = 0		MCR7 = 0 MCR6 = X MCR5 = 1		MCR7 MCR6 MCR5	= 0		MCR	7 = 1 6 = 1 5 = 1				
		Si	gnal	s	ignal	Sigi	nal	S	ignal	s	ignal			
Pin	Pin		Туре		Туре		Туре	\$2	Low	6:	? High			
#	Name	Name	(1)	Name	(2)	Name	(3)	Name	Type (2)	Name	Type (3)			
62	PD0	PD0	INPUT	PD0	OUTPUT	DATAO	1/0	A4	OUTPUT	DATAO	1/0			
63	PD1	PD1	INPUT	PD1	OUTPUT	DATA1	1/0	A5	OUTPUT	DATA1	I/O			
64	PD2	PD2	INPUT	PD2	OUTPUT	DATA2	1/0	A6	OUTPUT	DATA2	I/O			
1	PD3	PD3	INPUT	PD3	OUTPUT	DATA3	1/0	A7	OUTPUT	DATA3	I/O			
2	PD4	PD4	INPUT	PD4	OUTPUT	DATA4	1/0	A8	OUTPUT	DATA4	I/O			
3	PD5	PD5	INPUT	PD5	OUTPUT	DATA5	1/0	A9	OUTPUT	DATA5	I/O			
		PD6	INPUT	PD6	OUTPUT	DATA6	1/0	A10	OUTPUT	DATA6	1/0			
4	PD6	FUO												

(2) Tri-State Buffer is in Active Mode

(3) Tri-State Buffer is in Active Mode only during the phase 2 portion of a Write Cycle



Figure 4-1. Bus Mode Configurations



Figure 4-2. Memory Map

# SECTION 5 SERIAL INPUT/OUTPUT CHANNEL

The device provides a full duplex Serial I/O channel with programmable bit rates and operating modes. The serial I/O functions are controlled by the Serial Communication Control Register (SCCR). The SCCR bit assignment is shown in Figure 5-1. The serial bit rate is determined by Counter A for all modes except the Receiver Shift Register (RCVR S/R) mode for which an external shift clock must be provided. The maximum data rate using the internal clock is 62.5K bits per second (at  $\emptyset 2 = 1$  MHZ). The transmitter (XMTR) and receiver (RCVR) can be independently programmed to operate in different modes and can be independently enabled or disabled.



Figure 5-1. Serial Communication Control Register

Except for the Receiver Shift Register Mode (RCVR S/R), all XMTR and RCVR bit rates will occur at one sixteenth of the Counter A interval timer rate. Counter A is forced into an interval timer mode whenever the serial I/O is enabled in a mode requiring an internal clock.

Whenever Counter A is required as a timing source it must be loaded with the hexadecimal code that selects the data rate for the serial I/O Port. Refer to Counter A (paragraph 6.1) for a table of hexadecimal values to represent the desired data rate.

### 5.1 TRANSMITTER OPERATION (XTMR)

The XTMR operation and the transmitter related control/ status functions are enabled by bit 7 of the Serial Communications Control Register (SCCR). The transmitter, when in the Asynchronous (ASYN) mode, automatically adds a start bit, one or two stop bits, and, when enabled, a parity bit to the transmitted data. A word of transmitted data (in asynchronous parity mode) can have 5, 6, 7, or 8 bits of data. The nine data modes are shown in Figure 5-2. When parity is disabled, the 5, 6, 7 or 8 bits of data are terminated with two stop bits.



Figure 5-2. SIO Data Modes

In the S/R mode, eight data bits are always shifted out. Bits/ character and parity control bits are ignored. The serial data is shifted out via the SO output (PA6) and the shift clock is available at the CA (PA4) pin. When the transmitter underruns in the S/R mode the SO output and shift clock are held in a high state.

The XMTR Interrupt Flag bit (IFR7) is controlled by Serial Communication Status Register bits SCSR5, SCSR6 and SCSR7.

### 5.2 RECEIVER OPERATION (RCVR)

The receiver and its selected control and status functions are enabled when SCCR-6 is set to a "1." In the ASYN mode, data format must have a start bit, the appropriate number of data bits, a parity bit (if enabled), and one stop bit. Refer to paragraph 5.1 for a diagram of bit allocations. The receiver bit period is divided into 8 sub-intervals for internal synchronization. The receiver bit stream is synchronized by the start bit and a strobe signal is generated at the approximate center of each incoming bit. Refer to Figure 5-3 for ASYN Receive Data Timing. The character assembly process does not start if the start bit signal is less than one-half the bit time after a low level is detected on the Receive Data Input. Framing error, over-run, and parity error conditions or a RCVR Data Register Full will set the appropriate status bits. Any of the above conditions will cause an Interrupt Request if the Receiver Interrupt Enable bit is set to logic 1.



Figure 5-3. ASYN Receive Data Timing

In the S/R mode, an external shift clock must be provided at CA (PA4) pin along with 8 bits of serial data (LSB first) at the SI input (PA7). The maximum data rate using an external shift clock is one-eighth the internal clock rate. Refer to Figure 5-4 for S/R Mode Timing.



Figure 5-4. S/R Mode Timing

A RCVR interrupt (IFR6) is generated whenever any of SCSR0-3 are true.

### 5.3 SERIAL COMMUNICATION STATUS REGISTER (SCSR)

The Serial Communication Status Register (SCSR) holds information on various communication error conditions, status of the transmitter and receiver data registers, a transmitter end-of-transmission condition, and a receiver idle line condition (Wake-Up Feature). The SCSR bit assignment is shown in Figure 5-5. Bit assignments and functions of the SCSR are as follows:

- SCSR 0: Receiver Data Register Full—Set to a logic 1 when a character is transferred from the Receiver Shift Register to the Receiver Data Register. This bit is cleared by reading the Receiver Data Register, or by RES and is disabled if SCCR 6 = 0. The SCSR 0 bit will not be set to a logic 1 if the received data contains an error condition; instead, a corresponding error bit will be set to a logic 1.
- SCSR 1: Over-Run Error—Set to a logic 1 when a new character is transferred from the Receiver Shift Register with the last character still in the Receiver Data Register. This bit is cleared by reading the Receiver Data Register or by RES.
- SCSR 2: Parity Error—Set to logic 1 when the RCVR is in the ASYN Mode, Parity Enable bit is set, and the

received data has a parity error. This bit is cleared by reading the Receiver Data Register or by RES.

- SCSR 3: Framing Error—Set to a logic 1 when the received data contains a zero bit after the last data or parity bit in the stop bit slot. Cleared by reading the Receiver Data Register or by RES (ASYN Mode only).
- SCSR 4: Wake-Up—Set to a logic 1 by writing a "1" in bit 4 of address: 0016. The Wake-Up bit is cleared by RES or when the receiver detects a string of ten consecutive 1's. When the Wake-Up bit is set SCSR0 through SCSR3 are inhibited.
- SCSR 5: End of Transmission—Set to a logic 1 by writing a "1" in bit position 5 of address: 0016. The End of Transmission bit is cleared by RES or upon writing a new data word into the Transmitter Data Register. When the End-of-Transmission bit is true the Transmitter Register Empty bit is disabled until a Transmitter Under-Run occurs.
- SCSR 6: Transmitter Data Register Empty—Set to a logic 1 when the contents of the Transmitter Data Register are transferred to the Transmitter Shift Register. Cleared upon writing new data into the Transmit Data Register. This bit is initialized to a logic 1 by RES.
- SCSR 7: *Transmitter Under-Run*—Set to a logic 1 when the last data bit is transmitted if the transmitter is in a S/R Mode or when the last stop bit is transmitted if the XMTR is in the ASYN Mode while the Transmitter Data Register Empty Bit is set. Cleared by a transfer of new data into the Transmitter Shift Register or by RES.



#### Figure 5-5. SCSR Bit Allocations 5.4 WAKE-UP FEATURE

In a multi-distributed microprocessor or microcomputer applications, a destination address is usually included at the beginning of the message. The Wake-Up Feature allows non-selected CPU's to ignore the remainder of the message until the beginning of the next message by setting the Wake-Up bit. As long as the Wake-Up flag is true, the Receiver Data Register Full Flag remains false. The Wake-Up bit is automatically cleared when the receiver detects a string of 11 consecutive 1's which indicates an idle transmit line. When the next byte is received, the Receiver Data Register Full Flag signals the CPU to wake-up and read the received data.

# SECTION 6 COUNTER/TIMERS

The device contains two 16-bit counters (Counter A and Counter B) and three 16-bit latches associated with the counters. Counter A has one 16-bit latch and Counter B has two 16-bit latches. Each counter can be independently programmed to operate in one of four modes:

#### Counter A

### Counter B • Retriggerable Interval Counter

 Pulse width measurement

Event Counter

- Asymmetrical Pulse Generation
- Pulse Generation
   Interval Timer
- Interval Timer
- Event Counter

Operating modes of Counter A and Counter B are controlled by the Mode Control Register. All counting begins at the initialization value and decrements. When modes are selected requiring a counter input/output line, PA4 is automatically selected for Counter A and PA5 is automatically selected for Counter B (see Table 4.2).

## 6.1 COUNTER A

Counter A consists of a 16-bit counter and a 16-bit latch organized as follows: Lower Counter A (LCA), Upper Counter A (UCA), Lower Latch A (LLA), and Upper Latch A (ULA). The counter contains the count of either  $\emptyset$ 2 clock pulses or external events, depending on the counter mode selected. The contents of Counter A may be read any time by executing a read at location 0019 for the Upper Counter A and at location 0018 also clears the Counter A Underflow Flag (IFR4).

The 16-bit latch contains the counter initialization value and can be loaded at any time by executing a write to the Upper Latch A at location 0019 and the Lower Latch A at location 0018. In either case, the contents of the accumulator are copied into the applicable latch register.

Counter A can be started at any time by writing to address: 001A. The contents of the accumulator will be copied into the



Figure 6-1. Interval Timer Timing Diagram

Upper Latch A before the contents of the 16-bit latch are transferred to Counter A. Counter A is set to the latch value whenever Counter A underflows. When Counter A decrements from 0000 the next counter value will be the latch value—not FFFF—and the Counter A Underflow Flag (IFR 4) will be set to "1". This bit may be cleared by reading the Lower Counter A at location 0018, by writing to address location 001A, or by RES.

Counter A operates in any of four modes. These modes are selected by the Counter A Mode Control bits in the Control Register.

MCR1 (bit 1)	MCR0 (bit 0)	Mode
0	0	Interval Timer
0	1	Pulse Generation
1	0	Event Counter
1	1	Pulse Width Measurement

The Interval Timer, Pulse Generation, and Pulse Width Measurement Modes are  $\phi$ 2 clock counter modes. The Event Counter Mode counts the occurrences of an external event on the CNTR line.

The Counter is set to the Interval Timer Mode (00) when a RES signal is generated.

#### 6.1.1 Interval Timer

In the Interval Timer mode the Counter is initialized to the Latch value by either of two conditions:

- 1. When the Counter is decremented from 0000, the next Counter value is the Latch value (not FFFF).
- 2. When a write operation is performed to the Load Upper Latch and Transfer Latch to Counter address 001A, the Counter is loaded with the Latch value. Note that the contents of the Accumulator are loaded into the Upper Latch before the Latch value is transferred to the Counter.

The Counter value is decremented by one count at the 02 clock rate. The 16-bit Counter can hold from 1 to 65535 counts. The Counter Timer capacity is therefore 1, $\mu$ s to 65,535 ms at the 1 MHz Ø2 clock rate or 0.5  $\mu$ s to 32.767 ms at the 2 MHz Ø2 clock rate. Time intervals greater than the maximum Counter value can be easily measured by counting IRQ interrupt requests in the counter IRQ interrupt routine.

When Counter A decrements from 0000, the Counter A Underflow (IFR4) is set to logic 1. If the Counter A Interrupt Enable Bit (IER4) is also set, an  $\overline{IRQ}$  interrupt request will be generated. The Counter A Underflow bit in the Interrupt Flag Register can be examined in the  $\overline{IRQ}$  interrupt routine to determine that the  $\overline{IRQ}$  was generated by the Counter A Underflow.

While the timer is operating in the Interval Timer Mode, PA4 operates as a PA I/O bit.

A timing diagram of the Interval Timer Mode is shown in Figure 6-1.

#### 6.1.2 Pulse Generation Mode

In the Pulse Generation mode, the CA line operates as a Counter Output. The line toggles from low to high or from high to low whenever a Counter A Underflow occurs or a write is performed to address 001A.

The normal output waveform is a symmetrical square-wave. The CA output is initialized high when entering the mode and transitions low when writing to 001A.

Asymmetric waveforms can be generated if the value of the latch is changed after each counter underflow.

A one-shot waveform can be generated by changing from Pulse Generation to Interval Timer mode after only one occurrence of the output toggle condition.

#### 6.1.3 Event Counter Mode

In this mode the CA is used as an Event Input line, and the Counter will decrement with each rising edge detected on this line. The maximum rate at which this edge can be detected is one-half the  $\emptyset$ 2 clock rate.

The Counter can count up to 65,535 occurrences before underflowing. As in the other modes, the Counter A Underflow bit (IER4) is set to logic 1 if the underflow occurs.

Figure 6.2 is a timing diagram of the Event Counter Mode.



Figure 6-2. Event Counter Mode

#### 6.1.4 Pulse Width Measurement Mode

This mode allows the accurate measurement of a low pulse duration on the CA line. The Counter decrements by one count at the  $\emptyset$ 2 clock rate as long as the CA line is held in the low state. The Counter is stopped when CA is in the high state.

The Counter A underflow flag will be set only when the count in the timer reaches zero. Upon reaching zero the timer will be loaded with the latch value and continue counting down as long as the CA pin is held low. After the counter is stopped by a high level on CA, the count will hold as long as CA remains high. Any further low levels on CA will again cause the counter to count down from its present value. The state of the CA line can be determined by testing the state of PAA.

A timing diagram for the Pulse Width Measurement Mode is shown in Figure 6.3.



Figure 6-3. Pulse Width Measurement

#### 6.1.5 Serial I/O Data Rate Generation

Counter A also provides clock timing for the Serial I/O which establishes the data rate for the Serial I/O port. When the Serial I/O is enabled, Counter A is forced to operate at the internal clock rate. Counter A is not required for the RCVR S/R mode. The Counter I/O (PA4) may also be required to support the Serial I/O (see Table 4-2).

Table 6-1 identifies the values to be loaded in Counter A for selecting standard data rates with a  $\phi$ 2 clock rate of 1 MHz and 2 MHz. Although Table 6-1 identifies only the more common data rates, any data rate from 1 to 62.5K bps can be selected by using the formula:

$$N = \frac{\oint 2}{16 \times bps} - 1$$

where

- N = decimal value to be loaded into Counter A using its hexadecimal equivalent.
- $\phi 2$  = the clock frequency (1 MHz or 2 MHz)
- bps = the desired data rate.

#### NOTE

In Table 6-1 you will notice that the standard data rate and the actual data rate may be slightly different. Transmitter and receiver errors of 1.5% or less are acceptable. A revised clock rate is included in Table 6-1 for those baud rates which fall outside this limit.

Table 6-1. Counter A Values for Baud Rate Selection

Standard Baud	Hexad Va		Acto Bao Rate	bu	Nee To Stan	Rate ded Get dard Rate
Rate	1 MHz	2 MHz	1 MHz	2 MHz	1 MHz	2 MHz
50	04E1	09C3	50.00	50.00	1.0000	2.0000
75	0340	0682	75.03	74.99	1.0000	2.0000
110	0237	046F	110.04	110.04	1.0000	2.0000
150	01A0	0340	149.88	150.06	1.0000	2.0000
300	00CF	01A0	300.48	299.76	1.0000	2.0000
600	0067	00CF	600.96	600.96	1.0000	2.0000
1200	0033	0067	1201.92	1201.92	1.0000	2.0000
2400	0019	0033	2403.85	2403.85	1.0000	2.0000
3600	0010	0021	3676.47	3676.47	0.9792	1.9584
4800	000C	0019	4807.69	4807.69	1.0000	2.0000
7200	0008	0010	6944.44	7352.94	1.0368	1.9584
9600	0006	000C	8928.57	9615.38	1.0752	2.0000

## 6.2 COUNTER B

Counter B consists of a 16-bit counter and two 16-bit latches organized as follows: Lower Counter B (LCB), Upper Counter B (UCB), Lower Latch B (LLB), Upper Latch B (ULB), Lower Latch C (LLC), and Upper Latch C (ULC). Latch C is used only in the asymmetrical pulse generation mode. The counter contains the count of either  $\emptyset 2$  clock pulses or external events depending on the counter mode selected. The contents of Counter B may be read any time by executing a Read at location 001D for the Upper Counter B. A Read at location 001E or 001C for the Counter B. A Read at location 001C also clears the Counter B Underflow Flag.

Latch B contains the counter initialization value and can be loaded at any time by executing a Write to the Upper Latch B at location 001D and the Lower Latch B at location 001C. In each case, the contents of the accumulator are copied into the applicable latch register.

Counter B can be initialized at any time by writing to address: 001E. The contents of the accumulator is copied into the Upper Latch B before the value in the 16-bit Latch B is transferred to Counter B. Counter B will also be set to the latch value and the Counter B Underflow Flag bit (IFR5) will be set to a "1" whenever Counter B underflows by decrementing from 0000.

IFR 5 may be cleared by reading the Lower Counter B at location 001C, by writing to address location 001E, or by RES.

Counter B operates in the same manner as Counter A in the Interval Timer and Event Counter modes. The Pulse Width Measurement Mode is replaced by the Retriggerable Interval Timer mode and the Pulse Generation mode is replaced by the Asymmetrical Pulse Generation Mode. Mode Control Register bits MCR2 and MCR3 select the four Counter B modes in a similar manner and coding as MCR0 and MCR1 select the modes of Counter A.

#### 6.2.1 Retriggerable Interval Timer Mode

When operating in the Retriggerable Interval Timer mode, Counter B is initialized to the latch value by writing to address 001E, by a Counter B underflow, or whenever a positive edge occurs on the CB pin (PA5). The Counter B interrupt flag will be set if the counter underflows before a positive edge occurs on the CB line. Figure 6-4 illustrates the operation.



Figure 6-4. Counter B. Retriggerable interval Timer Mode

### 6.2.2 Asymmetrical Pulse Generation Mode

Counter B has a special Asymmetrical Pulse Generation Mode whereby a pulse train with programmable pulse width and period can be generated without the processor intervention once the latch values are initialized.

In this mode, the 16-bit Latch B is initialized with a value which corresponds to the duration between pulses (referred to as D in the following descriptions). The 16-bit Latch C is initialized with a value corresponding to the desired pulse width (referred to as P in the following descriptions). The initialization sequence for Latch B and C and the starting of a counting sequence are as follows:

- The lower 8 bits of P are loaded into LLB by writing to address 001C; the upper 8 bits of P are loaded into ULB and the full 16 bits are transferred to Latch C by writing to address location 001D. At this point both Latch B and Latch C contain the value of P.
- 2. The lower 8 bits of D are loaded into LLB by writing to address 001C; the upper 8 bits of D are loaded into ULB by writing to address location 001E. Writing to address location 001E also causes the contents of the 16-bit Latch B to be downloaded into the Counter B and the CB output to go low as shown in Figure 6-5.
- 3. When Counter B underflow occurs the contents of the Latch C are loaded into the Counter B and the CB output toggles to a high level, staying high until another underflow occurs. Latch B is then down-loaded and the CB output toggles to a low level repeating the whole process.

# SECTION 7 POWER ON/INITIALIZATION CONSIDERATIONS

### 7.1 POWER ON TIMING

After application of V<sub>cc</sub> and V<sub>RR</sub> power to the device,  $\overline{\text{RES}}$  must be held low for at least eight  $\oint$ 2 clock cycles after V<sub>cc</sub> reaches operating range and the internal oscillator has stabilized. This stabilization time is dependent upon the input V<sub>cc</sub> voltage and performance of the internal oscillator. The clock can be monitored at  $\oint$ 2 (pin 3). Figure 7-1 illustrates the power turn-on waveforms. Clock stabilization time is typically 20 ms.



Figure 7-1. Power Turn-On Timing Detail

### 7.2 POWER-ON RESET

When RES goes from low to high, the device sets the Interrupt Mask Bit—bit 2 of the Processor Status Register and initiates a reset vector fetch at address FFFC and FFFD (or optionally 7FFE and 7FFF) to begin user program execution. All of the I/O ports (PA, PB, PC, PD) will be forced to the high (logic 1) state. All bits of the Control Register will be cleared to logic 0 causing the Interval Timers counter mode (mode 00) to be selected and all interrupt enabled bits to be reset.



Figure 6-5. Counter B Pulse Generation

## 7.3 RESET (RES) CONDITIONING

When  $\overline{\text{RES}}$  is driven from low to high the device is put in a reset state causing the registers and I/O ports to be configured as shown in Table 7-1.

Table 7-1.	RES	Initialization o	f I/O	Ports	and	Registers
------------	-----	------------------	-------	-------	-----	-----------

Bit No.	7	6	5	4	3	2	1	0
REGISTERS								
Processor Status	—	—			—	1	—	-
Mode Control (MCR)	0	0	0	0	0	0	0	0
Int. Enable (IER)	0	0	0	0	0	0	0	0
Int. Flag (IFR)	0	0	0	0	0	0	0	0
Ser. Com. Control (SCCR)	0	0	0	0	0	0	0	0
Ser. Com. Status (SCSR)	0	1	0	0	0	0	0	0
PORTS								
PA Latch	1	1	1	1	1	1	1	1
PB Latch	1	1	1	1	1	1	1	1
PC Latch	1	1	1	1	1	1	1	1
PD Latch	1	1	1	1	1	1	1	1

All RAM and other CPU registers will initialize in a random, non-repeatable data pattern.

### 7.4 INITIALIZATION

Any initialization process for the device should include a RES, as indicated in the preceeding paragraphs. After stabilization of the internal clock (if a power on situation) an initialization subroutine should be executed to perform (as a minimum) the following functions:

- 1. The Stack Pointer should be set
- 2. Clear or Set Decimal Mode
- 3. Set or Clear Carry Flag
- 4. Set up Mode Controls as required
- 5. Clear Interrupts

A typical initialization subroutine could be as follows:

- LDX Load stack pointer starting address into X Register
- TXS Transfer X Register value to Stack Pointer
- CLD Clear Decimal Mode
- SEC Set Carry Flag
  - ... Set-up Mode Control and ... special function registers
- .... special function registers .... and clear RAM as required
- CLI Clear Interrupts

# APPENDIX A ENHANCED R6502 INSTRUCTION SET

This appendix contains a summary of the Enhanced R6502 instruction set. For detailed information, consult the R6502 Microcomputer System Programming Manual, Document 29650 N30. The four instructions notated with a \* are added instructions to enhance the standard 6502 instruction set.

### A.1 INSTRUCTION SET IN ALPHABETIC SEQUENCE

Mnemonic	Instruction	Mnemonic	Instruction
ADC	Add Memory to Accumulator with Carry	LDA	Load Accumulator with Memory
AND	"AND" Memory with Accumulator	LDX	Load Index X with Memory
ASL	Shift Left One Bit (Memory or Accumulator)	LDY	Load Index Y with Memory
		LSR	Shift One Bit Right (Memory or
*BBR	Branch on Bit Reset Relative		Accumulator)
*BBS	Branch on Bit Set Relative		
BCC	Branch on Carry Clear	NOP	No Operation
BCS	Branch on Carry Set		
BEQ	Branch on Result Zero	ORA	"OR" Memory with Accumulator
BIT	Test Bits in Memory with Accumulator		
BMI	Branch on Result Minus	PHA	Push Accumulator on Stack
BNE	Branch on Result not Zero	PHP	Push Processor Status on Stack
BPL	Branch on Result Plus	PLA	Pull Accumulator from Stack
BRK	Force Break	PLP	Pull Processor Status from Stack
BVC	Branch on Overflow Clear		
BVS	Branch on Overflow Set	*RMB	Reset Memory Bit
		ROL	Rotate One Bit Left (Memory or
CLC	Clear Carry Flag		Accumulator)
CLD	Clear Decimal Mode	ROR	Rotate One Bit Right (Memory or
CLI	Clear Interrupt Disable Bit		Accumulator)
CLV	Clear Overflow Flag	RTI	Return from Interrupt
CMP	Compare Memory and Accumulator	RTS	Return from Subroutine
CPX	Compare Memory and Index X		
CPY	Compare Memory and Index Y	SBC	Subtract Memory from Accumulator with
			Borrow
DEC	Decrement Memory by One	SEC	Set Carry Flag
DEX	Decrement Index X by One	SED	Set Decimal Mode
DEY	Decrement Index Y by One	SEI	Set Interrupt Disable Status
		*SMB	Set Memory Bit
EOR	"Exclusive-Or" Memory with	STA	Store Accumulator in Memory
	Accumulator	STX	Store Index X in Memory
		STY	Store Index Y in Memory
INC	Increment Memory by One		•
INX	Increment Index X by One	TAX	Transfer Accumulator to Index X
INY	Increment Index X by One	TAY	Transfer Accumulator to Index Y
	·	TSX	Transfer Stack Pointer to Index X
JMP	Jump to New Location	TXA	Transfer Index X to Accumulator
JSR	Jump to New Location Saving Return	TXS	Transfer Index X to Stack Register
	Address	TYA	Transfer Index Y to Accumulator

SUMMARY TABLE
SET
R6500/13 INSTRUCTION
AND
R6511Q
A.2

OPER	OPERATION																•	į		1	!	2	ź	2																			CODES	CODES		
		WW	IMMEDIATE ABSOLUTEZERO PAGE	ABS		Ē	B	PAGI		ACCUM.	_	IMPLIED	ş		(x 'QN)		(IND)	۶	Z. P.	PAGE, X		ABS,	×	A	ABS, 1	۲	REL	RELATIVE		INDIRECT		Z. PAGE		7	BITA	DDR	ESSI	BIT ADDRESSING (OP	"	ᇤ	<b>(</b>	7 6	5 4	~	5 7	•
		-		-	c		-+	*	8	=	*	8	*	9	c		۲ ۹0	*	9	- -	。 *	ء م	*	9	-	*	6	* c	٩ ٩	с 4	*	ď	*	•	-	~	•	4	s	ø	~	> z	· -	0	~	6
A · M · C · A A M · A C · [7 Branch on M <sub>6</sub> - Branch on M <sub>6</sub> -	A · M · C · A (4)(1) A M · A (1) C · $7$ (1) Branch on M <sub>6</sub> = 0 (5)(2) Branch on M <sub>6</sub> - 1 (5)(2)	5 6	0 0 0 0	9028	440	0 10 	65 25 06 55 25	0 0 0 0 0 0	0 A	2	-			515	φφ	~~~	31 5	N N	75 35 16	440	19.7	7D 4 3D 4 1E 7	999 11	39	44	n n								58	<u></u>	2F AF	ж Ж	н4 С Ц	5	6F 6F	75	> · · · · z z z · ·			NNN	0.0.
Branch on Branch on Branch on A A M	C=0 (2) C=1 (2) Z=1 (2)			5		~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~		~																			885	0 0 0	000											Ĵ						
Branch on N = 1 Branch on Z = 0 Branch on N = 0 Break (See Fig. 1)	N = 1 (2) Z = 0 (2) N = 0 (2)			2	;							Ę	-						-			_					203	~~~~	000												-	ź • • • ⊻ • • •			N · · ·	• • • •
Branch on Branch on	V=0 (2) V=1 (2)																										<u>8</u>	0 0	~ ~													· · ·			· · ·	
												8 29 39 29	~ ~ ~ ~ ~																															• • •		0
E WWW VXX		888	0 0 0	886	444	000	842	0 0 0 0 0 0 0						ū	9	~	5 10	5	D5	4	2	60	е т	8	4	e	-															•			· N N	• • • •
¥×: ↓↓ ₩×:					tω							ð	~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~						å	9	2	DE 7	۳ ۲																			 z z z				0
Y 1Y AVMAA M-1N	(1)	6	N N	40 EE	4 0	6 CC 4 M	E6 3	о е						41	9	~~~~	51 5	5 2	55 F6	4 0	10	명 문 4 ٢		29	4	e																 				
INX X -1X INY Y -1Y JMP Jump to New Loc JSR Jump Sub (See F LDA MA (1)	X - 1→X Y - 1→Y Jump to New Loc Jump Sub (See Fig. 2) M→A (1)			AD 20 40	e 6 4	• • • • •						88	 N N	A1	ø	~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~	B1	2	8	4	8 	80 4	en 						29	0 0	e											 				
×× <sup>E</sup> c	t C	P F	N N N N		440		A4 46 50 50 50 50 50 50 50 50 50 50 50 50 50	0 0 0 0 0 0	4A	5	-		•						56 B4					88	4							B6	4									2 Z Z O		• • • •	1 N N N	• • • 0
AVM-A (1) A-Ms S 1-S P-Ms S 1-S	(1) S 1 - S	60	5	00	4	8	05	د، ص						01	9	~	=	5	15	4		5 4	en 11	19	4	m																 . z .		•••	• N •	
	S MS-A S MS-P (5)			2E	Ŷ	~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~	26	2	2A	N	-	3 8 8							36	ę	о С	38 7	3										·······	07	12	27	37	47	57	67	22	 .zz	e	(Restored		• • • •
Rtrn Int (	Rtm Int (See Fig. 1) Rtm Sub (See Fig. 2)				ø							<del>6</del> 8	 9 9														•															 z .	. ë .	estored)	N	
5 200 + X 2 - 1	(i) (5)	 ല	N	8	4	m m	<u></u>	<u>π</u>				8, 19, 39	N N N	ũ	ø	~		2	5	4	N N	5 4	m #	£	4	e								1				1	č	t	1	> · · · z · · ·		• • - •	N · · ·	ê - · ·
Z∑:				88	44	000	86 3	9 9 9 9						8	9	~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~	916	6 2				3 06	5	Ĵ	è.	۳.						96	4	6	6	A7	81	6	01	E7	5	· · ·		•••		
₩ × ≻  				ຮ	4														8	4	N																					• z	•••	•••	• • •	
× < 0																																	<u> </u>									 z z z		•••		
YA		$\neg$	-				-	_									_			-	-		·						_					_								 . z		• •		
N if page t N if branch	<ul> <li>Add 1 to N if page boundary is crossed</li> <li>Add 1 to N if branch occurs to same page</li> </ul>	ossed ne pa	_ <b>6</b>																												ч × Е	JENC	lndex X index Y	××							<b>ž</b> .∣	0 0 0		Memory Bit Add Subtract	14 0 1	
Add 2 to N if branch 3. Carry not = Borrow 4. If in decimal mode Z	Add 2 to N if branch occurs to different page 3. Carry not = Borrow 4. If in decimal mode 2 flag is invalid	leren.	page	_																											< ۲ ۲	< 2 2 < 3 2	Men.	Accumulator Memory per effective address Memory per stack pointer	for er ef	flectiv tick p	Accumulator Memory per effective address Memory per stack pointer	Iress			< > ≯	8 8 8		And Or Exclusive Or	ò	

3-162

## A.3 INSTRUCTION CODE MATRIX

USW DSW	SD 0	1	2	3	4	5	6	7	8	9	Α	в	с	D	E	F	_
Ŭ 0	BRK Implied 1 7	ORA (IND, X) 2 6				ORA ZP 2 3	ASL ZP 2 5	RMB0 ZP 2 5	PHP Implied 1 3	ORA IMM 2 2	ASL Accum 1 2			ORA ABS 3 4	ASL ABS 3 6	BBR0 ZP 3 5**	0
1	BPL Relative 2 2**	ORA (IND), Y 2 5*				ORA ZP, X 2 4	ASL ZP, X 2 6	RMB1 ZP 2 5	CLC Implied 1 2	ORA ABS, Y 3 4*				ORA ABS, X 3 4*	ASL ABS, X 3 7	BBR1 ZP 3 5**	1
2	JSR Absolute 3 6	AND (IND, X) 2 6			BIT ZP 2 3	AND ZP 2 3	ROL ZP 2 5	RMB2 ZP 2 5	PLP Implied 1 4	AND IMM 2 2	ROL Accum 1 2		BIT ABS 3 4	AND ABS 3 4	ROL ABS 3 6	BBR2 ZP 3 5**	2
3	BMI Relative 2 2**	AND (IND, Y) 2 5*				AND ZP, X 2 4	ROL ZP, X 2_6	RMB3 ZP 2 5	SEC Implied 1 2	AND ABS, Y 3 4*				AND ABS, X 3 4*	ROL ABS, X 3 7	BBR3 ZP 3 5**	3
4	RTI Implied 1 6	EOR (IND, X) 2 6				EOR ZP 2 3	LSR ZP 2 5	RMB4 ZP 2 5	PHA Implied 1 3	EOR IMM 2 2	LSR Accum 1 2		JMP ABS 3 3	EOR ABS 3 4	LSR ABS 3 6	BBR4 ZP 3 5**	4
5	BVC Relative 2 2**	EOR (IND), Y 2 5*				EOR ZP, X 2 4	LSR ZP, X 2 6	RMB5 ZP 2 5	CLI Implied 1 2	EOR ABS, Y 3 4*				EOR ABS, X 3 4*	LSR ABS, X 3 7	BBR5 ZP 3 5**	5
6	RTS Implied 1 6	ADC (IND, X) 2 6				ADC ZP 2 3	ROR ZP 2 5	RMB6 ZP 2 5	PLA Implied 1 4	ADC IMM 2 2	ROR Accum 1 2		JMP Indirect 3 5	ADC ABS 3 4	ROR ABS 3 6	BBR6 ZP 3 5**	6
7	BVS Relative 2 2**	ADC (IND, Y) 2 5*				ADC ZP, X 2 4	ROR ZP, X 2 6	RMB7 ZP 2 5	SEI Implied 1 2	ADC ABS, Y 3 4*				ADC ABS, X 3 4*	ROR ABS, X 3 7	BBR7 ZP 3 5**	7
8		STA (IND, X) 2 6			STY ZP 2 3	STA ZP 2 3	STX ZP 2 3	SMB0 ZP 2 5	DEY Implied 1 2		TXA Implied 1 2		STY ABS 3 4	STA ABS 3 4	STX ABS 3 4	BBS0 ZP 3 5**	8
9	BCC Relative 2 2**	STA (IND, Y) 2 6			STY ZP, X 2 4	STA ZP, X 2 4	STX ZP, Y 2 4	SMB1 ZP 2 5	7YA Implied 1 2	STA ABS, Y 3 5	TXS Implied 1 2			STA ABS, X 3 5		BBS1 ZP 3 5**	9
•	LDY IMM 2 2	LDA (IND, X) 2 6	LDX IMM 2 2		LDY ZP 2 3	LDA ZP 2 3	LDX ZP 2 3	SMB2 ZP 2 5	TAY Implied 1 2	LDA IMM 2 2	TAX Implied 1 2		LDY ABS 3 4	LDA ABS 3 4	LDX ABS 3 4	BBS2 ZP 3 5**	•
в	BCS Relative 2 2**	LDA (IND), Y 2 5*			LDY ZP, X 2 4	LDA ZP, X 2 4	LDX ZP, Y 2 4	SMB3 ZP 25	CLV Implied 1 2	LDA ABS, Y 3 4*	TSX Implied 1 2		LDY ABS, X 3 4*	LDA ABS, X 3 4*	LDX ABS, Y 3 4*	BBS3 ZP 3 5**	в
с	CPY IMM 2 2	CMP (IND, X) 2 6			CPY ZP 2 3	CMP ZP 2 3	DEC ZP 2 5	SMB4 ZP 2 5	INY Implied 1 2	CMP IMM 2 2	DEX Implied 1 2		CPY ABS 3 4	CMP ABS 3 4	DEC ABS 3 6	BBS4 ZP 3 5**	с
D	BNE Relative 2 2**	CMP (IND), Y 2 5*				CMP ZP, X 2 4	DEC ZP, X 2 6	SMB5 ZP 2 5	CLD Implied 1 2	CMP ABS, Y 3 4*				CMP ABS, X 3 4*	DEC ABS, X 3 7	BBS5 ZP 3 5**	D
E	CPX IMM 2 2	SBC (IND, X) 2 6			CPX ZP 2 3	SBC ZP 2 3	INC ZP 2 5	SMB6 ZP 2 5	INX Implied 1 2	SBC IMM 2 2	NOP Implied 1 2		CPX ABS 3 4	SBC ABS 3 4	INC ABS 3 6	BBS6 ZP 3 5**	E
F	BEQ Relative 2 2**	SBC (IND), Y 2 5*				SBC ZP, X 2 4	INC ZP, X 2 6	SMB7 ZP 2 5	SED Implied 1 2	SBC ABS, Y 3 4*				SBC ABS, X 3 4*	INC ABS, X 3 7	BBS7 ZP 3 5**	F
	0	1	2	3	4	5	6	7	8	9	A	в	с	D	Е	F	

0 BRK 0 Implied 1 7

-OP Code

-Addressing Mode --Instruction Bytes; Machine Cycles

\*Add 1 to N if page boundary is crossed. \*\*Add 1 to N if branch occurs to same page; add 2 to N if branch occurs to different page.



# APPENDIX C ADDRESS ASSIGNMENTS/MEMORY MAPS/PIN FUNCTIONS

# C.1 I/O AND INTERNAL REGISTER ADDRESSES

ADDRESS (HEX)	READ	WRITE
001F 1E 1D 1C	Lower Counter B Upper Counter B Lower Counter B, CLR Flag	—— Upper Latch B, Cntr B←Latch B, CLR Flag Upper Latch B, Latch C←Latch B Lower Latch B.
1B 1A 19 18	Lower Counter A Upper Counter A Lower Counter A, CLR Flag	 Upper Latch A, Cntr A←Latch A, CLR Flag Upper Latch A Lower Latch A
17 16 15 14	Serial Receiver Data Register Serial Comm. Status Register Serial Comm. Control Register Mode Control Register	Serial Transmitter Data Register Serial Comm. Status Reg. Bits 4 & 5 only Serial Comm. Control Register Mode Control Register
13 12 11 0010	 Interrupt Enable Register Interrupt Flag Register Read FF	Interrupt Enable Register 
0F 0E 0D 0C		
0B 0A 09 08	These addresses are reserve operation over the external D	RESERVED Id and are used by the CPU during Read and Write ata Bus (D0-D7).
07 06 05 04	T	
03 02 01 0000	Port D Port C Port B Port A	Port D Port C Port B Port A

## C.2 FULL ADDRESS MODE MEMORY MAP R6511Q OR R6500/13

### C.3 FULL ADDRESS MODE MEMORY MAP R6500/13 ONLY



# C.4 MULTIPLE FUNCTION PIN ASSIGNMENTS-PORT C AND PORT D

PIN NUMBER	FULL ADDRESS MODE	I/O PORT FUNCTION	ABBREVIATED PORT FUNCTION	MULTIPLEXED PORT FUNCTION
54	PC0	PC0	AQ	AO
55	PC1	PC1	A1	A1
56	PC2	PC2	A2	A2
57	PC3	PC3	A3	A3
58	PC4	PC4	A12	A12
59	PC5	PC5	B/W	B/W
60	A13	PC6	A13	A13
61	A14	PC7	EMS	EMS
62	PD0	PD0	D0	A4/D0
63	PD1	PD1	D1	A5/D1
64	PD2	PD2	D2	A6/D2
1	PD3	PD3	D3	A7/D3
2	PD4	PD4	D4	A8/D4
3	PD5	PD5	D5	A9/D5
4	PD6	PD6	D6	A10/D6
5	PD7	PD7	D7	A11/D7

# **APPENDIX D ELECTRICAL SPECIFICATIONS**

### **MAXIMUM RATINGS\***

Parameter	Symbol	Value	Unit
Supply Voltage	V <sub>CC</sub> & V <sub>RR</sub>	-0.3 to +7.0	Vdc
Input Voltage	V <sub>IN</sub>	-0.3 to +7.0	Vdc
Operating Temperature Commercial Industrial	TA	T <sub>L</sub> to T <sub>H</sub> 0 to +70 -40 to +85	۰c
Storage Temperature	T <sub>STG</sub>	- 55 to + 150	°C

\*NOTE: Stresses above those listed may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the other sections of this document is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

## DC CHARACTERISTICS

(V<sub>CC</sub> = 5.0V  $\pm$  5%, V<sub>RR</sub> = V<sub>CC</sub>; V<sub>SS</sub> = 0V; T<sub>A</sub> = 0° to 70°, unless otherwise specified)

Parameter	Symbol	Min	Typ <sup>1</sup>	Max	Unit	Test Conditions
RAM Standby Voltage (Retention Mode)	V <sub>RR</sub>	3.0		V <sub>cc</sub>	V	
RAM Standby Current (Retention Mode) Commercial Industrial	I <sub>RR</sub>	=	4 5.2		mA	T <sub>A</sub> = 25°C
Input High Voltage All Except XTLI and Ø2 in Slave Option XTLI and Ø2 in Slave Option	VIH	+ 2.0 + 4.0	_	V <sub>cc</sub> V <sub>cc</sub>	v	
Input Low Voltage	VIL	- 0.3	-	+ 0.8	V	
Input Leakage Current RES, NMI	l <sub>in</sub>	-	-	± 10.0	μΑ	$V_{\rm IN} = 0$ to 5.0V
Input Low Current PA, PB, PC, PD	1 <sub>IL</sub>	-	- 1.0	- 1.6	mA	$V_{IL} = 0.4V$
Output High Voltage (Except XTLO)	V <sub>OH</sub>	+ 2.4	-	V <sub>cc</sub>	v	$I_{LOAD} = -100 \ \mu A$
Output Low Voltage	VOL	_	_	+ 0.4	v	$I_{LOAD} = 1.6 \text{ mA}$
I/O Port Pull-Up Resistance PA0PA7, PB0-PB7, PC0-PC7	RL	3.0	6.0	11.5	Kohm	
Output Leakage Current (Three-State Off)	IOUT	-	_	± 10	μA	
Input Capacitance XTLI, XTLO All Others	C <sub>IN</sub>		_	50 10	pF	$T_{A} = 25^{\circ}C$ $V_{IN} = 0V$ $f = 1.0 \text{ MHz}$
Output Capacitance (Three-State Off)	C <sub>OUT</sub>	-	_	10	pF	$T_A = 25^{\circ}C$ $V_{IN} = 0V$ f = 1.0  MHz
Power Dissipation (Outputs High) Commercial Industrial	P <sub>D</sub>		750	1100 1200	mW	$T_A = 0^{\circ}C$

1. Typical values measured at  $T_A = 25^{\circ}C$  and  $V_{CC} = 5.0V$ . 2. Negative sign indicates outward current flow, positive indicates inward flow.

# APPENDIX E TIMING REQUIREMENTS AND CHARACTERISTICS

## E.1 GENERAL NOTES

- 1.  $V_{cc} = 5V \pm 5\%$ , 0°C  $\leq$  TA  $\leq$  70°C
- 2. A valid  $V_{CC}/\overline{RES}$  sequence is required before proper operation is achieved.
- 3. All timing reference levels are 0.8V and 2.0V, unless otherwise specified.
- 4. All time units are nanoseconds, unless otherwise specified.
- All capacitive loading is 130pf maximum, except as noted below:

PA, PB –		50pf maximum
PC (I/O Modes Only) -	_	50pf maximum
PC (ABB and Mux Mode) -	-	130pf maximum
PC6, PC7 (Full Address Mode) -		130pf maximum





## E.2 CLOCK TIMING

SYMBOL	PARAMETER	1 1	AHz	2 MHz		
STMBOL	PARAMETER	MIN	MAX	MIN MAX		
Тсус	Cycle Time	1000	10 μs	500	10 μs	
T <sub>PWX1</sub>	XTLI Input Clock Pulse Width XTLO = VSS	500 ± 25	-	250 ± 10	-	
T <sub>PW02</sub>	Output Clock Pulse Width at Minimum T <sub>cyc</sub>	T <sub>PWX1</sub>	T <sub>PWX1</sub> ± 25	T <sub>PWX1</sub>	T <sub>PWX1</sub> ± 20	
T <sub>R</sub> , T <sub>F</sub>	Output Clock Rise, Fall Time	—	25	-	15	
T <sub>IR</sub> , T <sub>IF</sub>	Input Clock Rise, Fall Time	-	10	-	10	





## E.3 ABBREVIATED MODE TIMING-PC AND PD

#### (MCR 5 = 1, MCR 6 = 0, MCR 7 = 1)

SYMBOL	PARAMETER	11	1 MHz		2 MHz	
	PARAMELER	MIN	MAX	MIN         MAX           —         140           —         140           35         —           10         —           30         —           30         —           30         —           30         —	MAX	
T <sub>PCRS</sub>	(PC5) R/W Setup Time	-	225	—	140	
T <sub>PCAS</sub>	(PC0-PC4, PC6) Address Setup Time	-	225		140	
TPBSU	(PD) Data Setup Time	50	-	35	-	
Треня	(PD) Data Read Hold Time	10	_	10	-	
Т <sub>рвни</sub>	(PD) Data Write Hold Time	30		30	—	
T <sub>PBDD</sub>	(PD) Data Output Delay	-	175	-	150	
T <sub>PCHA</sub>	(PC0-PC4, PC6) Address Hold Time	30	_	30		
T <sub>PCHR</sub>	(PC5) R/W Hold Time	30	_	30		
Т <sub>РСНУ</sub>	(PC7) EMS Hold Time	10	-	10		
T <sub>PCVP</sub>	(PC7) EMS Stabilization Time	30	-	30	—	
T <sub>esu</sub>	EMS Setup Time	-	350	—	210	

## E.3.1 Abbreviated Mode Timing Diagram



## E.4 MULTIPLEXED MODE TIMING-PC AND PD

#### (MCR 5 = 1, MCR 6 = 1, MCR 7 = 1)

SYMBOL	PARAMETER	11	1 MHz		2 MHz	
	PARAMETER	MIN	MAX	MIN	MAX	
TPCRS	(PC5) R/W Setup Time	_	225	-	140	
TPCAS	(PC0-PC4, PC6) Address Setup Time	_	225	—	140	
TPBAS	(PD) Address Setup Time	-	225	—	140	
TPBSU	(PD) Data Setup Time	50	-	35		
Трвня	(PD) Data Read Hold Time	10	-	10		
Т <sub>рвни</sub>	(PD) Data Write Hold Time	30	_	30	-	
TPBDD	(PD) Data Output Delay		175	—	150	
	(PC0-PC4, PC6) Address Hold Time	30	_	30	-	
Трена	(PD) Address Hold Time	10	100	10	80	
TPCHR	(PC5) R/W Hold Time	30	-	30	_	
TPCHV	(PC7) EMS Hold Time	10	—	10	-	
T <sub>PCVD</sub> <sup>(1)</sup>	(PC7) Address to EMS Delay Time	30		30		
TPCVP	(PC7) EMS Stabilization Time	30		30		
T <sub>ESU</sub>	EMS Setup Time	-	350	_	210	
NOTE 1: V	alues assume PC0-PC4, PC6 and PC7 have t	he same o	apacitive	load.		

## E.4.1 Multiplex Mode Timing Diagram



# E.5 I/O, EDGE DETECT, COUNTERS, AND SERIAL I/O TIMING

SYMBOL		1 MHz		2 MHz	
	PARAMETER		MAX	MIN	MAX
	Internal Write to Peripheral Data Valid				
T <sub>PDW</sub> <sup>(1)</sup>	PA, PB, PC TTL	-	500	_	500
T <sub>CMOS</sub> <sup>(1)</sup>	PA, PB, PC CMOS	_	1000	-	1000
TPDOW	PD	-	175	-	150
	Peripheral Data Setup Time				
TPOSU	PA, PB, PC	200	-	200	
TPOSU	PD	50	-	50	-
	Peripheral Data Hold Time				
Теня	PA, PB, PC	75	_	75	
Теня	PD	10	-	10	—
Terw	PA0-PA3 Edge Detect Pulse Width	Тстс	-	Тсус	—
	Counters A and B				
TCPW	PA4, PA5 Input Pulse Width	Тстс	-	Тстс	—
T <sub>CD</sub> <sup>(1)</sup>	PA4, PA5 Output Delay	-	500	-	500
	Port B Latch Mode				
TPBLW	PA0 Strobe Pulse Width	Тстс	_	Тстс	
TPISU	PB Data Setup Time	175	-	150	_
Трасн	PB Data Hold Time	30	-	30	
	Serial I/0				
T <sub>PDW</sub> <sup>(1)</sup>	PA6 XMTR TTL	_	500	-	500
T <sub>CMOS</sub> <sup>(1)</sup>	PA6 XMTR CMOS	-	1000	1 1	1000
TCPW	PA4 RCVR S/R Clock Width	4 T <sub>CYC</sub>	-	4 T <sub>cvc</sub>	
T <sub>PDW</sub> <sup>(1)</sup>	PA4 XMTR Clock—S/R Mode (TTL)		500	-	500
T <sub>CMOS</sub> <sup>(1)</sup>	PA4 XMTR Clock—S/R Mode (CMOS)		1000		1000

1: Maximum Load Capacitance: Passive Pull-Up Required

# E.5.1 I/O, Edge Detect, Counter, and Serial I/O Timing



# E.6 MICROPROCESSOR TIMING (D0-D7, A0-A12, A15, SYNC, R/W)

SYMBOL		1 1	1 MHz		IHz
	PARAMETER	MIN	MAX	MIN	Hz MAX 140 75 — — 130 175 —
T <sub>RWS</sub>	R/W Setup Time	-	225	-	140
T <sub>ADS</sub>	A0-A12, A15 Setup Time	ł	150	-	75
TDSU	D0-D7 Data Setup Time	50	—	35	—
Т <sub>нв</sub>	D0-D7 Read Hold Time	10	_	10	—
T <sub>HW</sub>	D0-D7 Write Hold Time	30	-	30	—
T <sub>MOS</sub>	D0-D7 Write Output Delay	—	175	—	130
TSYN	SYNC Setup	_	225	-	175
T <sub>HA</sub>	A0-A12, A15 Hold Time	30	-	30	—
T <sub>HRW</sub>	R/W Hold Time	30	-	30	-
T <sub>ACC</sub>	External Memory Access Time $T_{ACC} = T_{CYC} - T_F - T_{ADS} - T_{DSU}$	—	T <sub>ACC</sub>	-	T <sub>ACC</sub>
Т <sub>зүн</sub>	SYNC Hold Time	30	-	30	-

## E.6.1 Microprocessor Timing Diagram

