

SANYO**LC7535M**

Electronic Volume/Loudness Control with Serial Data Control and High Voltage-Handling Capacity



Overview

The LC7535M is an electronic volume and loudness control IC that provides volume, balance, and loudness functions with a minimal number of external components and that can be controlled electronically.

Functions

- Volume: Provides 81 positions from 0 dB to -79 dB in 1-dB steps and $-\infty$. A balance function can be implemented by controlling the left and right volume levels independently.
- Loudness: A loudness function can be implemented by attaching external capacitors at the output tap provided at the -20-dB position in the 5-dB step volume control.
- S (select) pin: Up to two LC7535M chips can be used on the same bus.
- Serial data input: The LC7535M supports communication with the controller in the CCB format.

- CCB is a trademark of SANYO ELECTRIC CO., LTD.
- CCB is SANYO's original bus format and all the bus addresses are controlled by SANYO.


Feature

- High voltage-handling capacity: ± 16 V.

Package Dimensions

unit: mm

3216A-MFP30S



Specifications

Absolute Maximum Ratings at $T_a = 25^\circ\text{C}$, $V_{SS} = 0$ V

Parameter	Symbol	Conditions	Ratings	Unit
Maximum supply voltage	$V_{DD\text{ max}}$	$V_{EE} \leq V_{SS} < V_{CC} < V_{DD}$	V_{SS} to $V_{SS} + 18$	V
	$V_{EE\text{ max}}$	$V_{EE} \leq V_{SS} < V_{CC} < V_{DD}$	$V_{SS} - 18$ to V_{SS}	V
	$V_{CC\text{ max}}$	$V_{EE} \leq V_{SS} < V_{CC} < V_{DD}$	V_{SS} to $V_{SS} + 7$	V
Maximum input voltage	$V_{IN\text{ max1}}$	CL, DI, CE	0 to $V_{CC} + 0.3$	V
	$V_{IN\text{ max2}}$	L5dBIN, R5dBIN, L1dBIN, R1dBIN	$V_{EE} - 0.3$ to $V_{DD} + 0.3$	V
	$V_{IN\text{ max3}}$	S	$V_{CC} - 0.3$ to $V_{DD} + 0.3$	V
Allowable power dissipation	$P_{d\text{ max}}$	$T_a \leq 75^\circ\text{C}$	250	mW
Operating temperature	T_{opr}		-30 to +75	$^\circ\text{C}$
Storage temperature	T_{stg}		-40 to +125	$^\circ\text{C}$

Allowable Operating Ranges at $T_a = 25^\circ\text{C}$, $V_{SS} = 0$ V

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Supply voltage	V_{DD}	V_{DD}	$V_{CC} + 4.5$		16	V
	V_{EE}	V_{EE}	-16		0	V
	V_{CC}	V_{CC}	4.5	5	5.5	V
Input high-level voltage	V_{IH1}	CL, DI, CE	$0.8 V_{CC}$		V_{CC}	V
	V_{IH2}	S	$0.8 \times (V_{DD} - V_{CC}) + V_{CC}$		V_{DD}	V
Input low-level voltage	V_{IL1}	CL, DI, CE	V_{SS}		$0.2 V_{CC}$	V
	V_{IL2}	S	V_{CC}		$0.2 \times (V_{DD} - V_{CC}) + V_{CC}$	V

Continued on next page.

SANYO Electric Co., Ltd. Semiconductor Business Headquarters

TOKYO OFFICE Tokyo Bldg., 1-10, 1 Chome, Ueno, Taito-ku, TOKYO, 110-8534 JAPAN

LC7535M


Continued from preceding page.

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Input voltage amplitude	V_{IN}	L5dBIN, R5dBIN, L1dBIN, R1dBIN	V_{EE}		V_{DD}	Vp-p
Input pulse width	t_{ow}	CL	1			μs
Setup time	$t_{\text{set up}}$	CL, DI, CE	1			μs
Hold time	t_{hold}	CL, DI, CE	1			μs
Operating frequency	t_{opg}	CL			500	kHz

Electrical Characteristics at $T_a = 25^\circ\text{C}$, $V_{SS} = 0\text{ V}$


Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Total harmonic distortion	THD	$V_{IN} = 1\text{ Vrms}$, $f = 1\text{ kHz}$, With all tone control settings flat, $V_{DD} - V_{EE} = 30\text{ V}$		0.002		%
Crosstalk	C_T	$V_{IN} = 1\text{ Vrms}$, $f = 1\text{ kHz}$, With all tone control settings flat, $R_G = 1\text{ k}\Omega$, $V_{DD} - V_{EE} = 30\text{ V}$		70		dB
Output at maximum attenuation	V_{Omin}	$V_{IN} = 1\text{ V rms}$, $f = 1\text{ kHz}$, with the volume set at ∞ , $V_{DD} - V_{EE} = 30\text{ V}$		-95		dB
Output noise voltage	V_N	With all tone control settings flat, $R_g = 1\text{ k}\Omega$ IHF-A, $V_{DD} - V_{EE} = 30\text{ V}$		2	10	μV
Total resistance	Rvol1	5-dB volume control block		75		$\text{k}\Omega$
	Rvol2	1-dB volume control block		20		$\text{k}\Omega$
Output off leakage current	I_{OFF}	L5dBIN, R5dBIN, LCT1, RCT1, LCT2, RCT2, L5dBOUT, R5dBOUT, L1dBIN, R1dBIN, L1dBOUT, R1dBOUT, LVM, RVM	-10		+10	μA
Input high-level current	I_{IH}	CL, DI, CE : $V_{IN} = V_{CC}$			10	μA
Input low-level current	I_{IL}	CL, DI, CE : $V_{IN} = V_{SS}$	-10			μA
Current drain	I_{DD}	$V_{DD} = 16\text{ V}$			1	mA
	I_{CC}	$V_{CC} = 5.5\text{ V}$			1	mA

Equivalent Circuit




A08915

Sample Application Circuit




A08916

Test Circuit
Total Harmonic Distortion




A08917


Output Noise Voltage












Crosstalk



Pin Assignment




Pin Descriptions


Pin No.	Pin	Function	Equivalent circuit
2	L5dBIN	<ul style="list-style-type: none"> • 5-dB step attenuator inputs These inputs must be driven by low-impedance circuits. 	 A08921
29	R5dBIN		
3	LCT1	<ul style="list-style-type: none"> • Loudness circuit connections Connect the high-band compensation capacitors between the CT1 and 5dBIN pins, and connect the low band compensation capacitors between the CT2 and the V_M pins. 	 A08922
28	RCT1		
4	LCT2		 A08923
27	RCT2		
5	L5dBOUT	<ul style="list-style-type: none"> • 5-dB step attenuator outputs These outputs must be accepted by circuits with an impedance of between 47 kΩ and 1 MΩ. 	 A08924
26	R5dBOUT		
7	L1dBIN	<ul style="list-style-type: none"> • 1-dB step attenuator inputs These inputs must be driven by low-impedance circuits. 	 A08925
24	R1dBIN		
8	L1dBOUT	<ul style="list-style-type: none"> • 1-dB step attenuator outputs These outputs must be accepted by circuits with an impedance of between 47 kΩ and 1 MΩ. 	 A08926
23	R1dBOUT		
9	LV _M	<ul style="list-style-type: none"> • Common connections for the volume control circuit. The impedance of the printed circuit board pattern connected to these pins must be kept as low as possible. Since the LV_M, RV_M, and V_{SS} pins are not connected internally, they must be connected externally as required by the various specifications. When a single-sided power supply is used, the capacitors between V_M and V_{SS} become the residual resistance when the volume control is set at its maximum attenuation. This means that care is required in selecting the values of these capacitors. 	 A08927
22	RV _M		
12	S	<ul style="list-style-type: none"> • Selection input for the address code in the data format. If this pin is connected to V_{DD}, data will be accepted when the address code is 9, and if connected to V_{CC}, data will be accepted when the address code is 8. 	 A08928
17	CL	<ul style="list-style-type: none"> • Input pins for the serial data used to control the device. These inputs must have an amplitude of 0 to 5 V. In applications in which any of microcontroller CL, DI, or CE may go high in backup mode (when V_{DD} = V_{CC} = 0 V), the signal lines must have series resistors of at least 2 kΩ inserted. 	 A08929
18	DI		
19	CE		
10	V _{EE}	<ul style="list-style-type: none"> • Power supply connections. All these pins must be connected to the corresponding power supply voltage. When power is first applied, the V_{CC} voltage must not rise before V_{DD}. 	
13	V _{DD}		
14	V _{SS}		
21	V _{CC}		
1, 6, 11, 15, 16, 20, 25, 30	NC	<ul style="list-style-type: none"> • Unconnected (NC) pins Do not connect any signals or devices to these pins. 	

Control System Timing and Data Format

The stipulated serial data must be input to the CL, DI, and CE pins to control the LC7535M. The data consists of a total of 20 bits, of which 4 bits are address and 16 bits are data.



A08930



S pin	A0	A1	A2	A3
V _{DD}	1	0	0	1
V _{CC}	0	0	0	1

Right channel 5-dB step control

Set state	D0	D1	D2	D3
-75dB	0	0	0	0
-70dB	1	0	0	0
-65dB	0	1	0	0
-60dB	1	1	0	0
-55dB	0	0	1	0
-50dB	1	0	1	0
-45dB	0	1	1	0
-40dB	1	1	1	0
-35dB	0	0	0	1
-30dB	1	0	0	1
-25dB	0	1	0	1
-20dB	1	1	0	1
-15dB	0	0	1	1
-10dB	1	0	1	1
-5dB	0	1	1	1
0dB	1	1	1	1



Loudness
1: On
0: Off

Right channel 1-dB step control

Set state	D4	D5	D6
-∞	0	0	0
Dummy *	1	0	0
-4dB	0	1	0
-3dB	1	1	0
-2dB	0	0	1
-1dB	1	0	1
0dB	0	1	1



Note *: To minimize switching noise, applications should input dummy data in the following sequence: -79 dB → dummy → -∞

Loudness Characteristics





T00125

Volume Step Characteristics





T00126

THD — Frequency Characteristics (1)





T00127

THD — Frequency Characteristics (2)





T00127



THD – Power-Supply Voltage Characteristics (1)





THD – Power-Supply Voltage Characteristics (2)





THD – Input Level Characteristics (1)





THD – Input Level Characteristics (2)



THD – Output Level Characteristics (1)



THD – Output Level Characteristics (2)



Usage Notes

- The state of the internal analog switches are undefined when power is first applied. Applications should apply external muting to the output signal until the control data has been set up.
- To prevent the high-frequency digital signals transmitted over the CL, DI, and CE pin lines from entering the analog signal system, these lines should either be covered by the ground pattern or shielded cables should be used.

- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall:
 - ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use:
 - ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of May, 1998. Specifications and information herein are subject to change without notice.