


# MC33039

## Closed Loop Brushless Motor Adapter

The MC33039 is a high performance closed-loop speed control adapter specifically designed for use in brushless DC motor control systems. Implementation will allow precise speed regulation without the need for a magnetic or optical tachometer. This device contains three input buffers each with hysteresis for noise immunity, three digital edge detectors, a programmable monostable, and an internal shunt regulator. Also included is an inverter output for use in systems that require conversion of sensor phasing. Although this device is primarily intended for use with the MC33035 brushless motor controller, it can be used cost effectively in many other closed-loop speed control applications.

- Digital Detection of Each Input Transition for Improved Low Speed Motor Operation
- TTL Compatible Inputs With Hysteresis
- Operation Down to 5.5 V for Direct Powering from MC33035 Reference
- Internal Shunt Regulator Allows Operation from a Non-Regulated Voltage Source
- Inverter Output for Easy Conversion between 60°/300° and 120°/240° Sensor Phasing Conventions

### CLOSED LOOP BRUSHLESS MOTOR ADAPTER SEMICONDUCTOR TECHNICAL DATA




**P SUFFIX**  
PLASTIC PACKAGE  
CASE 626




**D SUFFIX**  
PLASTIC PACKAGE  
CASE 751  
(SO-8)

### Representative Block Diagram



### PIN CONNECTIONS



### ORDERING INFORMATION

Device	Operating Temperature Range	Package
MC33039D	$T_A = -40^\circ \text{ to } +85^\circ \text{C}$	SO-8
MC33039P		Plastic DIP

## MAXIMUM RATINGS

Rating	Symbol	Value	Unit
$V_{CC}$ Zener Current	$I_{Z(V_{CC})}$	30	mA
Logic Input Current (Pins 1, 2, 3)	$I_{IH}$	5.0	mA
Output Current (Pins 4, 5), Sink or Source	$I_{DRV}$	20	mA
Power Dissipation and Thermal Characteristics Maximum Power Dissipation @ $T_A = +85^{\circ}\text{C}$ Thermal Resistance, Junction-to-Air	$P_D$ $R_{\theta JA}$	650 100	mW $^{\circ}\text{C/W}$
Operating Junction Temperature	$T_J$	+ 150	$^{\circ}\text{C}$
Operating Ambient Temperature Range	$T_A$	– 40 to + 85	$^{\circ}\text{C}$
Storage Temperature Range	$T_{stg}$	– 65 to + 150	$^{\circ}\text{C}$

ELECTRICAL CHARACTERISTICS ( $V_{CC} = 6.25\text{ V}$ ,  $R_T = 10\text{ k}$ ,  $C_T = 22\text{ nF}$ ,  $T_A = 25^{\circ}\text{C}$ , unless otherwise noted)

Characteristic	Symbol	Min	Typ	Max	Unit
----------------	--------	-----	-----	-----	------

## LOGIC INPUTS

Input Threshold Voltage					V
High State	$V_{IH}$	2.4	2.1	—	
Low State	$V_{IL}$	—	1.4	1.0	
Hysteresis	$V_H$	0.4	0.7	0.9	
Input Current					$\mu\text{A}$
High State ( $V_{IH} = 5.0\text{ V}$ )	$I_{IH}$	– 40	– 60	– 80	
$\phi_A$		—	– 0.3	– 5.0	
$\phi_B, \phi_C$					
Low State ( $V_{IL} = 0\text{ V}$ )	$I_{IL}$	– 190	– 300	– 380	
$\phi_A$		—	– 0.3	– 5.0	
$\phi_B, \phi_C$					


## MONOSTABLE AND OUTPUT SECTIONS

Output Voltage					V
High State	$V_{OH}$	3.60	3.95	4.20	
$f_{out}$ ( $I_{source} = 5.0\text{ mA}$ )		4.20	4.75	—	
$\phi_A$ ( $I_{source} = 2.0\text{ mA}$ )					
Low State	$V_{OL}$	—	0.25	0.50	
$f_{out}$ ( $I_{sink} = 10\text{ mA}$ )		—	0.25	0.50	
$\phi_A$ ( $I_{sink} = 10\text{ mA}$ )					
Capacitor $C_T$ Discharge Current	$I_{dischg}$	20	35	60	mA
Output Pulse Width (Pin 5)	$t_{PW}$	205	225	245	$\mu\text{s}$

## POWER SUPPLY SECTION

Power Supply Operating Voltage Range ( $T_A = -40^{\circ}$ to $+85^{\circ}\text{C}$ )	$V_{CC}$	5.5	—	$V_Z$	V
Power Supply Current	$I_{CC}$	1.8	3.9	5.0	mA
Zener Voltage ( $I_Z = 10\text{ mA}$ )	$V_Z$	7.5	8.25	9.0	V
Zener Dynamic Impedance ( $\Delta I_Z = 10\text{ mA}$ to $20\text{ mA}$ , $f \leq 1.0\text{ kHz}$ )	$ Z_{ka} $	—	2.0	5.0	$\Omega$

Figure 1. Typical Three Phase, Six Step Motor Application



## OPERATING DESCRIPTION


The MC33039 provides an economical method of implementing closed-loop speed control of brushless DC motors by eliminating the need for a magnetic or optical tachometer. Shown in the timing diagram of Figure 1, the three inputs (Pins 1, 2, 3) monitor the brushless motor rotor position sensors. Each sensor signal transition is digitally detected, OR'ed at the Latch 'Set' Input, and causes  $C_T$  to discharge. A corresponding output pulse is generated at  $f_{out}$  (Pin 5) of a defined amplitude, and programmable width determined by the values selected for  $R_T$  and  $C_T$  (Pin 6). The average voltage of the output pulse train increases with motor speed. When fed through a low pass filter or integrator, a DC voltage proportional to speed is generated. Figure 2 shows the proper connections for a typical closed loop

application using the MC33035 brushless motor controller. Constant speed operation down to 100 RPM is possible with economical three phase four pole motors.


The  $\phi_A$  inverter output (Pin 4) is used in systems where the controller and motor sensor phasing conventions are not compatible. A method of converting from either convention to the other is shown in Figure 3. For a more detailed explanation of this subject, refer to the text above Figure 39 on the MC33035 data sheet.

The output pulse amplitude  $V_{OH}$  is constant with temperature and controlled by the supply voltage on  $V_{CC}$  (Pin 8). Operation down to 5.5 V is guaranteed over temperature. For systems without a regulated power supply, an internal 8.25 V shunt regulator is provided.


### Figure 2. Typical Closed Loop Speed Control Application




**Figure 3.  $f_{out}$ , Pulse Width versus Timing Resistor**




**Figure 4.  $f_{out}$ , Pulse Width Change versus Temperature**




**Figure 5.  $f_{out}$ , Pulse Width Change versus Supply Voltage**




**Figure 6. Supply Current versus Supply Voltage**




**Figure 7.  $f_{out}$ , Saturation versus Load Current**



**Figure 8.  $f_{out}$ , Saturation Change versus Temperature**



## OUTLINE DIMENSIONS



Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters can and do vary in different applications. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

## How to reach us:

**USA / EUROPE:** Motorola Literature Distribution;  
P.O. Box 20912; Phoenix, Arizona 85036. 1-800-441-2447

**MFAX:** RMFAX0@email.sps.mot.com - TOUCHTONE (602) 244-6609  
**INTERNET:** http://Design-NET.com

**JAPAN:** Nippon Motorola Ltd.; Tatsumi-SPD-JLDC, Toshikatsu Otsuki,  
6F Seibu-Butsuryu-Center, 3-14-2 Tatsumi Koto-Ku, Tokyo 135, Japan. 03-3521-8315

**HONG KONG:** Motorola Semiconductors H.K. Ltd.; 8B Tai Ping Industrial Park,  
51 Ting Kok Road, Tai Po, N.T., Hong Kong. 852-26629298

