

Digital transistors (built-in resistors)

DTA143ZE / DTA143ZUA / DTA143ZKA / DTA143ZSA


●Features

- 1) Built-in bias resistors enable the configuration of an inverter circuit without connecting external input resistors (see equivalent circuit).
- 2) The bias resistors consist of thin-film resistors with complete isolation to allow positive biasing of the input. They also have the advantage of almost completely eliminating parasitic effects.
- 3) Only the on/off conditions need to be set for operation, making device design easy.

●Structure


PNP digital transistor
(with built-in resistors)

●Equivalent circuit




●External dimensions (Units: mm)


DTA143ZE




DTA143ZUA



DTA143ZKA



DTA143ZSA



●Absolute maximum ratings ($T_a = 25^\circ\text{C}$)

Parameter	Symbol	Limits(DTA143Z□)				Unit
		E	UA	KA	SA	
Supply voltage	V _{CC}	-50				V
Input voltage	V _{IN}	-30~+5				V
Output current	I _o	-100				mA
	I _{C(Max.)}	-100				
Power dissipation	P _d	150	200		300	mW
Junction temperature	T _j	150				℃
Storage temperature	T _{stg}	-55~+150				℃

●Electrical characteristics ($T_a = 25^\circ\text{C}$)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Input voltage	$V_{I(off)}$	—	—	-0.5	V	$V_{CC} = -5V, I_o = -100\mu\text{A}$
	$V_{I(on)}$	-1.3	—	—		$V_o = -0.3V, I_o = -5\text{mA}$
Output voltage	$V_{O(on)}$	—	-0.1	-0.3	V	$I_o/I_i = -5\text{mA}/-0.25\text{mA}$
Input current	I_i	—	—	-1.8	mA	$V_i = -5V$
Output current	$I_{O(off)}$	—	—	-0.5	μA	$V_{CC} = -50V, V_i = 0V$
DC current gain	G_i	80	—	—	—	$V_o = -5V, I_o = -10\text{mA}$
Input resistance	R_i	3.29	4.7	6.11	$k\Omega$	—
Resistance ratio	R_2/R_1	8	10	12	—	—
Transition frequency	f_r	—	250	—	MHz	$V_{CE} = -10V, I_E = 5\text{mA}, f = 100\text{MHz}$ *

* Transition frequency of the device

●Packaging specifications

Part No.	Package	EMT3	UMT3	SMT3	SPT
	Packaging type	Taping	Taping	Taping	Taping
	Code	TL	T106	T146	TP
	Basic ordering unit (pieces)	3000	3000	3000	5000
DTA143ZE		○	—	—	—
DTA143ZUA		—	○	—	—
DTA143ZKA		—	—	○	—
DTA143ZSA		—	—	—	○

●Electrical characteristic curves




Fig.1 Input voltage vs. output current (ON characteristics)




Fig.2 Output current vs. input voltage (OFF characteristics)




Fig.3 DC current gain vs. output current




Fig.4 Output voltage vs. output current