

AN8808SB

Three-Beam Method Head Amplifier IC for CD (supporting the hologram pick-up)

■ Overview


The AN8808SB is a head amplifier IC supporting the digital servo (supporting the voltage output hologram pick). Combination of this IC and the MN6627XX series allows the rational CD system to be constructed with small number of external parts.


■ Features

- Single supply operation
- I-V amplifier, tracking error amplifier, focus error amplifier, RF amplifier and APC built-in
- Detectors of DO, CROSS, OFTR and vibration built-in
- Combination with the MN6627XX series providing complete automatic adjustment for tracking balance, tracking gain, tracking offset, focus balance, focus gain and focus offset

■ Application

CD player





■ Pin Description

Pin No.	Pin Name	I/O	Function Description
1	P _D	I	Signal input of P _D for LD output monitor
2	LD	O	Connected to base of external Tr for LD drive
3	LDON	I	ON/OFF switching of LD APC
4	C. CRS	—	Capacity connecting pin for CROSS
5	V _{CC}	—	Supply connecting pin
6	RF [−]	I	Reverse rotation input pin of RF Amp. for connecting a resistance
7	RFOUT	O	Output pin of RF Amp. (reverse rotation amp.)
8	RFIN	I	RF AGC input pin
9	C. AGC	—	C-connecting pin for RF AGC loop filter
10	ARF	O	RF output pin after AGC
11	C. ENV	—	C-connecting pin for RF
12	C. EA	—	C-connecting pin for amp.
13	C. SBDO	—	C-connecting pin for low speed detection of dark level DO
14	BDO	O	BDO detection output pin; positive logic
15	C. SBRT	—	C-connecting pin for OFTR low speed detection
16	OFTR	O	OFF TRACK detection output pin; positive logic
17	NRFDET	O	Output pin of RF signal amplitude detection ; negative logic
18	GND	—	Ground pin
19	ENV	O	ENV output pin
20	V _{REF}	O	V _{CC} × 0.5 (V) output pin
21	LD OFF	I	Input pin for forced stop of LD APC
22	VDET	O	Output pin of amplitude detection
23	TEBPF	I	Input pin of amplitude detection
24	CROSS	O	Output pin of TE CROSS detection signal
25	TEOUT	O	Output pin of TE Amp.
26	TE [−]	I	Reverse rotation input pin of TE Amp. for connecting a resistance
27	FEOUT	O	Output pin of FE Amp.
28	FE [−]	I	Reverse rotation input pin of FE Amp. for connecting a resistance
29	FBAL	I	Control signal input pin for FO balance adjustment
30	TBAL	I	Control signal input pin for TE balance adjustment
31	PDFR	—	Resistance-connected pin setting the I – V conversion resistance value of PDE
32	PDER	—	Resistance-connected pin setting the I – V conversion resistance value of PDF
33	PDE	I	Connected to PIN Diode E
34	PDF	I	Connected to PIN Diode F
35	PDBD	I	Connected to B/D of astigmatic 4-division P _D
36	PDAC	I	Connected to A/C of astigmatic 4-division P _D

■ Absolute Maximum Ratings (T_a=25°C)

Parameter	Symbol	Rating	Unit
Supply Voltage	V _{CC}	6	V
Supply Current	I _{CC}	40	mA
Power Dissipation	P _D	240	mW
Operating Ambient Temperature	T _{opr}	−30 ~ + 85	°C
Storage Temperature	T _{stg}	−55 ~ + 125	°C

■ Recommended Operating Range (Ta=25°C)

Parameter	Symbol	Range
Operating Supply Voltage Range	V _{CC}	3.4V ~ 5.5V

■ Electrical Characteristics (Ta=25°C±2°C)

Parameter	Symbol	Condition	min.	typ.	max.	Unit
Total Circuit Current	I _{tot}	V _{CC} =5V	8.8	12.6	16.4	mA
V _{REF} Output Voltage	V _{REF}	V _{CC} =5V	2.20	2.50	2.80	V

Focus Error Amp.

Output Offset Voltage of Focus Error Amp.	V _{FO-OF}	V _{CC} =5V	-350	0	350	mV
Crosstalk Quantity of Focus Error Offset Balance	V _{FO-OF8}	V _{CC} =5V V _{FB} =V _{REF} ±0.9V Applied	-300	—	300	mV
I-V Conversion Gain of Focus Error Amp.	R _{FO}	V _{CC} =5V, V _{FB} =V _{REF}	539	770	1001	kΩ
I-V Conversion Relative Gain of Focus Error Amp.	DR _{FO}	V _{CC} =5V, V _{FB} =V _{REF}	-15	0	15	%
Focus Balance Variable Range 1 – H	B _{FO1-H}	V _{CC} =5V, V _{FB} =V _{REF} +0.9V	0.20	0.31	0.42	—
Focus Balance Variable Range 1 – L	B _{FO1-L}	V _{CC} =5V, V _{FB} =V _{REF} -0.9V	1.23	1.75	2.21	—
Focus Balance Variable Range 2 – H	B _{FO2-H}	V _{CC} =5V, V _{FB} =V _{REF} +0.9V	1.23	1.75	2.21	—
Focus Balance Variable Range 2 – L	B _{FO2-L}	V _{CC} =5V, V _{FB} =V _{REF} -0.9V	0.20	0.31	0.42	—
Frequency Characteristics of Focus Error Amp.	G _{FO}	V _{CC} =5V, f=1kHz, 30kHz Input	-4.5	-3	1.5	dB

Tracking Error Amp.

Output Offset Voltage of Tracking Error Amp.	V _{TR-OF}	V _{CC} =5V	-150	0	150	mV
Crosstalk Quantity of Tracking Error Offset Balance	V _{TR-OFB}	V _{CC} =5V V _{TB} =V _{REF} ±0.9V Applied	-180	—	180	mV
I-V Conversion Gain of Tracking Error Amp.	R _{TR}	V _{CC} =5V, V _{TB} =V _{REF}	1099	1570	2041	kΩ
I-V Conversion Relative Gain of Tracking Error Amp.	DR _{TR}	V _{CC} =5V, V _{TB} =V _{REF}	-15	0	15	%
Tracking Balance Variable Range 1 – H	B _{TR1-H}	V _{CC} =5V, V _{TB} =V _{REF} +0.9V	0.25	0.38	0.51	—
Tracking Balance Variable Range 1 – L	B _{TR1-L}	V _{CC} =5V, V _{TB} =V _{REF} -0.9V	1.19	1.70	2.21	—
Tracking Balance Variable Range 2 – H	B _{TR2-H}	V _{CC} =5V, V _{TB} =V _{REF} +0.9V	1.19	1.70	2.21	—
Tracking Balance Variable Range 2 – L	B _{TR2-L}	V _{CC} =5V, V _{TB} =V _{REF} -0.9V	0.24	0.37	0.50	—
Frequency Characteristics of Tracking Error Amp.	G _{TR}	V _{CC} =5V, f=10kHz, 100kHz	-3.5	-2	-0.5	dB

CROSS Detection

CROSS Output H Level	V _{CR-H}	V _{CC} =5V, V _{TB} =V _{REF} , f=10kHz	4.2	—	—	V
CROSS Output L Level	V _{CR-L}	V _{CC} =5V, V _{TB} =V _{REF} , f=10kHz	—	—	0.8	V

RF-Amp.

RF-Amp. Offset Voltage	V _{RE-OF}	V _{CC} =5V	-75	0	75	mV
RF-Amp. I-V Conversion Gain	R _{RF}	V _{CC} =5V	58	83	108	kΩ
RF-Amp. I-V Conversion Relative Gain 1	DR _{RF}	V _{CC} =5V	-15	0	15	%
RF-Amp. Frequency Characteristics 1 ^{Note)}	G _{RF}	V _{CC} =5V, f=500kHz, 3MHz	-1.6	1.5	3.8	dB

Note) The value may fluctuate by the influence of printed board, socket and etc.

■ Electrical Characteristics (Cont.) (Ta=25°C±2°C)

Parameter	Symbol	Condition	min.	typ.	max.	Unit
AGC						
AGC Max. Gain	G_{AGC}	$V_{CC}=5V$, $f=500kHz$, Sine Wave	10.0	14.5	19.0	dB
AGC Operation Gain	G_{OP-AGC}	$f=500kHz$, $V_{IN}=500mV_{P-P}$	4	6	9	dB
AGC Compressibility	G_{cm-AGC}	$f=500kHz$, $V_{IN}=100mV_{P-P}$	3	6	9	dB
AGC Frequency Characteristics	G_{f-AGC}	$f=3MHz$, $V_{IN}=500mV_{P-P}$	-2	0	2	dB
RFDET						
RFDET Detection Operation	V_{NRF}	$f=500kHz$	0.085	0.125	0.165	V_{P-P}
RFDET H Level	V_{NRF-H}	$f=500kHz$	4.2	—	—	V
RFDET L Level	V_{NRF-L}	$f=500kHz$	—	—	0.8	V
BDO						
BDO Detection Current	I_{BDO}	$V_{CC}=5V$	1.0	1.4	1.8	μA
BDO H Level	V_{BDO-H}	$V_{CC}=5V$, $f=2kHz$ Rectangle Wave	4.2	—	—	V
BDO L Level	V_{BDO-L}	$V_{CC}=5V$, $f=2kHz$ Rectangle Wave	—	—	0.8	V
OFTR						
OFTR Detection Current	I_{OFTR}	$V_{CC}=5V$	1.0	1.4	1.8	μA
OFTR H Level	V_{OFTR-H}	$V_{CC}=5V$, $f=2kHz$ Rectangle Wave	4.2	—	—	V
OFTR L Level	V_{OFTR-L}	$V_{CC}=5V$, $f=2kHz$ Rectangle Wave	—	—	0.8	V
LD – APC						
LD ON H Input Level	V_{LDON-H}	$V_{CC}=5V$	3.5	—	—	V
LD OFF H Input Level	$V_{LDOFF-H}$	$V_{CC}=5V$	3.5	—	—	V
LD ON Operation Voltage	V_{LD}	$V_{CC}=5V$, V_1 : DC Sweep	0.135	0.170	0.205	V
V. Detection						
V. Det. Level (1)	$V_{Det.(1)}$	$V_{CC}=5V$, V_{23} : DC Sweep	52	75	98	mV
V. Det. Level (2)	$V_{Det.(2)}$	$V_{CC}=5V$, V_{23} : DC Sweep	-98	-75	-52	mV
V. Det. H Level	$V_{Det.-H}$	$V_{CC}=5V$, V_{23} : DC Sweep	4.2	—	—	V
V. Det. L Level	$V_{Det.-L}$	$V_{CC}=5V$, V_{23} : DC Sweep	—	—	0.8	V
3TENV						
CENV Detection Current	I_{CENV}	$V_{CC}=5V$	8.5	11	13.5	μA
CEA-ENV Transmission Characteristics	$G_{CEA-ENV}$	$V_{CC}=5V$	21	23	25	dB
CEA Input Impedance	R_{CEA}	$V_{CC}=5V$	6.6	8.3	10	$k\Omega$
ENV Output Impedance	R_{ENV}	$V_{CC}=5V$	6.2	7.8	9.4	$k\Omega$
ENV-Amp. Offset Voltage	V_{OP-ENV}	$V_{CC}=5V$	-85	0	85	mV
CEA-Amp. Operation Voltage	V_{OP-CEA}	$V_{CC}=5V$	55.0	137.5	220.0	mV

■ Operational Description (The values shown below are design values when supply voltage $V_{CC}=5V$.)

• RF Amplifier

As shown in Figure 1, RF signals are generated by three-beam method pick-up. Equivalent resistance to RFOUT (Pin7) is 127k Ω , when resistance between RF- and RFOUT is 12k Ω .




Figure 1 : RF Amplifier

• Focus Error Amplifier

As shown in Figure 2, the operation result of $(A + C) - (B + D)$ is outputted to FEOUT (Pin27). Equivalent resistance to FEOUT is 212k Ω , when resistance between FE and FEOUT is 20k Ω .




Figure 2 : Focus Error Amplifier

The VCBA is for focus balance adjustment. Connecting 47kΩ of an external resistance to Pin29, signal ratio between A + C and B + D can be controlled as shown in Table 1.

Table 1

V_c	$\frac{A + C}{B + D}$	$\frac{B + D}{A + C}$
1.5V	0.14	7.0
2.5V	1.0	1.0
3.5V	7.0	0.14

•Tracking Error Amplifier

As shown in Figure 3, the tracking error amplifier receives the output currents E and F of three-beam method pin photo diode for sub-beam detection, and outputs the operation result of E-F to TEOUT (Pin25).




Figure 3 : Tracking Error Amplifier

Pins31 and 32 are used to make the resistance converting the current to voltage variable. When these pins are directly connected to V_{REF} and $20k\Omega$ of resistance is connected between TE and TE-, and between TE and TEOUT respectively, equivalent resistance to TEOUT is $629k\Omega$.

Table 2

V_C	E/F	F/E
1.5V	0.14	7.0
2.5V	1.0	1.0
3.5V	7.0	0.14

The VCBA is for tracking balance adjustment in the same way of for focus. Table 2 shows the tracking balance ratio under the same conditions as shown in Table 1.

•AGC

In order to absorb the attenuation of RF signal by disk, pick-up dispersion, finger print and other factors, AGC circuit for RF is incorporated.

The input impedance of Pin8 is approx. $27.9k\Omega$. ByPin10 (ARF), the gain-controlled RF-signal is outputted. Input allowable level is approx. $1V_{P-P} \sim 500mV_{P-P} \sim 250mV_{P-P}$, and output is $1V_{P-P}$. Pin9 is a connecting pin with capacity for constructing the AGC loop filter, and it is recommended that the external capacitor of $1\mu F$ around should be connected to it for V_{CC} .




Figure 4 : AGC

•RFDET

The RFDET detects amplitude of RF signal inputted to Pin8. Threshold value is approx. 100mV ($f=500kHz$), and RF Present = L, RF Absent = H are outputted.

•BDO Detection

BDO is detected by the low speed detection circuit and high speed detection circuit. The high speed detection circuit is incorporated. On the other hand, the capacitor of the low speed detection circuit must be connected to Pin13. The capacity value is 2200pF and it is recommended that it should be connected for V_{CC} . When this capacity value of Pin13 is increased, BDO is detected with large RF missing rate. When it is decreased, BDO can be detected with small RF missing rate.

BDO present = H
BDO absent = L

•OFTR Detection

OFTR detection reversely corresponds with BDO detection. However, its detection method is the same as for BDO. Capacitor for the low speed detection must be connected to Pin15. It is recommended that it should be connected to V_{CC} at 2200pF in the same way as for Pin13. The relation between the capacity value and OFTR detection timing is as the same for BDO.

OFTR=H
Off from OFTR=L

•APC




Figure 5 : APC

The reference voltage of LD is approx. 170mV fixed.

•Reference Supply

Servo reference supply is incorporated. Pin20 outputs $V_{CC}/2$, and has approx. 3mA of current capacity for sink/source. It is recommended that it should be given 1μF to 10μF of capacity in addition.

•Vibration Detection

The AN8808SB has a wind comparator of approx. $\pm 75\text{mV}$. Abnormal vibration components of tracking error are detected and the data for whether vibration is present or not is outputted to Pin22.

•Envelope Detection

The envelope detection circuit extracts fluctuation of RF signal required for adjustment of focus balance.

Pins 11 and 12 are connecting pins with capacity for constructing the filter. It is recommended that for Pin 11, a capacitor of 100pF around, and for Pin 12, an external capacitor of 0.027 μ F around should be connected against V_{CC} .

Pin 19 is for output and must have external capacity for constructing the filter, and it is recommended that an external capacitor of 0.027 μ F around should be connected to it for V_{REF} .




Figure 6 : Envelope Detection

•CROSS Detection




Figure 7 : CROSS Detection

Track cross signals are detected from tracking error output. Pin 4 is a connecting pin for constructing the filter, and it is recommended that a capacitor of 2.2 μ F around should be connected to it for V_{REF} .