

## 24-Bit, Multi-Standard D/A Converter for Digital Audio

### Features


- 24 Bit Conversion
- Up to 192 kHz Sample Rates
- 120 dB Dynamic Range
- -100 dB THD+N
- Supports PCM, DSD and External Interpolation filters
- Advanced Dynamic-Element Matching
- Low Clock Jitter Sensitivity
- Digital De-emphasis for 32 kHz, 44.1 kHz and 48 kHz
- External Reference Input

### Description

The CS4397 is a complete high performance 24-bit 48/96/192 kHz stereo digital-to-analog conversion system. The device includes a digital interpolation filter followed by a oversampled multi-bit delta-sigma modulator which drives dynamic-element-matching (DEM) selection logic. The output from the DEM block controls the input to a multi-element switched capacitor DAC/low-pass filter, with fully-differential outputs. This multi-bit architecture features significantly lower out-of-band noise and jitter sensitivity than traditional 1-bit designs, and the advanced DEM guarantees low noise and distortion at all signal levels.

### ORDERING INFORMATION

CS4397-KS -10° to 70° C 28-pin Plastic SOIC  
CDB4397 Evaluation Board



### Advance Product Information

This document contains information for a new product.  
Cirrus Logic reserves the right to modify this product without notice.

**TABLE OF CONTENTS**

<b>1.0 CHARACTERISTICS/SPECIFICATIONS .....</b>	<b>4</b>
ANALOG CHARACTERISTICS.....	4
Dynamic Performance - Single Speed Mode - Fs equal to 48 kHz .....	4
Dynamic Performance - Double Speed Mode - Fs equal to 96 kHz .....	4
Dynamic Performance - Quad-Speed Mode - Fs equal to 192 kHz .....	4
ANALOG CHARACTERISTICS.....	5
Power Supplies .....	5
Analog Output .....	5
Combined Digital and On-chip Analog Filter Response - Single Speed Mode ....	6
Combined Digital and On-chip Analog Filter Response - Double Speed Mode ...	6
Combined Digital and On-chip Analog Filter Response - Quad-Speed Mode .....	6
ANALOG CHARACTERISTICS - DSD MODE .....	7
Dynamic Performance - DSD Mode .....	7
Analog Output - DSD Mode .....	7
Combined Digital and On-chip Analog Filter Response - DSD Mode .....	7
ANALOG CHARACTERISTICS - 8X INTERPOLATOR MODE .....	8
Dynamic Performance Mode .....	8
Analog Output .....	8
Combined Digital and On-chip Analog Filter Response - 8x Interpolator Mode ..	8
DIGITAL CHARACTERISTICS.....	9
ABSOLUTE MAXIMUM RATINGS .....	9
RECOMMENDED OPERATING CONDITIONS.....	9
SWITCHING CHARACTERISTICS .....	10
DSD - SWITCHING CHARACTERISTICS .....	11
8X INTERPOLATOR - SWITCHING CHARACTERISTICS.....	12
SWITCHING CHARACTERISTICS - CONTROL PORT .....	13
I <sup>2</sup> C® Mode .....	13
SPI Mode .....	14
<b>2.0 TYPICAL CONNECTION DIAGRAM .....</b>	<b>15</b>
<b>3.0 REGISTER DESCRIPTION .....</b>	<b>16</b>
3.1 Differential DC offset calibration .....	16
3.2 Soft Mute .....	16
3.3 Mode Select .....	17
3.4 Power DowN .....	17
<b>4.0 PIN DESCRIPTION - PCM MODE .....</b>	<b>18</b>
<b>5.0 PIN DESCRIPTION - DSD MODE .....</b>	<b>23</b>
<b>6.0 PIN DESCRIPTION - 8X INTERPOLATOR MODE .....</b>	<b>24</b>
<b>7.0 APPLICATIONS .....</b>	<b>25</b>
7.1 Recommended Power-up Sequence .....	25
<b>8.0 CONTROL PORT INTERFACE .....</b>	<b>26</b>
8.1 SPI Mode .....	26
8.2 I <sup>2</sup> C Mode .....	26
8.2 Memory Address Pointer (MAP) .....	26
<b>9.0 PARAMETER DEFINITIONS .....</b>	<b>33</b>
<b>10.0 REFERENCES .....</b>	<b>33</b>
<b>11.0 PACKAGE DIMENSIONS .....</b>	<b>34</b>

---

**TABLE OF FIGURES**

Figure 1. Serial Audio Input Timing .....	10
Figure 2. Direct Stream Digital - Serial Audio Input Timing .....	11
Figure 3. Serial Audio Input Timing .....	12
Figure 4. I <sup>2</sup> C Control Port Timing .....	13
Figure 5. SPI Control Port Timing .....	14
Figure 6. Typical Connection Diagram - Hardware Mode (Control Port Mode) .....	15
Figure 7. Control Port Timing, I <sup>2</sup> C Mode .....	27
Figure 8. Control Port Timing, SPI mode .....	27
Figure 9. Single-speed Transition Band .....	29
Figure 10. Single-speed Stopband Rejection .....	29
Figure 11. Single-speed Transition Band .....	29
Figure 12. Single-speed Frequency Response .....	29
Figure 13. Double-speed Stopband .....	29
Figure 14. Double-speed Transition Band .....	29
Figure 15. Double-speed Transition Band .....	29
Figure 16. Double-speed Frequency Response .....	29
Figure 17. Quad-speed Stopband Rejection .....	30
Figure 18. Quad-speed Transition Band .....	30
Figure 19. Quad-speed Transition Band .....	30
Figure 20. Quad-speed Frequency Response .....	30
Figure 21. 8x Interpolator Stop Band .....	30
Figure 22. 8x Interpolator Transition Band .....	30
Figure 23. 8x Interpolator Transition Band .....	30
Figure 24. 8x Interpolator Frequency Response .....	30
Figure 25. DSD Frequency Response .....	31
Figure 26. DSD Transition Band .....	31
Figure 27. DSD Transition Band .....	31
Figure 28. De-Emphasis Curve .....	31
Figure 29. Format 0, Left Justified .....	32
Figure 30. Format 1, I <sup>2</sup> S .....	32
Figure 31. Format 2, Right Justified, 16-Bit Data .....	32
Figure 32. Format 3, Right Justified, 24-Bit Data .....	32
Figure 33. Format 4, 8x Interpolator Mode .....	32

---

**Contacting Cirrus Logic Support**

For a complete listing of Direct Sales, Distributor, and Sales Representative contacts, visit the Cirrus Logic web site at:  
<http://www.cirrus.com/corporate/contacts/>

"The I<sup>2</sup>C-Bus Specification: Version 2.0" Philips Semiconductors, December 1998.  
<http://www.semiconductors.philips.com>

Preliminary product information describes products which are in production, but for which full characterization data is not yet available. Advance product information describes products which are in development and subject to development changes. Cirrus Logic, Inc. has made best efforts to ensure that the information contained in this document is accurate and reliable. However, the information is subject to change without notice and is provided "AS IS" without warranty of any kind (express or implied). No responsibility is assumed by Cirrus Logic, Inc. for the use of this information, nor for infringements of patents or other rights of third parties. This document is the property of Cirrus Logic, Inc. and implies no license under patents, copyrights, trademarks, or trade secrets. No part of this publication may be copied, reproduced, stored in a retrieval system, or transmitted, in any form or by any means (electronic, mechanical, photographic, or otherwise) without the prior written consent of Cirrus Logic, Inc. Items from any Cirrus Logic website or disk may be printed for use by the user. However, no part of the printout or electronic files may be copied, reproduced, stored in a retrieval system, or transmitted, in any form or by any means (electronic, mechanical, photographic, or otherwise) without the prior written consent of Cirrus Logic, Inc. Furthermore, no part of this publication may be used as a basis for manufacture or sale of any items without the prior written consent of Cirrus Logic, Inc. The names of products of Cirrus Logic, Inc. or other vendors and suppliers appearing in this document may be trademarks or service marks of their respective owners which may be registered in some jurisdictions. A list of Cirrus Logic, Inc. trademarks and service marks can be found at <http://www.cirrus.com>.

## 1.0 CHARACTERISTICS/SPECIFICATIONS

**ANALOG CHARACTERISTICS** ( $T_A = 25^\circ\text{C}$ ; Logic "1" =  $V_D = 5\text{ V}$ ;  $V_A = 5\text{V}$ ; Logic "0" = DGND; Full-Scale Output Sine Wave, 997 Hz; MCLK = 12.288 MHz; SCLK = 3.072 MHz, Measurement Bandwidth 10 Hz to 20 kHz, unless otherwise specified. Test load  $R_L = 1\text{ k}\Omega$ ,  $C_L = 10\text{ pF}$ )

Parameter	Symbol	Min	Typ	Max	Unit	
<b>Dynamic Performance - Single Speed Mode - <math>F_s</math> equal to 48 kHz</b>						
Dynamic Range 24-Bit 16-Bit (Note 2)	(Note 1) unweighted A-Weighted		TBD TBD -	117 120 95 98	- - - -	dB dB dB dB
Total Harmonic Distortion + Noise 24-Bit 16-Bit (Note 2)	(Note 1) 0 dB -20 dB -60 dB 0 dB -20 dB -60 dB	THD+N	- - - -	-100 -97 -57 -95 -75 -35	TBD TBD TBD - - -	dB dB dB dB dB dB
<b>Dynamic Performance - Double Speed Mode - <math>F_s</math> equal to 96 kHz</b>						
Dynamic Range 24-Bit 40 kHz bandwidth 16-Bit (Note 2)	(Note 1) unweighted A-Weighted unweighted unweighted A-Weighted		TBD TBD TBD -	117 120 114 92 98	- - - - -	dB dB dB dB dB
Total Harmonic Distortion + Noise 24-Bit 16-Bit (Note 2)	(Note 1) 0 dB -20 dB -60 dB 0 dB -20 dB -60 dB	THD+N	- - - -	-100 -97 -57 -95 -75 -35	TBD TBD TBD - - -	dB dB dB dB dB dB
<b>Dynamic Performance - Quad-Speed Mode - <math>F_s</math> equal to 192 kHz</b>						
Dynamic Range 24-Bit 40 kHz bandwidth 16-Bit (Note 2)	(Note 1) unweighted A-Weighted unweighted unweighted A-Weighted		TBD TBD TBD -	117 120 114 92 98	- - - - -	dB dB dB dB dB
Total Harmonic Distortion + Noise 24-Bit 16-Bit (Note 2)	(Note 1) 0 dB -20 dB -60 dB 0 dB -20 dB -60 dB	THD+N	- - - -	-100 -97 -57 -95 -75 -35	TBD TBD TBD - - -	dB dB dB dB dB dB

- Notes: 1. Triangular PDF dithered data.  
 2. Performance limited by 16-bit quantization noise.

## ANALOG CHARACTERISTICS (Continued)

Parameter	Symbol	VD = 3 V			VD = 5 V			Unit
		Min	Typ	Max	Min	Typ	Max	
<b>Power Supplies</b>								
Supply Current VA = 5 V	normal operation I <sub>A</sub> normal operation I <sub>D</sub> power-down state I <sub>D</sub> + I <sub>A</sub>	-	20	TBD	-	20	TBD	mA
Power Dissipation VA = 5 V	normal operation power-down	-	TBD	TBD	-	TBD	TBD	mW
Power Supply Rejection Ratio (1 kHz) (Note 3) (120 Hz)	PSRR	-	60	-	-	60	-	dB
		-	40	-	-	40	-	dB

Parameter	Symbol	Min	Typ	Max	Unit
<b>Analog Output</b>					
Full Scale Differential Output Voltage		TBD	1.4VREF	TBD	V <sub>pp</sub>
Common Mode Voltage		-	0.5VREF	-	V <sub>DC</sub>
Interchannel Gain Mismatch		-	0.1	-	dB
Gain Drift		-	100	-	ppm/°C
Differential DC Offset		-	2.0	TBD	mV
AC-Load Resistance	R <sub>L</sub>	1	-	-	kΩ
Load Capacitance	C <sub>L</sub>	-	-	100	pF
Interchannel Isolation (1 kHz)		-	90	-	dB

Notes: 3. Valid with the recommended capacitor values on FILT+ and CMOUT as shown in Figure 1. Increasing the capacitance will also increase the PSRR.

## ANALOG CHARACTERISTICS (Continued)

Parameter	Symbol	Min	Typ	Max	Unit
<b>Combined Digital and On-chip Analog Filter Response - Single Speed Mode</b>					
Passband (Note 4) to -0.1 dB corner to -3 dB corner		- -	- -	0.470 0.492	Fs Fs
Frequency Response 10 Hz to 20 kHz		.020	-	+0.015	dB
Passband Ripple		-	-	$\pm 0.0001$	dB
StopBand		.5465	-	-	Fs
StopBand Attenuation (Note 5)		102	-	-	dB
Group Delay (Note 6)	tgd	-	37/Fs	-	s
De-emphasis Error (Note 7) (Relative to 1 kHz)	Fs = 32 kHz Fs = 44.1 kHz Fs = 48 kHz	- - -	- - -	$\pm 0.10$ $\pm 0.10$ $\pm 0.13$	dB dB dB
<b>Combined Digital and On-chip Analog Filter Response - Double Speed Mode</b>					
Passband (Note 4) to -0.1 dB corner to -3 dB corner		0 0	- -	0.448 0.486	Fs Fs
Frequency Response 10 Hz to 20 kHz		-0.017	-	0.035	dB
Passband Ripple		-	-	$\pm 0.0008$	dB
StopBand		.570	-	-	Fs
StopBand Attenuation (Note 5)		82	-	-	dB
Group Delay	tgd	-	20/Fs	-	s
<b>Combined Digital and On-chip Analog Filter Response - Quad-Speed Mode</b>					
Passband (Note 4) to -0.1 dB corner to -3 dB corner		- -	- -	0.385 0.472	Fs Fs
Frequency Response 10 Hz to 20 kHz		0	-	+0.015	dB
Passband Ripple		-	-	$\pm 0.00065$	dB
StopBand		0.635	-	-	Fs
StopBand Attenuation (Note 5)		83	-	-	dB
Group Delay	tgd	-	11/Fs	-	s

- Notes:
4. Response is clock dependent and will scale with Fs. Note that the response plots (*Figures 9-28*) have been normalized to Fs and can be de-normalized by multiplying the X-axis scale by Fs.
  5. For Single-Speed Mode, the Measurement Bandwidth is 0.5465 Fs to 1.4 Fs.  
 For Double-Speed Mode, the Measurement Bandwidth is 0.570 Fs to 1.4 Fs.  
 For Quad-Speed Mode, the Measurement Bandwidth is 0.635 Fs to 1.3 Fs.
  6. Group Delay for Fs=48 kHz 37/48 kHz=770  $\mu$ s
  7. De-emphasis is available only in Single Speed Mode.

**ANALOG CHARACTERISTICS - DSD MODE** ( $T_A = 25^\circ\text{C}$ ; Logic "1" =  $VD = 5\text{ V}$ ;  $VA = 5\text{V}$ ; Logic "0" = AGND; Full-Scale Output Sine Wave, 997 Hz; Measurement Bandwidth 10 Hz to 20 kHz, unless otherwise specified. Test load  $R_L = 1\text{ k}\Omega$ ,  $C_L = 10\text{ pF}$ )

Parameter	Symbol	Min	Typ	Max	Unit
<b><i>Dynamic Performance - DSD Mode</i></b>					
Dynamic Range (Note 1)					
unweighted		TBD	117	-	dB
A-Weighted		TBD	120	-	dB
Total Harmonic Distortion + Noise (Note 1)	THD+N				
0 dB		-	-100	TBD	dB
-20 dB		-	-94	TBD	dB
-60 dB		-	-54	TBD	dB
<b><i>Analog Output - DSD Mode</i></b>					
Full Scale Differential Output Voltage (Note 8)		TBD	1.2VREF	TBD	Vpp
Common Mode Voltage		-	0.5VREF	-	VDC
Interchannel Gain Mismatch		-	0.1	-	dB
Gain Drift		-	100	-	ppm/°C
Differential DC Offset		-	2.0	TBD	mV
<b><i>Combined Digital and On-chip Analog Filter Response - DSD Mode</i></b>					
Passband (Note 4)					
to -0.1 dB corner		-	-	0.95	Fs
to -3 dB corner		-	-	2.70	Fs
Frequency Response 10 Hz to 20 kHz		-0.013	-	0	dB
Group Delay	tgd	-	0.2/Fs	-	s

Notes: 8. Assumes a DSD modulation index of 0.7.

**ANALOG CHARACTERISTICS - 8X INTERPOLATOR MODE** ( $T_A = 25^\circ\text{C}$ ; Logic "1" =  $\text{VD} = 5 \text{ V}$ ;  $\text{VA} = 5\text{V}$ ; Logic "0" = AGND; Full-Scale Output Sine Wave, 997 Hz; Base Band  $\text{Fs} = 48 \text{ kHz}$ ,  $\text{SCLK} = 6.144 \text{ MHz}$ , Measurement Bandwidth 10 Hz to 20 kHz, unless otherwise specified. Test load  $R_L = 1 \text{ k}\Omega$ ,  $C_L = 10 \text{ pF}$ )

Parameter	Symbol	Min	Typ	Max	Unit
<b>Dynamic Performance Mode</b>					
Dynamic Range (Note 1) unweighted A-Weighted		TBD	117	-	dB
		TBD	120	-	dB
Total Harmonic Distortion + Noise (Note 1) 0 dB -20 dB -60 dB	THD+N	-	-100	TBD	dB
		-	-97	TBD	dB
		-	-57	TBD	dB
<b>Analog Output</b>					
Full Scale Differential Output Voltage		TBD	0.7VREF	TBD	Vpp
Common Mode Voltage		-	0.5VREF	-	VDC
Interchannel Gain Mismatch		-	0.1	-	dB
Gain Drift		-	100	-	ppm/ $^\circ\text{C}$
Differential DC Offset		-	2.0	TBD	mV
<b>Combined Digital and On-chip Analog Filter Response - 8x Interpolator Mode</b>					
Passband (Note 4) to -0.1 dB corner to -3 dB corner		-	-	2.10	Fs
		-	-	3.52	Fs
Frequency Response 10 Hz to 20 kHz		-0.0008	-	0	dB
Passband Ripple		-	-	0	dB
StopBand		6.08	-	-	Fs
StopBand Attenuation (Note 9)		56	-	-	dB
Group Delay	tgd	-	0.9/Fs	-	s

Notes: 9. Measurement Bandwidth is 6.08 to 9.6 Fs

**DIGITAL CHARACTERISTICS** ( $T_A = 25^\circ\text{C}$ ;  $VD = 3.0\text{V} - 5.25\text{V}$ )

Parameters		Symbol	Min	Typ	Max	Units
High-Level Input Voltage	$VD = 5\text{ V}$	$V_{IH}$	2.0	-	-	V
	$VD = 3\text{ V}$		2.0	-	-	V
Low-Level Input Voltage	$VD = 5\text{ V}$	$V_{IL}$	-	-	0.8	V
	$VD = 3\text{ V}$		-	-	0.8	V
Input Leakage Current		$I_{in}$	-	-	$\pm 10$	$\mu\text{A}$
Input Capacitance			-	8	-	pF
Maximum MUTEC Drive Current			-	3	-	mA

**ABSOLUTE MAXIMUM RATINGS** (AGND = 0 V, all voltages with respect to ground.)

Parameter	Symbol	Min	Max	Unit
DC Power Supply: Positive Analog Positive Digital Reference Voltage	$VA$	-0.3	6.0	V
	$VD$	-0.3	6.0	V
	$VREF$	-0.3	VA	V
Input Current, Any Pin Except Supplies	$I_{in}$	-	$\pm 10$	mA
Digital Input Voltage	$V_{IND}$	-0.3	$(VD)+0.4$	V
Ambient Operating Temperature (power applied)	$T_A$	-55	125	$^\circ\text{C}$
Storage Temperature	$T_{stg}$	-65	150	$^\circ\text{C}$

WARNING: Operation at or beyond these limits may result in permanent damage to the device. Normal operation is not guaranteed at these extremes.

**RECOMMENDED OPERATING CONDITIONS** (DGND = 0V; all voltages with respect to ground)

Parameter	Symbol	Min	Typ	Max	Unit
DC Power Supply: Positive Digital Positive Analog Reference Voltage	$VD$	3.0	3.3	5.25	V
	$VA$	4.75	5.0	5.25	V
	$VREF$	TBD	5.0	VA	V
Specified Temperature Range	$T_A$	-10	-	70	$^\circ\text{C}$

## SWITCHING CHARACTERISTICS ( $T_A = -10$ to $70^\circ\text{C}$ ; Logic 0 = AGND = DGND; Logic 1 = $V_D = 5.25$ to $3.0$ Volts; $C_L = 20 \text{ pF}$ )

Parameter	Symbol	Min	Typ	Max	Unit
Input Sample Rate (Single-speed mode)	Fs	16	-	50	kHz
(Double-speed mode)	Fs	50	-	100	kHz
(Quad-speed mode)	Fs	100	-	200	kHz
LRCK Duty Cycle		45	50	55	%
MCLK Frequency (Single-speed 256 Fs, Double speed 128 Fs or Quad-speed 64 Fs)		4.096	-	12.8	MHz
MCLK Frequency (Single-speed 384 Fs, Double speed 192 Fs or Quad-speed, 96 Fs)		6.144	-	19.2	MHz
MCLK Frequency (Single-speed 512 Fs, Double speed 256 Fs or Quad-speed, 128 Fs)		8.192	-	25.6	MHz
MCLK Frequency (Single-speed 768 Fs, Double speed 384 Fs or Quad-speed, 192 Fs)		12.288	-	38.4	MHz
MCLK Duty Cycle		40	50	60	%
SCLK Frequency (Single-speed mode)		-	-	256xFs	Hz
(Double-speed mode)		-	-	128xFs	Hz
(Quad-speed mode)		-	-	64xFs	Hz
SCLK rising to LRCK edge delay	$t_{slrd}$	20	-	-	ns
SCLK rising to LRCK edge setup time	$t_{slrs}$	20	-	-	ns
SDATA valid to SCLK rising setup time	$t_{sdlrs}$	20	-	-	ns
SCLK rising to SDATA hold time	$t_{sdh}$	20	-	-	ns




Figure 1. Serial Audio Input Timing

**DSD - SWITCHING CHARACTERISTICS** ( $T_A = -10$  to  $70^\circ\text{C}$ ; Logic 0 = AGND = DGND; Logic 1 =  $V_D = 5.25$  to  $3.0$  Volts;  $C_L = 20 \text{ pF}$ )

Parameter	Symbol	Min	Typ	Max	Unit
Input Bit Rate per Channel (64x Oversampled) (128x Oversampled)		1.024	-	3.2	Mb/s
		2.048	-	6.4	Mb/s
Master Clock Frequency (CLKMODE = 0) (CLKMODE = 1)		4.096	-	12.8	MHz
		6.144	-	19.2	MHz
MCLK Duty Cycle (All DSD modes)		40	-	60	%
DSD_SCLK Pulse Width Low	$t_{sclkL}$	20	-	-	ns
DSD_SCLK Pulse Width High	$t_{sclkH}$	20	-	-	ns
DSD_SCLK Frequency (64x Oversampled) (128x Oversampled)		1.024	-	3.2	MHz
		2.048	-	6.4	MHz
DSD_LI_R valid to DSD_SCLK rising setup time	$t_{sdlrs}$	20	-	-	ns
DSD_SCLK rising to DSD_L or DSD_R hold time	$t_{sdh}$	20	-	-	ns





Figure 2. Direct Stream Digital - Serial Audio Input Timing

**8X INTERPOLATOR - SWITCHING CHARACTERISTICS** ( $T_A = -10$  to  $70^\circ\text{C}$ ;Logic 0 = AGND = DGND; Logic 1 = VD = 5.25 to 3.0 Volts;  $C_L = 20 \text{ pF}$ )

Parameter	Symbol	Min	Typ	Max	Unit
Input Sample Rate (Note 10)	Fs	128	-	400	kHz
MCLK Frequency (MCLK = 32xFs)		4.096	-	12.8	MHz
(MCLK = 48xFs)		6.144	-	19.2	MHz
(MCLK = 64xFs)		8.192	-	25.6	MHz
(MCLK = 96xFs)		12.288	-	28.4	MHz
MCLK Duty Cycle		40	-	50	%
WCKI Duty Cycle		25	-	75	%
BCKI Frequency				32xFs	MHz
BCKI rising to WCKI edge delay	$t_{slrd}$	20	-	-	ns
BCKI rising to WCKI edge setup time	$t_{slrs}$	20	-	-	ns
SDATA valid to BCKI rising setup time	$t_{sdlrs}$	20	-	-	ns
BCKI rising to DIL/DIR hold time	$t_{sdh}$	20	-	-	ns


Notes: 10. Fs refers to the input sample rate to the Digital-to-Analog converter, i.e.  $Fs = 44.1 \text{ kHz} \times 8 = 352.8 \text{ kHz}$ .**Figure 3. Serial Audio Input Timing**

**SWITCHING CHARACTERISTICS - CONTROL PORT**

(TA = 25 °C; VD = 5.25 V to 3.0 Volts; Inputs: logic 0 = AGND, logic 1 = VD, CL = 30 pF)

Parameter	Symbol	Min	Max	Unit
<b>I<sup>2</sup>C® Mode</b>				
SCL Clock Frequency	f <sub>scl</sub>	-	100	KHz
RST Rising Edge to Start	t <sub>irs</sub>	500	-	ns
Bus Free Time Between Transmissions	t <sub>buf</sub>	4.7	-	μs
Start Condition Hold Time (prior to first clock pulse)	t <sub>hdst</sub>	4.0	-	μs
Clock Low time	t <sub>low</sub>	4.7	-	μs
Clock High Time	t <sub>high</sub>	4.0	-	μs
Setup Time for Repeated Start Condition	t <sub>sust</sub>	4.7	-	μs
SDA Hold Time from SCL Falling (Note 11)	t <sub>hdd</sub>	0	-	μs
SDA Setup time to SCL Rising	t <sub>sud</sub>	250	-	ns
Rise Time of Both SDA and SCL Lines	t <sub>r</sub>	-	1	μs
Fall Time of Both SDA and SCL Lines	t <sub>f</sub>	-	300	ns
Setup Time for Stop Condition	t <sub>susp</sub>	4.7	-	μs

Notes: 11. Data must be held for sufficient time to bridge the 300 ns transition time of SCL.


Figure 4. I<sup>2</sup>C Control Port Timing

**SWITCHING CHARACTERISTICS - CONTROL PORT**(T<sub>A</sub> = 25 °C; VD = 5.25 V to 3.0 Volts; Inputs: logic 0 = AGND, logic 1 = VD, C<sub>L</sub> = 30 pF)

Parameter	Symbol	Min	Max	Unit
<b>SPI Mode</b>				
CCLK Clock Frequency	f <sub>sclk</sub>	-	6	MHz
RST Rising Edge to CS Falling	t <sub>srs</sub>	500	-	ns
CCLK Edge to CS Falling (Note 12)	t <sub>spi</sub>	500	-	ns
CS High Time Between Transmissions	t <sub>csh</sub>	1.0	-	μs
CS Falling to CCLK Edge	t <sub>css</sub>	20	-	ns
CCLK Low Time	t <sub>scl</sub>	66	-	ns
CCLK High Time	t <sub>sch</sub>	66	-	ns
CDIN to CCLK Rising Setup Time	t <sub>dsu</sub>	40	-	ns
CCLK Rising to DATA Hold Time (Note 13)	t <sub>dh</sub>	15	-	ns
Rise Time of CCLK and CDIN (Note 14)	t <sub>r2</sub>	-	100	ns
Fall Time of CCLK and CDIN (Note 14)	t <sub>f2</sub>	-	100	ns
CCLK Falling to CDOUT valid	t <sub>ov</sub>	45	-	ns

Notes: 12. t<sub>spi</sub> only needed before first falling edge of CS after RST rising edge. t<sub>spi</sub> = 0 at all other times.

13. Data must be held for sufficient time to bridge the transition time of CCLK.

14. For F<sub>SCK</sub> < 1 MHz**Figure 5. SPI Control Port Timing**

## 2.0 TYPICAL CONNECTION DIAGRAM




Figure 6. Typical Connection Diagram - Hardware Mode (Control Port Mode)

### 3.0 REGISTER DESCRIPTION

#### 3.1 DIFFERENTIAL DC OFFSET CALIBRATION

*Mode Control Register (address 01h)*

7	6	5	4	3	2	1	0
CAL	MUTE	M4	M3	M2	M1	M0	PDN

*Access:*

R/W in I<sup>2</sup>C and SPI.

*Default:*

0 - Disabled

*Function:*

Enabling this function will initiate a calibration to minimize the differential DC offset. This function will be automatically reset following completion of the calibration sequence.

CAL	MODE
0	Disabled : CAL complete
1	Enabled : CAL initiated

Table 1.

#### 3.2 SOFT MUTE

*Mode Control Register (address 01h)*

7	6	5	4	3	2	1	0
CAL	MUTE	M4	M3	M2	M1	M0	PDN

*Access:*

R/W in I<sup>2</sup>C and SPI.

*Default:*

0 - Enabled

*Function:*

The analog outputs will ramp to a muted state when enabled. The ramp requires 1152 left/right clock cycles in Single Speed, 2304 cycles in Double Speed and 4608 cycles in Quad Speed mode. The bias voltage on the outputs will be retained and MUTE will go low at the completion of the ramp period.

The analog outputs will ramp to a normal state when this function transitions from the enabled to disabled state. The ramp requires 1152 left/right clock cycles in Single Speed, 2304 cycles in Double Speed and 4608 cycles in Quad Speed mode. The MUTE will go high immediately on disabling of MUTE.

MUTE	MODE
0	Enabled
1	Disabled

Table 2.

### 3.3 MODE SELECT

*Mode Control Register (address 01h)*

7	6	5	4	3	2	1	0
CAL	MUTE	M4	M3	M2	M1	M0	PDN

*Access:*

R/W in I<sup>2</sup>C and SPI.

*Default:*

00000

*Function:*

The Mode Select pins determine the operational mode of the device as detailed in Tables 9-14. The options include:

Selection of the Digital Interface Format which determines the required relationship between the Left/Right clock, serial clock and serial data as detailed in Figures 29-33

Selection of the standard 15 µs/50 µs digital de-emphasis filter response, Figure 28, which requires re-configuration of the digital filter to maintain the proper filter response for 32, 44.1 or 48 kHz sample rates.

Selection of the appropriate clocking mode to match the input sample rates.

Access to the Direct Stream Digital Mode

Access to the 8x Interpolation Input Mode

### 3.4 POWER DOWN

*Mode Control Register (address 01h)*

7	6	5	4	3	2	1	0
CAL	MUTE	M4	M3	M2	M1	M0	PDN

*Access:*

R/W in I<sup>2</sup>C and SPI.

*Default:*

1 - Powered Down

*Function:*

The analog and digital sections will be placed into a power-down mode when this function is enabled. This bit must be cleared to resume normal operation.

PDN	MODE
0	Disabled
1	Enabled

Table 3.

## 4.0 PIN DESCRIPTION - PCM MODE

Reset	<u>RST</u>	1	28	VREF	Voltage Reference
See Description	<b>M4(AD0/CS)</b>	2	27	FILT+	Reference Filter
See Description	<b>M3(AD1/CDIN)</b>	3	26	FILT-	Reference Ground
See Description	<b>M2(SCL/CCLK)</b>	4	25	CMOUT	Common ModeS Voltage
See Description	<b>M0(SDA/CDOUT)</b>	5	24	AOUTL-	Differential Output
Digital Ground	<b>DGND</b>	6	23	AOUTL+	Differential Output
Digital Power	<b>VD</b>	7	22	VA	Analog Power
Digital Power	<b>VD</b>	8	21	AGND	Analog Ground
Digital Ground	<b>DGND</b>	9	20	AOUTR+	Differential Output
Master Clock	<b>MCLK</b>	10	19	AOUTR-	Differential Output
Serial Clock	<b>SCLK</b>	11	18	<u>AGND</u>	Analog Ground
Left/Right Clock	<b>LRCK</b>	12	17	<u>MUTEC</u>	Mute Control
Serial Data	<b>SDATA</b>	13	16	<u>C/H</u>	Control port/Hardware select
See Description	<b>M1</b>	14	15	<b>MUTE</b>	Soft Mute

### Reset - RST

*Pins 1, Input*

*Function:*

The device enters a low power mode and all internal state machines registers are reset when low. When high, the device will be in a normal operation mode .

<b>RST</b>	<b>DESCRIPTION</b>
0	Enabled
1	Normal operation mode

### Digital Ground - DGND

*Pins 6 and 9, Inputs*

*Function:*

Digital ground reference.

### Digital Power - VD

*Pins 7 and 8, Input*

*Function:*

Digital power supply. Typically 5.0 to 3.0 VDC.

### Master Clock - MCLK

*Pin 10, Input*

*Function:*

The master clock frequency must be either 256x, 384x, 512x or 768x the input sample rate in Single Speed Mode; either 128x, 192x 256x or 384x the input sample rate in Double Speed Mode; or 64x, 96x 128x or 192x the input sample rate in Quad Speed Mode. Tables 4-6 illustrate the standard audio sample rates and the required master clock frequencies.

Sample Rate (kHz)	MCLK (MHz)			
	256x	384x	512x	768x
32	8.1920	12.2880	16.3840	24.5760
44.1	11.2896	16.9344	22.5792	33.8688
48	12.2880	18.4320	24.5760	36.8640

**Table 4. Single Speed (16 to 50 kHz sample rates) Common Clock Frequencies**

Sample Rate (kHz)	MCLK (MHz)			
	128x	192x	256x	384x
64	8.1920	12.2880	16.3840	24.5760
88.2	11.2896	16.9344	22.5792	33.8688
96	12.2880	18.4320	24.5760	36.8640

**Table 5. Double Speed (50 to 100 kHz sample rates) Common Clock Frequencies**

Sample Rate (kHz)	MCLK (MHz)			
	64x	96x	128x	192x
176.4	11.2896	16.9344	22.5792	33.8688
192	12.2880	18.4320	24.5760	36.8640

**Table 6. Quad Speed (100 to 200 kHz sample rates) Common Clock Frequencies****Serial Clock - SCLK***Pin 11, Input**Function:*

Clocks individual bits of serial data into the SDATA pin. The required relationship between the Left/Right clock, serial clock and serial data is defined by either the Mode Control Byte in Control Port Mode or the M0 - M4 pins in Hardware Mode. The options are detailed in Figures 29-33

**Left/Right Clock - LRCK***Pin 12, Input**Function:*

The Left/Right clock determines which channel is currently being input on the serial audio data input, SDATA. The frequency of the Left/Right clock must be at the input sample rate. Audio samples in Left/Right sample pairs will be simultaneously output from the digital-to-analog converter whereas Right/Left pairs will exhibit a one sample period difference. The required relationship between the Left/Right clock, serial clock and serial data is defined by the Mode Control Byte and the options are detailed in Figures 29-33

**Serial Audio Data - SDATA***Pin 13, Input**Function:*

Two's complement MSB-first serial data is input on this pin. The data is clocked into SDATA via the serial clock and the channel is determined by the Left/Right clock. The required relationship between the Left/Right clock, serial clock and serial data is defined by the Mode Control Byte and the options are detailed in Figures 29-33

**Soft Mute - MUTE***Pin 15, Input**Function:*

The analog outputs will ramp to a muted state when enabled. The ramp requires 1152 left/right clock cy-

cles in Single Speed, 2304 cycles in Double Speed and 4608 cycles in Quad Speed mode. The bias voltage on the outputs will be retained and MUTEC will go active at the completion of the ramp period.

The analog outputs will ramp to a normal state when this function transitions from the enabled to disabled state. The ramp requires 1152 left/right clock cycles in Single Speed, 2304 cycles in Double Speed and 4608 cycles in Quad Speed mode. The MUTEC will release immediately on setting MUTE = 1.

The converter analog outputs will mute when enabled. The bias voltage on the outputs will be retained and MUTEC will go active during the mute period.

Mute	DESCRIPTION
0	Enabled
1	Normal operation mode

#### Control Port / Hardware Mode Select - C/H

*Pin 16, Input*

*Function:*

Determines if the device will operate in either the Hardware Mode or Control Port Mode.

C/H	DESCRIPTION
0	Hardware Mode Enabled
1	Control Port Mode Enabled

#### Mute Control - MUTEC

*Pin 17, Output*

*Function:*

The Mute Control pin goes low during power-up initialization, reset, muting, master clock to left/right clock frequency ratio is incorrect or power-down. This pin is intended to be used as a control for an external mute circuit to prevent the clicks and pops that can occur in any single supply system. Use of Mute Control is not mandatory but recommended for designs requiring the absolute minimum in extraneous clicks and pops.

#### Analog Ground - AGND

*Pins 18 and 21, Inputs*

*Function:*

Analog ground reference.

#### Differential Analog Outputs - AOUTR- , AOUTR+ and AOUTL- , AOUTL+

*Pins 19, 20, 23 and 24, Outputs*

*Function:*

The full scale differential analog output level is specified in the Analog Characteristics specifications table.

#### Analog Power - VA

*Pin 22, Input*

*Function:*

Power for the analog and reference circuits. Typically 5VDC.

**Common Mode Voltage - CMOUT***Pin 25, Output**Function:*

Filter connection for internal bias voltage, typically 50% of VREF. Capacitors must be connected from CMOUT to analog ground, as shown in Figure 6. CMOUT has a typical source impedance of 25 kΩ and any current drawn from this pin will alter device performance

**Reference Ground - FILT-***Pin 26, Input**Function:*

Ground reference for the internal sampling circuits. Must be connected to analog ground.

**Reference Filter - FILT+***Pin 27, Output**Function:*

Positive reference for internal sampling circuits. External capacitors are required from FILT+ to analog ground, as shown in Figure 6. The recommended values will typically provide 60 dB of PSRR at 1 kHz and 40 dB of PSRR at 120 Hz. FILT+ is not intended to supply external current.

**Voltage Reference Input- VREF***Pin 28, Input**Function:*

Analog voltage reference. Typically 5VDC.

**HARDWARE MODE****Mode Select - M0, M1, M2, M3, M4***Pins 2, 3, 4, 5 and 14, Inputs**Function:*

The Mode Select pins determine the operational mode of the device as detailed in Tables 9-14. The options include;

Selection of the Digital Interface Format which determines the required relationship between the Left/Right clock, serial clock and serial data as detailed in Figures 29-33

Selection of the standard 15 µs/50 µs digital de-emphasis filter response, Figure 28, which requires re-configuration of the digital filter to maintain the proper filter response for 32, 44.1 or 48 kHz sample rates.

Selection of the appropriate clocking mode to match the input sample rates.

Access to the Direct Stream Digital Mode

Access to the 8x Interpolation Input Mode

**CONTROL PORT MODE****Address Bit 0 / Chip Select - AD0 /  $\overline{CS}$** *Pin 2, Input**Function:*

In I<sup>2</sup>C mode, AD0 is a chip address bit.  $\overline{CS}$  is used to enable the control port interface in SPI mode. The device will enter the SPI mode at anytime a high to low transition is detected on this pin. Once the device has entered the SPI mode, it will remain until either the part is reset or undergoes a power-down cycle.

**Address Bit 1 / Control Data Input - AD1/CDIN**

*Pin 3, Input*

*Function:*

In I<sup>2</sup>C mode, AD1 is a chip address bit. CDIN is the control data input line for the control port interface in SPI mode.

**Serial Control Interface Clock - SCL/CCLK**

*Pin 4, Input*

*Function:*

In I<sup>2</sup>C mode, SCL clocks the serial control data into or from SDA/CDOUT.

In SPI mode, CCLK clocks the serial data into AD1/CDIN and out of SDA/CDOUT.

**Serial Control Data I/O - SDA/CDOUT**

*Pin 5, Input/Output*

*Function:*

In I<sup>2</sup>C mode, SDA is a data input/output. CDOUT is the control data output for the control port interface in SPI mode.

**M1 - Mode Select**

*Pin 14, Input*

*Function:*

This pin is not used in Control Port Mode and must be terminated to ground.

## 5.0 PIN DESCRIPTION - DSD MODE

Refer to PCM mode	RST	1	28	VREF	Refer to PCM mode
Refer to PCM mode	M4(ADO/CS)	2	27	FILT+	Refer to PCM mode
Refer to PCM mode	M3(AD1/CDIN)	3	26	FILT-	Refer to PCM mode
Refer to PCM mode	M2(SCL/CCLK)	4	25	CMOUT	Refer to PCM mode
Refer to PCM mode	M0(SDA/CDOUT)	5	24	AOUTL-	Refer to PCM mode
Refer to PCM mode	DGND	6	23	AOUTL+	Refer to PCM mode
Refer to PCM mode	VD	7	22	VA	Refer to PCM mode
Refer to PCM mode	VD	8	21	AGND	Refer to PCM mode
Refer to PCM mode	DGND	9	20	AOUTR+	Refer to PCM mode
Master Clock	MCLK	10	19	AOUTR-	Refer to PCM mode
DSD Serial Clock	DSD_SCLK	11	18	AGND	Refer to PCM mode
Master Clock Mode	CLKMODE	12	17	MUTEC	Refer to PCM mode
Left Channel Data	DSD_L	13	16	C/H	Refer to PCM mode
Right Channel Data	DSD_R	14	15	MUTE	Refer to PCM mode

### Master Clock - MCLK

*Pin 10, Input*

*Function:*

The master clock frequency must be either 4x or 6x the DSD data rate for 64x oversampled DSD data and 2x or 3x the DSD data rate for 128x oversampled DSD data, refer to Table 7.

### CLKMODE

*Pin 12, Input*

*Function:*

This pin determines the allowable Master Clock to DSD data ratio as defined in Table 7.

**CLKMODE**

DSD Over-Sampling Ratio	64x	CLKMODE	
		0	1
	128x	4x	6x
		2x	3x

**Table 7. MCLK to DSD Data Rate Clock Ratios**

### DSD Serial Clock - DSD\_SCLK

*Pin 11, Input*

*Function:*

Clocks the individual bits of the DSD audio data into the DSD\_L and DSD\_R pins.

### Audio Data - DSD\_L and DSD\_R

*Pins 13 and 14, Inputs*

*Function:*

Direct Stream Digital audio data is clocked into DSD\_L and DSD\_R via the DSD serial clock.

## 6.0 PIN DESCRIPTION - 8X INTERPOLATOR MODE

Refer to PCM mode  
 Refer to PCM mode  
 Refer to PCM mode  
 Refer to PCM mode  
 Refer to PCM mode  
 Refer to PCM mode  
 Refer to PCM mode  
 Refer to PCM mode  
 Refer to PCM mode  
 Master Clock  
 Bit Clock  
 Word Clock  
 Left Channel Data  
 Right Channel Data

<b>RST</b>	•	1	28	<b>VREF</b>	Refer to PCM mode
<b>M4(AD0/CS)</b>		2	27	<b>FILT+</b>	Refer to PCM mode
<b>M3(AD1/CDIN)</b>		3	26	<b>FILT-</b>	Refer to PCM mode
<b>M2(SCL/CCLK)</b>		4	25	<b>CMOUT</b>	Refer to PCM mode
<b>M0(SDA/CDOUT)</b>		5	24	<b>AOUTL-</b>	Refer to PCM mode
<b>DGND</b>		6	23	<b>AOUTL+</b>	Refer to PCM mode
<b>VD</b>		7	22	<b>VA</b>	Refer to PCM mode
<b>VD</b>		8	21	<b>AGND</b>	Refer to PCM mode
<b>DGND</b>		9	20	<b>AOUTR+</b>	Refer to PCM mode
<b>MCLK</b>		10	19	<b>AOUTR-</b>	Refer to PCM mode
<b>BCKI</b>		11	18	<b>AGND</b>	Refer to PCM mode
<b>WCKI</b>		12	17	<b>MUTEC</b>	Refer to PCM mode
<b>DIL</b>		13	16	<b>C/H</b>	Refer to PCM mode
<b>DIR</b>		14	15	<b>MUTE</b>	Refer to PCM mode

### Master Clock - MCLK

*Pin 10, Input*

*Function:*

The master clock frequency must be either 32x, 48x, 64x or 96x the input sample rate. Table 8 illustrates the standard audio sample rates and the required master clock frequencies.

<b>Sample Rate (kHz)</b>	<b>MCLK (MHz)</b>			
	<b>32x</b>	<b>48x</b>	<b>64x</b>	<b>96x</b>
32 x 8	8.1920	12.2880	16.384	24.576
44.1 x 8	11.2896	16.9344	22.579	33.869
48 x 8	12.2880	18.4320	24.576	36.864

Table 8. Common Clock Frequencies

### Bit Clock - BCKI

*Pin 11, Input*

*Function:*

Clocks the individual serial data bits into the DIL and DIR pins. Refer to Figure 33

### Word Clock - WCKI

*Pin 12, Input*

*Function:*

The word clock determines which channel is currently being input on the serial audio data input, SDATA. The frequency of the word clock must be at 8x the baseband sample rate. Refer to Figure 33.

### Serial Audio Data - DIR and DIL

*Pins 12 and 13, Inputs*

*Function:*

Two's complement MSB-first serial data is input on these pins. The data is clocked into DIL and DIR via the bit clock. Refer to Figure 33.

---

## 7.0 APPLICATIONS

### 7.1 Recommended Power-up Sequence

1. Hold  $\overline{\text{RST}}$  low until the power supplies, master, and left/right clocks are stable.
2. Bring  $\overline{\text{RST}}$  high.

## 8.0 CONTROL PORT INTERFACE

The control port is used to load all the internal settings of the CS4397. The operation of the control port may be completely asynchronous to the audio sample rate. However, to avoid potential interference problems, the control port pins should remain static if no operation is required.

The control port has 2 modes: SPI and I<sup>2</sup>C, with the CS4397 operating as a slave device in both modes. If I<sup>2</sup>C operation is desired, AD0/ $\overline{CS}$  should be tied to VD or DGND. If the CS4397 ever detects a high to low transition on AD0/ $\overline{CS}$  after power-up, SPI mode will be selected.

### 8.1 SPI Mode

In SPI mode,  $\overline{CS}$  is the CS4397 chip select signal, CCLK is the control port bit clock, CDIN is the input data line from the microcontroller, CDOUT is the data output and the chip address is 0010000. The data is clocked on the rising edge of CCLK.

Figure 7 shows the operation of the control port in SPI mode. To write to a register, bring  $\overline{CS}$  low. The first 7 bits on CDIN form the chip address, and must be 0010000. The eighth bit is a read/write indicator (R/W). The next 8 bits form the Memory Address Pointer (MAP), which is set to 01h. The next 8 bits are the data which will be placed into the register designated by the MAP.

### 8.2 I<sup>2</sup>C Mode

In I<sup>2</sup>C mode, SDA is a bi-directional data line. Data is clocked into and out of the part by the clock, SCL, with the clock to data relationship as shown in Figure 3. There is no  $\overline{CS}$  pin. Pins AD0 and AD1 form the partial chip address and should be tied to VD or DGND as required. The 7-bit address field, which is the first byte sent to the CS4397, must be 00100(AD1)(AD0) where (AD1) and (AD0) match the setting of the AD0 and AD1 pins. The eighth bit of the address byte is the R/W bit (high for a read, low for a write). If the operation is a write, the next byte is the Memory Address Pointer, MAP, which selects the register to be read or written. The MAP is then followed by the data to be written. If the operation is a read, then the contents of the register pointed to by the MAP will be output after the chip address.

For more information on I<sup>2</sup>C, please see “The I<sup>2</sup>C-Bus Specification: Version 2.0”, listed in the References section.

#### *Memory Address Pointer (MAP)*

7	6	5	4	3	2	1	0
INCR	Reserved	Reserved	Reserved	Reserved	MAP2	MAP1	MAP0
0	0	0	0	0	0	0	1

INCR (Auto MAP Increment Enable)


Default = '0'

0 - Disabled

1 - Enabled


MAP0-2 (Memory Address Pointer)

Default = '001'



MAP = Memory Address Pointer = 0

Figure 7. Control Port Timing, SPI mode



Note: If operation is a write, this byte contains the Memory Address Pointer, MAP.

Figure 8. Control Port Timing, I<sup>2</sup>C Mode

M4	M1 (DIF1)	M0 (DIF0)	DESCRIPTION	FORMAT	FIGURE
0	0	0	Left Justified, up to 24-bit data	0	29
0	0	1	I <sup>2</sup> S, up to 24-bit data	1	30
0	1	0	Right Justified, 16-bit Data	2	31
0	1	1	Right Justified, 24-bit Data	3	33

Table 9. Single Speed (16 to 50 kHz) Digital Interface Format Options

M4	M3 (DEM1)	M2 (DEM0)	DESCRIPTION	FIGURE
0	0	0	32 kHz De-Emphasis	28
0	0	1	44.1 kHz De-Emphasis	28
0	1	0	48 kHz De-Emphasis	28
0	1	1	De-Emphasis Disabled	-

Table 10. Single Speed (16 to 50 kHz) De-Emphasis Options

M4	M3	M2	M1	M0	DESCRIPTION
1	1	1	0	0	Left Justified up to 24-bit data, Format 0
1	1	1	0	1	I <sup>2</sup> S up to 24-bit data, Format 1
1	1	1	1	0	Right Justified 16-bit data, Format 2
1	1	1	1	1	Right Justified 24-bit data, Format 3

Table 11. Double Speed (50 to 100 kHz) Sample Rate Mode Options

M4	M3	M2	M1	M0	DESCRIPTION
1	1	0	0	0	Left Justified up to 24-bit data, Format 0
1	1	0	0	1	I <sup>2</sup> S up to 24-bit data, Format 1
1	1	0	1	0	Right Justified 16-bit data, Format 2
1	1	0	1	1	Right Justified 24-bit data, Format 3


Table 12. Quad (100 to 200 kHz) Sample Rate Mode Options

M4	M3	M2	M1	M0	DESCRIPTION
1	0	0	0	0	Right Justified 20-bit data
1	0	0	0	1	Right Justified 24-bit data


Table 13. 8x Interpolated Input Mode Options

M4	M3	M2	M1	M0	DESCRIPTION
1	0	1	0	0	64x Oversampled DSD
1	0	1	0	1	128x Oversampled DSD


Table 14. Direct Stream Digital Options




**Figure 9. Single-speed Transition Band**




**Figure 10. Single-speed Stopband Rejection**




**Figure 11. Single-speed Transition Band**




**Figure 12. Single-speed Frequency Response**




**Figure 13. Double-speed Stopband**




**Figure 14. Double-speed Transition Band**




**Figure 15. Double-speed Transition Band**




**Figure 16. Double-speed Frequency Response**




**Figure 17. Quad-speed Stopband Rejection**




**Figure 18. Quad-speed Transition Band**




**Figure 19. Quad-speed Transition Band**




**Figure 20. Quad-speed Frequency Response**




**Figure 21. 8x Interpolator Stop Band**




**Figure 22. 8x Interpolator Transition Band**




**Figure 23. 8x Interpolator Transition Band**




**Figure 24. 8x Interpolator Frequency Response**




**Figure 25. DSD Frequency Response**



**Figure 26. DSD Transition Band**



**Figure 27. DSD Transition Band**



**Figure 28. De-Emphasis Curve**




Figure 29. Format 0, Left Justified



Figure 30. Format 1, I<sup>2</sup>S

Figure 31. Format 2, Right Justified, 16-Bit Data




Figure 32. Format 3, Right Justified, 24-Bit Data




Figure 33. Format 4, 8x Interpolator Mode

## 9.0 PARAMETER DEFINITIONS

### Total Harmonic Distortion + Noise (THD+N)

The ratio of the rms value of the signal to the rms sum of all other spectral components over the specified bandwidth (typically 10Hz to 20kHz), including distortion components. Expressed in decibels.

### Dynamic Range

The ratio of the full scale rms value of the signal to the rms sum of all other spectral components over the specified bandwidth. Dynamic range is a signal-to-noise measurement over the specified bandwidth made with a -60 dBFS signal. 60 dB is then added to the resulting measurement to refer the measurement to full scale. This technique ensures that the distortion components are below the noise level and do not effect the measurement. This measurement technique has been accepted by the Audio Engineering Society, AES17-1991, and the Electronic Industries Association of Japan, EIAJ CP-307.

### Interchannel Isolation

A measure of crosstalk between the left and right channels. Measured for each channel at the converter's output with all zeros to the input under test and a full-scale signal applied to the other channel. Units in decibels.

### Interchannel Gain Mismatch

The gain difference between left and right channels. Units in decibels.

### Gain Error


The deviation from the nominal full scale analog output for a full scale digital input.

### Gain Drift

The change in gain value with temperature. Units in ppm/°C.

## 10.0 REFERENCES

- 1) "How to Achieve Optimum Performance from Delta-Sigma A/D & D/A Converters" by Steven Harris. Paper presented at the 93rd Convention of the Audio Engineering Society, October 1992.
- 2) CDB4397 Evaluation Board Datasheet
- 3) "The I<sup>2</sup>C-Bus Specification: Version 2.0" Philips Semiconductors, December 1998.  
<http://www.semiconductors.philips.com>

**11.0 PACKAGE DIMENSIONS****28L SOIC (300 MIL BODY) PACKAGE DRAWING**

DIM	INCHES		MILLIMETERS	
	MIN	MAX	MIN	MAX
A	0.093	0.104	2.35	2.65
A1	0.004	0.012	0.10	0.30
B	0.013	0.020	0.33	0.51
C	0.009	0.013	0.23	0.32
D	0.697	0.713	17.70	18.10
E	0.29G10	0.299	7.40	7.60
1				
e	0.040	0.060	1.02	1.52
H	0.394	0.419	10.00	10.65
L	0.016	0.050	0.40	1.27
$\infty$	0°	8°	0°	8°

**JEDEC #: MS-013**

**CRYSTAL**

---

• Notes •

---

SMART  
Analog™