



## Current Equipment Type



**TYPE 6BR7**  
(Previously Coded 8D5)  
**MINIATURE  
LOW MICROPHONY  
AMPLIFIER PENTODE**



B9A (Noval) Base

The BRIMAR type 6BR7 has been specially designed for use in the early stages of high gain A.F. amplifiers. Its thorough screening and rigid construction ensure low microphony and greatly reduced hum compared with existing types.

## RATINGS

Heater Voltage	...	...	...	...	...	...	...	6.3 volts
Heater Current	...	...	...	...	...	...	...	0.15 amp.
Anode Voltage	...	...	...	...	...	...	...	300 volts max.
Anode Dissipation	...	...	...	...	...	...	...	0.75 watt max.
Screen ( $g_2$ ) Voltage	...	...	...	...	...	...	...	125 volts max.
Screen Dissipation	...	...	...	...	...	...	...	0.3 watt max.

## OPERATING CHARACTERISTICS

(g<sub>3</sub> connected to Cathode)

Anode Voltage	...	...	...	...	100	250	volts
Anode Current	...	...	...	...	2.0	2.1	mA
Screen Voltage	...	...	...	...	100	100	volts
Screen Current	...	...	...	...	0.7	0.6	mA
Control Grid (g <sub>1</sub> ) Voltage	...	...	...	...	-3	-3	volts
Anode Impedance	...	...	...	...	1.5	2.3	meg.
Mutual Conductance	...	...	...	...	1.1	1.25	mA/V

## OPERATION AS RESISTANCE COUPLED AMPLIFIER

Anode and Screen Supply Voltage	...	...	100	200	300	volts
Anode Load Resistor	...	...	0.25	0.25	0.25	meg.
Screen Series Resistor	...	...	1.0	1.0	1.2	meg.
Cathode Bias Resistor	...	...	2,500	1,500	1,200	ohms
Peak Output	...	...	35	70	100	volts
Voltage gain	...	...	90	120	140	—

## INTER-ELECTRODE CAPACITANCES

Input	...	...	...	...	...	...	...	4.0 pF
Output	...	...	...	...	...	...	...	4.0 pF
Control Grid to Anode	...	...	...	...	...	...	...	0.01 pF max.

When connected as a triode (g<sub>3</sub> to Cathode, g<sub>2</sub> to Anode), type 6BR7 has similar characteristics to those of type 6C5G.

Type 6BR7 is a commercial equivalent of the CV2135.

