



**6BW7****Current Equipment Type**
**TYPE 6BW7  
MINIATURE  
HIGH SLOPE  
R.F. PENTODE**


The BRIMAR 6BW7 is a high slope R.F. pentode designed for use in the R.F. Frequency Changer, I.F. and Video stages of television receivers. The valve features high mutual conductance together with a high R.F. input impedance, achieved by the use of two cathode connections. Type 6BW7 will operate from a 180 or 250 volt H.T. rail, making it suitable for both AC/DC and AC operated receivers.

**RATINGS**

|                          |     |     |     |     |     |     |     |                 |
|--------------------------|-----|-----|-----|-----|-----|-----|-----|-----------------|
| Heater Voltage           | ... | ... | ... | ... | ... | ... | ... | 6.3 volts       |
| Heater Current           | ... | ... | ... | ... | ... | ... | ... | 0.3 amp.        |
| Anode Voltage            | ... | ... | ... | ... | ... | ... | ... | 275 volts max.  |
| Anode Dissipation        | ... | ... | ... | ... | ... | ... | ... | 2.75 watts max. |
| Screen ( $g_2$ ) Voltage | ... | ... | ... | ... | ... | ... | ... | 275 volts max.  |
| Screen Dissipation       | ... | ... | ... | ... | ... | ... | ... | 1.2 watts max.  |

**OPERATING CONDITIONS**(Suppressor Grid ( $g_3$ ) connected to Cathode)

|   |     |     |     |     |     |        |             |
|---|-----|-----|-----|-----|-----|--------|-------------|
| Anode Voltage   | ... | ... | ... | ... | ... | 180    | 250 volts   |
| Anode Current   | ... | ... | ... | ... | ... | 9.5    | 9.5 mA      |
| Screen Voltage  | ... | ... | ... | ... | ... | 180    | 250 volts   |
| Screen Current  | ... | ... | ... | ... | ... | 3.5    | 3.5 mA      |
| Cathode Bias Resistor   | ... | ... | ... | ... | ... | 100    | 180 ohms    |
| Mutual Conductance  | ... | ... | ... | ... | ... | 9.3    | 8.5 mA/V    |
| Anode Impedance   | ... | ... | ... | ... | ... | 0.6    | 0.75 meg.   |
| Input Impedance at 50 mc/s.                                     | ... | ... | ... | ... | ... | 14,000 | 16,000 ohms |
| Inner Amplification Factor ( $\mu_{g1}, g_2$ )                  | ... | ... | ... | ... | ... | 70     | 70          |
| Control Grid ( $g_1$ ) Voltage for anode current cut-off ...    | ... | ... | ... | ... | ... | -7     | -8 volts    |
| Suppressor Grid Voltage for $\frac{1}{10}$ normal anode current | ... | ... | ... | ... | ... | -50    | -75 volts   |

**INTER-ELECTRODE CAPACITANCES \***

|                       |     |     |     |     |     |     |     |               |
|-----------------------|-----|-----|-----|-----|-----|-----|-----|---------------|
| Input                 | ... | ... | ... | ... | ... | ... | ... | 9.5 pF        |
| Output                | ... | ... | ... | ... | ... | ... | ... | 3.5 pF.       |
| Control Grid to Anode | ... | ... | ... | ... | ... | ... | ... | 0.01 pF. max. |

\* With no external shield.

**6BW7**

