

★  
T.O. 31R2-4-17-14

**TECHNICAL MANUAL  
NON-ILLUSTRATED PARTS BREAKDOWN**

**RADIO RECEIVER  
Models SP-600-JX-1A,-17  
(Hammarlund)**

THIS PUBLICATION REPLACES T.O. 31R2-4-17-14 DATED 15 JUNE 1957

PUBLISHED UNDER AUTHORITY OF THE SECRETARY OF THE AIR FORCE

Reproduction for nonmilitary use of the information or illustrations contained in this publication is not permitted without specific approval of the issuing service (BuAer or USAF). The policy for use of Classified Publications is established for the Air Force in AFR 205-1 and for the Navy in Navy Regulations, Article 1509.

INSERT LATEST CHANGED PAGES. DESTROY SUPERSEDED PAGES.

## LIST OF EFFECTIVE PAGES

NOTE: The portion of the text affected by the changes is indicated by a vertical line in the outer margins of the page.

TOTAL NUMBER OF PAGES IN THIS PUBLICATION IS 36 CONSISTING OF THE FOLLOWING:

<i>Page No.</i>	<i>Issue</i>
Title .....	Original
A .....	Original
1-1 thru 1-3 .....	Original
1-4 blank .....	Original
2-1 thru 2-29 .....	Original
2-30 blank .....	Original

\* The asterisk indicates pages changed, added, or deleted by the current change.

ADDITIONAL COPIES OF THIS PUBLICATION MAY BE OBTAINED AS FOLLOWS:

USAF ACTIVITIES.—In accordance with T.O. 00-5-2.

USAF

NAVY ACTIVITIES.—Submit request to nearest supply point listed below, using form NavAer 140; NASD, Philadelphia, Pa.; NAS, Alameda, Calif.; NAS, Jacksonville, Fla.; NAS, Norfolk, Va.; NAS, San Diego, Calif.; NAS, Seattle, Wash.; ASD, NSC, Guam.

For listing of available material and details of distribution see Naval Aeronautics Publications Index NavAer 00-500.

## TABLE OF CONTENTS

Section		Page
I	INTRODUCTION .....	1-1
II	SPARE PARTS LIST .....	2-1
	Radio Receiver Model SP-600-JX-1A .....	2-1
	Radio Receiver Model SP-600-JX-17 .....	2-14

## SECTION I

## INTRODUCTION

## 1-1. GENERAL.

1-2. This Non-Illustrated Parts Breakdown for Radio Receiver Models SP-600-JX-1A, -17 lists all the spare parts designated for Organizational, Field, and Depot maintenance levels, as well as the equipment spares supplied with the equipment.

1-3. Section II lists the designated spare parts in alphabetical sequence by item name, and then in numerical order by reference designator or figure and index number. The Signal Corps, Air Force, or manufacturer's part number is given, as well as the Federal stock number. The maintenance levels (Organizational, Field, and Depot) which stock spare parts are indicated. The quantity of equipment spare parts, authorized for initial issue, is indicated for each item.

## 1-4. REFERENCE DESIGNATOR OR FIGURE AND INDEX NUMBER.

1-5. The first column of Section II gives the reference designator of each item; the designators are listed in numerical order. Where no reference designator has been assigned to an item, the column gives a compound numeral representing the figure number of the illustration which shows the part, and the index number of the part on the illustration. The first column is left blank when an item has no reference designator assigned and no illustration is available for identification purposes.

## 1-6. SIGNAL CORPS, AIR FORCE, OR MANUFACTURER'S PART NUMBER.

1-7. The Signal Corps, Air Force, or manufacturer's part number for each item is shown in the second column of Section II.

## 1-8. FSC OR FEDERAL STOCK NUMBER.

1-9. The FSC or Federal stock number for an item is given in the third column of Section II. Where no stock number has been assigned, the Federal stock code and the abbreviation N/L is used to indicate that the stock number is not listed.

## 1-10. ITEM NAME.

1-11. The name of each item is given in the fourth column of Section II. It consists of the noun name and, if necessary, a modifying adjective. All item names are in alphabetical order according to item name, and then in numerical order according to reference designator. A full description of the item may be secured from a Federal stock list.

## 1-12. QUANTITIES.

1-13. The fifth column "Quantities" of Section II is divided into four subcolumns. The first subcolumn "O" indicates Organizational maintenance level. The second subcolumn "F" indicates Field maintenance level. The third subcolumn "D" indicates Depot maintenance level. The fourth subcolumn "ES" indicates the quantity of equipment spares supplied with each equipment. The symbol X in a particular subcolumn indicates that spare parts are authorized for use at that maintenance level.

## 1-14. HOW TO USE THE NON-ILLUSTRATED PARTS BREAKDOWN.

1-15. Before using the Non-Illustrated Parts Breakdown, determine the item name of the part. Identify the part further by determining its reference designator. If the part has no reference designator, locate the figure number of the illustration showing the part, and the index number of the part on the illustration. The technical order containing the required illustration for identification of parts is given in paragraph 1-24 below. When no reference designator or figure and index number is available, the item name and part number can be used for identification.

1-16. After identification of the required part, refer to the Spare Parts List (Section II) and find the item name (the names are listed in alphabetical order). Locate the reference designator or figure and index number for the particular item.

1-17. When the part has been located, list other pertinent information given for the part, including the Signal Corps, Air Force, or manufacturer's part number; the Federal stock number; and the document from which the information was obtained.

1-18. Check the "Quantities" column to determine whether any equipment spares are available for immediate use. Requisition the required part from the maintenance level which can supply the part, as indicated in the "Quantities" subcolumn.

1-19. Exercise care in filling out requisitions. Accuracy is important. Be sure to include all information listed for the part. Avoid costly delays resulting from inadequate information.

#### 1-20. ABBREVIATIONS.

1-21. Abbreviations used in the Spare Parts List (Section II) and their meanings are as follows:

AF	audio frequency
bfo	beat-frequency oscillator
Co	Company
dia	diameter
FIIN	Federal Item Identification Number
FSC	Federal Stock Code
hex	hexagon
IF	intermediate frequency
in.	inch (es)
Inc	Incorporated
Jan	Joint Army-Navy
lg	long
mc	megacycle (s)
N/L	not listed
No.	number (s)
osc	oscillator
Reqn	Requisition
RF	radio frequency
Sig C	Signal Corps
T. O.	Technical Order
USAF	United States Air Force

#### 1-22. LIST OF MANUFACTURERS.

1-23. Manufacturers of Radio Receiver Models SP-600-JX-1A, -17 parts are listed below, together with the Federal Supply Codes used in the text.

Federal Supply Code	Manufacturer	Federal Supply Code	Manufacturer
00656	Aerovox Corp New Bedford, Mass.	80058	Communication Electronic Nomenclature Subpanel Washington, D. C.
01009	Alden Products Co Brockton, Mass.	80130	Times Facsimile Corp New York, N. Y.

Federal Supply Code	Manufacturer
80583	Hammarlund Mfg Co New York, N. Y.
81349	Military Specification
81350	Joint Army-Navy Specification
88044	Aeronautical Standards Group Depts of Air Force and Navy Washington, D. C.

1-24. ILLUSTRATIONS USED FOR IDENTIFICATION OF PARTS.

1-25. No illustrations are referenced in this technical order.

1-26. STOCK NUMBER VERIFICATION.

1-27. All FSC or Federal stock numbers listed in Non-Illustrated Parts Breakdown have been verified prior to issuance of this publication. Before requisitioning a part, the appropriate Federal stock list should be checked for the latest Federal stock number.

1-28. As a result of the Reduction of Items Program, certain items are no longer stocked. These items are replaced by suitable substitutes wherever possible. In the Spare Parts List (Section II) the new part number is listed wherever a replacement has been published. In the case where the new part number radically differs from the old number, both numbers are listed, with the phrase "For replacement use"



SECTION II  
SPARE PARTS LIST

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number	Class Code	FIIN	Item Name	Quantities O F D ES
--	---	----------------------	------------	------	-----------	------------------------

## RADIO RECEIVER, MODEL SP-600-JX-1A

E1	75173 No. 2-50 80583 No. M4904-5	5940-501-5683			BOARD, terminal	0 0 X 0
E2	80583 No. 31141-1	5940-242-7945			BOARD, terminal	0 0 X 0
E5 E8	80583 No. K16650-9	5940 N/L			BOARD, terminal	0 0 X 0
E7	71785 No. 1520 80583 No. K16650-12	5940-329-5502			BOARD, terminal	0 0 X 0
E9 E10 E11 E12	80583 No. K16650-11 74887 No. 2423	5940-242-7950			BOARD, terminal	0 0 X 0
E13 E14	71785 No. 56A 80583 No. K16650-10	5940-665-9848			BOARD, terminal	0 0 X 0
E15 E16	80583 No. 31163-G1	5820-503-7837			BOARD, terminal	0 0 X 0
E17	80583 No. 31162-G1	5820-518-6399			BOARD, terminal	0 0 X 0
E18	80583 No. 31454-G1	5940-665-8783			BOARD, terminal	0 0 X 0
	80583 No. K31425	5820-338-6301			BRACE, crossarm	0 0 0 0
	80583 No. K31202	5820-696-1994			BRACKET (movable support for main pointer)	0 0 0 0
	80583 No. K31240	5820-338-6299			BRACKET (supports BFO tuning shaft)	0 0 0 0
	80583 No. K31484	5910-355-8631			BRACKET (supports filter capacitor)	0 0 0 0
	80583 No. 6143-1	5995-090-1119			CABLE ASSEMBLY, power	0 0 0 0
	80583 No. K31173	5820-327-5181			CAM (2-1/2 in. lg)	0 0 X 0
	80583 No. K31201-G1	5820-327-5180			CAM (3-1/16 in. lg)	0 0 X 0
C3 C24	80583 No. 23012-1	5910-250-5404			CAPACITOR, fixed	X X X 2
C5 C27						
C19 C29						
C20 C40						
C21 C41						
C22 C42						
C23 C43	(Continued)					

Section II  
Spare Parts List

T.O. 31R2-4-17-14

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number Class Code	Item Name	Quantities O F D E S
C44 C100	(Continued)			
C47 C105	80583 No. 23012-1	5910-250-5404	CAPACITOR, fixed	X X X 2
C49 C115				
C61 C116				
C64 C121				
C66 C122				
C68 C127				
C70 C135				
C71 C153				
C72 C154				
C73 C155				
C74				
C6	81349 No. CM20C200J	5910-101-5575	CAPACITOR, fixed	0 0 X 0
C30				
C50				
C8	81349 No. CM30D242J	5910-190-7588	CAPACITOR, fixed	0 0 X 0
C32				
C52				
C132				
C9	81349 No. CM20C330J	5910-112-8189	CAPACITOR, fixed	0 0 X 0
C33				
C53				
C11	81349 No. CM30C152G	5910-161-6289	CAPACITOR, fixed	0 0 X 0
C17				
C35				
C55				
C12	81350 No. CC20CH070F	5910-270-3036	CAPACITOR, fixed	0 0 X 0
C138				
C145				
C14	81349 No. CM30C102G	5910-101-4018	CAPACITOR, fixed	0 0 X 0
C15	81350 No. CC20HH150J	5910-280-6492	CAPACITOR, fixed	0 0 X 0
C139				
C18	81349 No. CM20C101G	5910-101-5614	CAPACITOR, fixed	0 0 X 0
C25				
C45				
C75				
C110				
C112				
C113				
C37	80583 No. 23071-59	5910-249-4172	CAPACITOR, fixed	0 0 X 0
C57				
C67				
C39	81349 No. CM20C510G	5910-101-4886	CAPACITOR, fixed	0 0 X 0
C54				
C99				
C134				
C60	81350 No. CC21UJ120J	5910-101-4847	CAPACITOR, fixed	0 0 X 0
C88				

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	ES
C62	81349 No. CM30D222J		5910-101-5789	CAPACITOR, fixed	0	0	X	0
C63	81349 No. CM20C390J		5910-669-4235	CAPACITOR, fixed	0	0	X	0
C69 C107 C117 C124	81349 No. CM20D221G		5910-101-4705	CAPACITOR, fixed	0	0	X	0
C77	81349 No. CM30C332G		5910-101-5802	CAPACITOR, fixed	0	0	X	0
C78	80583 No. 23071-67		5910-648-8256	CAPACITOR, fixed	0	0	X	0
C79 C80	81350 No. CC21UJ050C		5910-195-7820	CAPACITOR, fixed	0	0	X	0
C82	80583 No. 23072-53		5910-242-6071	CAPACITOR, fixed	0	0	X	0
C83	81350 No. CM20B100K		5910-668-2940	CAPACITOR, fixed	0	0	X	0
C85	81350 No. CM30C122G		5910-668-3194	CAPACITOR, fixed	0	0	X	0
C87	80583 No. 23071-50		5910-249-4174	CAPACITOR, fixed	0	0	X	0
C89	80583 No. 23071-64		5910-648-7931	CAPACITOR, fixed	0	0	X	0
C91	80583 No. 23071-71		5910-648-9482	CAPACITOR, fixed	0	0	X	0
C92	81350 No. CC21UJ510F		5910-669-2957	CAPACITOR, fixed	0	0	X	0
C93	80583 No. 23071-63		5910-648-8253	CAPACITOR, fixed	0	0	X	0
C95	80583 No. 23071-69		5910-242-6067	CAPACITOR, fixed	0	0	X	0
C96	80583 No. 23072-52		5910-520-8318	CAPACITOR, fixed	0	0	X	0
C97	80583 No. 23071-58		5910-249-4173	CAPACITOR, fixed	0	0	X	0
C98 C102 C103 C104 C106 C108 C109	C118 C123 C136 C146 C148 C156 C157	80583 No. 23013-1 00656 No. P488-223M	5910-649-2272	CAPACITOR, fixed	X	X	X	1
C114	81350 No. CM20C271G		5910-668-3028	CAPACITOR, fixed	0	0	X	0
C119 C125	81350 No. CM20D301G		5910-668-2947	CAPACITOR, fixed	0	0	X	0
C120 C126	81349 No. CM30C132G		5910-280-7131	CAPACITOR, fixed	0	0	X	0
C128 C151 C158 C159 C160	81350 No. CE63C100H		5910-112-7845	CAPACITOR, fixed	X	X	X	1

Section II  
Spare Parts List

T.O. 31R2-4-17-14

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number	Item Name	Quantities O F D E S
		Class Code	FIIN	
C129A	81350 No. CP53B6EF503V	5910-112-7259	CAPACITOR, fixed	0 0 X 0
C129B				
C152A				
C152B				
C130	81350 No. CC21UJ270J	5910-112-8278	CAPACITOR, fixed	0 0 X 0
C131	81350 No. CM20C431G	5910-668-0925	CAPACITOR, fixed	0 0 X 0
C133				
C137	81350 No. CP28AIEC254M	5910-667-7562	CAPACITOR, fixed	0 0 X 0
C140	81350 No. CM35A102J	5910-668-3099	CAPACITOR, fixed	0 0 X 0
C141	81350 No. CC26SL101K	5910-112-8228	CAPACITOR, fixed	0 0 X 0
C142				
C143	81350 No. CM35B512J	5910-668-2971	CAPACITOR, fixed	0 0 X 0
C147				
C149				
C144	81349 No. CP28A1EF503K	5910-112-7486	CAPACITOR, fixed	0 0 X 0
C150	00656 No. 1441WP252K 80583 No. 23070-40	5910-648-7945	CAPACITOR, fixed	0 0 X 0
C161A	81350 No. CE33F200R	5910-160-2399	CAPACITOR, fixed	X X X 1
C161B				
C161C				
C1A	80583 No. P34001G1	5910-318-3580	CAPACITOR, variable	0 0 X 0
C1B				
C1C				
C1D				
C1E				
C1F				
C1G				
C1H				
C11	80583 No. 11776-1	5910-546-9200	CAPACITOR, variable	0 0 X 0
C65	80583 No. 11726-109	5910-546-9199	CAPACITOR, variable	0 0 X 0
	80583 No. K31463-1	5820-030-3078	CHART, recording	0 0 0 0
	80583 No. K11823-206 79963 No. 78	5340-234-0415	CLAMP (for 1/4 in. dia cable)	0 0 X 0
	80583 No. K11823-1 79963 No. 139	5340-329-1864	CLAMP (for 3/16 in. dia cable)	0 0 X 0
	80583 No. K11823-3 79963 No. 79	5340-329-1865	CLAMP (for 1/2 in. dia cable)	0 0 X 0
	80583 No. K31485-1	5915-334-3465	CLAMP, capacitor	0 0 X 0
	07387 No. 926C13	5960-249-4930	CLAMP, electron tube	0 0 X 0
	80583 No. 926B16	5960-151-7568	CLAMP, electron tube	0 0 X 0

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	E
	80583 No. 926B31		5960-249-4928	CLAMP, electron tube	0	0	X	0
	07387 No. 146		5940-260-0427	CLIP, one terminal	0	0	X	0
	07387 No. 33		5940-204-5693	CLIP, two terminal	0	0	X	0
L1	80583 No. K31245		5950-646-2869	COIL, RF	0	0	X	0
L2	80583 No. K31249		5950-518-1938	COIL, RF	0	0	X	0
L3	80583 No. K31252		5950-518-1942	COIL, RF	0	0	X	0
L4	80583 No. K31255		5950-518-1936	COIL, RF	0	0	X	0
L5	80583 No. K31258		5950-503-2801	COIL, RF	0	0	X	0
L6	80583 No. K31261		5950-503-2802	COIL, RF	0	0	X	0
L7	80583 No. 15612-1		5950-387-0480	COIL, RF	0	0	X	0
L14								
L24								
L35								
L8	80583 No. K31246		5950-268-8987	COIL, RF	0	0	X	0
L15								
L9	80583 No. K31250		5950-518-1990	COIL, RF	0	0	X	0
L16								
L10	80583 No. K31253		5950-518-1932	COIL, RF	0	0	X	0
L17								
L11	80583 No. K31256		5950-518-1944	COIL, RF	0	0	X	0
L18								
L12	80583 No. K31259		5950-645-2804	COIL, RF	0	0	X	0
L19								
L13	80583 No. K31262		5950-518-1951	COIL, RF	0	0	X	0
L20								
L21	80583 No. K15617		5950-648-5577	COIL, RF	0	0	X	0
L22	76493 No. 4540		5950-188-6450	COIL, RF	0	0	X	0
L23	80583 No. K15619-1 76493 No. 4541		5950-234-9991	COIL, RF	0	0	X	0
L25	80583 No. K31244		5950-518-1925	COIL, RF	0	0	X	0
L26	80583 No. K31248		5950-518-1939	COIL, RF	0	0	X	0
L27	80583 No. K31251		5950-518-1941	COIL, RF	0	0	X	0
L28	80583 No. K31254		5950-648-3582	COIL, RF	0	0	X	0
L29	80583 No. K31257		5950-648-5556	COIL, RF	0	0	X	0
L30	80583 No. K31260		5950-646-2956	COIL, RF	0	0	X	0

Section II  
Spare Parts List

T. O. 31R2-4-17-14

Reference Designator or: Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	E
L33	80583 No. 31111-1	5950-538-7202		COIL, RF	0	0	X	0
L34	80583 No. 31115-1	5950-648-3106		COIL, RF	0	0	X	0
L36	80583 No. 31093-1	5950-646-2520		COIL, RF	0	0	X	0
L37	80583 No. 31057-1	5950-648-3429		COIL, RF	0	0	X	0
L40	80583 No. 31026-1	5950-646-3486		COIL, RF	0	0	X	0
L43								
L44	80583 No. 31073-1	5950-538-6992		COIL, RF	0	0	X	0
L45	80583 No. 31072-1	5950-648-5558		COIL, RF	0	0	X	0
L46	80583 No. 15615-1	5950-648-3703		COIL, RF	0	0	X	0
L47	80583 No. K15616-1	5950-648-5559		COIL, RF	0	0	X	0
L48	80583 No. 15611 74956 No. CFIR 3/8-50/38	5950-645-9284		COIL, RF	0	0	X	0
L49	80583 No. 15613	5950-646-1514		COIL, RF	0	0	X	0
L50								
L38	80583 No. 31067-1	5950-518-2775		COIL ASSEMBLY, IF	0	0	X	0
L39								
L41								
L42								
J1	81350 No. UG-103/U	5935-500-8580		CONNECTOR, receptacle	0	0	X	0
J2	80583 No. K16111-1 02660 No. 83-1R	5935-259-0148		CONNECTOR, receptacle	0	0	X	0
J4	80583 No. K35013-1	5935-321-4931		CONNECTOR, receptacle	0	0	X	0
J5	01009 No. 402AC							
P2	81350 No. UG-102/U	5935-149-4018		CONNECTOR, plug	0	0	X	0
P4	02660 No. 83-1SP	5935-196-9704		CONNECTOR, plug	0	0	X	0
P3	80058 No. UG-104/U	5935-149-3128		CONNECTOR, male and female	0	0	X	0
S1A	80583 No. K31234-G1	5820-696-1993		CONTACT ASSEMBLY	0	0	X	0
S1B								
S1C								
S1D								
	80583 No. 31013-1	5950-565-9200		CORE, adjustable (1 1/8 in. lg)	0	0	X	0
	80583 No. 31090-1	5950-565-9202		CORE, adjustable (green)	0	0	X	0
	80583 No. 31018-1	5950-565-9201		CORE, adjustable (white)	0	0	X	0
	80583 No. 415-2	5910-668-4141		COUPLING, flexible	0	0	0	0
	80583 No. 415-3	5910-349-0066		COUPLING, flexible	0	0	0	0

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	ES
	80583 No. K31275		5975-289-7064	COUPLING, rigid	0	0	0	0
Y7	80583 No. K31130-1 71034 No. VX2		5955-646-4841	CRYSTAL UNIT, quartz	0	0	X	0
Y8	80583 No. 31471-1 71034 No. VX4		5955-275-6415	CRYSTAL UNIT, quartz	0	0	X	0
	80583 No. 31227G2		5355-668-6966	DIAL (audio gain control)	0	0	X	0
	80583 No. 31227G4		5355-668-6989	DIAL (bfo control)	0	0	X	0
	80583 No. 31227G3		5355-668-6967	DIAL (crystal phasing control)	0	0	X	0
	80583 No. 31227G1		5355-668-6965	DIAL (RF gain control)	0	0	X	0
	80583 No. 31227G5		5355-668-6988	DIAL (selectivity control)	0	0	X	0
	80583 No. P31283-1		5820-327-5214	ESCUTHEON	0	0	X	0
	80583 No. K31169		5820-327-5216	FLYWHEEL	0	0	X	0
F1	80583 No. K15928-8 71400 No. AGC3 For replacement use 81349 No. F02G3R00A		5920-010-6652	FUSE, cartridge	X	X	X	6
F2	71400 No. GJV-3/8		5920-284-6434	FUSE, cartridge	X	X	X	4
	80583 No. 31039-1		5820-342-2882	GEAR (24 teeth)	0	0	X	0
	80583 No. K31037-1		5820-289-7465	GEAR (36 teeth)	0	0	X	0
	80583 No. K31095G1		5820-304-8943	GEAR (48 teeth)	0	0	X	0
	80583 No. K31096G1		5820-288-5850	GEAR (48 teeth)	0	0	X	0
	80583 No. K31097G1		5820-288-5852	GEAR (93 teeth)	0	0	X	0
	80583 No. K31036-1		5820-289-7464	GEAR (144 teeth)	0	0	X	0
	80583 No. K31098G1		5820-305-1014	GEAR (168 teeth)	0	0	X	0
	80583 No. 31287		5820-305-1010	GEAR ASSEMBLY (24 teeth)	0	0	X	0
	80583 No. K31052G1		5820-313-7230	GEAR ASSEMBLY (24 teeth)	0	0	X	0
	80583 No. K31288G1		5820-305-1016	GEAR ASSEMBLY (36 teeth)	0	0	X	0
	80583 No. K31150G1		5820-305-1015	GEAR ASSEMBLY (168 teeth)	0	0	X	0
	80583 No. K31281		5355-518-0910	GLASS, main or vernier dial	0	0	0	0
	80583 No. K31282		5355-668-4515	GLASS, freq band dial	0	0	0	0
	80583 No. K15923-1 71400 No. HKP		5920-280-4039	HOLDER, fuse (marked FUSE)	0	0	0	0

Section II  
Spare Parts List

T.O. 31R2-4-17-14

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number Class Code FIIN	Item Name	Quantities O F D E S
	80583 No. K15923-4 71400 No. HKP	5920-280-4039	HOLDER, fuse (marked FUSE SPARE)	0 0 0 0
	80583 No. K31415	5820-509-1023	HOLDER, spring	0 0 0 0
	80583 No. K16619-5	5970-503-4557	INSULATOR, bushing	0 0 X 0
	20093 No. CC-80W-PP	5940-549-2652	INSULATOR, feed-thru	0 0 X 0
J3	80583 No. K5066-1 37942 No. 5C-1	5935-221-5821	JACK, telephone	0 0 X 0
	80583 No. 31434-G1	5355-668-4566	KNOB (3/4 in. dia)	0 0 X 0
	80583 No. 31215-1	5355-667-7495	KNOB (3 in. dia)	0 0 X 0
I1	24446 No. 47	6240-155-8706	LAMP, incandescent	X X X 2
I2				
I3				
I4				
M1	80583 No. 4903-2	0801 6625-648-9374	METER, audio level	0 0 X 0
	80583 No. K31276	5820-302-3784	MOUNTING, indicator	0 0 0 0
T6	80583 No. M31106	5820-505-2187	OSCILLATOR SUBASSEMBLY	0 0 X 0
	80583 No. M31131-1	5820-505-2776	OSCILLATOR SUBASSEMBLY (3.5 megacycles)	0 0 0 0
	80583 No. P31219-3	5820-518-4827	PANEL	0 0 0 0
	80583 No. P31166	5820-329-0542	PLATE, base	0 0 0 0
	80583 No. K31423	5820-392-6107	PLATE, pressure	0 0 0 0
	80583 No. T8222	5120-348-4775	PLIERS	0 0 X 0
	80583 No. K31186-1	5355-668-6096	POINTER, indicator (frequency range)	0 0 X 0
	80583 No. K31199-1	5355-668-5983	POINTER, indicator (main or vernier dial)	0 0 X 0
	80583 No. K31422	5307-515-8092	POST, supporting (filter choke)	0 0 0 0
	80583 No. K31424	5307-208-0438	POST, supporting (transformer)	0 0 0 0
L51	80583 No. 31030-2	5950-648-3233	REACTOR, fixed	0 0 X 0
L52	80583 No. 31031-2	5950-648-3232	REACTOR, fixed	0 0 X 0
R1	81349 No. RC20GF514J	5905-279-2516	RESISTOR, fixed	0 0 X 0
R13				
R26				
R2	81349 No. RC20GF103J	5905-185-8510	RESISTOR, fixed	0 0 X 0
R12				
R44				
R52	(Continued)			

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number	Item Name	Quantities O F D ES
		Class Code	FIIN	
R57	(Continued)			
R70	81349 No. RC20GF103J	5905-185-8510	RESISTOR, fixed	0 0 X 0
R82				
R90				
R91				
R92				
R4	81349 No. RC20GF102J	5905-195-6806	RESISTOR, fixed	0 0 X 0
R6				
R16				
R29				
R30				
R83				
R102				
R5	81349 No. RC20GF511J	5905-279-3511	RESISTOR, fixed	0 0 X 0
R15				
R32				
R103				
R104				
R105				
R106				
R107				
R108				
R109				
R110				
R7	81349 No. RC20GF510J	5905-279-3517	RESISTOR, fixed	0 0 X 0
R8				
R17				
R18				
R9	81349 No. RC20GF240J	5905-279-1750	RESISTOR, fixed	0 0 X 0
R19				
R10	81349 No. RC20GF220J	5905-279-3519	RESISTOR, fixed	0 0 X 0
R11				
R20				
R21				
R22	81349 No. RC20GF473J	5905-254-9201	RESISTOR, fixed	0 0 X 0
R23				
R64				
R65				
R77				
R24	81349 No. RC20GF181J	5905-279-3514	RESISTOR, fixed	0 0 X 0
R25				
R27	81349 No. RC20GF151J	5905-299-1541	RESISTOR, fixed	0 0 X 0
R28	81349 No. RC20GF682J	5905-279-3503	RESISTOR, fixed	0 0 X 0
R31	81349 No. RC20GF222J	5905-279-1876	RESISTOR, fixed	0 0 X 0
R37				
R41				
R46				
R49				
R54				
R58	(Continued)			

Section II  
Spare Parts List

T.O. 31R2-4-17-14

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number	Class Code	FIIN	Item Name	Quantities
						O F D ES
(Continued)						
R80	81349 No. RC20GF222J	5905-279-1876			RESISTOR, fixed	0 0 X 0
R34 R67	81349 No. RC20GF104J	5905-195-6761			RESISTOR, fixed	0 0 X 0
R35 R68						
R38 R75						
R43 R76						
R51 R81						
R56 R100						
R62						
R36 R96	81349 No. RC20GF223J	5905-171-2004			RESISTOR, fixed	0 0 X 0
R40	81349 No. RC32GF203J	5905-299-2021			RESISTOR, fixed	0 0 X 0
R42 R50 R55	81349 No. RC20GF100J	5905-190-8883			RESISTOR, fixed	0 0 X 0
R45	81349 No. RC20GF241J	5905-279-2593			RESISTOR, fixed	0 0 X 0
R46 R94	81349 No. RC20GF112J	5905-279-3508			RESISTOR, fixed	0 0 X 0
R47 R66	81349 No. RC20GF183J	5905-279-3500			RESISTOR, fixed	0 0 X 0
R59	81349 No. RC32GF222J	5905-279-1723			RESISTOR, fixed	0 0 X 0
R60 R61	81349 No. RC20GF105J	5905-279-2513			RESISTOR, fixed	0 0 X 0
R63	81349 No. RC20GF273J	5905-279-3499			RESISTOR, fixed	0 0 X 0
R72	81349 No. RC20GF203J	5905-192-0649			RESISTOR, fixed	0 0 X 0
R73	81349 No. RC32GF563J	5905-299-2011			RESISTOR, fixed	0 0 X 0
R78 R98	81349 No. RC20GF474J	5905-279-2515			RESISTOR, fixed	0 0 X 0
R79	81349 No. RC20GF681J	5905-195-6791			RESISTOR, fixed	0 0 X 0
R85	81350 No. RW32G252	5905-518-5254			RESISTOR, fixed	0 0 X 0
R86 R89 R95	81349 No. RC20GF823J	5905-279-3494			RESISTOR, fixed	0 0 X 0
R87 R88	81349 No. RC20GF124J	5905-192-3981			RESISTOR, fixed	0 0 X 0
R97	81349 No. RC20GF335J	5905-279-1883			RESISTOR, fixed	0 0 X 0
R99	81349 No. RC32GF361J	5905-279-2546			RESISTOR, fixed	0 0 X 0
R69 R74	81350 No. RA20A1SA102AK	5905-108-6369			RESISTOR, variable	0 0 X 0

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	ES
R84	01121 No. J1U5042P2032 80583 No. K15342-11	5905-502-8414		RESISTOR, variable	0	0	X	0
R93	01121 No. JS1U5031P3048 80583 No. K15342-21	5905-109-1581		RESISTOR, variable	0	0	X	0
R101	01121 No. J2U2532SD3032 80583 No. K15342-4	5905-259-3653		RESISTOR, variable	0	0	X	0
	80583 No. K31177	5820-327-5257		ROLLER, lever	0	0	X	0
	80583 No. M31105	5950-547-8324		SHIELD, coil (for 3.5 mc osc assembly)	0	0	0	0
	80583 No. M31133	5950-547-8097		SHIELD, coil (for T6 BFO assembly)	0	0	X	0
	80583 No. K31376	5820-332-4992		SHIELD, end (for T1)	0	0	0	0
	80583 No. K31378	5950-547-8325		SHIELD, transformer (for T1)	0	0	0	0
	80583 No. M31019	5950-547-8323		SHIELD, transformer (for T2, T4, or T5)	0	0	0	0
	80583 No. M31132	5950-504-8914		SHIELD, transformer (for T3)	0	0	0	0
	81350 No. TS102U01	5960-262-0015		SHIELD, electron tube	0	0	X	0
	81350 No. TS102U02	5960-272-9094		SHIELD, electron tube	0	0	X	0
	81350 No. TSF0T105	5960-504-8379		SHIELD, electron tube	0	0	X	0
	81350 No. TS102U03	5960-272-9092		SHIELD, electron tube	0	0	X	0
	80583 No. K31449-1	5960-351-4812		SHIELD ASSEMBLY, tube	0	0	X	0
X21	80583 No. K16092-5 72825 No. 9006	5935-536-1784		SOCKET, crystal	0	0	X	0
X1 X11	80583 No. K15989-28A	5935-232-3758		SOCKET, tube	0	0	X	0
X2 X12	81350 No. TS102C01							
X6 X13								
X7 X14								
X8 X15								
X9 X18								
X10 X20								
X3	80583 No. K16082-1	5935-501-6893		SOCKET, tube	0	0	X	0
X17	71785 No. 9859							
X19								
X4	80583 No. K15989-5 72825 No. 102M	5935-197-3964		SOCKET, tube	0	0	X	0
X5	80583 No. K15989 81350 No. TS102P01	5935-260-0516		SOCKET, tube	0	0	X	0

Section II  
Spare Parts List

T.O. 31R2-4-17-14

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number Class Code FIIN	Item Name	Quantities O F D ES
X16	80583 No. K16100-1 81350 No. TS103P01	5935-160-1365	SOCKET, tube	0 0 X 0
	80583 No. K31004-1	5340-355-9533	SPRING (0.351 in. lg)	0 0 0 0
	80583 No. K31003	5820-327-5274	SPRING (0.937 in. lg)	0 0 X 0
	80583 No. K31417	5820-509-1021	SPRING (25/32 in. lg)	0 0 X 0
	80583 No. K31239-1	5820-327-5278	SPRING (1-1/32 in. lg)	0 0 0 0
	80583 No. K31125	5340-200-6333	SPRING (1-13/32 in. lg)	0 0 X 0
	80583 No. K31279-1	5820-320-82	SPRING (1-7/16 in. lg)	0 0 0 0
	80583 No. K31023	5820-351-3843	SPRING (1-15/32 in. lg)	0 0 0 0
	80583 No. K31205	5820-547-3817	SPRING (1-1/2 in. lg)	0 0 X 0
	80583 No. K31278	5820-342-9418	SPRING (1-5/8 in. lg)	0 0 0 0
	80583 No. K31126	5820-320-8290	SPRING (2-11/16 in. lg)	0 0 X 0
S2	80583 No. K15879-1	5930-548-5711	SWITCH, rotary	0 0 X 0
S3	80583 No. K31469-1	5930-333-7471	SWITCH, rotary	0 0 X 0
S4	80583 No. 15862-1	5930-334-3690	SWITCH, rotary	0 0 X 0
S5A S5B S5C	80583 No. P15856-1	5930-296-4285	SWITCH, rotary	0 0 X 0
S6	15605 No. 8280	5930-259-9707	SWITCH, toggle	0 0 X 0
S7	80583 No. K15866-1 15605 No. 8360 For replacement use 81350 No. ST52P	5930-050-2708	SWITCH, toggle	0 0 X 0
S8	80583 No. K15867-1 15605 No. 8363	5930-296-9034	SWITCH, toggle	0 0 X 0
S9	81350 No. ST42D	5930-229-3390	SWITCH, toggle	0 0 X 0
S11	04009 No. 81057N	5930-296-9667	SWITCH, toggle	0 0 X 0
T7	80583 No. 31086-2	5950-646-2788	TRANSFORMER, AF	0 0 X 0
T1	80583 No. M31183	5950-647-7866	TRANSFORMER, IF	0 0 X 0
T2	80583 No. M31116	5950-648-5891	TRANSFORMER, IF	0 0 X 0
T3	80583 No. M31114	5950-648-6704	TRANSFORMER, IF	0 0 X 0
T4 T5	80583 No. M31102-G1	5950-647-8389	TRANSFORMER, IF	0 0 X 0
L31	80583 No. 31103-1	5950-648-6951	TRANSFORMER, IF	0 0 X 0

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number	Item Name	Quantities
		Class Code	FIIN	O F D ES
L32	80583 No. 31069-1	5950-504-8951	TRANSFORMER, IF	0 0 X 0
L53	80583 No. 31488-1	5950-547-8366	TRANSFORMER, IF	0 0 X 0
T8	80583 No. P31029-2	5950-646-0501	TRANSFORMER, power	0 0 X 0
V1	81349 No. JAN 5749/6BA6W	5960-264-2089	TUBE, electron	X X X 14
V2				
V7				
V9				
V10				
V11				
V12				
V3	81349 No. JAN 6AC7W	5960-166-7666	TUBE, electron	X X X 2
V4	81349 No. JAN 6C4	5960-503-4871	TUBE, electron	X X X 6
V8				
V13				
V5	81349 No. JAN 5750/6BE6W	5960-264-3002	TUBE, electron	X X X 4
V6				
V14	81349 No. JAN 6AL5	5960-296-9478	TUBE, electron	X X X 6
V15				
V20				
V16A	81349 No. JAN 6189/12AU7WA	5960-636-2218	TUBE, electron	X X X 2
V16B				
V17	81349 No. JAN 6V6GTY	5960-116-9927	TUBE, electron	X X X 2
V18	81349 No. JAN 0A2WA	5960-503-4880	TUBE, electron	X X X 2
V19	81349 No. JAN 5R4WGA	5960-262-1703	TUBE, electron	X X X 2
E1	80583 No. 31387	5950-648-0297	TUNER, RF	0 0 X 0
E2	80583 No. 31390	5950-648-0496	TUNER, RF	0 0 X 0
E3	80583 No. 31393	5950-648-0382	TUNER, RF	0 0 X 0
E4	80583 No. 31396	5820-568-0246	TUNER, RF	0 0 X 0
E5	80583 No. 31399	5950-647-9194	TUNER, RF	0 0 X 0
E6	80583 No. 31405-1	5950-647-9485	TUNER, RF	0 0 X 0
E8	80583 No. 31386	5950-647-9363	TUNER, RF	0 0 X 0
E9	80583 No. 31389	5950-648-0379	TUNER, RF	0 0 X 0
E16				
E10	80583 No. 31392	5950-648-0386	TUNER, RF	0 0 X 0
E17				
E11	80583 No. 31395	5950-645-2927	TUNER, RF	0 0 X 0
E18				

Section II  
Spare Parts List

T.O. 31R2-4-17-14

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	ES
E12	80583 No. 31398	5950-647-9193		TUNER, RF	0	0	X	0
E19								
E13	80583 No. 31404-1	5820-505-1479		TUNER, RF	0	0	X	0
E20								
E25	80583 No. 31385	5820-253-6747		TUNER, RF	0	0	X	0
E26	80583 No. 31388	5950-648-0495		TUNER, RF	0	0	X	0
E27	80583 No. 31391	5950-648-0385		TUNER, RF	0	0	X	0
E28	80583 No. 31394	5950-645-2928		TUNER, RF	0	0	X	0
E29	80583 No. 31397	5950-645-2992		TUNER, RF	0	0	X	0
E30	80583 No. 31403	5820-247-5419		TUNER, RF	0	0	X	0
	80583 No. K11806-2	5120-198-5398		WRENCH (1/16 in. hex drive)	0	0	0	0
	80583 No. K11806-3	5120-224-2504		WRENCH (5/64 in. hex drive)	0	0	0	0
	80583 No. K11806-4	5120-242-7410		WRENCH (3/32 in. hex drive)	0	0	0	0

RADIO RECEIVER DIVERSITY MODEL SP-600-JX-17

	80583 No. 16642-1	5935-295-4326	ADAPTER	0	0	X	0
E2	80583 No. 31141-1	5940-242-7945	BOARD, terminal	0	0	0	0
E3	80583 No. 31480-1	5820-502-6137	BOARD, terminal	0	0	0	0
E5	80583 No. 16650-12 71785 No. 1520	5940-329-5502	BOARD, terminal	0	0	0	0
E6	80583 No. 16650-11	5940-242-7950	BOARD, terminal	0	0	0	0
E7	74887 No. 2423						
E8							
E9							
E10							
E14	80583 No. 16650-10 71785 No. 56A	5940-665-9848	BOARD, terminal	0	0	0	0
E15	80583 No. 31163G1	5820-503-7837	BOARD, terminal	0	0	0	0
E16							
E17	80583 No. 31162G1	5820-518-6399	BOARD, terminal	0	0	0	0
E18	80583 No. 31454G1	5940-665-8783	BOARD, terminal	0	0	0	0
	80583 No. K31425-1	5820-338-6301	BRACE, crossarms	0	0	0	0
	80583 No. K31202-1	5820-696-1994	BRACKET	0	0	0	0

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number	Item Name	Quantities
		Class Code	FIIN	O F D ES
	80583 No. K31240-1	5820-338-6299	BRACKET	0 0 0 0
	80583 No. K31484-1	5910-355-8631	BRACKET, capacitor	0 0 0 0
	80583 No. K31173-1	5820-327-5181	CAM (2-1/2 in. lg)	0 0 X 0
	80583 No. 31201G1	5820-327-5180	CAM (3-1/16 in. lg)	0 0 X 0
C3 C68	80583 No. 23012-1	5910-250-5404	CAPACITOR, fixed	X X X 2
C5 C70				
C19 C71				
C20 C72				
C21 C73				
C22 C74				
C23 C101				
C24 C105				
C27 C115				
C29 C116				
C40 C121				
C41 C122				
C42 C127				
C43 C135				
C44 C153				
C47 C154				
C49 C155				
C60 C166				
C61 C175				
C66 C176				
C6 C30	81350 No. CM15C200J	5910-666-6608	CAPACITOR, fixed	0 0 X 0
C50				
C8 C32	81349 No. CM30D242J	5910-190-7588	CAPACITOR, fixed	0 0 X 0
C52 C132				
C9 C33	81350 No. CM15C330J	5910-227-0659	CAPACITOR, fixed	0 0 X 0
C53				
C11 C17	81349 No. CM30C152G	5910-161-6289	CAPACITOR, fixed	0 0 X 0
C35 C55				
C12	81350 No. CC20CH070F	5910-270-3036	CAPACITOR, fixed	0 0 X 0
C14 C62	81349 No. CM30C102G	5910-101-4018	CAPACITOR, fixed	X X X 1
C156 C169				
C15 C145	81350 No. CC20HH150J	5910-280-6492	CAPACITOR, fixed	0 0 X 0
C171				
C18 C25	81349 No. CM15C101G (Continued)	5910-636-2153	CAPACITOR, fixed	X X X 1

Section II  
Spare Parts List

T.O. 31R2-4-17-14

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number	Item Name	Quantities O F D E S
		Class Code	FIIN	
C37	(Continued)			
C57	81349 No. CM15C101G	5910-636-2153	CAPACITOR, fixed	X X X 1
C75				
C91				
C110				
C112				
C113				
C39	81350 No. CM15C510G	5910-280-7020	CAPACITOR, fixed	X X X 1
C59				
C95				
C99				
C134				
C45	81349 No. CM15C590F	5910-668-0065	CAPACITOR, fixed	0 0 X 0
C63	81349 No. CM15C390J	5910-668-0056	CAPACITOR, fixed	0 0 X 0
C65	80583 No. 11726-109	5910-546-9199	CAPACITOR, fixed	0 0 X 0
C67	80583 No. 23071-59	5910-249-4172	CAPACITOR, fixed	0 0 X 0
C69	81350 No. CM15C221G	5910-643-9191	CAPACITOR, fixed	0 0 X 0
C107				
C117				
C124				
C77	81349 No. CM30C332G	5910-101-5802	CAPACITOR, fixed	0 0 X 0
C78	80583 No. 23071-67	5910-648-8256	CAPACITOR, fixed	0 0 X 0
C79	81350 No. CC21UJ050C	5910-195-7820	CAPACITOR, fixed	0 0 X 0
C80				
C167				
C168				
C82	80583 No. 23072-53	5910-242-6071	CAPACITOR, fixed	0 0 X 0
C83	80583 No. 23003-2B For replacement use 81349 No. CM15B100K	5910-174-9964	CAPACITOR, fixed	0 0 X 0
C85	81350 No. CM30C122G	5910-668-3194	CAPACITOR, fixed	0 0 X 0
C87	80583 No. 23071-50	5910-249-4174	CAPACITOR, fixed	0 0 X 0
C88	81350 No. CC21UJ120J	5910-101-4847	CAPACITOR, fixed	0 0 X 0
C170				
C89	80583 No. 23071-64	5910-648-7931	CAPACITOR, fixed	0 0 X 0
C92	81350 No. CC21UJ510F	5910-669-2957	CAPACITOR, fixed	0 0 X 0
C138				
C139				
C93	80583 No. 23071-63	5910-648-8253	CAPACITOR, fixed	0 0 X 0
C96	80583 No. 23072-52	5910-520-8318	CAPACITOR, fixed	0 0 X 0
C97	80583 No. 23071-58	5910-249-4173	CAPACITOR, fixed	0 0 X 0

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	ES
C98 C118	80583 No. 23013-1		5910-649-2272	CAPACITOR, fixed		X	X	X 1
C100 C123	00656 No. P488-223M							
C102 C136								
C103 C146								
C104 C148								
C106 C156								
C108 C157								
C109 C162								
C114	80583 No. 23003-104C		5910-648-8064	CAPACITOR, fixed		0	0	X 0
C119	80583 No. 23003-105C		5910-666-7881	CAPACITOR, fixed		0	0	X 0
C125	81349 No. CM15C301G							
C120	81349 No. CM30C132G		5910-280-7131	CAPACITOR, fixed		0	0	X 0
C126								
C128	81350 No. CE63C100H		5910-112-7845	CAPACITOR, fixed		X	X	X 1
C151								
C158								
C159								
C160								
C129AB	81350 No. CP53B6EF503V		5910-112-7259	CAPACITOR, fixed		0	0	X 0
C130	81350 No. CC21UJ270J		5910-112-8278	CAPACITOR, fixed		0	0	X 0
C131	81350 No. CM20C431G		5910-668-0925	CAPACITOR, fixed		0	0	X 0
C133								
C140								
C164								
C137	81350 No. CP28AIEC254M		5910-667-7562	CAPACITOR, fixed		0	0	X 0
C141	81350 No. CC26SL101K		5910-112-8228	CAPACITOR, fixed		0	0	X 0
C142								
C143	81350 No. CM35B512J		5910-668-2971	CAPACITOR, fixed		0	0	X 0
C147								
C149								
C144	81350 No. CP28A1EG503K		5910-263-7385	CAPACITOR, fixed		0	0	X 0
C150	00656 No. 1441WP252K		5910-648-7945	CAPACITOR, fixed		0	0	X 0
C152	81350 No. CM35D103J		5910-668-2803	CAPACITOR, fixed		0	0	X 0
C174								
C177								
C161ABC	81350 No. CE33F200R		5910-160-2399	CAPACITOR, fixed		0	0	X 0
C163	81349 No. CP27A3EF254K		5910-280-6673	CAPACITOR, fixed		0	0	X 0
C172	81349 No. CM20C101G		5910-101-5614	CAPACITOR, fixed		0	0	X 0
C173	81350 No. CM20D651F		5910-668-1704	CAPACITOR, fixed		0	0	X 0
C1A	80583 No. P34001G1		5910-318-3580	CAPACITOR, variable		0	0	X 0
C1B								
C1C	(Continued)							

Section II  
Spare Parts List

T.O. 31R2-4-17-14

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number Class Code	Item Name	Quantities O F D ES
C1D	(Continued)			
C1E	80583 No. P34001G1	5910-318-3580	CAPACITOR, variable	0 0 X 0
C1F				
C1G				
C1H				
C111	80583 No. 11776-1	5910-546-9200	CAPACITOR, variable	0 0 X 0
	80583 No. 31463-1	5820-030-3078	CHART, recording	0 0 X 0
	80583 No. 11823-1 79963 No. 139	5340-329-1864	CLAMP (5/8 in. lg)	0 0 X 0
	80583 No. 11823-3 79963 No. 79	5340-329-1865	CLAMP (7/8 in. lg)	0 0 X 0
	80583 No. 11823-206 79963 No. 78	5340-234-0415	CLAMP (11/16 in. lg)	0 0 X 0
	80583 No. 16120-3 88044 No. AN3057-6B	5935-259-2019	CLAMP (1-5/64 in. lg)	0 0 X 0
	80583 No. 16120-5 88044 No. AN3057-10B	5935-280-1936	CLAMP (1-1/8 in. lg)	
	80583 No. 31485-1	5915-334-3465	CLAMP (for 1-3/8 in. capacitor)	0 0 X 0
	80583 No. 31496-1 71400 No. 4099	5940-283-7169	CLAMP, electrical (7/16 in. lg)	0 0 X 0
	80583 No. 11855-1 07387 No. 33	5940-204-5693	CLIP (1-3/4 in. lg)	0 0 X 0
	80583 No. 11816-2 07387 No. 103	5940-321-5135	CLIP (1 in. lg)	0 0 X 0
L1	80583 No. 31245-1	5950-646-2869	COIL, RF	0 0 X 0
L2	80583 No. 31249-1	5950-518-1938	COIL, RF	0 0 X 0
L3	80583 No. 3152-1	5950-518-1942	COIL, RF	0 0 X 0
L4	80583 No. 31255-1	5950-518-1936	COIL, RF	0 0 X 0
L5	80583 No. 31258-1	5950-503-2801	COIL, RF	0 0 X 0
L6	80583 No. 31261-1	5950-503-2802	COIL, RF	0 0 X 0
L7	80583 No. 15612-1	5950-387-0480	COIL, RF	0 0 X 0
L14				
L24				
L8	80583 No. 31246-1	5950-268-8987	COIL, RF	0 0 X 0
L15				
L9	80583 No. 31250-1	5950-518-1940	COIL, RF	0 0 X 0
L16				

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	ES
L10	80583 No. 31253-1		5950-518-1932	COIL, RF	0	0	X	0
L17								
L11	80583 No. 31256-1		5950-518-1944	COIL, RF	0	0	X	0
L18								
L12	80583 No. 31259-1		5950-645-2804	COIL, RF	0	0	X	0
L19								
L13	80583 No. 31262-1		5950-518-1951	COIL, RF	0	0	X	0
L20								
L21	80583 No. 15617-1		5950-648-5553	COIL, RF	0	0	X	0
L22	80583 No. 15621-1		5950-648-3583	COIL, RF	0	0	X	0
L23	80583 No. 15623-1		5950-538-6996	COIL, RF	0	0	X	0
L25	80583 No. 31244-1		5950-518-1925	COIL, RF	0	0	X	0
L26	80583 No. 31248-1		5950-518-1939	COIL, RF	0	0	X	0
L27	80583 No. 31251-1		5950-518-1941	COIL, RF	0	0	X	0
L28	80583 No. 31254-1		5950-638-3582	COIL, RF	0	0	X	0
L29	80583 No. 31257-1		5950-648-5556	COIL, RF	0	0	X	0
L30	80583 No. 31260-1		5950-646-2956	COIL, RF	0	0	X	0
L33	80583 No. 31111-1		5950-538-7202	COIL, RF	0	0	X	0
L34	80583 No. 31115-1		5950-648-3106	COIL, RF	0	0	X	0
L35	80583 No. 15622-1		5950-648-3587	COIL, RF	0	0	X	0
L36	80583 No. 31093-1		5950-646-2520	COIL, RF	0	0	X	0
L37	80583 No. 31057-1		5950-648-3429	COIL, RF	0	0	X	0
L40	80583 No. 31026-1		5950-646-3486	COIL, RF	0	0	X	0
L43								
L44	80583 No. 31073-1		5950-538-6992	COIL, RF	0	0	X	0
L45	80583 No. 31072-1		5950-648-5558	COIL, RF	0	0	X	0
L46	80583 No. 15615-2		5950-648-3703	COIL, RF	0	0	X	0
L47	80583 No. 15616-1		5950-648-5559	COIL, RF	0	0	X	0
L48	80583 No. 15611-1 74956 No. CFIR 3/8-50/38		5950-645-9284	COIL, RF	0	0	X	0
L49	80583 No. 15613-1		5950-646-1514	COIL, RF	0	0	X	0
L50								
L38	80583 No. 31067-1		5950-518-2775	COIL ASSEMBLY, IF	0	0	X	0
L39								
L41	(Continued)							

Section II  
Spare Parts List

T.O. 31R2-4-17-14

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	ES
(Continued)								
L42	80583 No. 31067-1		5950-518-2775	COIL ASSEMBLY, IF	0	0	X	0
	80583 No. 16112-1		5935-321-4840	CONNECTOR, male and female	0	0	X	0
	80063 No. M359A							
J1	02660 No. 83-1R		5935-259-0148	CONNECTOR, receptacle	0	0	X	0
J2								
J6								
J7								
J8								
J5	81349 No. AN3102A18-3P		5935-149-3435	CONNECTOR, receptacle	0	0	X	0
P1	02660 No. 83-1SP		5935-196-9704	CONNECTOR, receptacle	0	0	X	0
P2								
P6								
P7								
P8								
P4	81349 No. AN3108B14S-2P		5935-262-9344	CONNECTOR, plug	0	0	X	0
P5	81349 No. AN3108B18-3S		5935-276-9412	CONNECTOR, plug	0	0	X	0
S1A	80583 No. 31234G1		5820-696-1993	CONTACT ASSEMBLY	0	0	X	0
S1B								
S1C								
S1D								
(3 uses)	80583 No. 31090-1		5950-565-9202	CORE, adjustable tuning (1-5/16 in. lg)	0	0	X	0
(9 uses)	80583 No. 31018-1		5950-565-9201	CORE, adjustable tuning (1-5/16 in. lg)	X	X	X	1
(24 uses)	80583 No. 31013-1		5950-565-9200	CORE, adjustable tuning (1-1/8 in. lg)	X	X	X	1
(1 use)	80583 No. 415-2		5910-668-4141	COUPLING, flexible	0	0	X	0
(3 uses)	80583 No. 415-3		5910-349-0066	COUPLING, flexible	0	0	X	0
	80583 No. 31275-1		5975-289-7064	COUPLING, rigid	0	0	X	0
	80583 No. 31494-1		5920-636-4758	COVER, fuse	0	0	X	0
Y7	80583 No. 31130-1 71034 No. VX2		5955-646-4891	CRYSTAL UNIT, quartz	0	0	X	0
Y8	80583 No. 31471-2 71034 No. VX4		5955-275-6415	CRYSTAL UNIT, quartz	0	0	X	0
	80583 No. 31227G1		5355-668-6965	DIAL (RF gain control)	0	0	X	0
	80583 No. 31227G2		5355-668-6966	DIAL (audio gain control)	0	0	X	0
	80583 No. 31227G3		5355-668-6967	DIAL (crystal phasing control)	0	0	X	0
	80583 No. 31227G4		5355-668-6989	DIAL (bfo control)	0	0	X	0

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	ES
	80583 No. 31227G5		5355-668-6988	DIAL (selectivity control)	0	0	X	0
	80583 No. 31283-1		5820-327-5214	ESCUTCHEON, dial	0	0	X	0
	80583 No. 31169-1		5820-327-5216	FLYWHEEL, timing dial	0	0	X	0
F1	80583 No. 1583-1 71400 No. MDL 1-6/10		5920-131-9819	FUSE, cartridge		X	X	X 5
F2	80583 No. 15928-13 71400 No. AGC 3/8		5920-280-8628	FUSE, cartridge		X	X	X 5
	80583 No. 31036-1		5820-289-7464	GEAR (144 teeth)	0	0	X	0
	80583 No. 31037-1		5820-289-7465	GEAR (36 teeth)	0	0	X	0
(2 uses)	80583 No. 31039-1		5820-342-2882	GEAR (24 teeth)	0	0	X	0
	80583 No. 31095G1		5820-304-8943	GEAR (48 teeth)	0	0	X	0
	80583 No. 31096G1		5820-288-5850	GEAR (48 teeth)	0	0	X	0
	80583 No. 31097G1		5820-288-5852	GEAR (93 teeth)	0	0	X	0
	80583 No. 31098G1		5820-305-1014	GEAR (168 teeth)	0	0	X	0
	80583 No. 31052-G1		5820-313-7230	GEAR ASSEMBLY (24 teeth)	0	0	X	0
	80583 No. 31150-G1		5820-305-1015	GEAR ASSEMBLY (168 teeth)	0	0	X	0
	80583 No. 31287-1		5820-305-1010	GEAR ASSEMBLY (24 teeth)	0	0	X	0
	80583 No. 31288-G1		5820-305-1016	GEAR ASSEMBLY (36 teeth)	0	0	X	0
	80583 No. 31281-1		5355-518-0910	GLASS (main or vernier dial)	0	0	X	0
	80583 No. 31282-1		5355-668-4515	GLASS (frequency band dial)	0	0	X	0
	80583 No. 15923-1 71400 No. HKM		5920-280-4039	HOLDER, fuse	0	0	X	0
	80583 No. 31415-1		5820-509-1023	HOLDER, spring	0	0	X	0
E1	80583 No. 16619-5		5970-503-4557	INSULATOR, bushing	0	0	X	0
E19	80583 No. 31482-1 20093 No. CC-80W-PP		5940-549-2652	INSULATOR, feed-thru	0	0	X	0
J3	80583 No. 5066-1 80063 No. JK-34A		5935-221-5821	JACK, telephone	0	0	X	0
	80583 No. 31215-1		5355-667-7495	KNOB (3 in. dia)	0	0	X	0
	80583 No. 31434-2		5355-667-7496	KNOB (red)	0	0	X	0
	80583 No. 31434-G1		5355-668-4566	KNOB (black)	0	0	X	0
E101	24446 No. 47		6240-155-8706	LAMP, incandescent		X	X	X 2
E102								
E103	(Continued)							

Section II  
Spare Parts List

T.O. 31R2-4-17-14

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number Class Code	Item Name	Quantities O F D ES
E104	(Continued) 24446 No. 47	6240-155-8706	LAMP, incandescent	X X X 2
M1	80583 No. 4903-2	0801 6625-648-9374	METER, audio level	0 0 X 0
	80583 No. 31276-1	5820-302-3784	MOUNTING, indicator	0 0 0 0
	80583 No. 31131-1	5820-505-2776	OSCILLATOR SUBASSEMBLY (3.5 megacycles)	0 0 0 0
T6	80583 No. 31106-1	5820-505-2187	OSCILLATOR SUBASSEMBLY (beat-frequency)	0 0 0 0
	80583 No. 31166-1	5820-329-0542	PLATE, base	0 0 0 0
	80583 No. 31492-1	5820-515-8670	PLATE, identification (fuse ratings)	0 0 0 0
	80583 No. 31493-1	5820-205-0286	PLATE, identification (spare fuse ratings)	0 0 0 0
	80583 No. 31423-1	5820-392-6107	PLATE, pressure	0 0 0 0
	80583 No. T8222	5120-348-9775	PLIERS	0 0 0 0
	80583 No. 31186-1	5820-668-6096	POINTER, indicator (frequency range)	0 0 X 0
	80583 No. 31199-1	5820-668-5983	POINTER, indicator (main or vernier dial)	0 0 X 0
	80583 No. 31422-1	5307-515-8092	POST, supporting (filter choke)	0 0 X 0
	80583 No. 31424-1	5307-208-0438	POST, supporting (transformer)	0 0 X 0
L51	80583 No. 31030-2	5950-648-3233	REACTOR (150 ohms resistance)	0 0 X 0
L52	80583 No. 31031-2	5950-648-3232	REACTOR (354 ohms resistance)	0 0 X 0
R1	75042 No. BTR514J		RESISTOR, fixed	0 0 X 0
R13	For replacement use			
R26	81349 No. RC20GF514J	5905-279-2516		
R2	81349 No. RC20GF103J	5905-185-8510	RESISTOR, fixed	X X X 1
R12				
R44				
R52				
R57				
R70				
R82				
R90				
R91				
R92				
R116				
R122				

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number Class Code	Item Name	Quantities O F D ES
R3 R14 R39	81349 No. RC20GF333J	5905-171-1998	RESISTOR, fixed	0 0 X 0
R4 R6 R16 R29 R30 R83 R121	81349 No. RC20GF102J	5905-195-6806	RESISTOR, fixed	X X X 1
R5 R15 R32	81349 No. RC20GF511J	5905-279-3511	RESISTOR, fixed	0 0 X 0
R7 R8 R17 R18 R119	81349 No. RC20GF510J	5905-279-3517	RESISTOR, fixed	X X X 1
R9 R19	81349 No. RC20GF240J	5905-279-1750	RESISTOR, fixed	0 0 X 0
R10 R11 R20 R21	81349 No. RC20GF220J	5905-279-3519	RESISTOR, fixed	0 0 X 0
R22 R64 R65 R77	81349 No. RC20GF473J	5905-254-9201	RESISTOR, fixed	0 0 X 0
R23	81349 No. RC20GF223J	5905-171-2004	RESISTOR, fixed	0 0 X 0
R24 R25 R120	81349 No. RC20GF181J	5905-279-3514	RESISTOR, fixed	0 0 X 0
R27	81349 No. RC20GF151J	5905-299-1541	RESISTOR, fixed	0 0 X 0
R28	81349 No. RC20GF682J	5905-279-3503	RESISTOR, fixed	0 0 X 0
R31 R37 R41 R49 R54 R58 R80 R116	81349 No. RC20GF222J	5905-279-1876	RESISTOR, fixed	X X X 1
R33	81349 No. RC20GF152J	5905-279-1757	RESISTOR, fixed	0 0 X 0
R34	81349 No. RC30GF104J	5905-299-2003	RESISTOR, fixed	0 0 X 0
R35 R51 R43 R56	81349 No. RC20GF104J (Continued)	5905-195-6761	RESISTOR, fixed	0 0 X 0

Section II  
Spare Parts List

T.O. 31R2-4-17-14

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	ES
R62 R81	(Continued)							
R67 R100	81349 No. RC20GF104J		5905-195-6761	RESISTOR, fixed	0	0	X	0
R68 R115								
R75 R117								
R76								
R36 R96	81349 No. RC20GF223J		5905-171-2004	RESISTOR, fixed	0	0	X	0
R38	81349 No. RC20GF433J		5905-279-3498	RESISTOR, fixed	0	0	X	0
R40	81349 No. RC32GF203J		5905-299-2021	RESISTOR, fixed	0	0	X	0
R42 R50	81349 No. RC20GF100J		5905-190-8883	RESISTOR, fixed	0	0	X	0
R55								
R45	81349 No. RC20GF241J		5905-279-2593	RESISTOR, fixed	0	0	X	0
R46 R94	81349 No. RC20GF112J		5905-279-3508	RESISTOR, fixed	0	0	X	0
R47 R66	81349 No. RC20GF183J		5905-279-3500	RESISTOR, fixed	0	0	X	0
R48 R60	81349 No. RC20GF105J		5905-279-2513	RESISTOR, fixed	0	0	X	0
R61								
R53 R97	81349 No. RC20GF335J		5905-279-1883	RESISTOR, fixed	0	0	X	0
R59	81349 No. RC32GF222J		5905-279-1723	RESISTOR, fixed	0	0	X	0
R63 R103	81349 No. RC20GF273J		5905-279-3499	RESISTOR, fixed	X	X	X	1
R104								
R105								
R106								
R107								
R108								
R109								
R110								
R71 R79	81349 No. RC20GF681J		5905-195-6791	RESISTOR, fixed	0	0	X	0
R72	80583 No. 19397-41		5905-173-7968	RESISTOR, fixed	0	0	X	0
R73	80583 No. 19397-43		5905-500-5288	RESISTOR, fixed	0	0	X	0
R74	81349 No. RC20GF101J		5905-190-8889	RESISTOR, fixed	0	0	X	0
R78 R98	81349 No. RC20GF474J		5905-279-2515	RESISTOR, fixed	0	0	X	0
R85	81350 No. RW32G252		5905-518-5254	RESISTOR, fixed	0	0	X	0
R87 R88	81349 No. RC20GF124J		5905-192-3981	RESISTOR, fixed	0	0	X	0

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	ES
R86	81349 No. RC20GF823J	5905-279-3494		RESISTOR, fixed	0	0	X	0
R89								
R95								
R99	81349 No. RC32GF361J	5905-279-2546		RESISTOR, fixed	0	0	X	0
R102	81349 No. RC20GF821J	5905-171-1999		RESISTOR, fixed	0	0	X	0
R111	81349 No. RC20GF473J	5905-254-9201		RESISTOR, fixed	0	0	X	0
R112	81349 No. RC20GF391J	5905-279-1890		RESISTOR, fixed	0	0	X	0
R113	81349 No. RC20GF334J	5905-279-2519		RESISTOR, fixed	0	0	X	0
R114	81349 No. RC20GF471J	5905-192-3973		RESISTOR, fixed	0	0	X	0
R69	80583 No. 15366-1	5905-502-2111		RESISTOR, variable	0	0	X	0
R84	01121 No. J1U5042P2032 80583 No. 15342-11	5905-502-8414		RESISTOR, variable	0	0	X	0
R93	80583 No. 15342-21 01121 No. JS1U5031P3048	5905-109-1581		RESISTOR, variable	0	0	X	0
R101	01121 No. J2U2532SD3032 80583 No. 15342-4	5905-259-3653		RESISTOR, variable	0	0	X	0
	80130 No. 4 HAT 42 POST 80583 No. 16140-2	5960-563-0276		RETAINER, electron tube	0	0	X	0
	80130 No. 2 HAT 32 POST 80583 No. 16141-2	5960-246-4623		RETAINER, electron tube	0	0	X	0
	80583 No. 31177-1	5820-327-5257		ROLLER, lever	0	0	X	0
	80583 No. 31495-1	5305-285-6969		SCREW, captive	0	0	X	0
	80583 No. 16641-1 81349 No. UG-177/U	5935-518-6981		SHELL, electrical connector	0	0	X	0
	80583 No. 31105-1	5950-547-8324		SHIELD, coil (for 3.5 megacycle oscillator assembly)	0	0	X	0
	80583 No. 31133-1	5950-547-8097		SHIELD, coil (for T6 BFO assembly)	0	0	0	0
	80583 No. 33924-1	5930-548-7457		SHIELD, contact	0	0	X	0
	80583 No. 31376-1	5820-332-4992		SHIELD, end	0	0	X	0
	80583 No. 31019-1	5950-547-8323		SHIELD, transformer (for T2, T4, or T5)	0	0	X	0
	80583 No. 31132-1	5950-504-8914		SHIELD, transformer (for T3)	0	0	X	0
	80583 No. 31378-1	5950-547-8325		SHIELD, transformer (for T1)	0	0	X	0

Section II  
Spare Parts List

T.O. 31R2-4-17-14

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	ES
	81350 No. TS102U01		FSC 5960-262-0015	SHIELD, electron tube	0	0	X	0
	81350 No. TS102U02		5960-272-9094	SHIELD, electron tube	0	0	X	0
	81350 No. TS102U03		FSC 5960-272-9092	SHIELD, electron tube	0	0	X	0
	81350 No. TS103U02		FSC 5960-296-3651	SHIELD, electron tube	0	0	X	0
	80583 No. 31449-1		5960-351-4812	SHIELD ASSEMBLY, tube	0	0	X	0
X21	80583 No. 16092-5		5935-501-8361	SOCKET, crystal	0	0	X	0
X22	72825 No. 9748-1							
X23								
X24								
X25								
X26								
X1    X11	81350 No. TS102P01		5935-260-0516	SOCKET, tube	0	0	X	0
X2    X12								
X3    X13								
X6    X14								
X7    X15								
X8    X18								
X9    X20								
X10								
X4	80583 No. 15989-5 72825 No. 102M		5935-197-3964	SOCKET, tube	0	0	X	0
X5	81350 No. TS102C01		5935-232-3758	SOCKET, tube	0	0	X	0
X16	81350 No. TS103P01		5935-160-1365	SOCKET, tube	0	0	X	0
X17	81350 No. TS101P01		5935-260-0517	SOCKET, tube	0	0	X	0
X19								
	80583 No. 31003-1		5820-327-5274	SPRING (for RF coil assemblies)	0	0	0	0
	80583 No. 31004-1		5820-342-9417	SPRING (for RF coil)	0	0	0	0
	80583 No. 31023-1		5820-351-3843	SPRING (for IF transformer shields)	0	0	0	0
	80583 No. 31125-1		5340-200-6333	SPRING (conversion switch)	0	0	0	0
	80583 No. 31126-1		5820-320-8290	SPRING (indicator slide)	0	0	0	0
	80583 No. 31205-1		5820-547-3817	SPRING (band change detent)	0	0	0	0
	80583 No. 31239-1		5820-327-5278	SPRING (for anti-backlash in gear train assembly)	0	0	0	0
	80583 No. 31278-1		5930-548-5796	SPRING (for turret rotor shaft grounding -- 1-5/8 in. lg)	0	0	0	0
	80583 No. 31279-1		5820-320-8288	SPRING (for turret rotor shaft grounding -- 1-7/16 in. lg)	0	0	0	0

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	ES
	80583 No. 31417-1		5820-509-1021	SPRING (crystal holding)	0	0	0	0
S2	80583 No. 15879-2		5930-548-5711	SWITCH, rotary	0	0	X	0
S3	80583 No. 31469-1		5930-333-7471	SWITCH, rotary	0	0	X	0
S4	80583 No. 15862-2		5930-507-4330	SWITCH, rotary	0	0	X	0
S5A S5B S5C	80583 No. 15856-1		5930-296-4285	SWITCH, rotary	0	0	X	0
S12	80583 No. 31469-3		5930-548-4018	SWITCH, rotary	0	0	X	0
S13	80583 No. 31469-2		5930-548-4017	SWITCH, rotary	0	0	X	0
S6 S7 S9	80583 No. 15864-1 15605 No. 8280 For replacement use 81350 No. ST42D			SWITCH, toggle		X	X	X
S8	80583 No. 15867-1 15605 No. 8363		5930-296-9034	SWITCH, toggle		X	X	X
S11	80583 No. 15880-1 04009 No. 81057N		5930-296-9667	SWITCH, toggle	0	0	X	0
T7	80583 No. 310086-2		5950-646-2788	TRANSFORMER, AF	0	0	X	0
T1	80583 No. 31183-1		5950-647-7866	TRANSFORMER, IF	0	0	X	0
T2	80583 No. 31116-2		5950-648-5891	TRANSFORMER, IF	0	0	X	0
T3	80583 No. 31114-2		5950-648-6704	TRANSFORMER, IF	0	0	X	0
T4 T5	80583 No. 31102-2		5950-647-8389	TRANSFORMER, IF	0	0	X	0
L31	80583 No. 31103-1		5950-648-6951	TRANSFORMER, IF	0	0	X	0
L32	80583 No. 31069-1		5950-504-8951	TRANSFORMER, IF	0	0	X	0
L53 L54	80583 No. 31488-1 74956 No. 1369		5950-547-8366	TRANSFORMER, IF	0	0	X	0
T8	80583 No. 31029-2		5950-646-0501	TRANSFORMER, power	0	0	X	0
T35	80583 No. 33922-G1		5950-295-8370	TRANSFORMER, RF	0	0	X	0
V1 V2 V7 V9 V10 V11 V12	81349 No. JAN 5749/6BA6W	5960-264-2089		TUBE, electron		X	X	X
V3	81349 No. JAN 6AH6	5960-166-7667		TUBE, electron	0	0	0	0

Section II  
Spare Parts List

T.O. 31R2-4-17-14

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	E
V4	81349 No. JAN 6C4		5960-503-4871	TUBE, electron		X	X	X 3
V8								
V13								
V5	81349 No. JAN 5750/6BE6W		5960-296-9478	TUBE, electron		X	X	X 2
V6								
V14	81349 No. JAN 6AL5		5960-296-9478	TUBE, electron		X	X	X 3
V15								
V20								
V16A	81349		5960-636-2218	TUBE, electron		X	X	X 2
V16B	No. JAN 6189/12AU7WA							
V17	81349 No. JAN 6V6GTY		5960-116-9927	TUBE, electron		X	X	X 2
V18	81349 No. JAN OA2WA		5960-503-4880	TUBE, electron		X	X	X 2
V19	81349 No. JAN 5R4WGA		5960-262-1703	TUBE, electron		X	X	X 2
E61	80583 No. 31387-1		5950-648-0297	TUNER, RF		0	0	X 0
E62	80583 No. 31390-1		5950-648-0496	TUNER, RF		0	0	X 0
E63	80583 No. 31393-1		5950-648-0382	TUNER, RF		0	0	X 0
E64	80583 No. 31396-1		5950-568-0246	TUNER, RF		0	0	X 0
R65	80583 No. 31399-1		5950-648-9194	TUNER, RF		0	0	X 0
E66	80583 No. 31405-1		5950-647-9485	TUNER, RF		0	0	X 0
E68	80583 No. 31386-1		5950-647-9363	TUNER, RF		0	0	X 0
E75								
E69	80583 No. 31389-1		5950-648-0379	TUNER, RF		0	0	X 0
E76								
E70	80583 No. 31392-1		5950-648-0386	TUNER, RF		0	0	X 0
E77								
E71	80583 No. 31395-1		5950-645-2927	TUNER, RF		0	0	X 0
R78								
E72	80583 No. 31398-1		5950-647-9193	TUNER, RF		0	0	X 0
E79								
E73	80583 No. 31404-1		5950-505-1479	TUNER, RF		0	0	X 0
E80								
E85	80583 No. 31385-1		5950-253-6747	TUNER, RF		0	0	X 0
E86	80583 No. 31388-1		5950-648-0495	TUNER, RF		0	0	X 0
E87	80583 No. 31391-1		5950-648-0385	TUNER, RF		0	0	X 0
E88	80583 No. 31394-1		5950-645-2928	TUNER, RF		0	0	X 0
E89	80583 No. 31397-1		5950-645-2992	TUNER, RF		0	0	X 0

Reference Designator or Figure and Index No.	Signal Corps, Air Force or Manufacturer's Part Number	Federal Stock Number		Item Name	Quantities			
		Class Code	FIIN		O	F	D	ES
E90	80583 No. 31403-1		5950-247-5419	TUNER, RF	0	0	X	0
	80583 No. 11806-4		5120-198-5398	WRENCH (1-27/32 in. lg)	0	0	0	0
	80583 No. 11806-4		5120-242-7410	WRENCH (2-3/32 in. lg)	0	0	0	0
	80583 No. 11806-3		5120-224-2504	WRENCH (1-31/32 in. lg)	0	0	0	0

