PRODUCT INFORMATION 16/77E

2 CH - BALANCING UNIT (1.091.004)

2 CH - BALANCING UNIT 1.091.004

Block Diagram



TECHNICAL DESCRIPTION

The stereo balancing unit 1.091.004 is used to change an unbalanced audio equipment (e.g. semi professional equalizers -limiter/compressors, -tape recorders, -cassette recorders and so on) into an equipment with balanced and floating line in- and outputs.

The circuit, including a power supply, is housed in a cabinet of approx. 205 x 140 x 75 mm.

(A rack mounting kit (19" x 88 mm) for two units 1.091.004 is available on request.)

All balanced in- and outputs are equipped with XLR-type connectors and all unbalanced in- and outputs with phono sockets (cinch). (0 dBu ♠ 0,775 V)

Balanced and floating in- and outputs:

- Input impedance > 5 kOhm
- Max. input level (line level) +21 dBu
- Output impedance 🗲 50 Ohm
- Max. output level (line level) (200 Ohm load) +20 dBu
- Max. output level (line level) (600 Ohm load) +21 dBu

Unbalanced in- and outputs:

- Output impedance ≤ 100 Ohm
- Min. load (input impedance of unbalanced equipment) >1 kOhm
- Output level: (input level of unbalanced equipment) adjustable between line level and 30 dB below line level, max level +15dBu
- Input impedance (\$ load of unbalanced equipment) > 5 kOhm (higher impedance on request)
- Input level (output level of unbalanced equipment) adjustable
 between line level and 15 dB below line level (15 ... 30 dB
 below line level with an additional plug-in amplifier (optional))

The unbalanced equipment has to meet the following requirements:

- Input impedance >1 kOhm
- Input level: between line level and 30 dB below line level
- Min. output load: 5 kOhm
- Output level: between line level and 15 dB below line level (for 15 ... 30 dB below line level, an additional plug-in amplifier in 1.091.004 is necessary)
- Price sFr. 760.-

Information in this publication supersedes all previously published material. Specification and price change privilegs reserved.