

Parts Change Notice

Model No. CF-72 Series

Please revise the original parts list in the Service Manual to conform to the change(s) shown herein.

If new part numbers are shown, be sure to use them ordering parts.

<i>Reason for change</i>		*The circled item indicates the reason. If no marking, see the Notes in the bottom column.	
1. Improve performance		1.	Item *1 to *13 on the below list should be changed simultaneously.
2. Change of material or dimension		2.	When changing of Item *1, check set revision attached on bottom cabinet. In case set revision = 0, update of a driver(VGA) is required. The driver is contained in the following recovery disk.
3. To meet approved specification			
4. Standardization			
5. Addition			Recovery CD Prinstall Master
6. Deletion			Win98SE DFQX3478MC V5.01L12M00
7. Correction			Dual (NT/2k) DFQX3477MC V10.01L12M01
8. Other			Dual (2k/XP) DFQX3556LA V11.01L11M00
<i>Interchangeability Code</i>		**The circled item indicates the interchangeability. If no marking, see the Notes in the bottom column.	
Parts	Set Production		
A Original New	 Early Late	Original or new parts may be used in early or late production set. Use original parts until exhausted, then stock new parts.	
B Original New	 Early Late	Original parts may be used in early production sets only. New parts may be used in early or late production sets. Use original parts where possible, then stock new parts.	
C Original New	 Early Late	New parts only may be used in early or late production sets. Stock new parts.	
D Original New	 Early Late	Original parts may be used in early production sets only. New parts may be used in late production sets only. Stock both original and new parts.	
E Other			

<i>Part Number</i>						
Model No.	Ref. No.	Original Part No.	New Part No.	Notes(**)	Part Name & Descriptions	Q'TY
CF-72Q3JRWDG CF-72TCJU/WZxM	A2 	CGA-E/605A	CGA-E/607A	8, A	BATTERY PACK	1
CF-72TCJU/WZxM	E1	DL3U11156BAA *1	DL3U11156CAA	1, B	PCB, MAIN	1
	--	F1G1C104A031 *2	--	6, B	CAPACITOR (Deletion C223 227 231 236 735 736 737)	139→132
	--	-- *3	F1G1A224A018	5, B	CAPACITOR (Addition C223 227 231 236 735 736 737)	0→7
	--	-- *4	DCUE1A106ZFL	5, B	CAPACITOR (Addition C219)	21→22
	IC2	C1DB00000857 *5	C1DB00000917	1, B	IC, CHIPSET, GMCH3	1
	IC3	C1DB00000858 *6	C1DB00000908	1, B	IC, CHIPSET, ICH3	1
	IC4	C1DB00000859 *7	C1DB00000930	1, B	IC, VGA	1
	--	ERA3YED102V *8	--	6, B	RESISTOR (Deletion R147)	8→7
	--	-- *9	ERA3YED132V	5, B	RESISTOR (Addition R147)	0→1
	--	ERJ2GEJ330X *10	--	6, B	RESISTOR (Deletion R151 152)	6→4
	--	ERJ2GEJ330X *11	--	6, B	RESISTOR (Deletion R668 669)	4→2
	--	-- *12	ERJ2GE0R00X	5, B	RESISTOR (Addition R151 152 668 669)	13→17
	--	ERJ6GEY0R00V *13	--	6, B	RESISTOR (Deletion R675)	8
				5, B	(Addition R674)	
	E2	DL3U21156BAA	DL3U21156CAA	8, A	PCB, LED	1

File this Parts Change Notice with your copy of the Service Manual.