MAY 1983-REVISED MARCH 1988


- Current Sinking Capability up to 80 mA
- Guaranteed Fan-Out of 30 Series 54/74 Loads
- Dependable Texas Instruments Quality and Reliability

description

These devices contain four independent 2-input NAND buffers. The open-collector outputs require pull-up resistors to perform correctly. They may be connected to other open-collector outputs to implement active-low wired-OR or active-high wired-AND functions. Open-collector devices are often used to generate higher VOH levels.

The SN5439 is characterized for operation over the full military temperature range of ~55°C to 125°C. The SN7439 is characterized for operation from 0°C to 70°C.


logic symbol†



[†] This symbol is in accordance with ANSI/IEEE Std 91-1984 and IEC Publication 617-12.


FUNCTION TABLE (each gate)

INP	UTS	Ουπρυτ
Α	В	Y
н	Н	L
L	×	н
х	L	н




1B 3 12 4B 2Y 4 11 4A 2A 5 10 3Y 2B 6 9 3B GND 7 8 3A

schematics (each gate)



logic diagram



positive logic

$$Y = \overline{A \cdot B}$$
 or $Y = \overline{A} + \overline{B}$

SN5439, SN7439 QUADRUPLE 2-INPUT POSITIVE NAND BUFFERS WITH OPEN-COLLECTOR OUTPUTS

NOTE 1: Voltage values are with respect to network ground terminal.

recommended operating conditions

			SN5439			SN7439			
		MIN	NOM	MAX	MIN	NOM	MAX	רומט	
Vcc	Supply voltage	4.5	5	5.5	4.5	5	5.5	٧	
VIН	High-level input voltage	2		_	2			٧	
VIL	Low-level input voltage			0.8			8.0	٧	
Voн	High-level output voltage			5.5			5.5	٧	
IOL Low-level output voltage	Law lavel output valtage			60			60	- ^	
	CON-level output voitage						80 [†]	mΑ	
TA	Operating free-air temperature	-55		125	0		70	°c	

 $^{^{\}dagger}\text{Ths}$ extended limit applies only if V $_{CC}$ is maintained between 4.75 and 5.25 V.

electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

PARAMETER	TEST CONDITIONS [†]	SN5439			SN7439			
		MIN	TYP	MAX	MIN	TYP	MAX	UNIT
v _{IK}	$V_{CC} = MIN$, $i_j = -12 \text{ mA}$			- 1.5			- 1.5	V
	$V_{CC} = MIN$, $V_{IL} = 0.8 \text{ V}$, $V_{OH} = 5.5 \text{ V}$	T				-	0.25	- 4
tон	$V_{CC} = MIN$, $V_{IL} = 0.7 \text{ V}$, $V_{OH} = 5.5 \text{ V}$			0.25				mA
VOL	V _{CC} = MIN, I _{OL} = 48 mA			0.4			0.4	
	VCC = MIN, IOL = 60 mA			0.5			0.5	V
	V _{CC} = 4.75 V, I _{OL} = 80 mA				_		0.6	
11	V _{CC} = MAX, V _I = 5.5 V			1			1	mΑ
liн	V _{CC} = MAX, V _I = 2.4 V			40			40	μA
IIL	VCC = MAX, V _I = 0.4 V			-1.6			-1.6	mΑ
¹ ссн	$V_{CC} = MAX$, $V_I = 0$			54			54	πА

[†]For conditions shown as MIN or MAX, use the appropriate value specified under recommended operating conditions.

switching characteristics, VCC = 5 V, TA = 25°C (see note 2)

PARAMETER	FROM	то	TEST CONDITIONS		SN5	439	SN7	439	4.4417	
	(INPUT)	(OUTPUT)			MIN	MAX	MIN	MAX	UNIT	
^t PLH	AorB	Y	$R_L = 133 \Omega$, $C_L = 45 pF$	Ri = 133.0	C. = 45 pF		22		22	ns
[‡] PHL					18		18	. 115		

NOTE 2: Load circuits and voltage waveforms are shown in Section 1.

IMPORTANT NOTICE

Texas Instruments (TI) reserves the right to make changes to its products or to discontinue any semiconductor product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

TI warrants performance of its semiconductor products and related software to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

Certain applications using semiconductor products may involve potential risks of death, personal injury, or severe property or environmental damage ("Critical Applications").

TI SEMICONDUCTOR PRODUCTS ARE NOT DESIGNED, INTENDED, AUTHORIZED, OR WARRANTED TO BE SUITABLE FOR USE IN LIFE-SUPPORT APPLICATIONS, DEVICES OR SYSTEMS OR OTHER CRITICAL APPLICATIONS.

Inclusion of TI products in such applications is understood to be fully at the risk of the customer. Use of TI products in such applications requires the written approval of an appropriate TI officer. Questions concerning potential risk applications should be directed to TI through a local SC sales office.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards should be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or services described herein. Nor does TI warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such semiconductor products or services might be or are used.

Copyright © 1996, Texas Instruments Incorporated