

STBV42

HIGH VOLTAGE FAST-SWITCHING NPN POWER TRANSISTOR

- MEDIUM VOLTAGE CAPABILITY
- LOW SPREAD OF DYNAMIC PARAMETERS
- MINIMUM LOT-TO-LOT SPREAD FOR RELIABLE OPERATION
- VERY HIGH SWITCHING SPEED


APPLICATIONS:


 ELECTRONIC BALLASTS FOR FLUORESCENT LIGHTING

DESCRIPTION

The device is manufactured using high voltage Multi Epitaxial Planar technology for high switching speeds and medium voltage capability. It uses a Cellular Emitter structure with planar edge termination to enhance switching speeds while maintaining the wide RBSOA.

The STBV42 is designed for use in compact fluorescent lamp application.





ABSOLUTE MAXIMUM RATINGS

Symbol	Parameter	Value	Unit
V _{CES}	Collector-Emitter Voltage (V _{BE} = 0)	700	V
Vceo	Collector-Emitter Voltage (I _B = 0)	400	V
V _{EBO}	Emitter-Base Voltage ($I_C = 0$)		V
Ic	Collector Current	1	Α
I _{CM}	Collector Peak Current (t _p < 5 ms)	2	Α
lв	Base Current	0.5	Α
I _{BM}	Base Peak Current (t _p < 5 ms)	1	Α
P _{tot}	Total Dissipation at T _{amb} = 25 °C	1	W
T _{stg}	Storage Temperature	-65 to 150	°C
Tj	Max. Operating Junction Temperature	150	°C

September 2000 1/5

THERMAL DATA


R _{thj-amb} Thermal Resistance Junction-ambient	Max	120	°C/W	1
--	-----	-----	------	---

ELECTRICAL CHARACTERISTICS (T_{case} = 25 °C unless otherwise specified)


Symbol	Parameter	Test Con	Min.	Тур.	Max.	Unit	
I _{CEV}	Collector Cut-off Current (V _{BE} = -1.5V)	V _{CE} = 700 V V _{CE} = 700 V	$T_{j} = 125^{\circ}$			1 5	mA mA
I _{EBO}	Emitter Cut-off Current (I _C = 0)	V _{EB} = 9 V				1	mA
V _{CEO(sus)*}	Collector-Emitter Sustaining Voltage (I _B = 0)	I _C = 1 mA L = 25mH		400			V
V _{CE(sat)} *	Collector-Emitter Saturation Voltage	I _C = 0.25 A I _C = 0.5 A I _C = 0.75 A	$I_B = 0.05 A$ $I_B = 0.125 A$ $I_B = 0.25 A$		0.2 0.3 0.4	0.5 1 1.5	> >
V _{BE(sat)} *	Base-Emitter Saturation Voltage	I _C = 0.25 A I _C = 0.5 A	$I_B = 0.05 A$ $I_B = 0.125 A$			1.0 1.2	V V
h _{FE} *	DC Current Gain	I _C = 0.4 A I _C = 0.8 A	V _{CE} = 5 V V _{CE} = 5 V	10 5		30 20	
t _f	INDUCTIVE LOAD Fall Time	$I_C = 0.25 \text{ A}$ $I_{B1} = -I_{B2} = 50 \text{ mA}$	$V_{clamp} = 300 \text{ V}$ L = 3 mH		0.3		μs

^{*} Pulsed: Pulse duration = 300μs, duty cycle = 1.5 %

Safe Operating Area




Derating Curve




2/5


DC Current Gain




Collector Emitter Saturation Voltage




Switching Time Inductive Load



DC Current Gain




Base Emitter Saturation Voltage



4

TO-92 MECHANICAL DATA

DIM.	mm			inch		
	MIN.	TYP.	MAX.	MIN.	TYP.	MAX.
А	4.58		5.33	0.180		0.210
В	4.45		5.2	0.175		0.204
С	3.2		4.2	0.126		0.165
D	12.7			0.500		
E		1.27			0.050	
F	0.4		0.51	0.016		0.020
G	0.35			0.14		



47/

Information furnished is believed to be accurate and reliable. However, STMicroelectronics assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of STMicroelectronics. Specification mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. STMicroelectronics products are not authorized for use as critical components in life support devices or systems without express written approval of STMicroelectronics.

The ST logo is a trademark of STMicroelectronics

© 2000 STMicroelectronics – Printed in Italy – All Rights Reserved STMicroelectronics GROUP OF COMPANIES

Australia - Brazil - China - Finland - France - Germany - Hong Kong - India - Italy - Japan - Malaysia - Malta - Morocco - Singapore - Spain - Sweden - Switzerland - United Kingdom - U.S.A.

http://www.st.com

