


International
IR Rectifier

203DNQ... SERIES

SCHOTTKY RECTIFIER

200 Amp




Major Ratings and Characteristics

Characteristics	203DNQ...	Units
$I_{F(AV)}$ Rectangular waveform	200	A
V_{RRM} range	80 to 100	V
I_{FSM} @ $t_p = 5 \mu s$ sine	16,000	A
V_F @ 100Apk, $T_J = 125^\circ C$ (per leg)	0.70	V
T_J range	-55 to 175	$^\circ C$

Description/Features

The 203DNQ center tap Schottky rectifier module series has been optimized for low reverse leakage at high temperature. The proprietary barrier technology allows for reliable operation up to $175^\circ C$ junction temperature. Typical applications are in high current switching power supplies, plating power supplies, UPS systems, converters, free-wheeling diodes, welding, and reverse battery protection.

- $175^\circ C$ T_J operation
- Center tap module
- High purity, high temperature epoxy encapsulation for enhanced mechanical strength and moisture resistance
- Low forward voltage drop
- High frequency operation
- Guard ring for enhanced ruggedness and long term reliability



Voltage Ratings

Part number	203DNQ080	203DNQ100
V_R Max. DC Reverse Voltage (V)	80	100
V_{RWM} Max. Working Peak Reverse Voltage (V)		

Absolute Maximum Ratings

Parameters		203DNQ	Units	Conditions		
I _{F(AV)}	Max. Average Forward Current * See Fig. 5 (Per Device)	200	A	50% duty cycle @ T _C = 136 °C, rectangular wave form		
I _{FSM}	Max. Peak One Cycle Non-Repetitive Surge Current (Per Leg) * See Fig. 7	16,000	A	5μs Sine or 3μs Rect. pulse	Following any rated load condition and with rated V _{RRM} applied	
		2,100		10ms Sine or 6ms Rect. pulse		
E _{AS}	Non-Repetitive Avalanche Energy (Per Leg)	15	mJ	T _J = 25 °C, I _{AS} = 1 Amps, L = 30 mH		
I _{AR}	Repetitive Avalanche Current (Per Leg)	1	A	Current decaying linearly to zero in 1 μsec Frequency limited by T _J max. V _A = 1.5 x V _R typical		

Electrical Specifications

Parameters		203DNQ	Units	Conditions	
V _{FM}	Max. Forward Voltage Drop (Per Leg) * See Fig. 1 (1)	0.86	V	@ 100A	T _J = 25 °C
		1.03	V	@ 200A	
		0.70	V	@ 100A	T _J = 125 °C
		0.84	V	@ 200A	
I _{RM}	Max. Reverse Leakage Current (Per Leg) * See Fig. 2 (1)	3	mA	T _J = 25 °C	V _R = rated V _R
		40	mA	T _J = 125 °C	
V _{F(TO)}	Threshold Voltage	0.50	V	T _J = T _J max.	
r _t	Forward Slope Resistance	1.08	mΩ		
C _T	Max. Junction Capacitance (Per Leg)	2,650	pF	V _R = 5V _{DC} (test signal range 100KHz to 1MHz) 25°C	
L _S	Typical Series Inductance (Per Leg)	7.0	nH	From top of terminal hole to mounting plane	
dv/dt	Max. Voltage Rate of Change (Rated V _R)	10,000	V/ μs		

Thermal-Mechanical Specifications(1) Pulse Width < 300 μs , Duty Cycle < 2%

Parameters	203DNQ	Units	Conditions
T_J Max. Junction Temperature Range	-55 to 175	$^\circ\text{C}$	
T_{stg} Max. Storage Temperature Range	-55 to 175	$^\circ\text{C}$	
R_{thJC} Max. Thermal Resistance Junction to Case (Per Leg)	0.40	$^\circ\text{C/W}$	DC operation * See Fig. 4
R_{thJC} Max. Thermal Resistance Junction to Case (Per Package)	0.20	$^\circ\text{C/W}$	DC operation
R_{thCS} Typical Thermal Resistance, Case to Heatsink	0.10	$^\circ\text{C/W}$	Mounting surface, smooth and greased
wt Approximate Weight	79(2.80)	g(oz.)	
T Mounting Torque	Min.	24 (20)	Kg-cm (lbf-in)
	Max.	35 (30)	
	Typ.	13.5 (12)	
	Min.	35 (30)	
	Max.	46 (40)	
Case Style	TO-244AB Isolated		Modified JEDEC




Fig. 1 - Max. Forward Voltage Drop Characteristics (Per Leg)




Fig. 2 - Typical Values Of Reverse Current Vs. Reverse Voltage (Per Leg)




Fig. 3 - Typical Junction Capacitance Vs. Reverse Voltage (Per Leg)




Fig. 4 - Max. Thermal Impedance Z_{thJC} Characteristics (Per Leg)




Fig. 5 - Max. Allowable Case Temperature Vs. Average Forward Current (Per Leg)




Fig. 6 - Forward Power Loss Characteristics (Per Leg)




Fig. 7 - Max. Non-Repetitive Surge Current (Per Leg)




Fig. 8 - Unclamped Inductive Test Circuit

(2) Formula used: $T_C = T_J - (P_d + P_{d_{REV}}) \times R_{thJC}$;

P_d = Forward Power Loss = $I_{F(AV)} \times V_{FM}$ @ ($I_{F(AV)} / D$) (see Fig. 6);

$P_{d_{REV}}$ = Inverse Power Loss = $V_{R1} \times I_R (1 - D)$; I_R @ $V_{R1} = 80\%$ rated V_R

Data and specifications subject to change without notice.
This product has been designed and qualified for Industrial Level.
Qualification Standards can be found on IR's Web site.

International
IOR Rectifier

IR WORLD HEADQUARTERS: 233 Kansas St., El Segundo, California 90245, USA Tel: (310) 252-7105
TAC Fax: (310) 252-7309
Visit us at www.irf.com for sales contact information. 07/01