


SANYO**FP103****DC/DC Converter Applications****Features**

- Composite type with a PNP transistor and a Schottky barrier diode contained in one package, facilitating high-density mounting.
- The FP103 is formed with 2chips, one being equivalent to the 2SB1121 and the other the SB07-03C, placed in one package.

Package Dimensions

unit:mm

2088A

**Specifications****Absolute Maximum Ratings** at $T_a = 25^\circ\text{C}$

Parameter	Symbol	Conditions	Ratings	Unit
[TR]				
Collector-to-Base Voltage	V_{CBO}		-30	V
Collector-to-Emitter Voltage	V_{CEO}		-25	V
Emitter-to-Base Voltage	V_{EBO}		-6	V
Collector Current	I_C		-2	A
Collector Current (Pulse)	I_{CP}		-5	A
Base Current	I_B		-400	mA
Collector Dissipation	P_C		1.3	W
Junction Temperature	T_J	Mounted on a ceramic board (250mm \times 0.8mm)	150	$^\circ\text{C}$
Storage Temperature	T_{stg}		-55 to +150	$^\circ\text{C}$
[SBD]				
Repetitive Peak Reverse Voltage	V_{RRM}		30	V
Non-repetitive Peak Reverse Surge Voltage	V_{RSM}		35	V
Average Rectified Current	I_O		700	mA
Surge Forward Current	I_{FSM}	50Hz sine wave, 1cycle	5	A
Junction Temperature	T_J		-55 to +125	$^\circ\text{C}$
Storage Temperature	T_{stg}		-55 to +125	$^\circ\text{C}$

Marking:103

■ Any and all SANYO products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your SANYO representative nearest you before using any SANYO products described or contained herein in such applications.


■ SANYO assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO products described or contained herein.

FP103

Electrical Characteristics at Ta = 25°C


.Parameter	Symbol	Conditons	Ratings			Unit
			min	typ	max	
[TR]						
Collector Cutoff Current	I _{CBO}	V _{CB} =−20V, I _E =0			−0.1	μA
Emitter Cutoff Current	I _{EBO}	V _{EB} =−4V, I _C =0			−0.1	μA
DC Current Gain	h _{FE1}	V _{CE} =−2V, I _C =−100mA	140		560	
	h _{FE2}	V _{CE} =−2V, I _C =−1.5A	65			
Gain-Bandwidth Product	f _T	V _{CE} =−10V, I _C =−50mA		150		MHz
Output Capacitance	Cob	V _{CB} =−10V, f=1MHz		32		pF
Collector-to-Emitter Saturation Voltage	V _{CE(sat)}	I _C =−1.5A, I _B =−75mA		−0.35	−0.6	V
Base-to-Emitter Saturation Voltage	V _{BE(sat)}	I _C =−1.5A, I _B =−75mA		−0.85	−1.2	V
Collector-to-Base Breakdown Voltage	V _{(BR)CBO}	I _C =−10μA, I _E =0	−30			V
Collector-to-Emitter Breakdown Voltage	V _{(BR)CEO}	I _C =−1mA, R _{BE} =∞	−25			V
Emitter-to-Base Breakdown Voltage	V _{(BR)EBO}	I _E =−10μA, I _C =0	−6			V
Turn-ON Time	t _{on}	See specified Test Circuit		60		ns
Storage Time	tstg	See specified Test Circuit		350		ns
Fall Time	t _f	See specified Test Circuit		25		ns
[SBD]						
Reverse Voltage	V _R	I _R =300μA	30			V
Forward Voltage	V _F	I _F =700mA			0.55	V
Reverse Current	I _R	V _R =15V			80	μA
Interterminal Capacitance	C	V _R =10V, f=1MHz		28		pF
Reverse Recovery Time	t _{rr}	I _F =I _R =100mA, See specified Test Circuit			10	ns
Thermal Resistance	Rthj-a	Mounted on a ceramic board (250mm²×0.8mm)		120		

Electrical Connection




Switching Time Test Circuit









[TR]








$$-20I_{B1}=20I_{B2}=I_C=-500mA$$

[SBD]







- Specifications of any and all SANYO products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- SANYO Electric Co., Ltd. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO products(including technical data,services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of SANYO Electric Co., Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only ; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of August, 2000. Specifications and information herein are subject to change without notice.