

Data: 31-Dec-07

Document reference: AN2511	PCB reference: STEVAL-ISQ002V1	
Company: ST Microelectronics		
Contact person: K.R. HARIHARASUDHAN	E-mail: kr.hariharasudhan@st.com	Phone:

Index	Quantity	Reference	Value / Generic Part Number	Package	Manufacturer	Manufacturer's ordering code / Orderable Part Number	Supplier	Supplier's ordering code
1	2	Capacitors: C7, C8	10nF	805	Any			
2	2	Capacitors: C5, C6	10pF	805	Any			
3	7	Capacitors: C2, C3, C9, C10, C11, C12, C13	100nF	805	Any			
4	1	Capacitors: C1	330nF	805	Any			
5	1	Polarized Capacitor (Axial): C4	100uF/10v	RB-5.5	Any			
6	3	Resistors: R1, R2, R3	4.7K	805	Any			
7	2	Resistors: R4, R5	100R	805	Any			
8	1	Resistors: R6	220R	805	Any			
9	1	Resistors: R7	10K	805	Any			
10	1	Connector TP3	CON1	SIP-1	Any			
11	6	Connector J2, J3, J4, JP1, JP2, POWER	CON2	SIP-2	Any			
12	2	Connector JP3, JP4	CON3	SIP-3	Any			
13	1	Connector J5	CON4	SIP-4	Any			
14	1	Connector J7	CON7	SIP-7	Any			
15	1	9 Pin Female RS232 connector: J6	DB9	DB9/F			GM (801-036)	
16	1	Crystal Y1	16MHz (KDS)	XTAL-1	Any			
17	1	Header: CON1	ICC	IDC-10B	Any			
18	1	Power Jack connector: J1	JACK	TAP 2.5mm			GM: K375A	
19	1	Regulator: U1	L7805CD2T-TR	TO-220	ST	L7805CD2T-TR		
20	1	LED: D1	SMD LED	LED-SMD	Faichild			
21	1	ST7 MCU: U2	ST72F264G1M6	SOL-28	ST	ST72F264G1M6		
22	1	RS232 level translator: U3	ST3232CTR	SO-16	ST	ST3232CTR		
23	1	Switch: S1	TACT SWITCH	PUSH-4	Any			
24	1	Diode: D2	1N5817	DO41	ST			
25	1	Zener Diode: ZD1	SMAJ20A-TR	TO220	ST			