

# 17CP4

### 17 CP4 ET-T1195 Page 1

## **CATHODE-RAY TUBE**

17-INCH, RECTANGULAR, METAL FOCUS—MAGNETIC DEFLECTION—MAGNETIC

14% BY 10<sup>1</sup>/<sub>6</sub>-INCH PICTURE SIZE FACEPLATE—SPHERICAL, GRAY, FROSTED

ION-TRAP GUN
70-DEGREE DEFLECTION ANGLE

### =DESCRIPTION AND RATING=

The 17CP4 is a magnetic-focus and -deflection, direct-view picture tube which provides a 14% by  $10\frac{11}{16}$ -inch picture for television applications. Features of this tube include a lightweight metal-cone envelope, a high-quality frosted gray faceplate to prevent specular reflection and increase picture contrast, a space-saving rectangular face shape, and an electron gun designed for use with an external single-field ion-trap magnet.

#### **GENERAL**


ELECTRICAL	
Heater Voltage	Volts
Heater Current	
Focusing Method—Magnetic	
Deflecting Method—Magnetic	
Deflection Angle, approximate	
Diagonal	Degrees
Horizontal	Degrees
Vertical	Degrees
Direct Interelectrode Capacitances, approximate	
Cathode to All Other Electrodes	$\mu\mu$ f
Grid-No. 1 to All Other Electrodes	$\mu\mu$ f
OPTICAL	
Phosphor Number-P4, Sulfide Type	
Fluorescent Color—White	
Phosphorescent Color—White	
Persistence—Short	
Faceplate—Gray	
Light Transmission at Center, approximate	Percent
Specular Reflection of Ambient Light, Maximum	



MECHANICAL	
Over-all Length	Inches
Greatest Bulb Dimensions	
Diagonal16 $\frac{13}{16}$ $\pm \frac{3}{16}$	
Width15 $\frac{15}{16} = \frac{1}{8}$	Inches
Height	Inches
Minimum Useful Screen Dimensions	
Diagonal	
Width	
Height	Inches
Neck Length	Inches
Bulb Contact—Metal Cone Lip	
Base—Small-shell Duodecal 5-pin, JETEC No. B5-57	
Basing, JETEC Designation—12D	
Base Alignment	
Pin-No. 3 Position Aligns with Horizontal Picture Axis ±30 Degrees	
Mounting Position—Any	
Net Weight, approximate	Pounds
MAXIMUM RATINGS	
DESIGN-CENTER VALUES*	
Anode Voltage†	Max Volts DC
Grid-No. 2 Voltage	
Grid-No. 1 Voltage	
Negative-Bias Value	
Positive-Bias Value	
Positive-Peak Value	Max Volts
Peak Heater-Cathode Voltage	
Heater Negative with Respect to Cathode	
During Warm-up Period not to Exceed 15 Seconds	Max Volts
After Equipment Warm-up Period180	
Heater Positive with Respect to Cathode180	Max Volts
TYPICAL OPERATING CONDITIONS!	
Anode Voltage‡14,000	
Grid-No. 2 Voltage	
Grid-No. 1 Voltage§	
Focusing-Coil Current $\pi$ , approximate	
Ion-Trap Field Intensity△, approximate	Gausses

### **CIRCUIT VALUES**

- ♦ All voltages are measured with respect to cathode.
- \* The maximum ratings provide a ten-percent safety factor in accordance with the standard design-center system of rating cathode-ray tubes. The tube will withstand the combined effects of variations in line voltage and components provided the maximum design-center values are not exceeded by more than ten percent.
- † Anode and grid-No. 3 which are connected together within the tube are referred to herein as anode.
- ‡ Brightness and focus quality decrease with decreasing anode voltage. In general, the anode voltage should not be less than 12,000 volts.
- § For visual extinction of focused raster.
- $\pi$  For RETMA focusing coil No. 109 with distance from the yoke-reference-line to center-of-air-gap equal to  $3\frac{1}{2}$  inches.  $\triangle$  Single-field ion-trap magnet adjusted to optimum position, equivalent to 37 milliamperes through RETMA ion-trap magnet No. 117.



#### NOTES:

I.REFERENCE LINE IS DETERMINED BY THE PLANE OF THE UPPER EDGE OF THE REFERENCE-LINE GAGE (RETMA NO. 110) WHEN THE GAGE IS RESTING ON THE CONE.

2.DEFLECTION ANGLE ON DIAGONAL IS 70 DEGREES.

3.METAL CONE OPERATES AT HIGH VOLTAGE AND MUST BE INSULATED TO WITHSTAND THE MAXIMUM APPLIED ANODE VOLTAGE.

4.CONE HEIGHT AT DIAGONAL IS 8 INCHES.

5.PIN-NO. 3 POSITION ALIGNS WITH HORIZONTAL PICTURE AXIS ±30 DEGREES.

6.APPROXIMATE POSITION OF ION-TRAP MAGNET.

7.RECOMMENDED POSITION FOR CENTER OF FOCUSING FIELD.

K-69087-72A697 6-20-55