
TUNG-SOL -

PENTODE MINIATURE TYPE



COATED UNIPOTENTIAL CATHODE

HEATER

18 VOLTS 0.10 AMP.

AC OR DC

ANY MOUNTING POSITION



BOTTOM VIEW MINIATURE BUTTON 7 PIN BASE 7 CC

THE 18FW6 IS A SEMI REMOTE CUTOFF PENTODE IN THE 7 PIN MINIATURE CONSTRUCTION. IT HAS A 100 MA HEATER AND IS DESIGNED FOR RF AND IF APPLICATIONS IN AC/DC TYPE RADIO RECEIVERS.

DIRECT INTERELECTRODE CAPACITANCES A

GRID #1 TO PLATE (MAX.)	.0035	$\mu\mu$ f
INPUT	5.5	$\mu\mu$ f
OUTPUT	5.0	μμ f

AEXTERNAL SHIELD #316 CONNECTED TO PIN 7 (CATHODE).

RATINGS INTERPRETED ACCORDING TO DESIGN MAXIMUM SYSTEM

HEATER VOLTAGE	18	VOLTS
MAXIMUM PLATE VOLTAGE	1.50	VOLTS
MAXIMUM GRID #2 SUPPLY VOLTAGE	150	VOLTS
MAXIMUM GRID #2 VOLTAGE	SEE RATING CHART	
MAXIMUM PLATE DISSIPATION	2.5	WATTS
MAXIMUM GRID #2 DISSIPATION	0.6	WATTS
MAXIMUM HEATER-CATHODE VOLTAGE	100	VOL TS

DESIGN-MAXIMUM RATINGS ARELIMITING VALUES OF OPERATING AND ENVIRONMENTAL CONDITIONS APPLICABLE TO A BOGEY ELECTRON DEVICE OF A SPECIFIED TYPE AS DEFINED BY ITS PUBLISHED DATA, AND SHOULD NOT BE EXCEEDED UNDER THE WORST PROBABLE CONDITIONS. THE DEVICE MANUFACTURER CHOOSES THESE VALUES TO PROVIDE ACCEPTABLE SERVICEABILITY OF THE DEVICE, TAKING RESPONSIBILITY FOR THE EFFECTS OF CHANGES IN OPERATING CONDITIONS DUE TO VARIATIONS IN DEVICE CHARACTERISTICS. THE EQUIPMENT MANUFACTURER SHOULD DESIGN SO THAT INITIALLY AND THROUGHOUT LIFE NO DESIGN-MAXIMUM VALUE FOR THE INTENDED SERVICE IS EXCEEDED WITH A BOGEY DEVICE UNDER THE WORST PROBABLE OPERATING CONDITIONS WITH RESPECT TO SUPPLY-VOLTAGE VARIATION, EQUIPMENT COMPONENT VARIATION,

TYPICAL OPERATING CONDITIONS AND CHARACTERISTICS

HEATER VOLTAGE HEATER CURRENT PLATE VOLTAGE		0.10 100	VOLTS AMP. VOLTS
GRID #3 VOLTAGE CONNECTED TO CATHODE	ΑТ	SOCKET	
GRID #2 VOLTAGE		100	VOLTS
CATHODE BIAS RESISTOR		68	OHMS
PLATE CURRENT		11	MA.
GRID #2 CURRENT		4.4	MA.
TRANSCONDUCTANCE		4400	μ MHOS
PLATE RESISTANCE (APPROX.)		0.25	MEGOHM
GRID #1 VOLTAGE FOR gm = 25 μ MHOS		-20	VOLTS