


Replacement Type

TYPE 1629
(OCTAL BASE)
"MAGIC EYE"

TUNING INDICATOR**CHARACTERISTICS**

Heater Voltage	12.6	volts		
Heater Current	0.15	amp.		
Anode Supply Voltage	100	200	250	volts
Anode Load Resistor	0.5	1.0	1.0	meg.
Anode Current *	0.2	0.2	0.24	mA
Target Voltage	100	200	250	volts
Target Current *	1	3	4	mA
Grid Voltage	-3.3	-6.5	-8	volts

(For 0° shadow angle.)

* For 90° shadow angle, grid voltage zero.