## BRIMAR=



## RECTIFIER VALVE TYPE V.L.S.61

This valve has been especially developed for supplying High Tension Power for Cathode Ray Oscillograph Equipments, Television Apparatus, etc.

## SPECIFICATION.

| Cathode    | ••• |     | Oxide coated filament.   |
|------------|-----|-----|--|
| Base       | ••• | ••• | B.V.A. 4 pin, "grid" and "plate" pins<br>not connected, plate connected to top<br>cap.   |
| Dimensions |     |     | Overall height 5½" (13.4 cms)<br>Bulb diameter 2" (5.1 cms)  |
| Constants  |     | ••• | Filament Voltage 2 volts<br>Nominal Fil, Current 1·2 amps.<br>Peak Instantaneous Current 10 m.a.<br>Peak Inverse Voltage 15,000 volts. |
| Output     |     |     | As half wave rectifier 6,000 volts 3 m.a.  |