RCA-831

R-F Power Amplifier, Oscillator

RCA-831 is a high-power, air-cooled transmitting tube of the three-electrode type containing a thoriated-tungsten filament. Each electrode is supported on a separate stem and each electrode lead is brought out of the bulb through a separate seal. The 831 can be operated at maximum ratings at frequencies as high as 20 megacycles. The plate dissipation for class C telegraph and class B services is 400 watts.

CHARACTERISTICS

MAXIMUM RATINGS

	Tele-	Tele-	Tele- graphy**	
D-C PLATE VOLTAGE	3500	3000	3500	Volts
D-C GRID VOLTAGE		-1000	-1000	Volts
D-C PLATE CURRENT	250	300	350	Milliamperes
D-C GRID CURRENT		75	75	Milliamperes
PLATE INPUT	600	650	1200	Watts
PLATE DISSIPATION	400	270	400	Watts

^{*} Carrier conditions per tube with a max. modulation factor of 1.0.

INSTALLATION AND APPLICATION

The filament base and grid cap of the 831 fit the standard RCA end mountings UT-1085 and UT-1086, respectively. The tube must be mounted in a vertical position with the grid cap down.

The plate of the 831 shows an orangered color at the maximum plate-dissipation rating for each class of service.

For high-frequency operation above 20 megacycles, see page 144.

For additional information, see chapters on INSTALLATION and APPLICATION

Connections to End-Mountings



^{**} Key-down conditions per tube without modulation. Modulation essentially negative may be used if the positive peak of the audio-frequency envelope does not exceed 115% of the carrier conditions.