Protessional Series Model 6006B Power Amplifier

60 waits @ less than 1.0% THD 40 T2 kHz= 85 dB signal to noise ratio Power output meter



The JBL 6006B is a highly reliable, conservatively rated amplifier, designed for professional sound engineering applications where a high degree of performance is required.

The circuitry has been carefully designed to reduce the possibility of failure within the specified environmental and electrical conditions. A protective circuit is utilized in this amplifier which makes it virtually impossible to damage it under any conditions of overload, including shorted or grossly mismatched load, inductive load at low frequencies, capacitive load at high frequencies, excessive input signal, white noise or installation errors.

The JBL 6006B can be overdriven by at least ten times normal input voltage, from 40 Hz-12 kHz, and eventually produces square waves increasing in RMS value up to about 110 watts at which point the output actually begins to decrease.

The DC fuse is intended as a protective device for the power supply in the event of output stage malfunction. It is not intended to protect the output transistors which are guarded by the special circuitry provided. As an indication of high-frequency stability, the JBL 6006B draws only 30% more power from the AC line at 12 kHz, 60W, than at 1 kHz for at least one hour without malfunction or entering the "protect" mode.

The 6006B amplifier is designed for maximum flexibility in varying input and output arrangements. A standard unbalanced 50K input is provided which can be converted to balanced line bridging or matching with the installation of the accessory 5195 transformer. A low cut filter switch reduces the possibility of damaging horns. All the power outputs are balanced and the bridging output unbalanced.

The excellent engineering of this unit is accompanied by an equally excellent layout with serviceability in mind at all times. All components are accessible and easily replaced with particular emphasis on output and driver device removal and installation.



Model 6006 B - Power Amplifier

Architectural Specifications

The amplifier shall be capable of delivering an output of 60W RMS with less than 1.0% THD, 40-12,000 Hz, and 75W RMS from 50 to 8000 Hz with less than 4% THD.

The high impedance program input shall be provided with a socket to accommodate a balanced line with isolation. Matching and bridging inputs shall be available. Screw type terminal boards shall be provided for the balanced line inputs as well as for the high impedance unbalanced input. In addition, a phono plug shall be provided for the high impedance input. A low frequency filter switch shall be provided.

The amplifier shall have balanced 8-ohm, 16-ohm and 70.7-volt outputs on a screw type terminal board listed by Underwriters' Laboratories, Inc. for class 2 wiring.

The amplifier shall be equipped with a protective circuit which will prevent damage due to overload. A power output meter shall be standard equipment.

The amplifier shall operate on 120/240 VAC, 50/60 Hz power source.

The performance specifications shall be as listed under SPECIFICATIONS and shall be met or exceeded.

The amplifier shall be listed by the Underwriters' Laboratories, Inc.

The amplifier shall be JBL Model 6006B.





Professional Series Professional Division

James B. Lansing Sound, Inc., 3249 Casitas Avenue, Los Angeles, California 90039

PPB60068/75 Printed in U.S.A

12

100

