ERVICE MANUAL CS-1554



CONTENTS

SPECIFICATIONS
SPECIFICATIONS
CONTROLS AND CONNECTORS ON FRONT PANEL 4
CONTROLS AND CONNECTORS ON REAR PANEL
CIRCUIT DESCRIPTION
TROUBLE SHOOTING 10 ~ 18
VOLTAGE WAVEFORMS AT INDIVIDUAL POINTS OF CIRCUIT
ADJUSTMENT POINTS ON PC BOARD
ADJUSTMENT
PARTS LAYOUT (REAR VIEW)
PARTS LAYOUT (TOP VIEW) 29 30 30
PARTS LAYOUT (SIDE VIEW)
PARTS LAYOUT (BOTTOM VIEW)
PC BOARD VERTICAL AMPLIEUER UNIT (V70 0011 00)
PC BOARD VERTICAL AMPLIFIER UNIT (X73-0011-00)
PC BOARD HORIZONTAL AMPLIFIER UNIT (X65-0008-01)
PARTS LIST OF CS-1554
PARTS LIST OF X65-0008-01 40 ~ 42
PARTS LIST OF X73-0011-00
BLOCK DIAGRAM
SCHEMATIC DIAGRAM
COLOR CODE
4/

(

()

SPECIFICATIONS

CATHODE RAY TUBE: VERTICAL SECTION

Display:

Deflection sensitivity:

Rise time: Input impedance: Frequency response:

Overshoot:

Sag:

Isolation between channels: Chopping frequency: Polarity inversion: Maximum input voltage:

SWEEP SECTION

Sweep rate:

Sweep magnification:

Linearity:

SWEEP TRIGGERING Mode:

Source and signal requirement:

CH1 only, CH2 only, CHOP-PED, ALTERNATE and ADD 0.01 V/cm - 20 V/cm ±5%, continuously adjustable in all 11 ranges. 35 n sec. $1 M\Omega$ shunted by 38 pFDC DC \sim 10 MHz (-3 dB) AC 2Hz~ 10 MHz (-3 dB) Less than 3% (100 kHz square wave) Less than 5% (AC, 50 Hz square wave) More than 55 dB at 1kHz 140 kHz CH2 signal can be inverted. 300V(DC + AC peak) or 600 Vpp 0.5 µsec/cm~0.5 sec/cm ±5%, continuously variable in all 19 ranges. TV - V (3.6m sec/cm) TV - H (13 µsec/cm) Each sweep rate can be increased 5 times by horizontally expanding the center portion of display. Better than 3% (0.5 sec/cm~ 2 µsec/cm ranges) Better than 5% (1 μ sec/cm ~ 0.5 µsec/cm ranges) Automatic triggering or adjust-

130 ARB 1

both channels)

(Specifications common to

able triggering at desired level Internal triggering (with an input signal level providing more than 10mm deflection CH1 (with an input signal level

Coupling:

1 Vpp)AC 30 Hz ~ 10 MHz (with
AUTO position 50 Hz ~ 10
MHz)LF 5 Hz ~10 kHz (with AUTO
position 10 Hz ~ 10 kHz)DC DC ~10 kHz (with AUTO
position 10 Hz ~ 10 kHz)slope:Either positive or negative
slope of the triggering signal

on the CRT)

more than 10m Vpp)

External triggering (with an

input signal level more than

Trigger slope:

EXTERNAL HORIZONTAL

AMPLIFIER

Deflection sensitivity: Frequency response Input impedance

CALIBRATOR:

INTENSITY MODULATION VOLTAGE:

POWER REQUIREMENT:

DIMENSIONS

(include all protrusion):

WEIGHT:

ACCESSORIES furnished

Probe (PC – 12) . . . 2:

Cable assembly

(CA – 36) 1:

Instruction manual . . 1 (0.5A for 230V source) 3

250 mV/cm DC ~ 1 MHz (-3 dB) 100 k Ω (±20%) shunted by less than 60pF 10 Vpp and 1 Vpp ±5%, 1 kHz square wave

More than 15 Vpp 100V AC (117V, 230V) 50/ 60 Hz, 27 watts

Width250 mm max.Height224 mm max.Depth438 mm max.8.4 kg

Attenuation 1/10 Input impedance 10MΩ shunted by 15pF

Shielded cable terminated on one end with a dual banana plug and on the other end with alligator clips.

CONTROLS AND CONNECTORS ON FRONT PANEL(1)



4

.

CONTROLS AND CONNECTORS ON REAR PANEL(2)



NOTE: Components numbers given in parenthesis apply to CH1.

1. VERTICAL SECTION (X73-0011-00)

1) INPUT CIRCUIT AND ATTENUATOR

Input signals applied to the VERTICAL INPUT 1 and 2 connectors can be ac-coupled, dc-coupled or internally disconnected by the AC-GND-DC selector switch. The signals passed through the switch are coupled to the frequency-compensated attenuators and are reduced to the desired level. The input impedance of each channel is 1 M Ω shunted by 38 pF through 11 ranges.

2) VERTICAL AMPLIFIER

The output signals from the attenuator networks are applied through the excessive input protection circuit using FET (Field Effect Transistor) O_2 (O_4) to the vertical Amplifier. The protection circuit, utilizing the diode characteristic of FET limits VGDs of O_5 (O_7) to below 1 volt. FET O_5 (O_7) is used as source followers to provide a high input impedance to the input circuit Also, FET O_6 (O_8) is used to form a balanced circuit for reducing the effect of drift due to variation of power source voltage and temperature. Further, the following stages O_9 , 10 (O_{11} , 12) provide a low output impedance and their output signals are connected to differential amplifier's O_{13} , 14 (O_{15} , 16).

The dc level is adjusted by the DC BAL source resistor VR101a (VR102a) to obtain the balance of the emitter GAIN circuit. VR103, VR1 (VR104, VR3) placed in the emitters of Q13, 14 (Q15, 16) respectively, provide the gain adjustment, and Q17, 18 VR101b VR2 (Q19, 20 VR102b VR4) shift the dc level to position the trace on the CRT at the proper position horizontally. The signal from CH1 is coupled directly to the dual-trace switching gate, the signal from CH2 is coupled through the CH2 POLARITY switch to the dual-trace switching gate circuit.

The dual-trace switching gate determines whether the CH1 signal or CH2 signal passes on to the differential amplifier $Q_{23} \sim Q_{26}$ through the emitter follower $Q_{21} \sim 22$.

This amplifier $Q_{23} \sim Q_{26}$ is connected in a cascade connection to reduce the Miller effect to the signal in the higher RF region. This allows the differential amplifier to provide sufficient bandwidth.

The output signal of the differential amplifier is fed through Q27, Q28 which presents low output impedance, to final stage amplifier. Also, the same output signal is fed through Q43 and Q44 serving as buffer and level shifter to the sweep trigger circuit for the internal trigger source. VR6 (INT DC ADJ) provides dc level adjustment of the trigger signal at zero volts.

The final stage $\Omega_{29} \sim \Omega_{32}$, which forms a cascade differential circuit is a frequency-compensated amplifier. In this stage, the signal is sufficiently amplified and directly connected to the vertical deflection plates of the CRT. The overall gain of the vertical amplifier is approximately 60 dB, which corresponds to a deflection sensitivity (factor) of 10 mV/cm measured on the CRT screen. Also, the frequency response of the vertical amplifier is DC to 10 MHz (-3 dB).

3) DUAL-TRACE SWITCHING GATE CIRCUIT

 $D_1 \sim D_4$ ($D_5 \sim D_8$) form the switching gate circuit. The four-diode gate can be considered as a switch that selects the channel signal desired at

the output amplifier. Two square wave outputs that are opposite in phase are produced from the switching multivibrator Q41, Q42 and are used to turn the four-diode gate circuits on and off. Thus, the preceding vertical amplifiers are switched alternately by the switching gate.

4) SWITCHING MULTIVIBRATOR AND CHOP-BLANKING CIRCUIT

The multivibrator Q41, Q42 is operated as a flip-flop or an astable multivibrator by biasing transistors. In the CHOP mode, the multivibrator operates as an astable multivibrator with 140 kHz repetition rate, from which the square wave output turns the four-diode gates on and off.

In the ALTER mode, the multivibrator operates as a flip-flop. Then, the signal to trigger the multivibrator is applied from the gate multivibrator in the sweep circuit through the unblanking amplifier and triggering circuit to the bases of Q41, Q42. Accordingly, at the end of each sweep, the output of the flip-flop is inverted and turns the four-diode gate on and off.

In the ADD mode, the power supply to the switching multivibrator is disconnected. Therefore, the four-diode gates of both channels are opened, and the added signal of CH1 and CH2 signal is connected to the output amplifier. In the CHOP mode, when the multivibrator is inverted, the pulse appears at the emitter of the multivibrator.

The pulse is amplified by Q45. This pulse and the unblanking signal are coupled to the first grid of the CRT for unblanking the switching interval trace and transient distortion during the chopping period.

5) TRIGGER SIGNAL AMPLIFIER

In the CH1 position of the SOURCE switch, the sweep is triggered by the signal applied from CH1 only.

Therefore, the trigger signal is applied from the emitter of Q11 (with a low output impedance), placed in front of the switching gate circuit, to the emitter follower Q33, Q47 which offers no disturbance to the preceding stage. For elimination of drift, the circuit is composed as a balanced amplifier. Further, the trigger signal is connected through Q34, Q35 (amplifier), Q36, Q37 (serving as impedance converter), PNP junction Q38, Q39 (amplifier and level shifter) and Q40 (emitter follower with a low output impedance) to the sweep trigger circuit.

The dc level of the trigger signal amplified in the above stages is adjusted by the emitter resistor VR5.

2. SWEEP TRIGGER CIRCUIT (X65-0008-01)

1) PHASE INVERTER AND LIMITER CIRCUIT

The SOURCE switch determines the source of the trigger signal to be coupled to this stage Ω_6 , Ω_7 . This circuit is a differential amplifier with a ground potential at its input. Because of its narrowed dynamic range, the level of its input signal is limited to a certain level. At the same time, this stage operates as a phase inverter. That is, in the positive (+) position of the SLOPE switch, the trigger signal is coupled to the base of Ω_6 . While in the negative (-) position, the signal is coupled to the base of Ω_7 , this causes the circuit to deliver the phase inverted output. In the above operation, the transistor with no input signal is biased through VR105a to adjust the triggering level. Also, in the AUTO position, the circuit with a ground potential input is biased with a fixed bias.

In the AC position of the MODE switch, the dc component of the trigger signal is blocked by the coupling capacitor C110 and the ac component of trigger signal is coupled to the SLOPE switch. In this position, triggering frequency bandwidth is 30 Hz \sim 10 MHz (50 Hz \sim 10 MHz, in the AUTO position). In the LF position, since noise and unwanted components of the chopping signal are rejected by the capacitor C111 (placed in the input circuit), triggering frequency bandwidth is limited to a very low frequency i. e. 5 Hz \sim 10 kHz (10 Hz \sim 10 kHz in the AUTO position). In the DC position, the sweep is triggered with frequencies down to dc, since the trigger signal is directly coupled to the sweep trigger circuit. Also, as in the LF position, the capacitor C111 is placed in the input circuit, and the triggering frequency bandwidth is DC \sim 10 kHz.

2) SQUARE WAVE SHAPER CIRCUIT

This stage consists of the Schmitt Circuit Q8, Q9 mainly. In this circuit, when the input level of the trigger signal reaches a certain level, the Schmitt Circuit produces a uniform square wave with a constant level coincident with the input signal. This square wave is coupled through the differentiation circuit to the gate multivibrator Q10 \sim Q13 as the triggering signal. When in the AUTO position, the bistable multivibrator is turned into an astable multivibrator with 40 \sim 50 Hz repetition rate. Under these conditions, if the input signal is not applied the sweep repetition rate is 40 \sim 50 Hz. Since this astable multivibrator is level sensitive, it will be easily pulled into synchronization with the input signal if supplied.

3. SWEEP CIRCUIT (X65-0008-01)

8

1) GATE MULTIVIBRATOR, MILLER INTEGRATOR AND HOLD-OFF CIRCUIT

The gate multivibrator $Q_{10} \sim Q_{13}$, i. e. a bistable multivibrator of the square wave shaper circuit, the Miller integrator $Q_{17} \sim Q_{20}$ and the hold-off circuit, Q_{14} , which is driven under control from the triggering signal, form a dc loop to generate a sawtooth wave. When the STABILITY control is adjusted, the multivibrator is conditioned to invert its state on the incoming trigger signal. That is, when the triggering signal is fed from the square wave shaper, the state of the multivibrator is changed and the switching diodes D3 and D4 are turned off.

This charges the time-base capacitors inserted in the gate circuit of FET Q17 in accordance with the time constant determined by the value of the time-base resistor and resistor. This charging signal is received through a high input impedance FET Q17, from which it is applied to the following stage Q18, Q19 amplify the charging signal, and invert the phase.

The output of the emitter follower Q_{20} with a low output impedance feed the horizontal amplifier. The amplified signal is the sweep voltage to the horizontal deflection plates of the CRT which displays the trace.

A prat of the output of Ω_{20} is fed back to one side of the time-base capacitor mentioned above. This enables the time-base capacitor to be charged with a constant current, thereby providing a linear sawtooth wave. The hold-off circuit provides delay for the charging waveform back to the input of the gate multivibrator until it reaches a given level, then it inverts the state of the gate multivibrator to the original condition to complete one sweep.

2) INVERTER CIRCUIT

The gate multivibrator produces a negative pulse for the output signal during a display. To obtain a positive pulse for the unblanking signal, this pulse is inverted in phase by Q15. The positive signal produced, together with the chop-blanking signal, is coupled to the grid of the CRT. This cuts off the CRT in the period of the blanking without input signal. Also, in the ALTER mode the output of the inverter is coupled through the differentiation circuit to the triggering circuit providing a trigger pulse for driving the flip-flop Q41, Q42 (X73-0011-00).

3) HORIZONTAL AMPLIFIER CIRCUIT

The sawtooth wave output of the Miller circuit is applied to emitter follower Ω_{21} , with a low output impedance. The output of emitter follower is fed to the differential amplifier Ω_{22} , Ω_{23} .

The variable resistor VR6 (MAG CENT) provides the shift of the bias of D23 to adjust the dc balance, which may be changed when the MAG switch is pulled out or in. The amplifier is also provided with a variable resistor VR7 (POS ADJ1) which is inserted between the emitter resistor R54 and R55 of Q22, D23, and provides a horizontal waveform position adjust on the CRT screen. To obtain the rated gain as selected by the MAG switch, the switch provides selection of VR8 (GAIN ADJ) and VR9 (MAG ADJ) inserted in the emitter circuit of Q22, Q23. In the case where the trace is swept by an external signal, the signal is connected from the EXT HORIZ connector to the variable resistor VR106b (GAIN), where ist gain adjusted. The signal from VR106b is applied to FET Q16 (serving as an impedance converter) and then to the horizontal amplifier mentioned above.

The variable resistor VR4 (POS ADJ2) is provided to adjust the dc level of the external signal to the same level as the mean voltage of the internal sweep signal in order to position the waveform to the horizontal center of the CRT screen. In this case, the horizontal amplifier provides a deflection sensitivity (factor) of 250 mV/cm and a frequency bandwidth of DC \sim 1 MHz (- 3 dB).

4. CALIBRATOR CIRCUIT (X65-0008-01)

The calibrator consists of 1 kHz multivibrator Q1, Q2 and the Schmitt circuit. The output of the 1 kHz multivibrator is fed to the Schmitt circuit. The Schmitt circuit turns the 1 kHz signal from the multivibrator into the square wave signal which is connected to the resistor voltage divider. Thus, calibration voltages of 10 Vpp and 1Vpp are delivered to the respective CAL terminals.

5. POWER SUPPLY CIRCUIT (Chassis and X65-0008-01)

The AC source voltage is applied to the primary windings of the power transformer. The source voltage is induced across the high voltage secondary windings and is rectified by high voltage selenium rectifiers D101 and D102. A voltage doubler provides high voltage for the CRT. The voltage induced across the low voltage secondary windings of the transformer is rectified by diodes D104, D105, D9 and D10 to provide the B supply voltage.

The low voltages for the vertical and horizontal amplifiers are supplied by the stabilized B supply through regulator Q24 and Zener diode D7.

REMOVAL OF CABINET PLATES

- 1. Remove four screws located on the rear-panel of the instrument.
- 2. While holding the top plate at the handle, slide the plate backward approximately 10mm and lift upward, then it comes off the side frames qutie easily.
- 3. Slide the side plate backward after removal of the top plate until they come off the side frame.
- 4. Remove six screws located on the bottom plate. Draw the plate backward while lifting its rear end up slightly and it comes off the side frames.

NOTE: The side plate and top plate can be separated independently.

CAUTION: When performing the above procedure, always turn off the power. Also, be careful not to touch 2500 volt section after removal of the case plates.

ASSEMBLY OF CABINET PLATES

To assemble the cabinet plates to the case frames, reverse the order given in REMOVAL of CABINET PLATES above. Note that the top plate should be assembled to the frames while sliding it forward with the handle being depressed by the hand.

CAUTION: When performing the above procedure, be careful not to touch a cathode ray tube socket, of which the metallic parts assume high voltage (1300V).





S.S.S.

ALC: NO

Callon .







ALL D













VOLTAGE WAVEFORMS AT INDIVIDUAL POINTS OF CIRCUIT

Measuring conditions:

1

Input signal 1 kHz wave 1V SWEEP TIME 0.1mS/CM

(1) WAVEFORMS OF SQUARE WAVE SHAPER CIRCUIT





(2) WAVEFORMS OF GATE MULTIVIBRATOR

* Q10 thru 13 (Q10, 3SK22GR, Q11 thru 13, 2SC371R) located on printed circuit board X65-0008-01.













0 V ------

,

VOLTAGE WAVEFORMS AT INDIVIDUAL POINTS OF CIRCUIT

(3) MILLER INTEGRATOR CIRCUIT

* Q17 thru 20 (Q17, 2SK30 (0); Q18 thru 20, 2SC371R) located on printed circuit board X65-0008-01.





(4) WAVEFORMS OF HOLD-OFF CIRCUIT

* Q14 (2SC371R) located on printed circuit board X65-0008-01.





ADJUSTMENT POINTS ON PC BOARD



ALC: N

- NOTE: * This instrument has been factory adjusted for the following adjustments. If re-adjustment is needed, it should be completed only after calibrating the power source voltage.
 - * Controls surrounded by bold line square are made on the panel.
 - * Figure (4) is an identification number appearing in the section of EXTERNAL VIEWS, CONTROLS AND CONNECTORS ON PANELS.

1. ASTIGMATISM AND FOCUS ADJUSTMENTS

 SWEEP TIME/CM (4)
 EXT

 DC-GND-AC (16) (17)
 GND

 INTENSITY (25)
 max.

Adjust ASTIG (35) so that the bright spot becomes smallest and circular when FOCUS (24) is turned from min. to max. Then confirm that the bright spot changes in the order of



as the FOCUS (24) is turned clockwise.



Conduct the following adjustments with INTENSITY (25) set to the position shown on the left. 3 o'clock position

CH I

NORM

2. BLANKING ADJUSTMENT

Apply 100 kHz sine wave to VERT INPUT 1 (21), and adjust VR10 (BLANK ADJ) located on printed circuit board X65-0008-01 so that portion A indicated becomes dark.





Adjustments and confirmations may be made with MODE (22) set to CH1. Set SOURCE (1), SLOPE (2), COUPLING (3) and CH2 POLARITY (23) to the positions shown below.

3. DC BAL ADJUSTMENT

Note: Numbers in parenthesis refer to CH2.

MODE (22) CH1 (CH2)

Set DC-GND-AC (17) ((16)) to GND.

Turn the vertical attenuator, VARIABLE (15) ((13)), to the minimum. Align the trace to the center of the scale by turning CH1 \blacklozenge POSITION (11) ((10)). Turn VARIABLE (15) ((13)) to the maximum and, if the trace moves accordingly, re-align the trace to the center using DC BAL provided inside the CH1 \blacklozenge POSITION (11) ((10)) knob.

Repeat the above controls for two to three times until the trace is no longer affected by use of VARIABLE (15) ((13)).

4. VERTICAL POSITION ADJUSTMENT

Set CH1 \blacklozenge POSITION (11) ((10)) knob to the mechanical center and then the trace to the center of the scale using VR4 (VR2) on printed circuit board X73-0011-00.

5. VERTICAL SENSITIVITY ADJUSTMENT

Apply 0.04 Vpp square wave to VERT INPUT 1 (21) ((19)). Adjust VR3 (VR1) on printed circuit board X73-0011-00 so that the vertical deflection is 40 mm.

NOTE: When utilizing the square wave output from CAL (28):

Connect CAL 1V connector (28) to VERT INPUT 1 (21) ((19)). Adjust VR3 (VR1) so that the vertical deflection is 50 mm.

6. VERTICAL ATTENUATOR ADJUSTMENT

Provide a 1 kHz square wave generator for 50mVpp and 100 Vpp outputs and apply the signals to VERT INPUT 1 (21) ((19)).

Set CH1 VOLTAGE/CM (14) ((12)) to .02V/CM and adjust trimmer TC 118 located on ATT printed circuit board inside the cabinet so that the waveform of the resultant square wave is of high quality.

Also, conduct the same adjustment on the individual ranges .05V/CM, 1V/CM 20V/CM in the procedure listed below.

.02V/CM	TC 118 (108)	1V/CM	TC 114 (104)
.05	TC 112 (110)	2	-
.1	TC 112 (102)	5	_
.2.	TC 117 (107)	10	TC 116 (106)
.5	TC 119 (109)	20	-

7. PROBE AND INPUT CAPACITANCE ADJUSTMENTS

Set CH1 VOLTAGE/CM (14) ((12)) to .01V/CM.

Connect the probe to VERT INPUT 1 (21) ((19)) connector, apply 1 kHz square wave to the probe tip, and adjust the trimmer in the probe so that the resultant waveform is of high quality. (In this case, the input voltage is attenuated to 1/10 but the input impedance is $10M\Omega$ 15pF.) Then set CH1 VOLTAGE/CM (14) ((12)) to .02V/CM and adjust trimmer TC117 on ATT printed circuit board inside the cabinet so that the square wave is of high quality. Also, conduct the same adjustment on the individual ranges 0.05V/CM, .1/CM 20V/CM in the procedure listed below.

.02V/CM	TC 117 (107)	1V/CM	TC 113 — —	
.05	TC 119 (109)	2		
.1	TC 111 (101)	5.		
.2	_	10	TC 115	
.5 –		[·] 20	-	

8. VERTICAL FREQUENCY RESPONSE

Apply 100 kHz sine wave to VERT INPUT 1 (21) ((19)) and calibrate for a deflection of 60 mm.

Then adjust TC1 on printed circuit board X73-0011-00 so that the deflection decrease to 43 mm when the input frequency is changed from 100 kHz to 10 MHz.

9. STABILITY ADJUSTMENT

TRIG LEVEL (7) AUTO

Apply 1 kHz sine wave to VERT INPUT 1 (21), set STABILITY (6) to the position shown in Fig. 1 below, and adjust VR3 on printed circuit board X65-0008-01 so that the waveform disappears.

Then check that the waveform becomes steady in the position of Fig. 2.

10. CALIBRATION VOLTAGE ADJUSTMENT

CH1 VARIABLE (15) max. (CAL)

Connect VERT INPUT 1 (21) to 1Vpp of CAL (28), and adjust VR2 on printed circuit board X65-0008-01 so that the deflection is 50 mm. Then adjust VR1 on printed circuit borad X65-0008-01 so that lengths A and B equal as shown below.

11. SWEEP RATE AND HORIZONTAL SWEEP SPAN **ADJUSTMENTS**

SWEEP TIME/CM (4)	.1mS
VARIABLE/HOR GAIN (5)	max. (CAL)
MODE (22)	CH1

Apply calibrated 1 kHz sine wave to VERT INPUT 1 (21), adjust the individual POSITION controls so that the starting point of the waveform is positioned at the left end of the scale and in the vertical center. Also adjust VRs on printed circuit board X65-0008-01 so that one wavelength of the wave is 100 mm on the CRT scale.

With this adjustment, since the length of the trace will change, adjust the length to 105 mm using VR5 on the same printed circuit board.

For ranges of from 10μ S to 0.5μ S/cm, the input frequency should be adjusted not with VRs, VRs but with the trimmers attached to the SWEEP TIME rotary switch, as listed below.

SWEEP TIME/CM	Input frequency	Trimmer to be adjusted	
10µS/cm	10 kHz	TC 121	
1µS/cm	100 kHz	TC 122	
0.5µS/cm	200 kHz	TC 123	





Fig. 1

Fig. 2







12. SWEEP MAGNIFICATION ADJUSTMENT

1) MAG X5 ADJUSTMENT

Apply 1 kHz (approximately) sine wave to VERT INPUT 1 (21), adjust the generator frequency and POSITION (9) to obtain 11 peaks of the waveform and to place each of these peaks on each vertical graticule line.

Adjust VR9 on printed circuit board X65-0008-01 so that distance from one peak to another is 50 mm when MAG X5 (9) is set to "X5"

2) MAG CENTER ADJUSTMENT

Apply 1 kHz square wave to VERT INPUT 1 (21) and adjust so that one cycle of the waveform lies extending from the first to last vertical graticule line. Set POSITION (9) to the mechanical center and MAG X-5 (9) to "X5", and adjust VRe on printed circuit board X65-0008-01 so that the rising (or falling) point in the center of the waveform coincides with that obtained with the normal position of the MAG X5 switch.





13. HORIZONTAL POSITION ADJUSTMENT (1)

POSITION (9).... Mechanical center

Place the starting point of the waveform on the left end of the scale using VR7 on printed circuit board X65-0008-1.

14. HORIZONTAL POSITION ADJUSTMENT (2)

SWEEP TIME/CM (4) EXT POSITION (9) Mechanical center

After completion of "13. HORIZONTAL POSITION ADJUSTMENT (1)", position the spot at the midpoint of the scale using VR4 on the same printed circuit board.

15. TRIG LEVEL ADJUSTMENT

* This adjustment should be carried out with TRIG LEVEL (7) set not to AUTO but by triggering with TRIG LEVEL (7).

1) INT DC LEVEL ADJUSTMENT

Apply 1 kHz sine wave to VERT INPUT 1 (21) and adjuts VR6 on printed circuit board X73-0011-00 so that the starting point may not move when COUPLING (3) is switched between AC and DC.

2) CH1 DC LEVEL ADJUSTMENT

Adjust VRs on printed circuit board X73-0011-00 in the same way1).

PARTS LAYOUT(FRONT VIEW)



PARTS LAYOUT(REAR VIEW)



-Califa

1

PARTS LAYOUT(TOP VIEW)



PARTS LAYOUT (SIDE VIEW)



PARTS LAYOUT(BOTTOM VIEW)



100

-

-

Circuit No.	Parts No.	Description	Remarks
	A10-0215-52	Chassis	
_	A13-0001-03	Frame (1)	
	A13-0005-24	Frame (5)	
	A13-0021-03	Frame (22)	
_	A13-0022-23	Frame (23)	
	A13-0022-23	Frame (24)	
_	A13-0023-33	Frame (26)	
	A20-0339-02	Panel	
	A20-0339-02 A22-0082-22	Sub-chassis	
	-		
_	A40-0061-03	Bottom plate	
-	A48-0003-13	Side plate	
	A52-0002-23	Top plate	
	B01-0002-13	Escucheon	
-	B19-0028-04	Celluloid plate	
-	B20-0170-14	Graticule	
-	B30-0042-15	Lamp	
-	B40-0332-14	Name plate	
104239 1	B42-0009-04	Passed sticker	
-	B48-0049-00	Label	
	B50-0589-00	Instruction manual	
-	D21-0144-24	Shaft (1)	
_	D21-0145-04	Shaft (2)	
15.51277	021-0140-04		
-	E01-1202-05	CRT socket	
-	E04-0102-05	Receptacle type M	
-	E05-0303-05	Power (line) plug	
-	E07-0701-05	Power (line) receptacle	
-	E13-0102-15	Pin jack	
-	E13-0104-05	Pin jack	
-	E14-0101-05	Pin plug	
-	E15-0029-15	Neon bulb bracket	
-	E18-0106-05	Banana tip receptacle	
	E21-0137-14	Metallic binding post	
-	E21-0207-13	Binding post	
_	E22-0206-05	Lug board	
-	E22-0404-05	Lug board	
-	E23-0015-04	Ground lug	
-	E23-0017-04	Ground lug	
-	E23-0042-00	Soldering lug	
-	E30-0085-03	Power (line) cord with plug (CA36)	
	F05-5013-05	Fuse	
_	F10-0183-04	Shield (1)	
_	F10-0184-04	Shield (2)	
	F10-0186-04	Shield (3)	
	F11-0110-14	Shield case (1)	
	F11-0110-14	Shield case (2)	
_	F11-0112-23	Shield case (3)	
_	F12-0007-12	CRT shield	
_	F12-0007-12 F14-0007-04	Soft tape	
	1 14-0007-04	SUIT tape	

Circuit No.	Parts No.	Description	Remarks
_	F20-0029-04	Insulator	
_	F20-0045-04	Insulator	
	1 20 0040 04	insulator	
_	G01-0186-04	Spring	
_	G13-0038-00	Cushion	
	010-0000-00	Cusinon	
_	H01-0498-03	Packing case	
-	H10-0023-04	Protection board	
_	H10-0611-03	Packing material, foamed styrene	
· 1	H20-0006-03	Protection cover	
	H25-0003-03	Protection bag	
	H25-0029-04	Polyethylene bag	
-	J01-0013-13	Metallic leg	
_	J02-0008-03	Molded leg	
	J10-0006-03	Bezel	
	J13-0004-05	Fuse holder	
_	J20-0004-04	Grip bracket	
112	J21-0040-04	Grip bracket (2)	
_	J21-0096-04	CRT bracket	
_	J21-0695-04	PC board bracket	
_	J21-0696-04	Lamp bracket (1)	
_	J21-0697-04	Lamp bracket (2)	
_	J25-0443-14	Printed circuit board	
_	J30-0071-04	Spacer	
_	J41-0006-00	Power (line) cord bushing	
_	J42-0009-04	Rubber bushing	
_	J42-0010-04	Rubber bushing	
	042 0010 04	Trabber basining	
_	K01-0029-04	Grip	
	K01-0036-03	Grip bracket	
	3		
-	L02-0028-25	Power transformer	
-	X65-0008-01	Horizontal amplifier unit	
-	X73-0011-00	Vertical amplifier unit	
-	Y87-0013-01	Probe (PC-12)	
. –		Cathode ray tube 130 ARB1	
	A	SWITCH	ų.
101	S32-2001-15	Slide switch	
102a~d	S06-4002-15	Rotary switch (VR103)	
103	S32-2001-15	Slide switch	
104a~d	S06-4002-15	Rotary switch (VR104)	
105a~e	S04-3007-15	Rotary switch	
106a~h	S12-4001-15	Rotary switch (VR106a, b)	
107	S32-2001-15	Slide switch	
108	S31-2007-05	Slide switch	
109	S32-2001-15	Slide switch	
110a, b	R08-9001-15	Variable resistor (VR105 a, b)	

3

-

Circuit No.	Parts No.	D	Remarks			
S111	R03-1016-05	Variable resistor (VR107)				
S112	R03-0001-15	Variable resistor (VR111)				
		KNO	3			
-	K21-0003-04	Knob				
-	K21-0006-14	Knob				
-	K21-0009-04	Knob				
_	K21-0102-04	Knob				
-	K21-0202-04	Knob	4.			Δ
		DIOD	E	an a		
0101,102		High voltage diode (ED01	-04)			
0103, 104		Diode (8-05-08)				
	5	POTENTION	METER			
/R101a, b	R06-3005-05	Variable resistor				
VR102a, b	R06-3005-05	Variable resistor				
VR103	S06-4002-15	Rotary switch (S102a~d)				
VR104	S06-4002-15	Rotary switch (S104a~d)				
/R105a, b	R08-9001-15	Variable resistor $100k\Omega$		0 k O (B)		
/R106a, b	S12-4001-15	Rotary switch (S106a~b)		UK32 (D)		
/R107	R03-1016-05	Variable resistor (S111)				
/R108	R03-6006-05	Variable resistor $250k\Omega$				<i>v</i>
VR109	R16-8005-05	Variable resistor $1M\Omega$ (B			-	
VR110	R16-7003-05	Variable resistor $500k\Omega$				
/R111	R03-0001-15	Variable resistor (S112)				
		RESIST				
R101,102	PD14BY2E470J	Insulated carbon film	47Ω	±5%	1/4W	
R103	PD14BY2H904F	Insulated carbon film	900kΩ	±1%	1/2W	
R104	PD14BY2H1113F	Insulated carbon film	111kΩ	±1%	1/2W	
R105	PD14BY2H994F	Insulated carbon film	990kΩ	±1%	1/2W	
R106	PD14BY2H1012F	Insulated carbon film	10.1kΩ	±1%	1/2W	
3107	PD14BY2H9993F	Insulated carbon film	999k Ω	±1%	1/2W	
R108	PD14BY2H102F	Insulated carbon film	1kΩ	±1%	1/2W	
R109	PD14BY2H504F	Insulated carbon film	500kΩ	±1%	1/2W	
R110	PD14BY2H105F	Insulated carbon film	1MΩ	±1%	1/2W	
R111	PD14BY2H804F	Insulated carbon film	800kΩ	±1%	1/2W	
R112	PD14BY2H254F	Insulated carbon film	250kΩ	±1%	1/2W	
3113	PD14BY2H904F	Insulated carbon film	900kΩ	±1%	1/2W	
R114	PD14BY2H1113F	Insulated carbon film	111kΩ	±1%	1/2W	×
115	PD14BY2H994F	Insulated carbon film	990kΩ	±1%	1/2W	
R116	PD14BY2H1012F	Insulated carbon film	10.1kΩ	±1%	1/2W	
R117	PD14BY2H9993F	Insulated carbon film	999kΩ	±1%	1/2W	
R118	PD14BY2H102F	Insulated carbon film	1kΩ	±1%	1/2W	
R119	PD14BY2H504F	Insulated carbon film	500kΩ	±1%	1/2W	
R120	PD14BY2H105F	Insulated carbon film	1MΩ	±1%	1/2W	
R121	PD14BY2H804F	Insulated carbon film	800kΩ	±1%	1/2W	
3122	PD14BY2H254F	Insulated carbon film	250kΩ	±1%	1/2W	
R123	PD14BY2E104J	Insulated carbon film	100kΩ	±5%	1/4W	
178 N 19211 W	PD14BY2E153J	Insulated carbon film	15k Ω	±5%	1/4W	
3124	PD14BY2H305F	Insulated carbon film	3MΩ	±1%	1/2W	

Circuit No.	Parts No.	Desc	ription			Remarks
R126, 127	PD14BY2H105F	Insulated acrbon film	$1M\Omega$	±1%	1/2W	1
R128	PD14BY2E272J	Insulated carbon film	2.7kΩ	±5%	1/4W	
R129	PD14BY2E333J	Insulated carbon film	33kΩ	±5%	1/4W	
R131	R92-0054-25	SC resistor	2.2MΩ	±5%	1W	
R132	PD14BY2H134J	Insulated carbon film	130kΩ	±5%	1/2W	
R134	RN14AA3A681J	Metal film	680Ω	±5%	1W	
R135	RN14AA3A391J	Metal film	390 Ω	±5%	1W	
R136	PD14BY2E104J	Insulated carbon film	100kΩ	±5%	1/4W	
R137	PD14BY2E470J	Insulated carbon film	47Ω	±5%	1/4W	
		CAPACITO	R			
C101, 102	C90-0021-05	Metalized film	0.1µF	±20%	600V	8
C103	CQ08S2B330J	Polystyrene	33pF	±5%	125V	
C104	CQ08S1H331J	Polystyrene	330pF	±5%	50V	
C105	CQ05S1H332J	Polystyrene	3300pF	±5%	50V	
C106	CQ08S2B330J	Polystyrene	33pF	±5%	125V	
C107	CQ08S1H331J	Polystyrene	330pF	±5%	50V	
C108	CQ05S1H332J	Polystyrene	3300pF	±5%	50V	
C109	CC94SL2H150J	Ceramic	15pF	±5%	500∨	
C110	CE04D1H010N	Non-polarized electrolytic	1μF		50V	
C111	CQ93M1H153M	Mylar	0.015µF	±20%	50V	
C112	CE04D1H010N	Non-polarized electrolytic	1µF		50V	
C113	C90-0018-05	Metalized film	1µF	±1%	200V	
C114	C90-0019-05	Metalized film	0.1µF	±1%	200V	
C115	C90-0020-05	Metalized film	0.01µF	±1%	200V	
C116	CM91D2H102F	Mica	0.001µF	±1%	500V	
C117	CM91D2H900J	Mica	90pF	±5%	500V	
C118	CC94SL2H121J	Ceramic	120pF	±5%	500V	
C119	CQ93M1H333K	Mylar	0.033µF	±10%	50V	
C120	CQ93M1H224K	Mylar	0.22µF	±10%	50V	
2121	CK94YY2H223M	Ceramic	0.022µF	±20%	500V	
C122	CK94YY2H222M	Ceramic	0.0022µF	±20%	500V	
C123	CK94YY2H102M	Ceramic	0.001µF	±20%	500V	
C124	CC94SL2H101J	Ceramic	100pF	±5%	500V	
C125	CC94SL2H100J	Ceramic	10pF	±5%	500V	
C126	CC94SL2H101J	Ceramic	100pF	±5%	500V	
C127	CK94YY2H103M	Ceramic	0.01µF	±20%	500V	а.
2128~131	C90-0042-05	Oil	0.5µF	±10%	1.5kV	
C132a~c	CE62AD2E470	Electrolytic block	47μF		250V	
2133	CM91D3C120K	Mica	12pF	±10%	1.6kV	
2134	CQ93M1H223M	Mylar	0.022µF	±20%	50V	
2135	CP02B2J104K	Oil	0.1µF	±10%	630V	
ГС101	C05-0015-15	Ceramic trimmer	40pF			
FC102	C05-0010-15	Ceramic trimmer	10pF			
rC103	C05-0015-15	Ceramic trimmer	40pF			
FC104	C05-0010-15	Ceramic trimmer	10pF			
rC105	C05-0015-15	Ceramic trimmer	40pF			
C106, 107	C05-0010-15	Ceramic trimmer	10pF	•		
C108	C05-0015-15	Ceramic trimmer	40pF			
C109, 110	C05-0013-15	Ceramic trimmer	20pF			т
			40pF			
PARTS LIST OF CS-1554

Circuit No.	Parts No.	Description	Remarks
TC112 TC113 TC114 TC115 TC116,117 TC118 TC119,120 TC121~123	C05-0010-15 C05-0015-15 C05-0010-15 C05-0015-15 C05-0010-15 C05-0015-15 C05-0013-15 C05-0011-05	Ceramic trimmer10pFCeramic trimmer40pFCeramic trimmer10pFCeramic trimmer40pFCeramic trimmer10pFCeramic trimmer40pFCeramic trimmer20pFCeramic trimmer10pF	
		· · ·	. 8
а ж			, , ,

30

ALC: N

PARTS LIST OF X65-0008-01

Circuit No.	Parts No.	Description	Remarks
	J25-0497-23	PC board	
		SEMICONDUCTOR	
Q1~9 Q10 Q11~14 Q15 Q16 Q17 Q18~21 Q22~24		2SC371 (R) 3SK22 (GR) 2SC371 (R) 2SC627 (2) 2SK19 (Y) 2SK30 (0) 2SC371 (R) 2SC627 (2)	×
D1 D2 D3 D4, 5 D6 D7 D8 D9 D10 D11 D12		ZB1-6 1S1555 1N60 1S1555 ZB1-12 SZ-200-25 ZB1-6 1S1850 1S1850R 1S1555 10D10	
		POTENTIOMETER	
VR1 VR2 VR3 VR4 VR5,6 VR7,8 VR9 VR10	R12-5002-05 R12-1004-05 R12-3004-05 R12-5002-05 R12-3002-05 R12-1002-05 R12-0004-05 R12-5018-05	PC trimmer potentiometer $100k\Omega$ (B)PC trimmer potentiometer $4.7k\Omega$ (B)PC trimmer potentiometer $47k\Omega$ (B)PC trimmer potentiometer $100k\Omega$ (B)PC trimmer potentiometer $10k\Omega$ (B)PC trimmer potentiometer $10k\Omega$ (B)PC trimmer potentiometer $1k\Omega$ (B)PC trimmer potentiometer 330Ω (B)PC trimmer potentiometer $220k\Omega$ (B)	
L		RESISTOR	L
R14 R15 R16 R17	PD14BY2E103J PD14BY2E473J PD14BY2E473J PD14BY2E473J PD14BY2E472J PD14BY2E470J PD14BY2E470J PD14BY2E103J PD14BY2E103J PD14BY2H501F PD14BY2E103J PD14BY2E103J PD14BY2E332J PD14BY2E332J PD14BY2E332J PD14BY2E102J PD14BY2E104J PD14BY2E104J PD14BY2E272J	Insulated carbon film $10k\Omega$ $\pm 5\%$ Insulated carbon film $47k\Omega$ $\pm 5\%$ Insulated carbon film $10k\Omega$ $\pm 5\%$ Insulated carbon film $10k\Omega$ $\pm 5\%$ Insulated carbon film $47k\Omega$ $\pm 5\%$ Insulated carbon film $4.7k\Omega$ $\pm 5\%$ Insulated carbon film 47Ω $\pm 5\%$ Insulated carbon film $27k\Omega$ $\pm 5\%$ Insulated carbon film $10k\Omega$ $\pm 5\%$ Insulated carbon film $10k\Omega$ $\pm 5\%$ Insulated carbon film $10k\Omega$ $\pm 5\%$ Insulated carbon film 120Ω $\pm 5\%$ Insulated carbon film $10k\Omega$ $\pm 5\%$ Insulated carbon film $10k\Omega$ $\pm 5\%$ Insulated carbon film $10k\Omega$ $\pm 5\%$ Insulated carbon film $3.3k\Omega$ $\pm 5\%$ Insulated carbon film $10k\Omega$ $\pm 5\%$ Insulated carbon film $100k\Omega$ $\pm 5\%$	1/4W 1/4W 1/4W 1/4W 1/4W 1/4W 1/4W 1/4W

PARTS LIST OF X65-0008-01

ARE IN

100.20

ALINA

Circuit No.	Parts No.	De	escription			Remarks
R19	PD14BY2E392J	Insulated carbon film	3.9kΩ	±5%	1/4W	
R20	PD14BY2E273J	Insulated carbon film	27kΩ	±5%	1/4W	
R21	PD14BY2E103J	Insulated carbon film	10kΩ	±5%	1/4W	
722	PD14BY2E183J	Insulated carbon film	18kΩ	±5%	1/4W	
723	PD14BY2E222J	Insulated carbon film	2.2kΩ	±5%	1/4W	
324	PD14BY2E104J	Insulated carbon film	100kΩ	±5%	1/4W	
R25	PD14BY2E273J	Insulated carbon film	27kΩ	±5%	1/4W	
120	PD14BY2E222J	Insulated carbon film	2.2kΩ	±5%	1/4W	
R27	PD14BY2E103J	Insulated carbon film	10kΩ	±5%	1/4W	
127	PD14BY2E182J	Insulated carbon film	1.8kΩ	±5%	1/4W	
R29	PD14BY2E103J	Insulated carbon film	10kΩ	±5%	1/4W	
120	PD14BY2E272J	Insulated carbon film	2.7kΩ	±5%	1/4W	
130	PD14BY2E472J	Insulated carbon film	4.7kΩ	±5%	1/4W	
32	PD14BY2E333J	Insulated carbon film	33kΩ	±5%	1/4W	
132	PD14BY2E103J	Insulated carbon film	10kΩ	±5%	1/4W	
135, 34	PD14BY2E821J	Insulated carbon film	820Ω	±5%	1/4W	
136	PD14BY2E223J	Insulated carbon film	82032 22kΩ	±5%	1/4W	
130	PD14BY2E822J	Insulated carbon film	22k32 8.2kΩ	±5%	1/4W	
40	PD14BY2E103J	Insulated carbon film	0.2K32 10kΩ	±5%	1/4W	
40 841	PD14BY2E183J	Insulated carbon film	18kΩ	±5%	1/4W	
43	PD14BY2E103J PD14BY2E273J	Insulated carbon film	$27k\Omega$	±5%	1/4W	
44	PD14BY2E183J	Insulated carbon film	27k32 18kΩ	±5%	1/4W	
45	PD14BY2E752J	Insulated carbon film	7.5kΩ	±5%	1/4W	
46	PD14BY2E332J	Insulated carbon film	$3.3k\Omega$	±5%	1/4W	
47	PD14BY2E105J	Insulated carbon film	1MΩ	±5%	1/4W	
48	PD14B12E103J PD14BY2E182J	Insulated carbon film	$1.8k\Omega$	±5%	1/4W	
49	PD14BY2E102J	Insulated carbon film	1.0k32 10kΩ	±5%	1/4W	
50	PD14BY2E153J	Insulated carbon film	15kΩ	±5%	1/4W	
51	PD14BY2E332J	Insulated carbon film	3.3kΩ	±5%	1/4W	
52	PD14B12E332J PD14BY2E821J	Insulated carbon film	820Ω	±5%	1/4W	
152	PD14BY2E123J	Insulated carbon film	12kΩ	±5%	1/4W	
54,55	PD14BY2E222J		$2.2k\Omega$	±5%	1/4W	
56 56		Insulated carbon film	2.2ks2 4.7kΩ	±5%	1/4W	
	PD14BY2E472J	Insulated carbon film			Contract Annual Contraction	
58,59	RN14AB3F153J	Metal film	15kΩ	±5%	3W	
60	RN14AB3A221J	Metal film	220Ω	±5%	1W	
61	PD14BY2E561J	Insulated carbon film	560Ω 1.5kΩ	±5%	1/4W	
62	PD14BY2E152J	Insulated carbon film	1.5kΩ	±5%	1/4W	
63	PD14BY2H470J	Insulated carbon film	47Ω	±5%	1/2W	
64	PD14BY2E181J	Insulated carbon film	180Ω	±5%	1/4W	
65	RN14AB3D471J	Metal film	470Ω	±5%	2W	
66	RN14AB3F123J	Metal film	12kΩ	±5%	3W	
67	PD14BY2H473J	Insulated carbon film	47kΩ	±5%	1/2W	8
70,71	R92-0055-25	SC resistor	1MΩ	±5%	1W	
72	PD14BY2H474J	Insulated carbon film	470kΩ	±5%	1/2W	
73	R92-0055-25	SC resistor	1MΩ	±5%	1W	
74	R92-0056-25	SC resistor	820kΩ	±5%	1W	
77	PD14BY2H474J	Insulated carbon film	470kΩ	±5%	1/2W	
78	PD14BY2E332J	Insulated carbon film	3.3kΩ	±5%	1/4W	
79	PD14BY2E272J	Insulated carbon film	2.7kΩ	±5%	1/4W	
80,	PD14BY2E104J	Insulated carbon film	100kΩ	±5%	1/4W	
81	PD14BY2E822J	Insulated carbon film	8.2kΩ	±5%	1/4W	
82	PD14BY2E101J	Insulated carbon film	100Ω	±5%	1/4W	

PARTS LIST OF X65-0008-01

Circuit No.	Parts No.	Desc	cription			Remarks
R90	PD14BY2E472J	Insulated carbon film	4.7kΩ	±5%	1/4W	
R91	PD14BY2E474J	Insulated carbon film	470kΩ	±5%	1/4W	
R92	PD14BY2E392J	Insulated carbon film	$3.9k\Omega$	±5%	1/4W	
R93	PD14BY2E104J	Insulated carbon film	$100k\Omega$	±5%	1/4W	
		CAPACI	TOR	-		
C1,2	СК94ҮҮ2Н103М	Ceramic	0.01µF	±20%	500V	
C3	CE04W1H010	PC electrolytic	1μ		50V	
24	CC94SL2H470J	Ceramic	47pF	±5%	500V	
25	CE04W1C101	PC electrolytic	100µF		16V	
6	CE04D1H010N	Non-polarized electrolytic	1μF		50V	
27	CC94SL2H101J	Ceramic	100pF	±5%	500V	
8	CC94SL2H150J	Ceramic	15pF	±5%	500V	
29	CC94SL2H050D	Ceramic	5pF	±0.5%	500V	
C10	CK94YY2H103M	Ceramic	0.01µF	±20%	500V	
C11	CC94SL2H101J	Ceramic	100pF	±5%	500V	
212	CK94YY2H681M	Ceramic	680pF	±20%	500V	
213	CC94SL2H300J	Ceramic	30pF	±5%	500∨	
214	CK94YY2H331M	Ceramic	330pF	±20%	500V	
215	CK94YY2H103M	Ceramic	0.01µF	±20%	500V	
216	CQ93M1H122J	Mylar	1200pF	±5%	50V	
:18	CK94YY2H103M	Ceramic	0.01µF	±20%	500∨	
:19	CE04W1C471	PC electrolytic	470µF		16V	
20~22	CE04W1H470	PC electrolytic	47µF		50V	
23	CE04W1E470	PC electrolytic	47µF		25V	
24	CE04W1H470	PC electrolytic	47µF		50V	
25,26	CE04W1H221	PC electrolytic	220µF		50V	
27	CE04W1C471	PC electrolytic	470µF.		16V	
28	CE04W1H221	PC electrolytic	220µF		50V	
29	CK94YY3C103M	Ceramic	0.01µF	±20%	1.6kV	
30	CM91B3C220K	Mica	22pF	±10%	1.6kV	
34	CC94SL1H100D	Ceramic	10pF	±0.5%	50V	
35	CE04W1C101	PC electrolytic	100µF		16V	
36 37	CK94YY1H222M	Ceramic	0.0022µF	±20%	50V	
38	CK94YY1H471M	Ceramic	470pF	±20%	50V	
39	CK94YY1H222M	Ceramic	0.0022µF	±20%	50V	
40	CK94YY2H221M	Ceramic	220pF	±20%	500V	
C1	C05-0029-15	Ceramic trimmer	50pF		a -	
				,		
× .)						
		а ж				6.1

PARTS LIST OF X73-0011-00

Ant

1000

Aller

Circuit No.	Parts No.	Des	cription			Remarks
_	J25-0444-13	PC board				
	F02-0004-05	Heat sink				
	F11-0026-04	Shield case				
- -	111-0020-04					
S1	S40-2007-15	Pushbutton switch			£	
	2	SEMICONDUC	TOR			
Q2,4		2SK19 (GR)				
Q5~8		2SK30 (O)				
Q9~30		2SC458 (C)				
Q31,32		2SC526				
Q33~37		2SC458 (C)				
Q38, 39		2SA562 (Y)				
Q40		2SC458 (C)			*I	
Q41,42		2SC371 (R)				
Q43		2SA562 (Y)				
Q44		2SC458 (C)				
Q45		2SC627 (3)				
Q46,47		2SC458 (C)				
		101555				
D1~8		1S1555				
D9,10		1N60				
D11,12		1S1555				
		POTENTIOME	TER		1	
VR1	R12-0004-05	PC trimmer potentiometer	330Ω (B)		ĸ	
VR2	R12-3004-05	PC trimmer potentiometer	47kΩ (B)			
VR3	R12-0004-05	PC trimmer potentiometer	330 Ω (B)			
VR4	R12-3004-05	PC trimmer potentiometer	47k Ω (B)			
VR5,6	R12-1004-05	PC trimmer potentiometer	4.7kΩ (B)			×
	5. ×	RESISTOR	1			
R3	PD14BY2E104J	Insulated carbon film	100k	±5%	1/4W	
R4	PD14BY2E102J	Insulated carbon film	1kΩ	±5%	1/4W	
R5	PD14BY2H105F	Insulated carbon film	1MΩ	±1%	1/2W	
R6	PD14BY2E102J	Insulated carbon film	1kΩ	±5%	1/4W	
R7~9	PD14BY2E562J	Insulated carbon film	5.6k Ω	±5%	1/4W	
R10	PD14BY2E101J	Insulated carbon film	100Ω	±5%	1/4W	
R11,12	PD14BY2E562J	Insulated carbon film	5.6k Ω	±5%	1/4W	х.
R13,14	PD14BY2E272J	Insulated carbon film	2.7k Ω	±5%	1/4W	
R16	PD14BY2E152J	Insulated carbon film	1.5k Ω	±5%	1/4W	
R17	PD14BY2E332J	Insulated carbon film	3.3k Ω	±5%	1/4W	
R18, 19	PD14BY2E272J	Insulated carbon film	2.7k Ω	±5%	1/4W	
R20	PD14BY2E332J	Insulated carbon film	$3.3k\Omega$	±5%	1/4W	
R23	PD14BY2E104J	Insulated carbon film	$100k\Omega$	±5%	1/4W	
R24	PD14BY2E102J	Insulated carbon film	1kΩ	±5%	1/4W	
R25	PD14BY2H105F	Insulated carbon film	1ΜΩ	±1%	1/2W	
R26	PD14BY2E102J	Insulated carbon film	1kΩ	±5%	1/4W	
R27~29	PD14BY2E562J	Insulated carbon film	5.6kΩ	±5%	1/4W	
R30	PD14BY2E101J	Insulated carbon film	100Ω	±5%	1/4W	
R31,32	PD14BY2E562J	Insulated carbon film	5.6kΩ	±5%	1/4W	
	PD14BY2E272J	Insulated carbon film	2.7kΩ	±5%	1/4W	
R33,34			2.1 144	-070	1/-1/4	

PARTS LIST OF X73-0011-00

R36 PD14BY2E152/ PD14BY2E322/ Insulated carbon film 1.5kΩ $\pm 5\%$ $1/4W$ R37 PD14BY2E322/ PD14BY2E322/ Insulated carbon film 2.7kQ $\pm 5\%$ $1/4W$ R40 PD14BY2E322/ PD14BY2E322/ Insulated carbon film 2.7kQ $\pm 5\%$ $1/4W$ R45-48 PD14BY2E222/ PD14BY2E222/ Insulated carbon film kQ $\pm 5\%$ $1/4W$ R51 PD14BY2E222/ Insulated carbon film kQ $\pm 5\%$ $1/4W$ R54 PD14BY2E2122/ Insulated carbon film kQ $\pm 5\%$ $1/4W$ R56, 57 PD14BY2E122/ Insulated carbon film $1kQ$ $\pm 5\%$ $1/4W$ R66, 67 PD14BY2E122/ Insulated carbon film $1kQ$ $\pm 5\%$ $1/4W$ R62 PD14BY2E121 Insulated carbon film $1kQ$ $\pm 5\%$ $1/4W$ R63, 67 RN14AA3A472J Metal film $2.7kQ$ $\pm 5\%$ $1/4W$ R74 PD14BY2E121 Insulated carbon film $5.6kQ$ $1/4W$ R74 PD14BY2E2221 Insulated carbon film $5.6kQ$ $1/4W$	Circuit No. Parts No.		De		Remarks		
R37 PD14BY2E332.1 Insulated carbon film 3.3kΩ ±5% 1/4W R38,39 PD14BY2E321.1 Insulated carbon film 2.7kΩ ±5% 1/4W R46 PD14BY2E321.1 Insulated carbon film 1.kΩ ±5% 1/4W R45-48 PD14BY2E321.1 Insulated carbon film 82.kΩ ±5% 1/4W R61.52 PD14BY2E2721.1 Insulated carbon film 82.kΩ ±5% 1/4W R55.57 PD14BY2E2721.1 Insulated carbon film 2.kΩ ±5% 1/4W R66.67 PD14BY2E1221.1 Insulated carbon film 1.2kΩ ±5% 1/4W R68.59 PD14BY2E1231.1 Insulated carbon film 1.2kΩ ±5% 1/4W R64.66 PD14BY2E1231.1 Insulated carbon film 1.0kΩ ±5% 1/4W R64.66 PD14BY2E1331.1 Insulated carbon film 1.0kΩ ±5% 1/4W R64.67 PD14BY2E1331.1 Insulated carbon film 1.0kΩ ±5% 1/4W R77.71 PD14BY2E331.1 <td< th=""><th>R36</th><th>PD14BY2E152J</th><th>Insulated carbon film</th><th>1.5kΩ</th><th>±5%</th><th>1/4W</th><th>*</th></td<>	R36	PD14BY2E152J	Insulated carbon film	1.5k Ω	±5%	1/4W	*
R38,39 PD14BY2E272J Insulated carbon film 2.7kΩ ±5% 1/4W R40 PD14BY2E32J Insulated carbon film 3.3kΩ ±5% 1/4W R46-48 PD14BY2E82J Insulated carbon film 8.2kΩ ±5% 1/4W R49.50 PD14BY2E82J Insulated carbon film 2.7kΩ ±5% 1/4W R51.52 PD14BY2E681J Insulated carbon film 2.7kΩ ±5% 1/4W R54.55 PD14BY2E102J Insulated carbon film 12.kΩ ±5% 1/4W R56.95 PD14BY2E12J Insulated carbon film 12.kΩ ±5% 1/4W R56.96 PD14BY2E12J Insulated carbon film 12.kΩ ±5% 1/4W R62 PD14BY2E12J Insulated carbon film 12.kΩ ±5% 1/4W R63 PD14BY2E13J Insulated carbon film 12.kΩ ±5% 1/4W R64 PD14BY2E51J Insulated carbon film 10.kΩ ±5% 1/4W R64 PD14BY2E562J Insulated carbon film				$3.3 k\Omega$	±5%	1/4W	
R40PD148Y2E32JInsulated carbon film $3.3k\Omega$ 45% $1/4W$ R45~48PD148Y2E102JInsulated carbon film $8.2k\Omega$ 45% $1/4W$ R51,52PD148Y2E272JInsulated carbon film $2.7k\Omega$ 45% $1/4W$ R53PD148Y2E102JInsulated carbon film $6.2k\Omega$ 45% $1/4W$ R56,57PD148Y2E13JInsulated carbon film $1k\Omega$ 45% $1/4W$ R56,57PD148Y2E13JInsulated carbon film $1k\Omega$ 45% $1/4W$ R66,67PD148Y2E13JInsulated carbon film $1k\Omega$ 45% $1/4W$ R60,61PD148Y2E13JInsulated carbon film $1kL\Omega$ 45% $1/4W$ R61,66PD148Y2E13JInsulated carbon film $12.0k\Omega$ 45% $1/4W$ R66,67PD148Y2E13JInsulated carbon film $12.0k\Omega$ 45% $1/4W$ R66,67PD148Y2E13JInsulated carbon film $10k\Omega$ 45% $1/4W$ R66,67PD148Y2E13JInsulated carbon film $10k\Omega$ 45% $1/4W$ R66,67PD148Y2E13JInsulated carbon film $10k\Omega$ 45% $1/4W$ R66,66PD148Y2E13JInsulated carbon film $10k\Omega$ 45% $1/4W$ R66,67PD148Y2E13JInsulated carbon film $2.7k\Omega$ 45% $1/4W$ R70,71PD148Y2E13JInsulated carbon film $2.7k\Omega$ 45% $1/4W$ R77,73PD148Y2E14JInsulated carbon film $2.6k\Omega$ 45% $1/4W$ R77,74PD1		PD14BY2E272J			±5%	1/4W	
R46-48PD148V2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R49,50PD148V2E82JInsulated carbon film $2,k\Omega$ $\pm 5\%$ $1/4W$ R51,52PD148V2E72JInsulated carbon film $2,k\Omega$ $\pm 5\%$ $1/4W$ R54,55PD148V2E102JInsulated carbon film $2,k\Omega$ $\pm 5\%$ $1/4W$ R56,57PD148V2E102JInsulated carbon film $1,k\Omega$ $\pm 5\%$ $1/4W$ R56,67PD148V2E102JInsulated carbon film $1,k\Omega$ $\pm 5\%$ $1/4W$ R60,61PD148V2E102JInsulated carbon film $1,k\Omega$ $\pm 5\%$ $1/4W$ R63PD148V2E102JInsulated carbon film $1,k\Omega$ $\pm 5\%$ $1/4W$ R64,65PD148V2E103JInsulated carbon film $2,kL\Omega$ $\pm 5\%$ $1/4W$ R66,67RN14AA3A472JMetal film $4,7k\Omega$ $\pm 5\%$ $1/4W$ R66,67PD148V2E103JInsulated carbon film $2,7k\Omega$ $\pm 5\%$ $1/4W$ R77,73PD148V2E252JInsulated carbon film $2,7k\Omega$ $\pm 5\%$ $1/4W$ R77,76PD148V2E22JInsulated carbon film $5,6k\Omega$ $\pm 5\%$ $1/4W$ R78PD148V2E16JInsulated carbon film $2,7k\Omega$ $\pm 5\%$ $1/4W$ R88PD148V2E10JInsulated carbon film $2,7k\Omega$ $\pm 5\%$ $1/4W$ R88PD148V2E10JInsulated carbon film $5,6k\Omega$ $\pm 5\%$ $1/4W$ R89PD148V2E10JInsulated carbon film $2,7k\Omega$ $\pm 5\%$ $1/4W$ R80PD		PD14BY2E332J	Insulated carbon film				
R49.50 PD14BY2E822J Insulated carbon film $8.2k\Omega$ $\pm 5\%$ $1/4W$ R51.52 PD14BY2E821J Insulated carbon film 680Ω $\pm 5\%$ $1/4W$ R54.55 PD14BY2E102J Insulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R56.57 PD14BY2E123J Insulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R56.57 PD14BY2E123J Insulated carbon film $12k\Omega$ $\pm 5\%$ $1/4W$ R66.67 PD14BY2E103J Insulated carbon film $180k\Omega$ $\pm 5\%$ $1/4W$ R66.67 PD14BY2E103J Insulated carbon film $120k\Omega$ $\pm 5\%$ $1/4W$ R66.67 PD14BY2E103J Insulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R66.67 PD14BY2E103J Insulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R66.67 PD14BY2E123J Insulated carbon film $2.6k\Omega$ $\pm 5\%$ $1/4W$ R66.67 RN14AA3A472J Metal film $4.5k\Omega$ $1/4W$ $174W$ R66.67 PD14BY2E123J Insulated carbon film $2.7k\Omega$ $\pm 5\%$		The Constant of All Assessment Line Apply A			÷.		
R51.52 PD148Y2E721 Insulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R54.55 PD148Y2E021 Insulated carbon film 680Ω $\pm 5\%$ $1/4W$ R55.59 PD148Y2E1021 Insulated carbon film $1.2k\Omega$ $\pm 5\%$ $1/4W$ R66.61 PD148Y2E1021 Insulated carbon film $1.2k\Omega$ $\pm 5\%$ $1/4W$ R66.61 PD148Y2E1021 Insulated carbon film $1.2k\Omega$ $\pm 5\%$ $1/4W$ R66.67 RN14AA3A4721 Insulated carbon film $10k\Omega$ $\pm 5\%$ $1/4W$ R68.69 PD148Y2E1031 Insulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R72,73 PD148Y2E1031 Insulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R74 PD148Y2E1311 Insulated carbon film 150Ω $\pm 5\%$ $1/4W$ R77,78 PD148Y2E1321 Insulated carbon film $16\Omega\Omega$ $\pm 5\%$ $1/4W$ R83 PD148Y2E1321 Insulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ R84 PD148Y2E321 Insulated carbon film $1.8k\Omega$ $\pm 5\%$	R49,50	interest of the second s	The second				
R53PD148Y2E681JInsulated carbon film680Ω $\pm 5\%$ $1/4W$ R54,55PD148Y2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R56,57PD148Y2E153JInsulated carbon film $12k\Omega$ $\pm 5\%$ $1/4W$ R60,61PD148Y2E123JInsulated carbon film $12k\Omega$ $\pm 5\%$ $1/4W$ R62PD148Y2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R63PD148Y2E102JInsulated carbon film $12k\Omega$ $\pm 5\%$ $1/4W$ R64,65PD148Y2E103JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R66,67RN14AA3A472JMetal film $4.7k\Omega$ $\pm 5\%$ $1/4W$ R68,68PD148Y2E023LInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R70,71PD148Y2E62JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R77,78PD148Y2E62JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R77PD148Y2E62JInsulated carbon film 86Ω $\pm 5\%$ $1/4W$ R82PD148Y2E162JInsulated carbon film 86Ω $\pm 5\%$ $1/4W$ R84PD148Y2E162JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R85PD148Y2E212JInsulated carbon film 86Ω $\pm 5\%$ $1/4W$ R86PD148Y2E163JInsulated carbon film 30Ω $\pm 5\%$ $1/4W$ R86PD148Y2E163JInsulated carbon film 80Ω $\pm 5\%$ $1/4W$ R87PD148Y2E163J <td< td=""><td></td><td></td><td></td><td></td><td></td><td></td><td></td></td<>							
R54,55PD14BY2E102.1Insulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R56,57PD14BY2E122.1Insulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ R60,61PD14BY2E122.1Insulated carbon film $1.2k\Omega$ $\pm 5\%$ $1/4W$ R60PD14BY2E102.1Insulated carbon film $1.2k\Omega$ $\pm 5\%$ $1/4W$ R63PD14BY2E102.1Insulated carbon film $1.2k\Omega$ $\pm 5\%$ $1/4W$ R64,67RN14AA3A472.1Metal film $4.7k\Omega$ $\pm 5\%$ $1/4W$ R66,67RN14AA3A472.1Insulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R70,71PD14BY2E103.1Insulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ R72,73PD14BY2E252.1Insulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ R74PD14BY2E252.1Insulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R75,76PD14BY2E263.1Insulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ R79PD14BY2E661.1Insulated carbon film $6.6k\Omega$ $\pm 5\%$ $1/4W$ R81PD14BY2E123.1Insulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ R82PD14BY2E123.1Insulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ R84PD14BY2E13.1Insulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ R85PD14BY2E13.1Insulated carbon film $1.6k\Omega$ $\pm 5\%$ $1/4W$ R86PD14BY2E13.1Insulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ <t< td=""><td></td><td>PD14BY2E681J</td><td></td><td></td><td></td><td>100</td><td></td></t<>		PD14BY2E681J				100	
Refs. 57 PD148Y2E122J Insulated carbon film 2.2kΩ ±5% 1/4W Refs. 59 PD148Y2E123J Insulated carbon film 15kΩ ±5% 1/4W Refs. 61 PD148Y2E102J Insulated carbon film 1kΩ ±5% 1/4W Refs. 62 PD148Y2E102J Insulated carbon film 1kΩ ±5% 1/4W Refs. 63 PD148Y2E173J Insulated carbon film 2.7kΩ ±5% 1/4W Refs. 63 PD148Y2E272J Insulated carbon film 2.7kΩ ±5% 1/4W Refs. 64 PD148Y2E272J Insulated carbon film 5.6kΩ ±5% 1/4W 770, 71 PD148Y2E162J Insulated carbon film 2.7kΩ ±5% 1/4W 777, 74 PD148Y2E10J Insulated carbon film 2.2kΩ ±5% 1/4W 777, 78 PD148Y2E10J Insulated carbon film 5.6kΩ ±5% 1/4W 777, 78 PD148Y2E10J Insulated carbon film 8.8kΩ ±5% 1/4W 780 PD148Y2E10ZJ In							
568.69 PD148Y2E163J Insulated carbon film 15kΩ ±5% 1/4W 660.61 PD148Y2E102J Insulated carbon film 1.kΩ ±5% 1/4W 663 PD148Y2E102J Insulated carbon film 1.kΩ ±5% 1/4W 683 PD148Y2E102J Insulated carbon film 2.7kΩ ±5% 1/4W 686.67 RN14AA3A472J Metal film 2.7kΩ ±5% 1/4W 77.77 PD148Y2E12J Insulated carbon film 10kΩ ±5% 1/4W 772.73 PD148Y2E62J Insulated carbon film 15ΩΩ ±5% 1/4W 776 PD148Y2E62J Insulated carbon film 15ΩΩ ±5% 1/4W 777 PD148Y2E62J Insulated carbon film 16kΩ ±5% 1/4W 788 PD148Y2E62J Insulated carbon film 1.8kΩ ±5% 1/4W 789 PD148Y2E62J Insulated carbon film 1.8kΩ ±5% 1/4W 780 PD148Y2E62J Insulated carbon film 2.7kΩ							
$360, 61$ PD148Y2E12JInsulated carbon film $1.2k\Omega$ $\pm 5\%$ $1/4W$ 362 PD148Y2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ $364, 65$ PD148Y2E13JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ $364, 65$ PD148Y2E103JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ $366, 69$ PD148Y2E103JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ $370, 71$ PD148Y2E151JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ 374 PD148Y2E151JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ $377, 78$ PD148Y2E151JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ $377, 78$ PD148Y2E62JInsulated carbon film $6.8k\Omega$ $\pm 5\%$ $1/4W$ 379 PD148Y2E182JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ 380 PD148Y2E102JInsulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ 381 PD148Y2E102JInsulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ 382 PD148Y2E102JInsulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ 384 PD148Y2E102JInsulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ 384 PD148Y2E562JInsulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ 384 PD148Y2E102JInsulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ 384 PD148Y2E13JInsulated carbon film $1.8k\Omega$ $\pm 5\%$						22	
R62PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R63PD14BY2E181JInsulated carbon film $180k\Omega$ $\pm 5\%$ $1/4W$ R64, 65PD14BY2E27JInsulated carbon film $2,7k\Omega$ $\pm 5\%$ $1/4W$ R66, 67RN14AA3A472JMetal film $4,7k\Omega$ $\pm 5\%$ $1/4W$ R68, 69PD14BY2E103JInsulated carbon film $5,6k\Omega$ $\pm 5\%$ $1/4W$ R72, 73PD14BY2E52JInsulated carbon film $5,6k\Omega$ $\pm 5\%$ $1/4W$ R72, 73PD14BY2E52JInsulated carbon film $2,7k\Omega$ $\pm 5\%$ $1/4W$ R75, 76PD14BY2E61JInsulated carbon film $2,2k\Omega$ $\pm 5\%$ $1/4W$ R77, 78PD14BY2E61JInsulated carbon film $56k\Omega$ $\pm 5\%$ $1/4W$ R80PD14BY2E561JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R81PD14BY2E562JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R81PD14BY2E562JInsulated carbon film $2,7k\Omega$ $\pm 5\%$ $1/4W$ R84PD14BY2E30JInsulated carbon film $2,7k\Omega$ $\pm 5\%$ $1/4W$ R85PD14BY2E53JInsulated carbon film $2,7k\Omega$ $\pm 5\%$ $1/4W$ R86PD14BY2E3JInsulated carbon film $10k\Omega$ $\pm 5\%$ $1/4W$ R86PD14BY2E103JInsulated carbon film $10k\Omega$ $\pm 5\%$ $1/4W$ R99PD14BY2E63JInsulated carbon film $10k\Omega$ $\pm 5\%$ $1/4W$ R99PD14BY2E163J </td <td></td> <td>PD14BY2E122J</td> <td></td> <td></td> <td></td> <td>1924</td> <td></td>		PD14BY2E122J				1924	
R63 PD14BY2E181J Insulated carbon film 180kΩ ±5% 1/4W R64,65 PD14BY2E272J Insulated carbon film 2,7kΩ ±5% 1/4W R66,67 RN14AA3472J Metal film 4,7kΩ ±5% 1/4W R68,69 PD14BY2E103J Insulated carbon film 5,6kΩ ±5% 1/4W R70,71 PD14BY2E162J Insulated carbon film 5,6kΩ ±5% 1/4W R74 PD14BY2E161J Insulated carbon film 2,2kΩ ±5% 1/4W R75,76 PD14BY2E682J Insulated carbon film 6,8kΩ ±5% 1/4W R79 PD14BY2E162J Insulated carbon film 6,8kΩ ±5% 1/4W R81 PD14BY2E182J Insulated carbon film 1,8kΩ ±5% 1/4W R81 PD14BY2E182J Insulated carbon film 2,7kΩ ±5% 1/4W R81 PD14BY2E172J Insulated carbon film 1,8kΩ ±5% 1/4W R84 PD14BY2E17J Insulated carbon film 1,8Ω ±5% 1/4W R86 PD14BY2E17J Insulated							
R64, 65 PD14BY2E272J Insulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R66, 67 RN14AA3A472J Metal film $4.7k\Omega$ $\pm 5\%$ $1/4W$ R70, 71 PD14BY2E103J Insulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ R72, 73 PD14BY2E562J Insulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R74 PD14BY2E151J Insulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ R75, 76 PD14BY2E22J Insulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ R75, 77 PD14BY2E561J Insulated carbon film 560Ω $\pm 5\%$ $1/4W$ R80 PD14BY2E182J Insulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ R81 PD14BY2E182J Insulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R83 PD14BY2E562J Insulated carbon film $2.8G\Omega$ $\pm 5\%$ $1/4W$ R84 PD14BY2E163J Insulated carbon film 390Ω $\pm 5\%$ $1/4W$ R86 PD14BY2E163J Insulated carbon film $16k\Omega$ $\pm 5\%$ $1/4W$							
ReferenceRN 14AA3A472JMetal film $4.7k\Omega$ $\pm 5\%$ 1WReferencePD14BY2E103JInsulated carbon film10kΩ $\pm 5\%$ 1/4WR72,73PD14BY2E562JInsulated carbon film5.6kΩ $\pm 5\%$ 1/4WR72,73PD14BY2E562JInsulated carbon film2.7kΩ $\pm 5\%$ 1/4WR74PD14BY2E562JInsulated carbon film2.2kΩ $\pm 5\%$ 1/4WR75,76PD14BY2E562JInsulated carbon film6.8kΩ $\pm 5\%$ 1/4WR79PD14BY2E561JInsulated carbon film6.8kΩ $\pm 5\%$ 1/4WR80PD14BY2E12JInsulated carbon film5.6kΩ $\pm 5\%$ 1/4WR81PD14BY2E562JInsulated carbon film2.7kΩ $\pm 5\%$ 1/4WR82PD14BY2E3DJInsulated carbon film2.7kΩ $\pm 5\%$ 1/4WR84PD14BY2E3DJInsulated carbon film $5.6k\Omega$ $\pm 5\%$ 1/4WR86PD14BY2E10JInsulated carbon film $16k\Omega$ $\pm 5\%$ 1/4WR86PD14BY2E13JInsulated carbon film $100k\Omega$ $\pm 5\%$ 1/4WR90PD14BY2E13JInsulated carbon film $100k\Omega$ $\pm 5\%$ 1/4WR91PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ 1/4WR90PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ 1/4WR91PD14BY2E104JInsulated carbon film $2k\Omega$ $\pm 5\%$ 1/4WR91PD14BY2E104JInsulated carbon film $2k\Omega$ <td< td=""><td></td><td></td><td></td><td></td><td></td><td>25.1</td><td></td></td<>						25.1	
R68, 69PD14BY2E103JInsulated carbon film $10k\Omega$ $\pm 5\%$ $1/4W$ R70, 71PD14BY2E562JInsulated carbon film $5,6k\Omega$ $\pm 5\%$ $1/4W$ R72, 73PD14BY2E151JInsulated carbon film $2,7k\Omega$ $\pm 5\%$ $1/4W$ R77, 78PD14BY2E222JInsulated carbon film $2,2k\Omega$ $\pm 5\%$ $1/4W$ R77, 78PD14BY2E661JInsulated carbon film $6,8k\Omega$ $\pm 5\%$ $1/4W$ R80PD14BY2E162JInsulated carbon film $6,8k\Omega$ $\pm 5\%$ $1/4W$ R81PD14BY2E102JInsulated carbon film $1,8k\Omega$ $\pm 5\%$ $1/4W$ R82PD14BY2E562JInsulated carbon film $1,8k\Omega$ $\pm 5\%$ $1/4W$ R83PD14BY2E562JInsulated carbon film $5,6k\Omega$ $\pm 5\%$ $1/4W$ R84PD14BY2E562JInsulated carbon film $5,6k\Omega$ $\pm 5\%$ $1/4W$ R86PD14BY2E102JInsulated carbon film 15Ω $\pm 5\%$ $1/4W$ R86PD14BY2E103JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ R88PD14BY2E103JInsulated carbon film $10k\Omega$ $\pm 5\%$ $1/4W$ R89PD14BY2E103JInsulated carbon film $10k\Omega$ $\pm 5\%$ $1/4W$ R91PD14BY2E2663JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ R91PD14BY2E2663JInsulated carbon film $10k\Omega$ $\pm 5\%$ $1/4W$ R91PD14BY2E2663JInsulated carbon film $10k\Omega$ $\pm 5\%$ $1/4W$ R92<						ALC: DOLLAR DOLLAR	
R70, 71PD14BY2E562JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ R72, 73PD14BY2E72JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R74PD14BY2E15JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R75, 76PD14BY2E22JInsulated carbon film $6.8k\Omega$ $\pm 5\%$ $1/4W$ R77, 78PD14BY2E68JInsulated carbon film $6.8k\Omega$ $\pm 5\%$ $1/4W$ R80PD14BY2E10JInsulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ R81PD14BY2E10JInsulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ R82PD14BY2E62JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R84PD14BY2E62JInsulated carbon film 390Ω $\pm 5\%$ $1/4W$ R85PD14BY2E471JInsulated carbon film 390Ω $\pm 5\%$ $1/4W$ R86PD14BY2E10JInsulated carbon film $10k\Omega$ $\pm 5\%$ $1/4W$ R87PD14BY2E10JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R88PD14BY2E10JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R90PD14BY2E10JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ R91PD14BY2E10JInsulated carbon film $20k\Omega$ $\pm 5\%$ $1/4W$ R92PD14BY2E10JInsulated carbon film $56k\Omega$ $\pm 5\%$ $1/4W$ R93PD14BY2E10JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R94PD14BY2E10J <td>NE2</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td>	NE2						
R72, 73PD14BY2E272JInsulated carbon film $2,7k\Omega$ $\pm5\%$ $1/4W$ R74PD14BY2E151JInsulated carbon film 150Ω $\pm5\%$ $1/4W$ R75, 76PD14BY2E682JInsulated carbon film $2,2k\Omega$ $\pm5\%$ $1/4W$ R77, 78PD14BY2E682JInsulated carbon film $6,8k\Omega$ $\pm5\%$ $1/4W$ R79PD14BY2E681JInsulated carbon film $6,8k\Omega$ $\pm5\%$ $1/4W$ R80PD14BY2E182JInsulated carbon film $1,8k\Omega$ $\pm5\%$ $1/4W$ R81PD14BY2E122JInsulated carbon film $1,8k\Omega$ $\pm5\%$ $1/4W$ R82PD14BY2E562JInsulated carbon film $2,7k\Omega$ $\pm5\%$ $1/4W$ R84PD14BY2E471JInsulated carbon film 390Ω $\pm5\%$ $1/4W$ R85PD14BY2E471JInsulated carbon film 390Ω $\pm5\%$ $1/4W$ R86PD14BY2E153JInsulated carbon film $18k\Omega$ $\pm5\%$ $1/4W$ R88PD14BY2E102JInsulated carbon film $100k\Omega$ $\pm5\%$ $1/4W$ R90PD14BY2E23JInsulated carbon film $2k\Omega$ $\pm5\%$ $1/4W$ R91PD14BY2E683JInsulated carbon film $2k\Omega$ $\pm5\%$ $1/4W$ R92PD14BY2E683JInsulated carbon film $2k\Omega$ $\pm5\%$ $1/4W$ R93PD14BY2E103JInsulated carbon film $2k\Omega$ $\pm5\%$ $1/4W$ R94PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ R95PD14BY2E103JInsulated							
R74PD14BY2E151JInsulated carbon film150Ω $\pm 5\%$ $1/4W$ R75,76PD14BY2E222JInsulated carbon film $2,2k\Omega$ $\pm 5\%$ $1/4W$ R77,78PD14BY2E561JInsulated carbon film $6,8k\Omega$ $\pm 5\%$ $1/4W$ R80PD14BY2E561JInsulated carbon film $1,8k\Omega$ $\pm 5\%$ $1/4W$ R81PD14BY2E562JInsulated carbon film $1,8k\Omega$ $\pm 5\%$ $1/4W$ R82PD14BY2E562JInsulated carbon film $2,7k\Omega$ $\pm 5\%$ $1/4W$ R83PD14BY2E562JInsulated carbon film $2,7k\Omega$ $\pm 5\%$ $1/4W$ R84PD14BY2E562JInsulated carbon film 390Ω $\pm 5\%$ $1/4W$ R85PD14BY2E562JInsulated carbon film 390Ω $\pm 5\%$ $1/4W$ R86PD14BY2E10JInsulated carbon film 18Ω $\pm 5\%$ $1/4W$ R87PD14BY2E10JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R88PD14BY2E10JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R90PD14BY2E653JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R91PD14BY2E10JJInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R92PD14BY2E10JJInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R93PD14BY2E10JJInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R94PD14BY2E10JJInsulated carbon film $16k\Omega$ $\pm 5\%$ $1/4W$ R95PD14BY2E10JJ <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td>							
R75, 76PD14BY2E22JInsulated carbon film $2,2k\Omega$ $\pm 5\%$ $1/4W$ R77, 78PD14BY2E68JInsulated carbon film $6,8k\Omega$ $\pm 5\%$ $1/4W$ R79PD14BY2E68JInsulated carbon film $6,8k\Omega$ $\pm 5\%$ $1/4W$ R80PD14BY2E18JInsulated carbon film $1,8k\Omega$ $\pm 5\%$ $1/4W$ R81PD14BY2E10JInsulated carbon film $1,k\Omega$ $\pm 5\%$ $1/4W$ R81PD14BY2E37JInsulated carbon film $2,7k\Omega$ $\pm 5\%$ $1/4W$ R83PD14BY2E30JInsulated carbon film $2,7k\Omega$ $\pm 5\%$ $1/4W$ R84PD14BY2E471JInsulated carbon film 30Ω $\pm 5\%$ $1/4W$ R86PD14BY2E10JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R87PD14BY2E10JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R88PD14BY2E10JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ R90PD14BY2E10JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ R91PD14BY2E10JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ R91PD14BY2E10JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ R91PD14BY2E10JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ R92PD14BY2E10JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ R93PD14BY2E10JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R94PD14BY2E10JInsulated carb							
R77, 78PD14BY2E682JInsulated carbon film $6.8k\Omega$ $\pm 5\%$ $1/4W$ R79PD14BY2E561JInsulated carbon film 560Ω $\pm 5\%$ $1/4W$ R80PD14BY2E182JInsulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ R81PD14BY2E102JInsulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ R82PD14BY2E272JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R83PD14BY2E391JInsulated carbon film 300Ω $\pm 5\%$ $1/4W$ R84PD14BY2E391JInsulated carbon film 300Ω $\pm 5\%$ $1/4W$ R85PD14BY2H102JInsulated carbon film 470Ω $\pm 5\%$ $1/4W$ R86PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ R87PD14BY2E683JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R88PD14BY2E683JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R90PD14BY2E683JInsulated carbon film $68k\Omega$ $\pm 5\%$ $1/4W$ 90PD14BY2E683JInsulated carbon film $68k\Omega$ $\pm 5\%$ $1/4W$ 91PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 92PD14BY2E13JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 93PD14BY2E13JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 94PD14BY2E13JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 95PD14BY2E13JInsulat			The line works where is more than the				
R79PD14BY2E561JInsulated carbon film560Ω±5%1/4WR80PD14BY2E182JInsulated carbon film1.8kΩ±5%1/4WR81PD14BY2E102JInsulated carbon film1.kΩ±5%1/4WR82PD14BY2E572JInsulated carbon film1.kΩ±5%1/4WR83PD14BY2E591JInsulated carbon film2.7kΩ±5%1/4WR84PD14BY2E391JInsulated carbon film390Ω±5%1/4WR85PD14BY2E153JInsulated carbon film470Ω±5%1/4WR86PD14BY2E163JInsulated carbon film1kΩ±5%1/4WR87PD14BY2E163JInsulated carbon film10kΩ±5%1/4WR88PD14BY2E104JInsulated carbon film10kΩ±5%1/4W89PD14BY2E23JInsulated carbon film22kΩ±5%1/4W90PD14BY2E104JInsulated carbon film56kΩ±5%1/4W91PD14BY2E23JInsulated carbon film22kΩ±5%1/4W92PD14BY2E104JInsulated carbon film10kΩ±5%1/4W93PD14BY2E153JInsulated carbon film15kΩ±5%1/4W94PD14BY2E153JInsulated carbon film15kΩ±5%1/4W95PD14BY2E153JInsulated carbon film15kΩ±5%1/4W96PD14BY2E153JInsulated carbon film15kΩ±5%1/4W97PD14BY2E153JInsulated carbon film <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td>							
R80PD14BY2E182JInsulated carbon film $1.8k\Omega$ $\pm 5\%$ $1/4W$ R81PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R82PD14BY2E562JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R83PD14BY2E562JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ R84PD14BY2E391JInsulated carbon film 30Ω $\pm 5\%$ $1/4W$ R85PD14BY2E471JInsulated carbon film 470Ω $\pm 5\%$ $1/4W$ R86PD14BY2E103JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R87PD14BY2E104JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ R88PD14BY2E23JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ R90PD14BY2E663JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ 901PD14BY2E563JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ 912PD14BY2E104JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ 914PD14BY2E563JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ 914PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 914PD14BY2E103JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 914PD14BY2E103JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 913PD14BY2E103JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 914PD14BY2E153JInsulated							
R81PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R82PD14BY2E272JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R83PD14BY2E562JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ R84PD14BY2E562JInsulated carbon film 390Ω $\pm 5\%$ $1/4W$ R85PD14BY2E10JInsulated carbon film 390Ω $\pm 5\%$ $1/4W$ R86PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R87PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R88PD14BY2E223JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R89PD14BY2E683JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ R90PD14BY2E683JInsulated carbon film $68k\Omega$ $\pm 5\%$ $1/4W$ R91PD14BY2E63JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R92PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R93PD14BY2E103JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R94PD14BY2E13JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R95PD14BY2E13JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R96PD14BY2E153JInsulated carbon film $2k\Omega$ $\pm 5\%$ $1/4W$ R97PD14BY2E33JInsulated carbon film $2k\Omega$ $\pm 5\%$ $1/4W$ R98PD14BY2E162JInsulated car							
R82PD14BY2E272JInsulated carbon film $2.7k\Omega$ $\pm 5\%$ $1/4W$ R83PD14BY2E562JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ R84PD14BY2E391JInsulated carbon film 390Ω $\pm 5\%$ $1/4W$ R85PD14BY2E471JInsulated carbon film 390Ω $\pm 5\%$ $1/4W$ R86PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R87PD14BY2E104JInsulated carbon film $16k\Omega$ $\pm 5\%$ $1/4W$ R88PD14BY2E23JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R89PD14BY2E68JJInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ R90PD14BY2E663JInsulated carbon film $68k\Omega$ $\pm 5\%$ $1/4W$ R91PD14BY2E663JInsulated carbon film $68k\Omega$ $\pm 5\%$ $1/4W$ R92PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R93PD14BY2E103JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R94PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R96PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R97PD14BY2E562JInsulated carbon film $2k\Omega$ $\pm 5\%$ $1/4W$ R98PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R96PD14BY2E162JInsulated carbon film $2k\Omega$ $\pm 5\%$ $1/4W$ R97PD14BY2E562JInsulated						and the second s	
R83PD14BY2E562JInsulated carbon film $5,6k\Omega$ $\pm5\%$ $1/4W$ R84PD14BY2E391JInsulated carbon film 390Ω $\pm5\%$ $1/4W$ R85PD14BY2E471JInsulated carbon film 470Ω $\pm5\%$ $1/4W$ R86PD14BY2H102JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ R87PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm5\%$ $1/4W$ R88PD14BY2E104JInsulated carbon film $10k\Omega$ $\pm5\%$ $1/4W$ R89PD14BY2E683JInsulated carbon film $22k\Omega$ $\pm5\%$ $1/4W$ 900PD14BY2E683JInsulated carbon film $68k\Omega$ $\pm5\%$ $1/4W$ 911PD14BY2E63JInsulated carbon film $56k\Omega$ $\pm5\%$ $1/4W$ 922PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm5\%$ $1/4W$ 933PD14BY2E104JInsulated carbon film $12k\Omega$ $\pm5\%$ $1/4W$ 944PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ 955PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ 964PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ 974PD14BY2E562JInsulated carbon film $22k\Omega$ $\pm5\%$ $1/4W$ 985PD14BY2E22JInsulated carbon film $2k\Omega$ $\pm5\%$ $1/4W$ 986PD14BY2E22JInsulated carbon film $2k\Omega$ $\pm5\%$ $1/4W$ 987PD14BY2E22JInsulated carbon film 2			a contraction of the second				
R84PD14BY2E391JInsulated carbon film 390Ω $\pm 5\%$ $1/4W$ R85PD14BY2E471JInsulated carbon film 470Ω $\pm 5\%$ $1/4W$ R86PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/2W$ R87PD14BY2E153JInsulated carbon film $1b\Omega\Omega$ $\pm 5\%$ $1/4W$ R88PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R89PD14BY2E23JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ R90PD14BY2E68JJInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ R91PD14BY2E104JInsulated carbon film $56k\Omega$ $\pm 5\%$ $1/4W$ R92PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R93PD14BY2E13JInsulated carbon film $10k\Omega$ $\pm 5\%$ $1/4W$ R94PD14BY2E13JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R95PD14BY2E13JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R96PD14BY2E13JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R97PD14BY2E472JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ R98PD14BY2E223JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ R96PD14BY2E102JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ R97PD14BY2E23JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ R100PD14BY2E22JInsulated c							
R85PD14BY2E471JInsulated carbon film 470Ω $\pm5\%$ $1/4W$ R86PD14BY2H102JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/2W$ R87PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm5\%$ $1/4W$ R88PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm5\%$ $1/4W$ R89PD14BY2E683JInsulated carbon film $22k\Omega$ $\pm5\%$ $1/4W$ R90PD14BY2E683JInsulated carbon film $68k\Omega$ $\pm5\%$ $1/4W$ P91PD14BY2E563JInsulated carbon film $56k\Omega$ $\pm5\%$ $1/4W$ R92PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm5\%$ $1/4W$ R93PD14BY2E23JInsulated carbon film $10k\Omega$ $\pm5\%$ $1/4W$ R94PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ R95PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ R96PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ R97PD14BY2E247JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ R98, 99PD14BY2E274JInsulated carbon film $22k\Omega$ $\pm5\%$ $1/4W$ R100PD14BY2E23JInsulated carbon film $22k\Omega$ $\pm5\%$ $1/4W$ R101PD14BY2E23JInsulated carbon film $22k\Omega$ $\pm5\%$ $1/4W$ R102PD14BY2E23JInsulated carbon film $22k\Omega$ $\pm5\%$ $1/4W$ R103PD14BY2E247JInsulated carbon film </td <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td>							
886PD14BY2H102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/2W$ 887PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ 888PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 89PD14BY2E223JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ 90PD14BY2E68JJInsulated carbon film $68k\Omega$ $\pm 5\%$ $1/4W$ 91PD14BY2E663JInsulated carbon film $68k\Omega$ $\pm 5\%$ $1/4W$ 92PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 93PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 94PD14BY2E13JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 95PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 96PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 97PD14BY2E562JInsulated carbon film $4.7k\Omega$ $\pm 5\%$ $1/4W$ 98, 99PD14BY2E562JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ 100PD14BY2E33JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 101PD14BY2E33JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ 102PD14BY2E33JInsulated carbon film $2k\Omega$ $\pm 5\%$ $1/4W$ 103PD14BY2E10JInsulated carbon film $3k\Omega$ $\pm 5\%$ $1/4W$ 104PD14BY2E10JInsulated carbon fil	85	PD14BY2E471J	Insulated carbon film				
887PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ 888PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 89PD14BY2E223JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ 90PD14BY2E683JInsulated carbon film $68k\Omega$ $\pm 5\%$ $1/4W$ 91PD14BY2E563JInsulated carbon film $68k\Omega$ $\pm 5\%$ $1/4W$ 92PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 93PD14BY2E123JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 94PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 95PD14BY2H102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 96PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 97PD14BY2E62JInsulated carbon film $4.7k\Omega$ $\pm 5\%$ $1/4W$ 98, 99PD14BY2E562JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 100PD14BY2E274JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 101PD14BY2E22JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 102PD14BY2E102JInsulated carbon film $3k\Omega$ $\pm 5\%$ $1/4W$ 103PD14BY2E102JInsulated carbon film $3k\Omega$ $\pm 5\%$ $1/4W$ 104PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 105PD14BY2E102JInsulated carb	86	PD14BY2H102J	Insulated carbon film				
88PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 89PD14BY2E223JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ 90PD14BY2E683JInsulated carbon film $68k\Omega$ $\pm 5\%$ $1/4W$ 91PD14BY2E563JInsulated carbon film $56k\Omega$ $\pm 5\%$ $1/4W$ 82PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 83PD14BY2E23JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 893PD14BY2E13JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ 894PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/2W$ 895PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 896PD14BY2E472JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 897PD14BY2E472JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ 898, 99PD14BY2E562JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ 8100PD14BY2E274JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 8101PD14BY2E233JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 8102PD14BY2E102JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 8103PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 8104PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 8105PD14BY2E102JIn	87	PD14BY2E153J				2011 C	
889PD14BY2E223JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ 90PD14BY2E683JInsulated carbon film $68k\Omega$ $\pm 5\%$ $1/4W$ 91PD14BY2E563JInsulated carbon film $56k\Omega$ $\pm 5\%$ $1/4W$ 892PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 893PD14BY2E223JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 894PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/2W$ 895PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/2W$ 896PD14BY2E172JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 897PD14BY2E472JInsulated carbon film $k.R\Omega$ $\pm 5\%$ $1/4W$ 898, 99PD14BY2E562JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ 8100PD14BY2E274JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 8101PD14BY2E233JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 8102PD14BY2E233JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 8103PD14BY2E102JInsulated carbon film $3k\Omega$ $\pm 5\%$ $1/4W$ 8104PD14BY2E163JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 8105PD14BY2E104JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 8106PD14BY2E104JInsulated carbon film $1bk\Omega$ $\pm 5\%$ $1/4W$ 8103PD14BY2E104J<	88	PD14BY2E104J				· · · · · · · · · · · · · · · · · · ·	
90PD14BY2E683JInsulated carbon film $68k\Omega$ $\pm 5\%$ $1/4W$ 91PD14BY2E563JInsulated carbon film $56k\Omega$ $\pm 5\%$ $1/4W$ 892PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 893PD14BY2E223JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ 894PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/2W$ 895PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/2W$ 896PD14BY2E172JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 897PD14BY2E472JInsulated carbon film $4.7k\Omega$ $\pm 5\%$ $1/4W$ 898, 99PD14BY2E562JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ 8100PD14BY2E222JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 8101PD14BY2E163JInsulated carbon film $2.70k\Omega$ $\pm 5\%$ $1/4W$ 8102PD14BY2E22JInsulated carbon film $2.70k\Omega$ $\pm 5\%$ $1/4W$ 8103PD14BY2E102JInsulated carbon film $32k\Omega$ $\pm 5\%$ $1/4W$ 8104PD14BY2E102JInsulated carbon film 18Ω $\pm 5\%$ $1/4W$ 8105PD14BY2E102JInsulated carbon film 18Ω $\pm 5\%$ $1/4W$ 8106PD14BY2E102JInsulated carbon film 18Ω $\pm 5\%$ $1/4W$ 8103PD14BY2E102JInsulated carbon film 18Ω $\pm 5\%$ $1/4W$ 8104PD14BY2E102J <td></td> <td></td> <td>A 82</td> <td></td> <td></td> <td></td> <td></td>			A 82				
991PD14BY2E563JInsulated carbon film $56k\Omega$ $\pm5\%$ $1/4W$ 892PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm5\%$ $1/4W$ 893PD14BY2E223JInsulated carbon film $22k\Omega$ $\pm5\%$ $1/4W$ 894PD14BY2H102JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/2W$ 895PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ 896PD14BY2H102JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ 897PD14BY2E472JInsulated carbon film $4.7k\Omega$ $\pm5\%$ $1/4W$ 898, 99PD14BY2E562JInsulated carbon film $5.6k\Omega$ $\pm5\%$ $1/4W$ 100PD14BY2E274JInsulated carbon film $2.2k\Omega$ $\pm5\%$ $1/4W$ 101PD14BY2E222JInsulated carbon film $2.2k\Omega$ $\pm5\%$ $1/4W$ 102PD14BY2E333JInsulated carbon film $3k\Omega$ $\pm5\%$ $1/4W$ 103PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ 104PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ 105PD14BY2E104JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ 106PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm5\%$ $1/4W$			NEW CONSERVATIONS OF ANY				
892PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 893PD14BY2E223JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ 894PD14BY2H102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/2W$ 895PD14BY2E153JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/2W$ 896PD14BY2H102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 897PD14BY2E472JInsulated carbon film $4.7k\Omega$ $\pm 5\%$ $1/4W$ 898, 99PD14BY2E562JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ 8100PD14BY2E274JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 8101PD14BY2E222JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 8102PD14BY2E333JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 8103PD14BY2E333JInsulated carbon film $3k\Omega$ $\pm 5\%$ $1/4W$ 8104PD14BY2E102JInsulated carbon film $3k\Omega$ $\pm 5\%$ $1/4W$ 8105PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 8103PD14BY2E103JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 8103PD14BY2E104JInsulated carbon film $1bk\Omega$ $\pm 5\%$ $1/4W$ 8104PD14BY2E104JInsulated carbon film $1bk\Omega$ $\pm 5\%$ $1/4W$ 8105PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 8106PD14BY2E104J<						1.2	
R93PD14BY2E223JInsulated carbon film $22k\Omega$ $\pm 5\%$ $1/4W$ R94PD14BY2H102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/2W$ R95PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ R96PD14BY2H102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R97PD14BY2E472JInsulated carbon film $4.7k\Omega$ $\pm 5\%$ $1/4W$ R98, 99PD14BY2E562JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ R100PD14BY2E274JInsulated carbon film $270k\Omega$ $\pm 5\%$ $1/4W$ R101PD14BY2E222JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ R102PD14BY2E333JInsulated carbon film $33k\Omega$ $\pm 5\%$ $1/4W$ R103PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ R104PD14BY2E102JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ R105PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ R105PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$						The second se	
894PD14BY2H102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/2W$ 895PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ 896PD14BY2H102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/2W$ 897PD14BY2E472JInsulated carbon film $4.7k\Omega$ $\pm 5\%$ $1/4W$ 98, 99PD14BY2E562JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ 100PD14BY2E274JInsulated carbon film $270k\Omega$ $\pm 5\%$ $1/4W$ 101PD14BY2E22JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 102PD14BY2E333JInsulated carbon film $33k\Omega$ $\pm 5\%$ $1/4W$ 103PD14BY2E102JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ 104PD14BY2E103JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ 105PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 106PD14BY2E224JInsulated carbon film $220k\Omega$ $\pm 5\%$ $1/4W$			Insulated carbon film				
995PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ 996PD14BY2H102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/2W$ 997PD14BY2E472JInsulated carbon film $4.7k\Omega$ $\pm 5\%$ $1/4W$ 98, 99PD14BY2E562JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ 100PD14BY2E274JInsulated carbon film $270k\Omega$ $\pm 5\%$ $1/4W$ 101PD14BY2E222JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 102PD14BY2E333JInsulated carbon film $33k\Omega$ $\pm 5\%$ $1/4W$ 103PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 104PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ 105PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 106PD14BY2E224JInsulated carbon film $220k\Omega$ $\pm 5\%$ $1/4W$		DALAR 20 NUMBER OF COMPACE CO				A29 541 51	
96PD14BY2H102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/2W$ 97PD14BY2E472JInsulated carbon film $4.7k\Omega$ $\pm 5\%$ $1/4W$ 98, 99PD14BY2E562JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ 100PD14BY2E274JInsulated carbon film $270k\Omega$ $\pm 5\%$ $1/4W$ 101PD14BY2E222JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 102PD14BY2E333JInsulated carbon film $33k\Omega$ $\pm 5\%$ $1/4W$ 103PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 104PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ 105PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 106PD14BY2E224JInsulated carbon film $220k\Omega$ $\pm 5\%$ $1/4W$			Installise de la deservation de la deserv				
197PD14BY2E472JInsulated carbon film $4.7k\Omega$ $\pm5\%$ $1/4W$ 98, 99PD14BY2E562JInsulated carbon film $5.6k\Omega$ $\pm5\%$ $1/4W$ 100PD14BY2E274JInsulated carbon film $270k\Omega$ $\pm5\%$ $1/4W$ 101PD14BY2E222JInsulated carbon film $2.2k\Omega$ $\pm5\%$ $1/4W$ 102PD14BY2E333JInsulated carbon film $33k\Omega$ $\pm5\%$ $1/4W$ 103PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ 104PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm5\%$ $1/4W$ 105PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm5\%$ $1/4W$ 106PD14BY2E224JInsulated carbon film $220k\Omega$ $\pm5\%$ $1/4W$							
98, 99PD14BY2E562JInsulated carbon film $5.6k\Omega$ $\pm 5\%$ $1/4W$ 100PD14BY2E274JInsulated carbon film $270k\Omega$ $\pm 5\%$ $1/4W$ 101PD14BY2E222JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 102PD14BY2E333JInsulated carbon film $33k\Omega$ $\pm 5\%$ $1/4W$ 103PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 104PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ 105PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 106PD14BY2E224JInsulated carbon film $220k\Omega$ $\pm 5\%$ $1/4W$		Description of the second seco					
100PD14BY2E274JInsulated carbon film $270k\Omega$ $\pm5\%$ $1/4W$ 101PD14BY2E222JInsulated carbon film $2.2k\Omega$ $\pm5\%$ $1/4W$ 102PD14BY2E333JInsulated carbon film $33k\Omega$ $\pm5\%$ $1/4W$ 103PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ 104PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm5\%$ $1/4W$ 105PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm5\%$ $1/4W$ 106PD14BY2E224JInsulated carbon film $220k\Omega$ $\pm5\%$ $1/4W$							
101PD14BY2E222JInsulated carbon film $2.2k\Omega$ $\pm 5\%$ $1/4W$ 102PD14BY2E333JInsulated carbon film $33k\Omega$ $\pm 5\%$ $1/4W$ 103PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 104PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ 105PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 106PD14BY2E224JInsulated carbon film $220k\Omega$ $\pm 5\%$ $1/4W$		Contraction and the second of the second sec					
102PD14BY2E333JInsulated carbon film $33k\Omega$ $\pm5\%$ $1/4W$ 103PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm5\%$ $1/4W$ 104PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm5\%$ $1/4W$ 105PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm5\%$ $1/4W$ 106PD14BY2E224JInsulated carbon film $220k\Omega$ $\pm5\%$ $1/4W$							
103PD14BY2E102JInsulated carbon film $1k\Omega$ $\pm 5\%$ $1/4W$ 104PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ 105PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 106PD14BY2E224JInsulated carbon film $220k\Omega$ $\pm 5\%$ $1/4W$							
104PD14BY2E153JInsulated carbon film $15k\Omega$ $\pm 5\%$ $1/4W$ 105PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 106PD14BY2E224JInsulated carbon film $220k\Omega$ $\pm 5\%$ $1/4W$						140	
105PD14BY2E104JInsulated carbon film $100k\Omega$ $\pm 5\%$ $1/4W$ 106PD14BY2E224JInsulated carbon film $220k\Omega$ $\pm 5\%$ $1/4W$		territoria de las territorias en la sintena ante				and the second second second	
106 PD14BY2E224J Insulated carbon film $220k\Omega \pm 5\%$ 1/4W		sectors as a manufactor and a sector of the last				and the second se	

PARTS LIST OF X73-0011-00

Circuit No.	Parts No.		Description			Remarks
			CAPACITOR			
C1	CK94YY2H103M	Ceramic	0.01µF	±20%	500V	-
C2~4	CE04W1C470	PC electrolytic	47µF		16V	
C5	CC94SL1H151J	Ceramic	150pF	±5%	50V	
C7	CK94YY2H103M	Ceramic	0.01µF	±20%	500V	
C8	CE04W1C470	PC electrolytic	47μF	-2070	16V	
C9	CC94SL1H101J	Ceramic	100pF	±5%	50V	
C11	CC94SL1H150J	Ceramic	15pF	±5%	50V	
C12	CC94SL1H220J	Ceramic	22pF	±5%	50V	
C13	CC94SL1H330J	Ceramic	33pF	±5%	50V 50V	
C14, 15		Ceramic				
	CK94YY1H103M		0.01µF	±20%	50V	
C16, 17	CE04W1C470	PC electrolytic	47µF		16V	
C18	CC94SL1H221K	Ceramic	220pF	±10%	50V	
C19~21	CC94SL1H151J	Ceramic	150pF	±5%	50V	
C22	CC94SL1H680J	Ceramic	68pF	±5%	50V	
C23	CE04W1H220	PC electrolytic	22µF		50V	
C24	CE04W1C470	PC electrolytic	47μF		16V	
C25,26	CK94YY1H103M	Ceramic	0.01µF	±20%	50V	
C27	CC94SL2H050D	Ceramic	5pF	±0.5%	500V	
228	CE04W1H101	PC electrolytic	100µF	NELSON PERSONNAL	50V	
229	CE02D2E220	PC electrolytic	22µF		250V	
FC1	C05-0029-15	Ceramic trimmer	50pF			
		C	OIL			
_1,2	L33-0060-05	Peaking coil			Pag.	
	*					
~						
-		•				
-						
					•	
	*					
-						

ACT:W

ALC: NO

ART

BLOCK DIAGRAM



COLOR CODE

RESISTOR

COLOR (meaning)	1st (value)	2nd (value)	3rd (multiplier)	4th (tolerance)	
Black	0	0	10 ⁰		
Brown	1	1	10 ¹	±1%	~
Red	2	2	10 ²	±2%	e ⁻
Orange	3	3	10 ³	-	2nd color 4th color
Yellow	4	4	104	-	1st color 3rd color
Green	5	5	10 ⁵	-	
Blue	6	6	106	-	
Purple	7	7	10 ⁷	_	
Grey	8	8	10 ⁸	-	2 1
White	9	9	10 ⁹	times	
Gold	-	-	10 ⁻¹	±5%	
Silver	-	_	10-2	±10%	
Non-color	-	-	2 	±20%	

and a

CAPACITOR (MICA)

COLOR (meaning)	1st (grade)	2nd (value)	3rd (value)	4th (multiplier)	5th (tolerance)	6th (characteristic)
Black	x	0	0	10 ⁰	±20%	-
Brown	-	1	1	10 ¹	±1%	В
Red	Z	2	2	10 ²	±2%	С
Orange	-	3	3	10 ³	-	D
Yellow	-	4	4	104	_	E
Green	-	5	5	_	*±5%	-
Blue	-	6	6	-		-
Purple	-	7	7	-	-	5 T-1
Grey	Y	8	8	-	-	
White	_	9	9	0.1	±10%	-







TRIO

Manufactured by TRIO ELECTRONICS INC., TOKYO, JAPAN.

©1972.6 PRINTED IN JAPAN (T)

PC BOARD VERTICAL AMPLIFIER UNIT(X73-0011-00)



PC BOARD HORIZONTAL AMPLIFIER UNIT(X65-0008-01)



D6: ZBI-I2, D7: SZ-200-25, D9: ISI850, DI0: ISI850R, DII: ISI555,

()



SCHEMATIC DIAGRAM OF CS-1554