CMOS IC

LC8955

CD-I Format ADPCM Data Replay IC

Overview

The SANYO LC8955 is a stereo/mono replay IC for CD-I format ADPCM data. In addition to an ADPCM decoding circuit, the LC8955 also incorporates a DMA interface, buffer RAM interface and a D/A converter serial interface. The LC8955 interfaces directly with the SANYO LC8951 Real-time Error-correction and Host Interface Processor, allowing a CD-I replay system to be configured easily.

The LC8955 is designed to operate with a host microprocessor which sets the operating mode. It operates from a single 5V supply, and is available in 80-pin plastic QIPs.

Features

- Real-time ADPCM decoder IC.
- Direct interface to SANYO's LC8951 error-correction IC for high-speed data transfer.
- Data transfer under program or DMA control.
- Independent data and control busses in auto-request transfer.
- 8K byte external static RAM interface.
- Buffers up to 64 ADPCM sound groups in external RAM.
- DAC interface circuit.
- 80-pin plastic QIP.

Functional Description

The LC8955 is divided into three major functional blocks.

ADPCM Input Block

The ADPCM input block has three data input modes, selected by setting internal registers.

① Auto-request transfer

Data is transferred automatically into the LC8955's data port without CPU intervention. A number of handshaking signals control data transfer. The input device can be an LC8951 Real-time Error-correction and Host Interface Processor or another CD-ROM output device.

② Program transfer

The CPU writes each byte of data directly into the LC8955 under program control. Data is transferred using the CPU data bus.

③ DMA transfer

Data is written into the LC8955 by an external DMA controller using the CPU data bus. Up to 64 ADPCM sound groups can be written to an external 8K byte buffer RAM. One sound group consists of 128 bytes of CD-I data.

The LC8955 then decodes data in the buffer without intervention from the CPU or DMA controller, leaving these devices free for other tasks.

Package Dimensions

unit:mm

3044B-QIP80A

SANYO : QIP80A

SANYO Electric Co.,Ltd. Semiconductor Company

TOKYO OFFICE Tokyo Bldg., 1-10, 1 Chome, Ueno, Taito-ku, TOKYO, 110-8534 JAPAN

Decoder Block

The decoder block converts the ADPCM data into 16-bit linear PCM data. Decoding parameters can either be set by the CPU, or read from subheader information in the ADPCM data stream.

DAC Interface Block

Two output formats are available. The first is suitable for input to SANYO's LC7833, 7833M DA converters, and the second is the standard CD-I format. The output circuit will also accept CD-DA format input data and, by setting an LC8955 internal register, switch it through to the output pins without processing.

Specifications

Absolute Maximum Ratings at $V_{SS} = 0V$

Parameter	Symbol	Conditions	Ratings	Unit
Maximum supply voltage	V_{DD} max	Ta=25°C	−0.3 to +7.0	V
Input/output voltage	V_I, V_O	Ta=25°C	−0.3 to V_{DD} +0.3	V
Allowable power dissipation	Pd max	Ta≤70°C	350	mW
Operating temperature	Topr		−30 to +70	°C
Storage temperature	Tstg		−55 to +125	°C
Solder temperature		10s., dipping of pins only	260	°C

Allowable Operating Conditions at Ta = −30 to +70°C, $V_{SS} = 0V$

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Supply voltage	V_{DD}		4.5	5.0	5.5	V
Input voltage range	V_{IN}		0		V_{DD}	V

DC Characteristics at Ta = −30 to +70°C, $V_{SS} = 0V$, $V_{DD} = 4.5$ to 5.5V

| Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Input high-level voltage	V_{IH1}	All input pins except RESETB, EOPB, IO7 to 0, SD7 to 0	2.2			V
Input low-level voltage	V_{IL1}				0.8	V
Input high-level voltage	V_{IH2}	RESETB, EOPB, IO7 to 0, SD7 to 0	2.5			V
Input low-level voltage	V_{IL2}				0.6	V
Output high-level voltage	V_{OH}	All output pins: $I_{OH}=-3mA$	2.4			V
Output low-level voltage	V_{OL}	All output pins: $I_{OL}=3mA$			0.4	V
Input leakage current	I_L	All input pins: $V_I=V_{SS}, V_{DD}$	−25		+25	µA
Pull-up resistor	R_{UP}	IO0 to 7, SD0 to 7	10	20	40	kΩ

LC8955

Pin Assignment

Type
I : Input pin
O : Output pin
B : Bidirectional pin
P : Power supply pin
NC : No connection

Note) All V_{DD} and V_{SS} pins should be connected to the positive supply or ground.

No.	Pin Name	Type		No.	Pin Name	Type
1	T2	I		41	WAITB	I
2	T1	I		42	MCK	I
3	OUTSET	I		43	DTENB	I
4	V_{SS}	P		44	EOPB	I
5	A12	O		45	SD7	B
6	A11	O		46	SD6	B
7	A10	O		47	SD5	B
8	A9	O		48	SD4	B
9	A8	O		49	SD3	B
10	A7	O		50	SD2	B
11	A6	O		51	SD1	B
12	A5	O		52	V_{SS}	P
13	V_{SS}	P		53	SD0	B
14	A4	O		54	SA1	I
15	A3	O		55	SA0	I
16	A2	O		56	CSB	I
17	A1	O		57	RDB	I
18	A0	O		58	WRB	I
19	MWEB	O		59	BUSY	O
20	MCSB	O		60	BUFFULL	O
21	V_{SS}	P		61	UNDFLOW	O
22	IO7	B		62	DATAEMP	O
23	IO6	B		63	MEMPHAS	O
24	IO5	B		64	MBITSPL	O
25	IO4	B		65	MSPLFRQ	O
26	IO3	B		66	MSTEMON	O
27	IO2	B		67	RESETB	I
28	IO1	B		68	LRCLK	O
29	IO0	B		69	WCLK	O
30	DD7	I		70	DATA	O
31	V_{DD}	P		71	BCLK	O
32	DD6	I		72	CLRCLK	I
33	DD5	I		73	V_{DD}	P
34	DD4	I		74	CWCLK	I
35	DD3	I		75	CDATA	I
36	DD2	I		76	CBCLK	I
37	DD1	I		77	REQB	O
38	DD0	I		78	DACKB	I
39	EFLAG	I		79	READYB	O
40	READB	O		80	DONEB	I

System Diagram

Block Diagram

LC8955

- ■ Specifications of any and all SANYO products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.

- ■ SANYO Electric Co., Ltd. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.

- ■ In the event that any or all SANYO products(including technical data,services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.

- ■ No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of SANYO Electric Co., Ltd.

- ■ Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO product that you intend to use.

- ■ Information (including circuit diagrams and circuit parameters) herein is for example only ; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of June, 2001. Specifications and information herein are subject to change without notice.