LM6152 Dual and LM6154 Quad High Speed/Low Power 45 MHz Rail-to-Rail I/O Operational Amplifiers

General Description

Using patent pending circuit topologies, the LM6152/54 provides new levels of speed vs power performance in applications where low voltage supplies or power limitations made compromise necessary. With only 1.5 mA/amp supply current, the 45 MHz bandwidth of this device supports new portable applications where higher power devices unacceptably drain battery life.

In addition, the LM6152/54 can be driven by voltages that exceed both power supply rails, thus eliminating concerns over exceeding the common-mode voltage range. The rail-to-rail output swing capability provides the maximum possible dynamic range at the output. This is particularly important when operating on low supply voltages. The LM6152/54 can also drive capacitive loads without oscillating.

Operating on supplies of 1.8V to over 24V, the LM6152/54 is excellent for a very wide range of applications, from battery operated systems with large bandwidth requirements to high speed instrumentation.

Features

(For 5V Supply)

- Rail-to-rail input CMVR __0.25V to 5.25V (max/min)
- Rail-to-rail output swing 0.01V to 4.99V (max/min)
- Wide gain-bandwidth: 45 MHz (typ) @ 50 kHz
- Slew rate 30 V/µs (typ)
- Low supply current 1.5/Amp (typ)
- Wide supply range 1.8V to 24V
- Fast settling time:
- Gain 108 dB (typ) with R_L = 10k ■ PSRR 87 dB (typ)

Applications

- Portable high speed instrumentation
- 5V signal conditioning amplifiers/ADC buffers
- Bar code scanners
- Wireless communications





Top View

Ordering Information

Connection Diagrams

Package	Temperature Range Industrial -40°C to +85°C	NSC Drawing
8-Pin Molded DIP	LM6142AIN, LM6142BIN	N08E
8-Pin Small Outline	LM6142AIM, LM6142BIM	M08A
14-Pin Molded DIP	LM6144AIN, LM6144BIN	N14A
14-Pin Small Outline	LM6144AIM, LM6144BIM	M14A

© 1999 National Semiconductor Corporation DS012350

www.national.com

National Semiconductor



www.national.com

2



www.national.com

mplifiers	Notes			
Ā				
)				
	LIFE SUPPORT POLICY			
	DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:			
	 Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness. 			
	National Semiconductor Corporation Americas Fax: 1-800-737-7018 Email: support@nsc.com National Semiconductor Europe National Semiconductor Asia Pacific Customer National Semiconductor Asia Pacific Customer Year Fax: +49 (0) 1 80-530 85 86 Fax: 1-800-737-7018 Email: support@nsc.com Fax: +49 (0) 1 80-530 85 85 English Tel: +49 (0) 1 80-532 78 32 Français Tel: +49 (0) 1 80-532 93 58 Fax: 65-2544466 Fax: 65-2544466 Fax: 81-3-5639-7507 Fax: 81-3-5639-7507 www.national.com Italiano Tel: +49 (0) 1 80-532 78 32 Français Tel: +49 (0) 1 80-532 18 60 Email: sea.support@nsc.com			

National does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and National reserves the right at any time without notice to change said circuitry and specifications.