

FEATURES

- **Performance matching 33-MHz Intel® '486-based PC**
 - More than 5 times the performance of the Motorola "DragonBall" (MC68328)
- **Ultra low power**
 - Designed for applications that require long battery life while using standard AA/AAA batteries or rechargeable cells
 - Average 45 mW/66 mW in Normal Operation (2.7 V/3.3 V, 13 MHz/18.432 MHz)
 - Average 15 mW in Idle state (clock to the CPU stopped, everything else running)
 - Average 50 μ W in Standby state (realtime clock on, everything else stopped)
- **LCD controller**
 - Interfaces directly to a single-scan panel monochrome LCD
 - Panel width size is programmable from 16 to 1024 pixels in 16-pixel increments
 - Video frame size programmable up to 128 Kbytes
 - Bits per pixel programmable from 1, 2, or 4

Ultra-Low-Power System-on-Chip with LCD Controller

OVERVIEW


The CL-PS7111 is designed for ultra-low-power applications such as organizers/PDAs, two-way pagers, smart cellular phones, and industrial handheld information appliances. The core-logic functionality of the device is built around an ARM710A microprocessor with 8 Kbytes of four-way set-associative unified cache.

At 18.432 MHz (for 3.3-V operation), the CL-PS7111 delivers roughly the same level of performance offered by a 33-MHz Intel® '486-based PC. A 32-bit Y2K-compliant Real-Time Clock (RTC) and comparator is provided.

(cont.)

(cont.)

Functional Block Diagram



FEATURES (cont.)

- **ARM710A microprocessor**
 - ARM7 CPU
 - 8 Kbytes of four-way set-associative cache
 - MMU with 64-entry TLB (transition look-aside buffer)
- **DRAM controller**
 - Supports both 16- and 32-bit-wide DRAMs
- **ROM/SRAM/FLASH memory control**
 - Decodes 4, 5, or 6 separate memory segments of up to 256 Mbytes
 - Each segment can be configured as 8, 16, or 32 bits wide and supports page-mode access
 - Programmable access time for conventional SRAM/ROM/FLASH memory
- **2 Kbytes of on-chip SRAM for fast program execution or as a frame buffer**
- **On-chip for manufacturing support boot ROM**
- **Two synchronous serial interfaces**
 - ADC (SSI1) Interface: Master mode only; SPI¹ and Microwire²-compatible (128 kbps operation)
 - Audio Codec interface (64 kbps operation); for 18 MHz operation only.
- **27-bit general-purpose I/O**
 - Three 8-bit and one 3-bit GPIO port
 - Supports scanning keyboard matrix
- **Two UARTs (16550 type)**
 - Supports bit rates up to 115.2 kbps
 - Contains two 16-byte FIFOs for Tx and Rx
 - UART1 supports modem control signals
- **SIR (up to 115.2 kbps) infrared encoder**
 - IrDA (Infrared Data Association) SIR protocol encoder can be optionally switched into Tx and Rx signals of UART1
- **DC-to-DC converter interface**
 - Provides two 96-kHz clock outputs with programmable duty ratio (from 1-in-16 to 15-in-16)
- **Two-timer counters**
- **3.3 V at 18.432 MHz and 2.7 V at 13 MHz**
- **208-pin LQFP and 256-ball PBGA packages**
- **Evaluation kit available with BOM, schematics, and design database**
- **Support for up to two ultra-low-power CL-PS6700 PC Card controllers**

¹ SPI is a registered trademark of Motorola®.

² Microwire is a registered trademark of National Semiconductor®.

OVERVIEW (cont.)

Power Management

The CL-PS7111 is designed for ultra-low-power operation. There are three basic power states:

- **Operating/Normal** — This state is the full performance state. All the clocks and peripheral logic are enabled.
- **Idle** — This state is the same as the Operating state, except the CPU clock is halted while waiting for an event such as a key press.
- **Standby** — This state is equivalent to the computer being switched off (no display), and the main oscillator shut down. An event such as a key press can wake-up the processor.

Memory Interfaces

There are two main external memory interfaces and a DMA controller that fetches video display data for the LCD controller from main DRAM memory.

The SRAM/ROM-style interface has programmable wait-state timings and includes burst-mode capability, with six chip selects decoding six 256-Mbyte sec-

tions of addressable space. For maximum flexibility, each bank can be specified to be 8, 16, or 32 bits wide to enable the use of low-cost memory in a 32-bit system. The system can have an 8-bit-wide boot option to optimize memory size. The on-chip boot ROM can be used in manufacturing to serially download system code into on-board FLASH.

The programmable 16- or 32-bit-wide DRAM interface allows direct connection of up to two banks of DRAM, each bank containing up to 256 Mbytes. To assure the lowest possible power consumption, the CL-PS7111 supports self-refresh DRAMs, which are placed in a low-power state by the device when it enters low-power Standby mode.

Serial Interfaces

For RS-232 serial communications, the CL-PS7111 includes two 16550-type UARTs, both of which have two 16-byte FIFOs for receive and transmit data. The UARTs support bit rates up to 115.2 kbps. An IrDA SIR protocol encoder/decoder can be optionally switched into the Rx/Tx signals to/from one of

CL-PS7111

Ultra-Low-Power System-on-a-Chip with LCD Controller



OVERVIEW (cont.)

the UARTs to enable these signals to drive an infrared communication interface directly.


A full-duplex codec interface allows direct connection of a standard audio codec chip to the CL-PS7111, allowing storage and playback of sound. A separate synchronous serial interface supports two industry-standard protocols (SPI[®] and Microwire[®]) for interfacing to standard devices (like an ADC), allowing for peripheral expansion (for example, a digitizer pen).

Packaging

The CL-PS7111 is available in a 208-pin LQFP package and a 256-ball PBGA package.

System Design

As shown in the system block diagram below, simply adding desired memory and peripherals to the highly integrated CL-PS7111 completes a low-power device system board. All the interface logic is integrated on-chip.



A CL-PS7111-Based System

Direct Sales Offices**Domestic****NORTHERN CA**

Fremont
TEL: 510/623-8300
FAX: 510/252-6020

SOUTHERN CA

Los Angeles
TEL: 310/826-9382
310/826-1602
FAX: 310/826-9532

NORTHWESTERN AREA

Portland, OR
TEL: 503/620-5547
FAX: 503/620-5665

SOUTH CENTRAL AREA

Austin, TX
TEL: 512/338-1831
FAX: 512/339-0196

CENTRAL AREA

Chicago, IL
TEL: 847/884-6750
FAX: 847/884-6795

MID-ATLANTIC AREA

Columbia, MD
TEL: 410/740-5654
FAX: 410/740-6961

SOUTHEASTERN AREA

Raleigh, NC
TEL: 919/859-5210
FAX: 919/859-5334
Boca Raton, FL
TEL: 561/395-1613
FAX: 561/395-1373

International**FRANCE**

Paris
TEL: 33/1-48-12-2812
FAX: 33/1-48-12-2810

GERMANY

Herrsching
TEL: 49/81-52-92460
FAX: 49/81-52-924699

HONG KONG

Kowloon
TEL: 852-2376-0801
FAX: 852-2375-1202

JAPAN

Tokyo
TEL: 81/3-3340-9111
FAX: 81/3-3340-9120

KOREA

Seoul
TEL: 82/2-565-8561
FAX: 82/2-565-8565

SINGAPORE

TEL: 65/743-4111
FAX: 65/742-4111

TAIWAN

Taipei
TEL: 886/2-2718-4533
FAX: 886/2-2718-4526

UNITED KINGDOM

Bucks, England
TEL: 44/01628-472211
FAX: 44/01628-486114

Cirrus Logic...where Analog meets Digital™

Cirrus Logic is a premier supplier of precision linear circuits and mixed-signal system-level chip solutions, the latter of which demand high-performance mixed-signal processing, embedded DSP, algorithms and firmware. The company's products, sold under its own name and the Crystal® product brand, enable high-volume applications in mass storage, communications, consumer electronics and industrial markets.

With more than 800 patents (issued and pending), Cirrus Logic continues to expand its intellectual property portfolio through R&D investments. Approximately 40 percent of the company's patents involve mixed-signal technology, a key to innovating system-on-chip solutions. Over the past decade, Cirrus Logic has achieved more than 50 industry firsts, many of which have set new standards within their respective markets.

To learn how your Cirrus Logic can add high value and differentiation to your products, contact one of our system and applications specialists today.

Copyright © 1999 Cirrus Logic, Inc. All rights reserved. Printed in USA.

Cirrus Logic, Inc. has made best efforts to ensure that the information contained in this document is accurate and reliable. However, the information is subject to change without notice and is provided "AS IS" without warranty of any kind (express or implied). No responsibility is assumed by Cirrus Logic, Inc. for the use of this information, nor for infringements of patents or other rights of third parties. This document is the property of Cirrus Logic, Inc. and implies no license under patents, copyrights, trademarks, or trade secrets. Furthermore, no part of this publication may be used as a basis for manufacture or sale of any items without the prior written consent of Cirrus Logic, Inc. The names of products of Cirrus Logic, Inc. or other vendors and suppliers appearing in this document may be trademarks or service marks of their respective owners, which may be registered in some jurisdictions. A list of Cirrus Logic, Inc. trademarks and service marks can be found at <http://www.cirrus.com>.