



### Si-MMIC-Amplifier in SIEGET® 25-Technologie

#### Preliminary data

- Cascadable 50 Ω-gain block
- Unconditionally stable
- Gain  $|S_{21}|^2 = 13$  dB at 1.8 GHz  
 $I_{P_{3\text{out}}} = +9$  dBm at 1.8 GHz  
 $(V_D = 3$  V,  $I_D = \text{typ. } 6.4$  mA)
- Noise figure  $NF = 2.2$  dB at 1.8 GHz
- Reverse isolation > 28 dB and  
 return loss  $IN / OUT > 12$  dB at 1.8 GHz



**Circuit Diagram**

EHA07385

**ESD:** Electrostatic discharge sensitive device, observe handling precaution!

Type	Marking	Ordering Code	Pin Configuration				Package
BGA 420	BLs	Q62702-G0057	1, IN	2, GND	3, OUT	4, VD	SOT-343

#### Maximum Ratings

Parameter	Symbol	Value	Unit
Device current	$I_D$	15	mA
Device voltage	$V_D$	6	V
Total power dissipation, $TS \leq tbd$ °C	$P_{tot}$	90	mW
$R_F$ input power	$P_{RFin}$	0	dBm
Junction temperature	$T_j$	150	°C
Ambient temperature	$T_A$	-65 ...+150	
Storage temperature	$T_{stg}$	-65 ...+150	

#### Thermal Resistance


Junction - soldering point 1)	$R_{thJS}$	$\leq tbd$	K/W
-------------------------------	------------	------------	-----

1)  $T_S$  is measured on the emitter (GND) lead at the soldering point to the PCB

**Electrical Characteristics** at  $T_A = 25^\circ\text{C}$ , unless otherwise specified.

Parameter	Symbol	Values			Unit
		min.	typ.	max.	
<b>AC characteristics</b>					
Device current	$I_D$	5.4	6.7	8	mA
Insertion power gain $f = 0.1 \text{ GHz}$	$ S_{21} ^2$	17	19	-	dB
$f = 1 \text{ GHz}$		15	17	-	
$f = 1.8 \text{ GHz}$		11	13	-	
Reverse isolation $f = 1.8 \text{ GHz}$	$S_{12}$	25	28	-	
Noise figure $f = 0.1 \text{ GHz}$	$NF$	-	1.9	2.2	
$f = 1 \text{ GHz}$		-	2	2.3	
$f = 1.8 \text{ GHz}$		-	2.2	2.5	
Intercept point at the output $f = 1 \text{ GHz}$	$IP_{3\text{out}}$	7.5	9	-	dBm
1dB compression point $f = 1 \text{ GHz}$	$P_{-1\text{dB}}$	-2.5	-1	-	
Return loss input $f = 1.8 \text{ GHz}$	$RL_{\text{in}}$	8	11	-	dB
Return loss output $f = 1.8 \text{ GHz}$	$RL_{\text{out}}$	12	16	-	

### Typical biasing configuration



EHA07386


Note: 1) Large-value capacitors should be connected from pin 4 to ground right at the device to provide a low impedance path!

2) The use of plated through holes right at pin 2 is essential for pc-board-applications. Thin boards are recommended to minimize the parasitic inductance to ground!

### Typical S-Parameters at $T_A = 25^\circ\text{C}$

f GHz	$S_{11}$		$S_{21}$		$S_{12}$		$S_{22}$	
	MAG	ANG	MAG	ANG	MAG	ANG	MAG	ANG
$V_D = 3 \text{ V}$ , $Z_0 = 50 \Omega$								
0.1	0.5686	-8.5	9.314	170.6	0.0268	12.7	0.2808	-8.6
0.5	0.5066	-19.2	8.393	149.4	0.0248	11.7	0.2613	-3.8
0.8	0.4404	-28.7	7.352	135.2	0.0236	25.6	0.2361	-6.7
1	0.3904	-34.6	6.69	126.8	0.024	35.9	0.2144	-9
1.5	0.2841	-50.5	5.244	111.1	0.0314	57.2	0.1398	-15
1.8	0.2343	-60.6	4.567	104	0.0378	63.5	0.0979	-18.2
1.9	0.2136	-64.1	4.355	102	0.0406	66.1	0.0838	-21.5
2	0.2062	-68.4	4.165	99.7	0.0426	67.2	0.0689	-22.2
2.4	0.1688	-89.7	3.417	91.7	0.0549	71.4	0.0224	-48
3	0.1558	-104.9	2.861	85.3	0.0682	73.1	0.0284	-147.5

### Spice-model BGA 420



T1	T501
$R_1$	14.5k $\Omega$
$R_2$	140 $\Omega$
$R_3$	2.4k $\Omega$
$C_1$	2.3pF
$C_{P1}$	0.2pF
$C_{P2}$	0.2pF
$C_{P3}$	0.6pF
$C_{P4}$	0.1pF


**Transistor Chip Data T1 (Berkley-SPICE 2G.6 Syntax) :**

IS =	0.21024	aA	BF =	83.23	-	NF =	1.0405	-
VAF =	39.251	V	IKF =	0.16493	A	ISE =	15.761	fA
NE =	1.7763	-	BR =	10.526	-	NR =	0.96647	-
VAR =	34.368	V	IKR =	0.25052	A	ISC =	0.037223	fA
NC =	1.3152	-	RB =	15	$\Omega$	IRB =	0.21215	mA
RBM =	1.3491	$\Omega$	RE =	1.9289	$\Omega$	RC =	0.12691	$\Omega$
CJE =	3.7265	fF	VJE =	0.70367	V	MJE =	0.37747	-
TF =	4.5899	ps	XTF =	0.3641	-	VTF =	0.19762	V
ITF =	1.3364	mA	PTF =	0	deg	CJC =	96.941	fF
VJC =	0.99532	V	MJC =	0.48652	-	XCJC =	0.08161	-
TR =	1.4935	ns	CJS =	0	fF	VJS =	0.75	V
MJS =	0	-	XTB =	0	-	EG =	1.11	eV
XTI =	3	-	FC =	0.99469	-	TNOM	300	K

**C'-E'-Diode Data (Berkley-SPICE 2G.6 Syntax) :**

IS =	2	fA	N =	1.02	-	RS =	20	$\Omega$
------	---	----	-----	------	---	------	----	----------

All parameters are ready to use, no scaling is necessary

**Package Equivalent Circuit:**

Extracted on behalf of SIEMENS Small Signal Semiconductors by:


Institut für Mobil- und Satellitentechnik (IMST)

© 1996 SIEMENS AG

For examples and ready to use parameters please contact your local Siemens distributor or sales office to obtain a Siemens CD-ROM or see Internet: <http://www.siemens.de/Semiconductor/products/35/35.htm>

**Insertion power gain  $|S_{21}|^2 = f(f)$**


$V_D, I_D$  = parameter



**Insertion power gain  $|S_{21}|^2 = f(f)$**


$V_D = 3V$

$T_A$  = parameter



**Noise figure  $NF = f(f)$**


$V_D, I_D$  = parameter



**Noise figure  $NF = f(f)$**

$V_D = 3V$


$T_A$  = parameter



### Intercept point at the output

$$IP_{3\text{out}} = f(f)$$

$V_D, I_D$  = parameter



### Intercept point at the output

$$IP_{3\text{out}} = f(f), V_D = 3V$$

$T_A$  = parameter

