

BP9917FS Non-isolated Buck Offline LED Driver

Description

BP9917FS is a high precision Buck constant current LED driver. The device operates in critical conduction mode and is suitable for 85Vac~265Vac universal input offline LED lighting.

The BP9917FS integrates a 500V power MOSFET. With patent pending MOSFET driving technique, the operating current of the IC is as low as 140uA. It doesn't need the auxiliary winding for VCC supply. It can achieve excellent constant current performance with very few external components, so the system cost and size are minimized.

BP9917FS utilizes patent pending current control method. It can achieve precise output current and excellent line regulation. The driver operates in critical conduction mode, the output current does not change with the inductance and output voltage.

The BP9917FS offers rich protections to improve the system reliability, including LED short circuit protection, VCC under voltage protection and thermal regulation function.

Features

- Internal 500V Power MOSFET
- Integrated HV JFET for VCC Power Supply
- Critical Conduction Mode Operation
- Low Operating Current
- ±5% LED Output Current Accuracy
- LED Short Protection
- VCC Under Voltage Protection
- Thermal Regulation Function
- Available in DIP7 Package

Applications

- LED Tube
- LED Ceiling Light
- LED Bulb
- Other LED Lighting

Typical Application




Figure 1. Typical application circuit for BP9917FS



Ordering Information

| Part Number | Package | Operating Temperature | Packing Method | Marking |
|-------------|---------|--------------------------|----------------|----------------|
| | | | Tube | BP9917F |
| BP9917FS | DIP7 | -40 ℃ to 105 ℃ | 50 Pcs/Tube | XXXXXY XYYS |

Pin Configuration and Marking Information




Figure 2. Pin configuration

Pin Definition

| Pin No. | Name | Description | |
|------------|-------|---|--|
| 1 | VCC | Power Supply Pin. | |
| 2 | NC | No Connection | |
| 3 | DRAIN | Internal HV Power MOSFET Drain. | |
| 4, 5, 6, 7 | CS | IC GND Pin, also for Current Sense. Connect a sense resistor between this pin and power GND. | |