SHATES IN V. S. A.


- TUNB-SOL .

VOLTAGE REGULATOR MINIATURE TYPE



COLD CATHODE

ANY MOUNTING POSITION



BOTTOM VIEW SMALL-BUTTON MINIATURE 7 PIN BASE

THE OB2 IS A TWO ELECTRODE, INERT-GAS-FILLED COLD CATHODE MINIATURE TUBE INTENDED FOR USE AS A VOLTAGE REGULATOR. THE TUBE HAS A MAINTAINING VOLTAGE OF APPROXIMATELY 108 VOLTS OVER A CURRENT RANGE OF 5 TO 30 MA. THE OB2 IS EXCELLENT FOR APPLICATIONS WHICH REQUIRE GOOD VOLTAGE REGULATION AND LONG LIFE.

ELECTRICAL DATA

CATHODE

COLD

MECHANICAL DATA

MOUNTING POSITION MAXIMUM OVERALL LENGTH MAXIMUM SEATED LENGTH MAXIMUM DIAMETER	ANY 2 5/8 2 3/8 3/4	INCHES INCHES INCH
WEIGHT (APPROX.) BULB BASE	0.3 T-5 1/2 SMALL-BUTTON MINIATURE 7-PIN	OUNCES

RATINGS ABSOLUTE VALUES

MAXIMUM AVERAGE STARTING CURRENT ^A	75	MA.
MAXIMUM DC CATHODE CURRENT	30	MA.
MINIMUM DC CATHODE CURRENT	5	MA.
MAXIMUM INVERSE VOLTAGE	50	VOLTS
AMBIENT TEMPERATURE	− 55 то +90	°c

CONTINUED ON FOLLOWING PAGE

A AVERAGED OVER STARTING PERIOD NOT EXCEEDING 10 SECONDS NORMAL OPERATION SHOULD BE CONTINUED FOR AT LEAST TWENTY MINUTES AFTER PASSING THIS CURRENT TO STABILIZE THE TUBE.

TUNS-SOL

CONTINUED FROM PRECEDING PAGE

CIRCUIT VALUES

MAXIMUM SHUNT CAPACITOR

0.1

 μ f


SERIES RESISTOR

SEE OPERATION NOTES

EQUIPMENT DESIGN AND RANGE VALUES

	MINIMUM VOLTS	AVERAGE VOLTS	MAXIMUM VOLTS
DC ANODE SUPPLY VOLTAGE	133 ^B		
ANODE BREAKDOWN VOLTAGE		114	133
TUBE VOLTAGE DROP	101	108	114
REGULATION (5 TO 30 MA.)		1.1	4

B IN ORDER TO ASSURE STARTING THROUGH TUBELIFE NOT LESS THAN THE SPECIFIED SUPPLY VOLTAGE SHOULD BE PROVIDED.



OPERATING NOTES

IN THE OPERATION OF A GLOW TUBE THERE ARE SEVERAL REQUIREMENTS WHICH MUST ALWAYS BE MET. THE FIRST IS THAT THE SUPPLY VOLTAGE MUST ALWAYS BE GREATER THAN THE ANODE BREAKDOWN VOLTAGE AND THE SECOND IS THAT SUFFICIENT RESISTANCE MUST ALWAYS BE PUT IN SERIES WITH THE TUBE IN ORDER TO LIMIT THE CURRENT TO THE MINIMUM AND MAXIMUM VALUES GIVEN IN THE RATINGS.

IN ORDER TO ILLUSTRATE HOW TO CALCULATE THE VALUE OF THE SERIES RESISTANCE A TYPICAL REGULATOR CIRCUIT IS SHOWN IN FIGURE 1.

FROM FIGURF 4 WE SEE THAT ${\bf v_4}$ is the unregulated supply voltage, ${\bf v_2}$ is the Tube voltage drop on the regulated voltage supplied to the load, ${\bf r_4}$ is the series limiting resistor, ${\bf r_L}$ is the variable load, ${\bf I_T}$ is the tube current and ${\bf I_L}$ is the load current.

WE SEE THAT THE TUBE CURRENT WILL BE A MAXIMUM WHEN THE SUPPLY VOLTAGE IS A MAXIMUM (V_1 MAX.); WHEN THE LOAD CURRENT IS A MINIMUM (I_L MIN.); AND WHEN THE TUBE VOLTAGE DROP IS A MINIMUM (V_2 MIN.). THEREFORE THE CONDITIONS WHICH DETERMINE THE LOWER LIMIT FOR THE SERIES RESISTANCE R_4 ARE THAT

$$R_{1} > \frac{V_{1} MAX. - V_{2} MIN.}{I_{T} MAX. + I_{1} MIN.}$$

IN A LIKE MANNER IT CAN BE SHOWN THAT THE VALUE OF ${\sf R_4}$ in order to limit the current to the minimum value requires that

$$R_1 < \frac{v_1 \cdot min. - v_2 \cdot max.}{I_T \cdot min. + I_L \cdot max.}$$

WHEN THESE VALUES HAVE BEEN COMPUTED, ONE SHOULD CHECK TO SEE IF THERE IS SUFFICIENT STARTING VOLTAGE BY THE FOLLOWING RELATION

$$v_1 \text{ MIN.} \frac{R_L}{R_1 + R_L} \le v \text{ STARTING}$$





FIGURE I

CONTINUED ON FOLLOWING PAGE

0B2



PRINTED IN U. S. A.


TUMS-SOL

WHEN THESE CALCULATIONS HAVE BEEN MADE AND THERE IS INSUFFICIENT START-ING VOLTAGE, A NEW LOAD CURRENT OF LOWER VALUE MUST BE USED AND THE CALCULATIONS REPEATED.

CIRCUITS WHICH HAVE A CAPACITOR IN SHUNT WITH THE 0B2 SHOULD BE LIMITED IN VALUE TO TO 0.1 μf , LARGER VALUES MIGHT CAUSE OSCILLATIONS.

OPERATION OF THE OB2 IN PARALLEL IS NOT RECOMMENDED UNLESS A RESISTANCE OF APPROXIMATELY 100 OHMS IS USED IN SERIES WITH EACH OB2 TO EQUILIZE DIVISION OF CURRENT. HOWEVER, IT SHOULD BE NOTED THAT WHILE THIS ENABLES ONE TO HANDLE MORE LOAD CURRENT IT REDUCES THE REGULATION THAT CAN BE OBTAINED.

IF IT IS DESIRED TO OBTAIN HIGHER REGULATING VOLTAGES, TÜBES MAY BE OPERATED IN SERIES AS INDICATED IN FIGURE 2. HOWEVER, CARE SHOULD BE TAKEN TO SEE THAT SUFFICIENT SUPPLY VOLTAGE IS AVAILABLE TO START BOTH TUBES.



TYPICAL APPLICATION OF OB2
USED IN VOLTAGE REGULATED POWER SUPPLY
FIGURE 4