
# SUPER CONTROL RF AMPLIFIER PENTODE

### MIDGET TYPE



COATED UNIPOTENTIAL CATHODE

HEATER\*
6.3 VOLTS 0.15 AMPERE
AC OR DC

GLASS BULB

MINIATURE BUTTON 7 PIN BASE

MOUNTING POSITION — ANY



BOTTOM VIEW

THE 9003 IS A REMOTE CUT-OFF MIDGET TYPE PENTODE INTENDED FOR USE AS AN AMPLIFIER AND MIXER AT ULTRA HIGH FREQUENCIES. ITS CONSTRUCTION, INCLUDING DOUBLE CATHODE LEADS, PERMITS CIRCUITS TO BE DESIGNED WITH EXTREMELY SHORT LEADS AND WITH MINIMUM INTER-CIRCUIT COUPLING. ELECTRICALLY ITS CHARACTERISTICS ARE IDENTICAL WITH TYPE 956.

#### RATINGS\*

MAXIMUM PLATE VOLTAGE	250	VOLTS
MAXIMUM SCREEN VOLTAGE	100	VOLTS
MINIMUM GRID VOLTAGE	<del>-</del> 3	VOLTS
MAXIMUM PLATE DISSIPATION	1.7	WATTS
MAXIMUM SCREEN DISSIPATION	0.3	WATT

<sup>\*</sup>INTERPRETED ACCORDING TO RMA STANDARD M8-210

#### DIRECT INTERELECTRODE CAPACITANCES

MAXIMUM GRID TO PLATE (WITH EXTERNAL SHIELD)	0.01	μμf
INPUT (WITH NO EXTERNAL SHIELD)	3.4	μμf
OUTPUT (WITH NO EXTERNAL SHIELD)	3.0	uu f

## TYPICAL OPERATING CONDITIONS AND CHARACTERISTICS

# CLASS A1 AMPLIFIER

PLATE VOLTAGE SCREEN VOLTAGE GRID VOLTAGE PLATE RESISTANCE (APPROX.) TRANSCONDUCTANCE GRID BIAS FOR TRANSCONDUCTANCE OF 15 MMHOS GRID BIAS FOR TRANSCONDUCTANCE OF 2 MMHOS	250 100 -3 0.7 1800 -35 -45 6.7	VOLTS VOLTS VOLTS MEGOHM µMHOS VOLTS VOLTS
GRID BIAS FOR TRANSCONDUCTANCE OF 2 MMHOS PLATE CURRENT SCREEN CURRENT	-45 6.7 2.7	VOLTS Ma. Ma.

CONTINUED NEXT PAGE

PLATE 1405 MARCH 15 1944

# TUNG-SOL -

CONTINUED FROM PRECEDING PAGE

### MIXER IN SUPERHETERODYNE CIRCUIT

PLATE VOLTAGE	250	VOLTS
SCREEN VOLTAGE	100	VOLTS
GRID VOLTAGE (APPROX.) <sup>B</sup>	10	VOLTS
CONVERSION TRANSCONDUCTANCE (APPROX.)	600	<b>дм</b> ноs

- A WHEN THE CATHODE IS NOT DIRECTLY CONNECTED TO THE HEATER THE POTENTIAL DIFFERENCE BETWEEN HEATER AND CATHODE SHOULD BE KEPT AS LOW AS POSSIBLE.
- B VALUES INDICATED ARE OPTIMUM. FOR AN OSCILLATOR PEAK VOLTAGE OF 9 VOLTS THE GRID BIAS IS MINIMUM.

TO PROVIDE THE SHORTEST POSSIBLE CIRCUIT RETURNS AND TO PREVENT INTER-STAGE COUPLING AT ULTRA HIGH FREQUENCIES, EACH RF AMPLIFIER STAGE MAY REQUIRE RF BY-PASSING AND SHIELDING. THIS CAN BE ACCOMPLISHED BY PLACING SMALL CONDENSERS CLOSE TO THE TUBE TERMINALS. IN ADDITION RF CHOKES MAY BE REQUIRED IN THE SUPPLY OF RETURN LEADS OF THE TUBE ELEMENTS.

THIS TUBE HAS TWO CATHODE LEADS. IF THE GRID RETURN IS CONNECTED TO ONE CATHODE TERMINAL AND THE PLATE AND SCREEN RETURNS ARE CONNECTED TO THE OTHER CATHODE TERMINAL, THE PLATE AND SCREEN RF CIRCUITS WILL BE COMPLETED WITH A MINIMUM OF INDUCTANCE IN COMMON WITH THE GRID CIRCUITS.

PLATE 1406 MARCH 15 1944