

OCXO 143-55

P.O. BOX 3389 CHARLOTTESVILLE, VIRGINIA 22903 PHONE: (804) 295-3101 FAX: (804) 977-1849

CRYSTAL OSCILLATOR SPECIFICATION

This specification defines the operating characteristics of an ovenized crystal oscillator. Long term stability is assured through use of premium components.

REV.	DESCRIPTION OF REVISION	REQ. BY	DWN. BY	DATE
_	This unit is the same as the OCXO 143-40 except the package	TST	TST	07-14-99
A	1.5. was 40% to 60%, Inserted 1.6., 2.1. was -5°C to +60°C, 2.4. was < $\pm 1 \times 10^{-8}$ in 3 minutes @+25°C, 3.4. was +2 VDC ± 0.4 VDC, 3.6. was > 50 k Ω , Added 3.7., 4.1. was +5 VDC ± 5 %, 4.3. was < 1.5 Watts @ +25°C, Added 2nd sentance to 3.2. and 3.4.	TST	TST	12-20-99

ISOTEMP RESEARCH INC.	CODE ID.	PART NO.	PAGE OI	F TOTAL	DWG. NO.	REV.
CHARLOTTESVILLE, VA. USA	31785	OCXO 143-55	1	3	114-901	A



OCXO 143-55

1. OUTPUT 1.1. Frequency 10.000 MHz Rectangular 1.2. Waveform 1.3. Level HCMOS a. "1" level > Vcc - 0.6 VDC b. "0" level < +0.3 VDC 2 HCMOS 1.4. Load 1.5. Duty cycle 45% to 55% @ +2.5 VDC 1.6. Rise/fall time < 10 ns (10% to 90%) 10 k Ω in parallel with 15 pF < -60 dBc 1.7. Spurious 2. FREQUENCY STABILITY < $\pm 2 \times 10^{-8}$ from 0°C to +55°C 2.1. Ambient (referenced to +25°C) 2.2. Aging a. At time of shipment < $\pm 1 \times 10^{-9} / day$ b. After indefinite storage < $\pm 1 \times 10^{-9}$ after 30 days i. Daily < $\pm 1 \times 10^{-7}$ ii. Yearly iii. 10 years < $\pm 3.5 \times 10^{-7}$ < $\pm 1 \times 10^{-8} / \pm 5$ % change 2.3. Voltage 2.4. Warm-up (referenced to 4 hours) < $\pm 1 \times 10^{-8}$ in 3 minutes a. @ +25°C b. @ 0°C < $\pm 1 \times 10^{-7}$ in 3 minutes 2.5. Phase noise a. @ 10 Hz < -115 dBc b. @ 100 Hz < -135 dBc c. @ 1 kHz < -145 dBc

ISOTEMP RESEARCH INC.	CODE ID.	PART NO.	PAGE OF	' TOTAL	DWG. NO.	REV.
CHARLOTTESVILLE, VA. USA	31785	OCXO 143-55	2	3	114-901	A





3. ELECTRICAL FREQUENCY ADJUSTMENT (PIN = "VCO INPUT") 3.1. Range $> \pm 4 \times 10^{-7}$ < $\pm 8 \times 10^{-7}$ (At time of shipment) (Referenced to nominal frequency) 0 VDC to Vref (+4 VDC) or 3.2. Control A 20 k Ω potentiometer connected between the "REFERENCE VOLTAGE" pin and "O VOLTS & CASE" pin with wiper connected to "VCO INPUT" pin. With the VCO input voltage at +5 VDC, the unit will perform normally and be within 2×10^{-6} of nominal frequency. 3.3. Slope Positive 3.4. Center +2 VDC ± 0.5 VDC Control voltage at which nominal frequency occurs at time of shipment. The VCO input pin is internally held, by a resistor divider network and can be left floating. 3.5. Linearity < ±10% 3.6. Input impedance > 250 k Ω ±30% 3.7. Frequency response DC to > 200 Hz 4. INPUT POWER (PIN = "+VDC") 4.1. Voltage +5 VDC ±2% 4.2. Current < 700 mA @ turn on 4.3. Steady state < 2.2 Watts @ 0°C 5. REFERENCE VOLTAGE (PIN = "REFERENCE VOLTAGE"), an output 5.1. Voltage +4 VDC ±5% 5.2. Load $> 4 k\Omega$ 5.3. Temperature stability < ±0.010 VDC (Over temperature range in 2.1.) 6. ENVIRONMENTAL MIL-STD-202F, Method 103A, Test 6.1. Humidity Condition A (95% R.H. @ +40°C, non-condensing, 240 hours) 6.2. Storage temperature -50°C to +105°C 6.3. Vibration (non-operating) MIL-STD-202F Method 201A. (0.06" Total p-p, 10 to 55 Hz) 6.4. Shock (non-operating) MIL-STD-202F, Method 213B, Test Condition J. (30 g, 11 ms half-sine) 6.5. Seal MIL-STD-202F, Method 112C, Test Condition D. 7. MECHANICAL 7.1. Applicable series OCXO 143 series 7.2. Model number OCXO 143-55 7.3. Outline drawing 125-569

ISOTEMP RESEARCH INC.	CODE ID.	PART NO.	PAGE OF	TOTAL	DWG. NO.	REV.
CHARLOTTESVILLE, VA. USA	31785	OCXO 143-55	3	3	114-901	A