SCLS256C - DECEMBER 1995 - REVISED MAY 1997


- Operating Range 2-V to 5.5-V V_{CC}
- EPIC™ (Enhanced-Performance Implanted CMOS) Process
- High Latch-Up Immunity Exceeds 250 mA Per JESD 17
- Package Options Include Plastic Small-Outline (D), Shrink Small-Outline (DB), Thin Shrink Small-Outline (PW), and Ceramic Flat (W) Packages, Ceramic Chip Carriers (FK), and Standard Plastic (N) and Ceramic (J) 300-mil DIPs

description


The 'AHC125 are quadruple bus buffer gates featuring independent line drivers with 3-state outputs. Each output is disabled when the associated output-enable (\overline{OE}) input is high. When \overline{OE} is low, the respective gate passes the data from the A input to its Y output.

The SN54AHC125 is characterized for operation over the full military temperature range of –55°C to 125°C. The SN74AHC125 is characterized for operation from –40°C to 85°C.

SN54AHC125 . . . J OR W PACKAGE SN74AHC125 . . . D, DB, N, OR PW PACKAGE (TOP VIEW)



SN54AHC125 . . . FK PACKAGE (TOP VIEW)



NC - No internal connection

FUNCTION TABLE (each buffer)

INPU	JTS	OUTPUT
OE	Α	Y
L	Н	Н
L	L	L
Н	Χ	Z



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.


EPIC is a trademark of Texas Instruments Incorporated



SN54AHC125, SN74AHC125 QUADRUPLE BUS BUFFER GATES WITH 3-STATE OUTPUTS


SCLS256C - DECEMBER 1995 - REVISED MAY 1997


logic symbol[†]



[†] This symbol is in accordance with ANSI/IEEE Std 91-1984 and IEC Publication 617-12. Pin numbers shown are for the D, DB, J, N, PW, and W packages.

logic diagram (positive logic)





Pin numbers shown are for the D, DB, J, N, PW, and W packages.

absolute maximum ratings over operating free-air temperature range (unless otherwise noted)‡

Supply voltage range, V _{CC}		–0.5 V to 7 V
Input voltage range, V _I (see Note 1)		0.5 V to 7 V
Output voltage range, VO (see Note 1)		. -0.5 V to V _{CC} + 0.5 V
Input clamp current, I _{IK} (V _I < 0)		–20 mA
Output clamp current, IOK (VO < 0 or VO > VCO	c)	±20 mA
Continuous output current, $I_O(V_O = 0 \text{ to } V_{CC})$		±25 mA
Continuous current through V _{CC} or GND		±50 mA
Package thermal impedance, θ _{JA} (see Note 2)): D package	127°C/W
	DB package	158°C/W
	N package	78°C/W
	PW package	170°C/W
Storage temperature range, T _{stg}		–65°C to 150°C

[‡] Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.



NOTES: 1. The input and output voltage ratings may be exceeded if the input and output current ratings are observed.

^{2.} The package thermal impedance is calculated in accordance with JESD 51, except for through-hole packages, which use a trace length of zero.

recommended operating conditions (see Note 3)

			SN54A	SN54AHC125		HC125	UNIT
			MIN	MAX	MIN	MAX	UNIT
Vcc	Supply voltage		2	5.5	2	5.5	V
		V _{CC} = 2 V	1.5		1.5		
VIН	High-level input voltage	V _{CC} = 3 V	2.1		2.1		V
		$V_{CC} = 5.5 \text{ V}$	3.85		3.85		
		V _{CC} = 2 V		0.5		0.5	
VIL	Low-level input voltage	V _{CC} = 3 V		0.9		0.9	V
		V _{CC} = 5.5 V		1.65		1.65	
٧ı	Input voltage		0	5.5	0	5.5	V
٧o	Output voltage		0	Vcc	0	VCC	V
		V _{CC} = 2 V		-50		-50	μΑ
IOH	High-level output current	$V_{CC} = 3.3 \text{ V} \pm 0.3 \text{ V}$		-4		-4	mΑ
		$V_{CC} = 5 V \pm 0.5 V$		-8		-8	ША
		V _{CC} = 2 V		50		50	μΑ
lOL	Low-level output current	$V_{CC} = 3.3 \text{ V} \pm 0.3 \text{ V}$		4		4	mA
		$V_{CC} = 5 V \pm 0.5 V$		8		8	IIIA
Δt/Δν	AA/A Inm. A Annua (Aire mine on fall make	$V_{CC} = 3.3 \text{ V} \pm 0.3 \text{ V}$		100		100	ns/V
ΔυΔν	Input transition rise or fall rate	$V_{CC} = 5 V \pm 0.5 V$		20		20	115/ V
TA	Operating free-air temperature	-	-55	125	- 40	85	°C

NOTE 3: Unused inputs must be held high or low to prevent them from floating.

electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

DA	ARAMETER	TEST CONDITIONS	vcc	T,	չ = 25°C	;	SN54AI	HC125	SN74AHC125		UNIT
PA	ARAWETER	TEST CONDITIONS		MIN	TYP	MAX	MIN	MAX	MIN	MAX	UNIT
			2 V	1.9	2		1.9		1.9		
		I _{OH} = -50 μA	3 V	2.9	3		2.9		2.9		
VOH			4.5 V	4.4	4.5		4.4		4.4		V
		I _{OH} = -4 mA	3 V	2.58			2.48		2.48		
		I _{OH} = -8 mA	4.5 V	3.94			3.8		3.8		
						0.1		0.1		0.1	
		Ι _{ΟL} = 50 μΑ	3 V			0.1		0.1		0.1	
VOL			4.5 V			0.1		0.1		0.1	V
		I _{OL} = 4 mA	3 V			0.36		0.5		0.44	
		I _{OL} = 8 mA	4.5 V			0.36		0.5		0.44	
Ц	A or OE inputs	V _I = V _{CC} or GND	5.5 V			±0.1		±1		±1	μΑ
loz		$V_O = V_{CC}$ or GND	5.5 V			±0.25		±2.5		±2.5	μΑ
Icc		$V_I = V_{CC}$ or GND, $I_O = 0$	5.5 V			4		40		40	μΑ
Ci		$V_I = V_{CC}$ or GND	5 V		4	10				10	pF

SN54AHC125, SN74AHC125 QUADRUPLE BUS BUFFER GATES WITH 3-STATE OUTPUTS

SCLS256C - DECEMBER 1995 - REVISED MAY 1997

switching characteristics over recommended operating free-air temperature range, V_{CC} = 3.3 V \pm 0.3 V (unless otherwise noted) (see Figure 1)

					SN	54AHC1	25		
PARAMETER	FROM (INPUT)	TO (OUTPUT)	LOAD CAPACITANCE	T _A :	= 25°C	;	MIN	MAX	UNIT
	(01)	(5511.51)		MIN	TYP	MAX	IVIIIN	WAX	
^t PLH*	А	Y	C _L = 15 pF		5.6	8	1	9.5	ns
^t PHL*	А	ı	OL = 13 pr		5.6	8	1	9.5	115
^t PZH*	ŌĒ	Y	C _L = 15 pF		5.4	8	1	9.5	ns
tPZL*	OE	ī	CL = 15 pr		5.4	8	1	9.5	115
^t PHZ*	ŌĒ	Y	C _I = 15 pF		7	9.7	1	11.5	ns
^t PLZ*	OE	ı	OL = 13 pr		7	9.7	1	11.5	115
^t PLH	^	Y	C _I = 50 pF		8.1	11.5	1	13	ns
^t PHL	- A Y		CL = 50 pr		8.1	11.5	1	13	115
^t PZH	ŌĒ	Y	C: 50 pF		7.9	11.5	1	13	
^t PZL	OE	Y C _L = 50 pF			7.9	11.5	1	13	ns
^t PHZ	ŌĒ	Y	C: 50 pF		9.5	13.2	1	15	
t _{PLZ}) OE	, r	C _L = 50 pF		9.5	13.2	1	15	ns

^{*} On products compliant to MIL-PRF-38535, this parameter is ensured but not production tested.

switching characteristics over recommended operating free-air temperature range, V_{CC} = 3.3 V \pm 0.3 V (unless otherwise noted) (see Figure 1)

					SN	74AHC1	25			
PARAMETER	FROM (INPUT)	TO (OUTPUT)	LOAD CAPACITANCE	TA	= 25°C	;	MIN	MAX	UNIT	
	(01)	(551151)	0/11/10/1/11/02	oai Adriand	MIN	TYP	MAX	IVIIIV	IVIAA	
t _{PLH}	А	Y	C 15 pE		5.6	8	1	9.5	20	
^t PHL		ī	C _L = 15 pF		5.6	8	1	9.5	ns	
^t PZH	OE	Y	C _I = 15 pF		5.4	8	1	9.5	ns	
^t PZL	OE	ī	C[= 15 pr		5.4	8	1	9.5	115	
^t PHZ	ŌĒ	Y	C _L = 15 pF		7	9.7	1	11.5	ns	
tPLZ	OE	ī	CL = 15 pr		7	9.7	1	11.5	115	
^t PLH	А	Y	C 50 pF		8.1	11.5	1	13	ns	
^t PHL	A	ī	C _L = 50 pF		8.1	11.5	1	13	115	
^t PZH	OE	Y	C: 50 pF		7.9	11.5	1	13	20	
t _{PZL}	OE	ſ	C _L = 50 pF		7.9	11.5	1	13	ns	
^t PHZ	ŌĒ	Y	C 50 pF		9.5	13.2	1	15	ns	
tPLZ	OE .	ľ	C _L = 50 pF	_	9.5	13.2	1	15	115	

SCLS256C - DECEMBER 1995 - REVISED MAY 1997

switching characteristics over recommended operating free-air temperature range, V_{CC} = 5 V \pm 0.5 V (unless otherwise noted) (see Figure 1)

				SI	N54AHC1	25		
PARAMETER	FROM (INPUT)	TO (OUTPUT)	LOAD CAPACITANCE	T _A = 25°	С	MIN	MAX	UNIT
	(01)	(0011 01)	OAI AOITANOL	MIN TYP	MAX	IVIIIN	WAX	
^t PLH*	А	Y	C _L = 15 pF	3.8	5.5	1	6.5	ns
tphL*		ī	CL = 15 pr	3.8	5.5	1	6.5	115
^t PZH*	- OE Y	C _L = 15 pF	3.6	5.1	1	6	no	
tpzL*		Ĭ	CL = 15 pr	3.6	5.1	1	6	ns
^t PHZ*	ŌĒ	Υ	C _I = 15 pF	4.6	6.8	1	8	ns
t _{PLZ} *	OE	ı	G[= 15 pr	4.6	6.8	1	8	115
^t PLH	А	Υ	C: -50 pF	5.3	7.5	1	8.5	ns
^t PHL	A	Y $C_L = 50 \text{ pF}$		5.3	7.5	1	8.5	115
^t PZH	ŌĒ	Υ	C 50 pF	5.1	7.1	1	8	no
t _{PZL}	OE .	Y C _L = 50 pF		5.1	7.1	1	8	ns
^t PHZ	ŌĒ	Y	C: - 50 pF	6.1	8.8	1	10	no
tPLZ	OE	Ĭ	C _L = 50 pF	6.1	8.8	1	10	ns

^{*} On products compliant to MIL-PRF-38535, this parameter is ensured but not production tested.

switching characteristics over recommended operating free-air temperature range, V_{CC} = 5 V \pm 0.5 V (unless otherwise noted) (see Figure 1)

				S	N74AHC1	25			
PARAMETER	FROM (INPUT)	TO (OUTPUT)	LOAD CAPACITANCE	T _A = 25	°C	MIN	MAX	UNIT	
	(01)	(0011 01)			MAX	IVIIIN	WAX		
^t PLH	А	Y	C _L = 15 pF	3.8	5.5	1	6.5	ns	
t _{PHL}			GL = 13 pr	3.8	5.5	1	6.5	115	
^t PZH	OE Y	C _I = 15 pF	3.6	5.1	1	6	ns		
^t PZL		OE T		OE 1	G[= 15 pr	3.6	5.1	1	6
^t PHZ	ŌĒ	Y	C _L = 15 pF	4.6	6.8	1	8	ns	
t _{PLZ}	OE	1 CL = 15 βF	4.6	6.8	1	8	113		
^t PLH	А	Y	C _L = 50 pF	5.3	7.5	1	8.5	ns	
^t PHL	٨	ı	GL = 30 pr	5.3	7.5	1	8.5	110	
^t PZH	<u>OE</u>	Y	C _L = 50 pF	5.1	7.1	1	8	20	
^t PZL	OE	ſ	CL = 50 pF	5.1	7.1	1	8	ns	
^t PHZ	ŌĒ	Y	C 50 pF	6.1	8.8	1	10	ne	
t _{PLZ}	OE	, , , , , , , , , , , , , , , , , , ,	C _L = 50 pF	6.′	8.8	1	10	ns	

output-skew characteristics, C_L = 50 pF (see Note 4)

			SN74A		
PARAMETER		VCC	T _A = 25°C	MINI MAY	UNIT
			MIN MAX	MIN MAX	
1	Output skew	$3.3~V\pm0.3~V$	1.5	1.5	no
tsk(o)	Output skew	5 V ± 0.5 V	1	1	ns

NOTE 4: Characteristics are determined during product characterization and ensured by design.



SCLS256C - DECEMBER 1995 - REVISED MAY 1997

noise characteristics, $V_{CC} = 5 \text{ V}$, $C_L = 50 \text{ pF}$, $T_A = 25^{\circ}\text{C}$ (see Note 5)


	PARAMETER		SN74AHC125		
			MAX	UNIT	
V _{OL(P)}	Quiet output, maximum dynamic V _{OL}		0.8	V	
V _{OL(V)}	Quiet output, minimum dynamic V _{OL}		-0.8	V	
VOH(V)	Quiet output, minimum dynamic VOH	4.4		V	
V _{IH(D)}	High-level dynamic input voltage	3.5		V	
V _{IL(D)}	Low-level dynamic input voltage		1.5	V	

NOTE 5: Characteristics are determined during product characterization and ensured by design for surface-mount packages only.


operating characteristics, $V_{CC} = 5 \text{ V}$, $T_A = 25^{\circ}\text{C}$


	PARAMETER		ONDITIONS	TYP	UNIT
C _{pd}	Power dissipation capacitance	No load,	f = 1 MHz	14	pF

PARAMETER MEASUREMENT INFORMATION



TEST	S 1
tPLH/tPHL	Open
tPLZ/tPZL	VCC
tPHZ/tPZH	GND





NOTES: A. C_L includes probe and jig capacitance.

- B. Waveform 1 is for an output with internal conditions such that the output is low except when disabled by the output control. Waveform 2 is for an output with internal conditions such that the output is high except when disabled by the output control.
- C. All input pulses are supplied by generators having the following characteristics: PRR \leq 1 MHz, $Z_O = 50 \Omega$, $t_f = 3$ ns. $t_f = 3$ ns.
- D. The outputs are measured one at a time with one input transition per measurement.

Figure 1. Load Circuit and Voltage Waveforms



IMPORTANT NOTICE

Texas Instruments (TI) reserves the right to make changes to its products or to discontinue any semiconductor product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

TI warrants performance of its semiconductor products and related software to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

Certain applications using semiconductor products may involve potential risks of death, personal injury, or severe property or environmental damage ("Critical Applications").

TI SEMICONDUCTOR PRODUCTS ARE NOT DESIGNED, INTENDED, AUTHORIZED, OR WARRANTED TO BE SUITABLE FOR USE IN LIFE-SUPPORT APPLICATIONS, DEVICES OR SYSTEMS OR OTHER CRITICAL APPLICATIONS.

Inclusion of TI products in such applications is understood to be fully at the risk of the customer. Use of TI products in such applications requires the written approval of an appropriate TI officer. Questions concerning potential risk applications should be directed to TI through a local SC sales office.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards should be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or services described herein. Nor does TI warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such semiconductor products or services might be or are used.

Copyright © 1996, Texas Instruments Incorporated