# International Rectifier


**PROVISIONAL** 

### IRF6603

### DirectFET<sup>TM</sup> Power MOSFET

- Application Specific MOSFETs
- Ideal for CPU Core DC-DC Converters
- Low Conduction Losses
- High Cdv/dt Immunity
- Low Profile (<0.7 mm)
- Dual Sided Cooling Compatible
- Compatible with existing Surface Mount Techniques

V <sub>DSS</sub>	V <sub>DSS</sub> R <sub>DS(on)</sub> max	
30V	$3.9 \text{m}\Omega @V_{GS} = 10V$	28A
	$5.5$ m $\Omega$ @ $V$ GS = $4.5$ V	22A





#### **Description**

The IRF6603 combines the latest HEXFET® Power MOSFET Silicon technology with the advanced DirectFET<sup>TM</sup> packaging to achieve the lowest on-state resistance in a package that has the footprint of an SO-8 and only 0.7 mm profile. The DirectFET package is compatible with existing layout geometries used in power applications, PCB assembly equipment and vapor phase, infra-red or convection soldering techniques. The DirectFET package allows dual sided cooling to maximize thermal transfer in power systems, IMPROVING previous best thermal resistance by 80%.

The IRF6603 balances both low resistance and low charge along with ultra low package inductance to reduce both conduction and switching losses. The reduced total losses make this product ideal for high efficiency DC-DC converters that power the latest generation of processors operating at higher frequencies. The IRF6603 has been optimized for parameters that are critical in synchronous buck converters including Rds(on), gate charge and Cdv/dt-induced turn on immunity. The IRF6603 offers particularly low Rds(on) and high Cdv/dt immunity for synchronous FET applications.

### **Absolute Maximum Ratings**

	Parameter	Max.	Units
$V_{DS}$	Drain- Source Voltage	30	V
I <sub>D</sub> @ T <sub>C</sub> = 25°C	Continuous Drain Current, V <sub>GS</sub> @ 10V	84	
I <sub>D</sub> @ T <sub>A</sub> = 25°C	Continuous Drain Current, V <sub>GS</sub> @ 10V	28	
I <sub>D</sub> @ T <sub>A</sub> = 70°C	Continuous Drain Current, V <sub>GS</sub> @ 10V	22	A
I <sub>DM</sub>	Pulsed Drain Current ①	220	
P <sub>D</sub> @T <sub>A</sub> = 25°C	Power Dissipation	5.0	107
P <sub>D</sub> @T <sub>A</sub> = 70°C	Power Dissipation	3.2	─ W
	Linear Derating Factor	40	mW/°C
$V_{GS}$	Gate-to-Source Voltage	+20/-12	V
T <sub>J,</sub> T <sub>STG</sub>	Junction and Storage Temperature Range	-55 to + 150	°C

#### **Thermal Resistance**

Symbol	Parameter	Тур.	Max.	Units	
$R_{\theta JA}$	Junction-to-Ambient3		25		
$R_{\theta JA}$	Junction-to-Ambient		12.5	1	
$R_{\theta JA}$	Junction-to-Ambient®		25	°C/W	
$R_{\theta JC}$	Junction-to-Case®		3.0	1	
R <sub>0J-PCB</sub>	Junction-to-PCB mounted		1.0	1	

www.irf.com 1



### Static @ $T_J = 25$ °C (unless otherwise specified)

	Parameter	Min.	Тур.	Max.	Units	Conditions
V <sub>(BR)DSS</sub>	Drain-to-Source Breakdown Voltage	30			V	$V_{GS} = 0V, I_D = 250\mu A$
$\Delta V_{(BR)DSS}/\Delta T_J$	Breakdown Voltage Temp. Coefficient		0.02		V/°C	Reference to 25°C, I <sub>D</sub> = 1mA
D ·	Static Drain-to-Source On-Resistance		2.8	3.9	mΩ	$V_{GS} = 10V, I_D = 28A$ ③
R <sub>DS(on)</sub>			3.9	5.5	11122	$V_{GS} = 4.5V, I_D = 22A$ ③
V <sub>GS(th)</sub>	Gate Threshold Voltage	1.0	2.5	3.2	V	$V_{DS} = V_{GS}$ , $I_D = 250\mu A$
lana	Drain-to-Source Leakage Current			30	μA	$V_{DS} = 24V$ , $V_{GS} = 0V$
I <sub>DSS</sub>	Diam-to-Source Leakage Current			TBA	μΛ	$V_{DS} = 24V, V_{GS} = 0V, T_{J} = 125^{\circ}C$
I <sub>GSS</sub>	Gate-to-Source Forward Leakage			100	nA	V <sub>GS</sub> = 20 V
	Gate-to-Source Reverse Leakage			-100	] '''A	V <sub>GS</sub> = -12 V

## Dynamic @ T<sub>J</sub> = 25°C (unless otherwise specified)

Symbol	Parameter	Min.	Тур.	Max.	Units	Conditions
g <sub>fs</sub>	Forward Transconductance	TBA			S	V <sub>DS</sub> = 16V, I <sub>D</sub> = 28A
Qg	Total Gate Charge Cont FET		86	120		$V_{GS} = 10V, V_{DS} = 16V, I_D = 28A$
Qg	Total Gate Charge Sync FET		69			$V_{GS} = 10V, V_{DS} < 100mV$
Q <sub>gs1</sub>	Pre-Vth Gate-Source Charge		12			$V_{DS} = 16V, I_D = 28A$
Q <sub>gs2</sub>	Post-Vth Gate-Source Charge		2.5		nC	
$Q_{gd}$	Gate to Drain Charge		19	28		
Q <sub>oss</sub>	Output Charge		32			$V_{DS} = 16V, V_{GS} = 0V$
$R_g$	Gate Resistance		2.0	2.5	Ω	
t <sub>d(on)</sub>	Turn-On Delay Time		TBA			$V_{DD} = 16V$
t <sub>r</sub>	Rise Time		TBA		ns	$I_D = 28A$
t <sub>d(off)</sub>	Turn-Off Delay Time		TBA			V <sub>GS</sub> = 5.0V ③
tf	Fall Time		TBA			Clamped Inductive Load
C <sub>iss</sub>	Input Capacitance		TBA		·	$V_{GS} = 0V$
Coss	Output Capacitance		TBA		pF	$V_{DS} = 16V$
C <sub>rss</sub>	Reverse Transfer Capacitance		TBA			f = 1.0MHz

### **Avalanche Characteristics**

Symbol	Parameter	Тур.	Max.	Units
E <sub>AS</sub>	Single Pulse Avalanche Energy@		553	mJ
I <sub>AR</sub>	Avalanche Current①		TBA	Α

### **Diode Characteristics**


Symbol	Parameter	Min.	Тур.	Max.	Units	Conditions	
Is	Continuous Source Current			28		MOSFET symbol	
	(Body Diode)			20	A	showing the	
I <sub>SM</sub>	Pulsed Source Current		2			integral reverse <sup>G</sup>	
	(Body Diode) ①			220		p-n junction diode.	
V <sub>SD</sub>	Diode Forward Voltage		1.0	TBA	V	$T_J = 25^{\circ}C$ , $I_S = 28A$ , $V_{GS} = 0V$ 3	
			TBA			T <sub>J</sub> = 125°C, I <sub>S</sub> = 28A, V <sub>GS</sub> = 0V ③	
t <sub>rr</sub>	Reverse Recovery Time		TBA	TBA	ns	$T_J = 25$ °C, $I_F = 28$ A, $V_R = 16$ V	
Q <sub>rr</sub>	Reverse Recovery Charge		145	174	nC	di/dt = 700A/µs ③	
Q <sub>rr(s)</sub>	Reverse Recovery Charge		TBA	TBA	nC	$di/dt = 100A/\mu s$	
	(with Parallel Schottky)					$V_{DS} = 16V, V_{GS} = 0V, I_{S} = 28A$	


2 www.irf.com

International

TOR Rectifier


## DirectFET™ Pad Layout





www.irf.com 3

### DirectFET™ Outline Dimension



#### Notes:

- ① Repetitive rating; pulse width limited by max. junction temperature.
- ② Pulse width  $\leq$  400 $\mu$ s; duty cycle  $\leq$  2%.
- 3 Surface mounted on 1 in square Cu board
- Used double sided cooling, mounting pad
- ⑤ Mounted on minimum footprint full size board with metalized back and with small clip heatsink
- © T<sub>C</sub> measured with thermal couple mounted to top (Drain) of part.

Data and specifications subject to change without notice.

This product has been designed and qualified for the Consumer market.

Qualification Standards can be found on IR's Web site.



IR WORLD HEADQUARTERS: 233 Kansas St., El Segundo, California 90245, USA Tel: (310) 252-7105

TAC Fax: (310) 252-7903

Visit us at www.irf.com for sales contact information.01/02