


INTERNATIONAL RECTIFIER



## AVALANCHE ENERGY RATED AND dv/dt RATED

## HEXFET® TRANSISTOR

IRFI064



N-CHANNEL

## 60 Volt, 0.017 Ohm HEXFET

The HEXFET® technology is the key to International Rectifier's advanced line of power MOSFET transistors. The efficient geometry design achieves very low on-state resistance combined with high transconductance.

The HEXFET transistors also feature all of the well established advantages of MOSFETs such as voltage control, very fast switching, ease of paralleling and temperature stability of the electrical parameters.

They are well suited for applications such as switching power supplies and virtually any application where military and/or high reliability is required.


## Product Summary

Part Number	BV <sub>DSS</sub>	R <sub>DS(on)</sub>	I <sub>D</sub>
IRFI064	60V	0.017Ω	45A*

## FEATURES:


- Avalanche Energy Rating
- Isolated and Hermetically Sealed
- Alternative to TO-3 Package
- Simple Drive Requirements
- Ease of Paralleling
- Ceramic Eyelets

## CASE STYLE AND DIMENSIONS



CAUTION

BERYLLOTA WARNING PER MIL-S-19500  
SEE PAGE I-251



\*For optional leadforms see page I-251, fig. 15

Conforms to JEDEC Outline TO-259AA\*  
Dimensions in Millimeters and (Inches)

**Absolute Maximum Ratings**

Parameter	IRFI064	Units
$I_D @ V_{GS} = 10V, T_C = 25^\circ C$ Continuous Drain Current	45*	
$I_D @ V_{GS} = 10V, T_C = 100^\circ C$ Continuous Drain Current	45*	A
$I_{DM}$ Pulsed Drain Current ①	400	
$P_D @ T_C = 25^\circ C$ Max. Power Dissipation	300	W
Linear Derating Factor	2.4	W/K ⑤
$V_{GS}$ Gate-to-Source Voltage	$\pm 20$	V
EAS Single Pulse Avalanche Energy ②	620	mJ
$dv/dt$ Peak Diode Recovery $dv/dt$ ③	4.5	V/ns
$T_J$ Operating Junction Temperature	-55 to 150	
$T_{STG}$ Storage Temperature Range		°C
Lead Temperature	300 (0.063 in. (1.6 mm) from case for 10s)	
Weight	10.9 (typical)	g

①  $I_D$  current limited by pin diameter**Electrical Characteristics @  $T_J = 25^\circ C$  (Unless Otherwise Specified)**

Parameter	Min.	Typ.	Max.	Units	Test Conditions
$BV_{DSS}$ Drain-to-Source Breakdown Voltage	60	—	—	V	$V_{GS} = 0V, I_D = 1.0\text{ mA}$
$\Delta BV_{DSS}/\Delta T_J$ Temperature Coefficient of Breakdown Voltage	—	0.048	—	V/°C	Reference to $25^\circ C, I_D = 1.0\text{ mA}$
$R_{DS(on)}$ Static Drain-to-Source On-State Resistance	—	—	0.017	Ω	$V_{GS} = 10V, I_D = 45A$ ④
$V_{GS(th)}$ Gate Threshold Voltage	2.0	—	4.0	V	$V_{DS} = V_{GS}, I_D = 25\mu A$
$g_{fs}$ Forward Transconductance	21	—	—	S (Ω)	$V_{DS} \geq 15V, I_D = 45A$ ④
$I_{DSS}$ Zero Gate Voltage Drain Current	—	—	25	μA	$V_{DS} = 0.8 \times \text{Max. Rating}, V_{GS} = 0V$
	—	—	250		$V_{DS} = 0.8 \times \text{Max. Rating}$
	—	—	—		$V_{GS} = 0V, T_J = 125^\circ C$
$I_{GSS}$ Gate-to-Source Leakage Forward	—	—	100	nA	$V_{GS} = 20V$
$I_{GSS}$ Gate-to-Source Leakage Reverse	—	—	-100		$V_{GS} = -20V$
$Q_g$ Total Gate Charge	—	—	240		$V_{GS} = 10V, I_D = 45A$
$Q_{gs}$ Gate-to-Source Charge	—	—	53	nC	$V_{DS} = 0.5 \times \text{Max. Rating}$
$Q_{gd}$ Gate-to-Drain ("Miller") Charge	—	—	78		See Fig. 6 and 14
$t_{d(on)}$ Turn-On Delay Time	—	—	27		$V_{DD} = 30V, I_D = 45A, R_G = 2.35\Omega$
$t_r$ Rise Time	—	—	120	ns	
$t_{d(off)}$ Turn-Off Delay Time	—	—	76		See Fig. 11
$t_f$ Fall Time	—	—	93		
$L_D$ Internal Drain Inductance	—	5.0	—	nH	Measured from the drain lead, 6 mm (0.25 in.) from package to center of die.
$L_S$ Internal Source Inductance	—	13	—		Measured from the source lead, 6 mm (0.25 in.) from package to source bonding pad.
$C_{iss}$ Input Capacitance	—	7400	—		Modified MOSFET symbol showing the internal inductances.
$C_{oss}$ Output Capacitance	—	3200	—	pF	
$C_{trs}$ Reverse Transfer Capacitance	—	540	—		$V_{GS} = 0V, V_{DS} = 25V$
$C_{DC}$ Drain-to-Case Capacitance	—	12	—		$f = 1.0\text{ MHz}$
					See Fig. 5
					$f = 1.0\text{ MHz}$

## Source-Drain Diode Ratings and Characteristics

Parameter		Min.	Typ.	Max.	Units	Test Conditions
I <sub>S</sub>	Continuous Source Current (Body Diode)	—	—	45*	A	Modified MOSFET symbol showing the integral Reverse p-n junction rectifier.
I <sub>SM</sub>	Pulsed Source Current (Body Diode) ①	—	—	400		
V <sub>SD</sub>	Diode Forward Voltage	—	—	3.0	V	T <sub>J</sub> = 25°C, I <sub>S</sub> = 45A, V <sub>GS</sub> = 0V ④
t <sub>rr</sub>	Reverse Recovery Time	—	—	220	nS	T <sub>J</sub> = 25°C, I <sub>F</sub> = 45A, dI/dt = ≤ 100 A/μs ④
Q <sub>RR</sub>	Reverse Recovery Charge	—	—	1.1	μC	V <sub>DD</sub> ≤ 50V
t <sub>on</sub>	Forward Turn-On Time	Intrinsic turn-on time is negligible. Turn-on speed is substantially controlled by L <sub>S</sub> + L <sub>D</sub> .				

\*I<sub>S</sub> current limited by pin diameter

## Thermal Resistance

Parameter		Min.	Typ.	Max.	Units	Test Conditions
R <sub>thJC</sub>	Junction-to-Case	—	—	0.42		
R <sub>thCS</sub>	Case-to-Sink	—	0.21	—	K/W ⑤	Mounting surface flat, smooth, and greased
R <sub>thJA</sub>	Junction-to-Ambient	—	—	30		Typical socket mount

① Repetitive Rating: Pulse width limited by maximum junction temperature (see figure 9)  
Refer to current HEXFET reliability report

③ I<sub>SD</sub> ≤ 130A, dI/dt ≤ 300 A/μs,  
V<sub>DD</sub> ≤ BV<sub>DSS</sub>, T<sub>J</sub> ≤ 125°C  
Suggested R<sub>G</sub> = 2.35Ω

⑤ K/W = °C/W  
W/K = W/°C

② @ V<sub>DD</sub> = 25V, Starting T<sub>J</sub> = 25°C,  
L ≥ 79 mH, R<sub>G</sub> = 25Ω,  
Peak I<sub>L</sub> = 45A

④ Pulse width ≤ 300 μs; Duty Cycle ≤ 2%

# IRFI064 Device




Fig. 1 — Typical Output Characteristics,  $T_C = 25^\circ\text{C}$




Fig. 2 — Typical Output Characteristics,  $T_C = 150^\circ\text{C}$




Fig. 3 — Typical Transfer Characteristics




Fig. 4 — Normalized On-Resistance Vs. Temperature




Fig. 5 — Typical Capacitance Vs. Drain-to-Source Voltage




Fig. 6 — Typical Gate Charge Vs. Gate-to-Source Voltage




Fig. 7 — Typical Source-Drain Diode Forward Voltage




Fig. 8 — Maximum Safe Operating Area




Fig. 9 — Maximum Effective Transient Thermal Impedance, Junction-to-Case Vs. Pulse Duration




Fig. 10 — Maximum Drain Current Vs. Case Temperature




Fig. 11a — Switching Time Test Circuit




Fig. 11b — Switching Time Waveforms




Fig. 12a — Unclamped Inductive Test Circuit




Fig. 12b — Unclamped Inductive Waveforms






Fig. 12c — Maximum Avalanche Energy Vs. Starting Junction Temperature

Fig. 13 — Peak Diode Recovery  $dv/dt$  Test Circuit




Fig. 14a — Basic Gate Charge Waveform




Fig. 14b — Gate Charge Test Circuit




Fig. 15 — Optional Leadforms for Outline TO-259

**BERYLLOA WARNING PER MIL-S-19500**

Packages containing beryllia shall not be ground, sandblasted, machined, or have other operations performed on them which will produce beryllia or beryllium dust. Furthermore, beryllium oxide packages shall not be placed in acids that will produce fumes containing beryllium.