

**STS7DNF30L****DUAL N - CHANNEL 30V - 0.018Ω - 7A SO-8
STripFET™ POWER MOSFET**

PRELIMINARY DATA

TYPE	V _{DSS}	R _{D(on)}	I _D
STS7DNF30L	30 V	< 0.022 Ω	7 A




- TYPICAL R_{D(on)} = 0.018 Ω
- STANDARD OUTLINE FOR EASY AUTOMATED SURFACE MOUNT ASSEMBLY
- LOW THRESHOLD DRIVE

DESCRIPTION

This Power MOSFET is the second generation of STMicroelectronics unique "Single Feature Size™" strip-based process. The resulting transistor shows extremely high packing density for low on-resistance, rugged avalanche characteristics and less critical alignment steps therefore a remarkable manufacturing reproducibility.

APPLICATIONS

- DC MOTOR DRIVE
- DC-DC CONVERTERS
- BATTERY MANAGEMENT IN NOMADIC EQUIPMENT
- POWER MANAGEMENT IN PORTABLE/DESKTOP PCs

**SO-8****ABSOLUTE MAXIMUM RATINGS**

Symbol	Parameter	Value	Unit
V _{DS}	Drain-source Voltage (V _{GS} = 0)	30	V
V _{DGR}	Drain-gate Voltage (R _{GS} = 20 kΩ)	30	V
V _{GS}	Gate-source Voltage	± 20	V
I _D	Drain Current (continuous) at T _c = 25 °C Single Operation	7	A
	Drain Current (continuous) at T _c = 100 °C Single Operation	4	A
I _{DM(•)}	Drain Current (pulsed)	28	A
P _{tot}	Total Dissipation at T _c = 25 °C Dual Operation Total Dissipation at T _c = 25 °C Single Operation	2 1.6	W W

(•) Pulse width limited by safe operating area

STS7DNF30L

THERMAL DATA

$R_{thj\text{-amb}}$	*Thermal Resistance Junction-ambient Single Operation	78	$^{\circ}\text{C}/\text{W}$
T_j	Junction Temperature	62.5	$^{\circ}\text{C}/\text{W}$
T_{stg}	Maximum Operating Junction Temperature	150	$^{\circ}\text{C}$
	Storage Temperature	-65 to 150	$^{\circ}\text{C}$

(*) Mounted on FR-4 board (Steady State)

ELECTRICAL CHARACTERISTICS ($T_{case} = 25^{\circ}\text{C}$ unless otherwise specified)

OFF

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Unit
$V_{(BR)DSS}$	Drain-source Breakdown Voltage	$I_D = 250 \mu\text{A}$ $V_{GS} = 0$	30			V
I_{DSS}	Zero Gate Voltage Drain Current ($V_{GS} = 0$)	$V_{DS} = \text{Max Rating}$ $V_{DS} = \text{Max Rating}$ $T_c = 125^{\circ}\text{C}$			1 10	μA μA
I_{GSS}	Gate-body Leakage Current ($V_{DS} = 0$)	$V_{GS} = \pm 20 \text{ V}$			± 100	nA

ON (*)

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Unit
$V_{GS(\text{th})}$	Gate Threshold Voltage	$V_{DS} = V_{GS}$ $I_D = 250 \mu\text{A}$	1	1.6	2.5	V
$R_{DS(on)}$	Static Drain-source On Resistance	$V_{GS} = 10 \text{ V}$ $I_D = 3.5 \text{ A}$ $V_{GS} = 4.5 \text{ V}$ $I_D = 3.5 \text{ A}$		0.018 0.021	0.022 0.026	Ω Ω
$I_{D(on)}$	On State Drain Current	$V_{DS} > I_{D(\text{on})} \times R_{DS(\text{on})\text{max}}$ $V_{GS} = 10 \text{ V}$	7			A

DYNAMIC

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Unit
$g_{fs} (*)$	Forward Transconductance	$V_{DS} > I_{D(\text{on})} \times R_{DS(\text{on})\text{max}}$ $I_D = 3.5 \text{ A}$		10		S
C_{iss} C_{oss} C_{rss}	Input Capacitance Output Capacitance Reverse Transfer Capacitance	$V_{DS} = 25 \text{ V}$ $f = 1 \text{ MHz}$ $V_{GS} = 0 \text{ V}$		1050 250 85		pF

ELECTRICAL CHARACTERISTICS (continued)

SWITCHING ON

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Unit
$t_{d(on)}$ t_r	Turn-on Delay Time Rise Time	$V_{DD} = 15 \text{ V}$ $I_D = 3.5 \text{ A}$ $R_G = 4.7 \Omega$ $V_{GS} = 4.5 \text{ V}$ (Resistive Load, see fig. 3)		22 60		ns ns
Q_g Q_{gs} Q_{gd}	Total Gate Charge Gate-Source Charge Gate-Drain Charge	$V_{DD} = 24 \text{ V}$ $I_D = 8 \text{ A}$ $V_{GS} = 5 \text{ V}$		17.5 4 7	23	nC nC nC

SWITCHING OFF

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Unit
$t_{d(off)}$ t_f	Turn-off Delay Time Fall Time	$V_{DD} = 15 \text{ V}$ $I_D = 3.5 \text{ A}$ $R_G = 4.7 \Omega$ $V_{GS} = 4.5 \text{ V}$ (Resistive Load, see fig. 3)		42 10		ns ns
$t_{r(V_{off})}$ t_f t_c	Off-voltage Rise Time Fall Time Cross-over Time	$V_{clamp} = 24 \text{ V}$ $I_D = 7 \text{ A}$ $R_G = 4.7 \Omega$ $V_{GS} = 4.5 \text{ V}$ (Inductive Load, see fig. 5)		11 12 25		ns ns ns

SOURCE DRAIN DIODE

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Unit
I_{SD} $I_{SDM}(\bullet)$	Source-drain Current Source-drain Current (pulsed)				8 32	A A
$V_{SD} (\ast)$	Forward On Voltage	$I_{SD} = 7 \text{ A}$ $V_{GS} = 0$			1.2	V
t_{rr} Q_{rr} I_{RRM}	Reverse Recovery Time Reverse Recovery Charge Reverse Recovery Current	$I_{SD} = 7 \text{ A}$ $di/dt = 100 \text{ A}/\mu\text{s}$ $V_{DD} = 20 \text{ V}$ $T_j = 150 \text{ }^\circ\text{C}$ (see test circuit, fig. 5)		50 40 1.6		ns nC A

(\ast) Pulsed: Pulse duration = 300 μs , duty cycle 1.5 %

(\bullet) Pulse width limited by safe operating area

STS7DNF30L

Fig. 1: Unclamped Inductive Load Test Circuit




Fig. 2: Unclamped Inductive Waveform




Fig. 3: Switching Times Test Circuits For Resistive Load




Fig. 4: Gate Charge test Circuit






Fig. 5: Test Circuit For Inductive Load Switching And Diode Recovery Times



SO-8 MECHANICAL DATA

DIM.	mm			inch		
	MIN.	TYP.	MAX.	MIN.	TYP.	MAX.
A			1.75			0.068
a1	0.1		0.25	0.003		0.009
a2			1.65			0.064
a3	0.65		0.85	0.025		0.033
b	0.35		0.48	0.013		0.018
b1	0.19		0.25	0.007		0.010
C	0.25		0.5	0.010		0.019
c1		45 (typ.)				
D	4.8		5.0	0.188		0.196
E	5.8		6.2	0.228		0.244
e		1.27			0.050	
e3		3.81			0.150	
F	3.8		4.0	0.14		0.157
L	0.4		1.27	0.015		0.050
M			0.6			0.023
S		8 (max.)				



0016023

Information furnished is believed to be accurate and reliable. However, STMicroelectronics assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of STMicroelectronics. Specification mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. STMicroelectronics products are not authorized for use as critical components in life support devices or systems without express written approval of STMicroelectronics.

The ST logo is a trademark of STMicroelectronics

© 1999 STMicroelectronics – Printed in Italy – All Rights Reserved
STMicroelectronics GROUP OF COMPANIES

Australia - Brazil - China - Finland - France - Germany - Hong Kong - India - Italy - Japan - Malaysia - Malta - Morocco -
Singapore - Spain - Sweden - Switzerland - United Kingdom - U.S.A.

<http://www.st.com>