


FAST RECOVERY RECTIFIER DIODES

- VERY LOW REVERSE RECOVERY TIME
- VERY LOW SWITCHING LOSSES
- LOW NOISE TURN-OFF SWITCHING

Cathode connected to case



SOD93
(Plastic)

SUITABLE APPLICATIONS

- FREE WHEELING DIODE IN CONVERTERS AND MOTOR CONTROL CIRCUITS
- RECTIFIER IN S.M.P.S.

ABSOLUTE RATINGS (limiting values)

Symbol	Parameter	Value	Unit
I_{FRM}	Repetitive Peak Forward Current	500	A
I_F (RMS)	RMS Forward Current	50	A
I_F (AV)	Average Forward Current	30	A
I_{FSM}	Surge non Repetitive Forward Current	350	A
P	Power Dissipation	50	W
T_{stg} T_j	Storage and Junction Temperature Range	- 40 to + 150 - 40 to + 150	°C

Symbol	Parameter	Value	Unit
V_{RRM}	Repetitive Peak Reverse Voltage	400	V
V_{RSM}	Non Repetitive Peak Reverse Voltage	440	V

THERMAL RESISTANCE

Symbol	Parameter	Value	Unit
R_{th} (j - c)	Junction-case	1	°C/W

ELECTRICAL CHARACTERISTICS

STATIC CHARACTERISTICS

Symbol	Test Conditions		Min.	Typ.	Max.	Unit
I_R	$T_j = 25^\circ C$	$V_R = V_{RRM}$			35	μA
	$T_j = 100^\circ C$				6	mA
V_F	$T_j = 25^\circ C$	$I_F = 30A$			1.5	V
	$T_j = 100^\circ C$				1.4	

RECOVERY CHARACTERISTICS

Symbol	Test Conditions			Min.	Typ.	Max.	Unit
t_{rr}	$T_j = 25^\circ C$	$I_F = 1A$	$di_F/dt = -15A/\mu s$	$V_R = 30V$		100	ns
		$I_F = 0.5A$	$I_R = 1A$	$I_{rr} = 0.25A$		50	

TURN-OFF SWITCHING CHARACTERISTICS (Without Series Inductance)

Symbol	Test Conditions		Min.	Typ.	Max.	Unit
t_{IRM}	$di_F/dt = -120A/\mu s$	$V_{CC} = 200 V$ $I_F = 30A$ $L_p \leq 0.05\mu H$ $T_j = 100^\circ C$ See figure 11			75	ns
	$di_F/dt = -240A/\mu s$			50		
I_{RM}	$di_F/dt = -120A/\mu s$				9	A
	$di_F/dt = -240A/\mu s$			12		

TURN-OFF OVERVOLTAGE COEFFICIENT (With Series Inductance)

Symbol	Test Conditions			Min.	Typ.	Max.	Unit
$C = \frac{V_{RP}}{V_{CC}}$	$T_j = 100^\circ C$	$V_{CC} = 60V$	$I_F = I_{F(AV)}$		3.3		

To evaluate the conduction losses use the following equations:

$$V_F = 1.1 + 0.0095 I_F \quad P = 1.1 \times I_{F(AV)} + 0.0095 I_F^2 (\text{RMS})$$

Figure 1. Low frequency power losses versus average current




Figure 2. Peak current versus form factor




Figure 3. Non repetitive peak surge current versus overload duration




Figure 4. Thermal impedance versus pulse width




Figure 5. Voltage drop versus forward current




Figure 6. Recovery charge versus di_F/dt




Figure 7. Recovery time versus di_F/dt




Figure 8. Peak reverse current versus di_F/dt




Figure 9. Peak forward voltage versus dI_F/dt .




Figure 10. Dynamic parameters versus junction temperature.




Figure 11. Turn-off switching characteristics (without series inductance).






Figure 12. Turn-off switching characteristics (with series inductance)



PACKAGE MECHANICAL DATA :
 SOD93 Plastic



REF.	DIMENSIONS					
	Millimeters			Inches		
	Min.	Typ.	Max.	Min.	Typ.	Max.
A	4.70		4.90	0.185		0.193
C	1.17		1.37	0.046		0.054
D		2.50			0.098	
D1		1.27			0.050	
E	0.50		0.78	0.020		0.031
F	1.10		1.30	0.043		0.051
F3		1.75			0.069	
G	10.80		11.10	0.425		0.437
H	14.70		15.20	0.578		0.598
L			12.20			0.480
L2			16.20			0.638
L3		18.0			0.709	
L5	3.95		4.15	0.156		0.163
L6		31.00			1.220	
O	4.00		4.10	0.157		0.161

- **Marking:** type number
- Cooling method: by conduction (method C)
- Weight: 3.79g
- Recommended torque value: 80cm. N
- Maximum torque value: 100cm. N

Information furnished is believed to be accurate and reliable. However, STMicroelectronics assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of STMicroelectronics. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied.
STMicroelectronics products are not authorized for use as critical components in life support devices or systems without express written approval of STMicroelectronics.

The ST logo is a registered trademark of STMicroelectronics

© 1999 STMicroelectronics - Printed in Italy - All rights reserved.

STMicroelectronics GROUP OF COMPANIES

Australia - Brazil - China - Finland - France - Germany - Hong Kong - India - Italy - Japan - Malaysia
Malta - Morocco - Singapore - Spain - Sweden - Switzerland - United Kingdom - U.S.A.

<http://www.st.com>