

## FDP6670AL/FDB6670AL N-Channel Logic Level PowerTrench™ MOSFET

## **General Description**


This N-Channel Logic Level MOSFET has been designed specifically to improve the overall efficiency of DC/DC converters using either synchronous or conventional switching PWM controllers.


These MOSFETs feature faster switching and lower gate charge than other MOSFETs with comparable  $R_{\tiny \text{DS(on)}}$  specifications.


The result is a MOSFET that is easy and safer to drive (even at very high frequencies), and DC/DC power supply designs with higher overall efficiency.

## Features

- 80 A, 30 V.  $R_{DS(ON)} = 0.0065~\Omega @ V_{GS} = 10~V, R_{DS(ON)} = 0.0085~\Omega @ V_{GS} = 4.5~V.$
- Critical DC electrical parameters specified at elevated temperature.
- Rugged internal source-drain diode can eliminate the need for an external Zener diode transient suppressor.
- High performance trench technology for extremely low R<sub>DE/CAN</sub>.
- 175°C maximum junction temperature rating.







## **Absolute Maximum Ratings** T<sub>c</sub> = 25°C unless otherwise noted

Symbol	Parameter	FDP6670AL	FDB6670AL	Units
V <sub>DSS</sub>	Drain-Source Voltage	30		V
V <sub>GSS</sub>	Gate-Source Voltage	±20		V
D	Drain Current - Continuous (Note 1)	80		А
	- Pulsed (Note 1)	240		
P <sub>D</sub>	Total Power Dissipation @ T <sub>C</sub> = 25°C	75		W
	Derate above 25°C	0.5		W/°C
$T_J$ , $T_{STG}$	Operating and Storage Temperature Range	-65 to 175		°C
Γ	Maximum lead temperature for soldering purposes, 1/8" from case for 5 seconds	275		°C
THERMA	L CHARACTERISTICS			
R <sub>euc</sub>	Thermal Resistance, Junction-to-Case	2		°C/W
R <sub>øJA</sub>	Thermal Resistance, Junction-to-Ambient	62.5		°C/W

W <sub>DSS</sub> I <sub>AR</sub> OFF CHARA  BV <sub>DSS</sub> \[ \DSS \]  \[ \DSS \]	RCE AVALANCHE RATINGS (Note 1)  Single Pulse Drain-Source Avalanche Energy Maximum Drain-Source Avalanche Current CTERISTICS  Drain-Source Breakdown Voltage Breakdown Voltage Temp. Coefficient Zero Gate Voltage Drain Current Gate - Body Leakage, Forward Gate - Body Leakage, Reverse TERISTICS (Note 2)	$V_{DD} = 15 \text{ V}, I_{D} = 80 \text{ A}$ $V_{GS} = 0 \text{ V}, I_{D} = 250  \mu\text{A}$ $I_{D} = 250  \mu\text{A}, \text{ Referenced to } 25 \text{ °C}$ $V_{DS} = 24 \text{ V}, V_{GS} = 0 \text{ V}$ $V_{GS} = 20 \text{ V}, V_{DS} = 0 \text{ V}$ $V_{GS} = -20 \text{ V}, V_{DS} = 0 \text{ V}$	30	22	300 80	mJ A V mV/°C
I <sub>AR</sub> OFF CHARA  BV <sub>DSS</sub> ΔBV <sub>DSS</sub> /ΔT <sub>J</sub> I <sub>DSS</sub> I <sub>GSSF</sub> I <sub>GSSR</sub>	Maximum Drain-Source Avalanche Current  CTERISTICS  Drain-Source Breakdown Voltage  Breakdown Voltage Temp. Coefficient  Zero Gate Voltage Drain Current  Gate - Body Leakage, Forward  Gate - Body Leakage, Reverse	$V_{GS} = 0 \text{ V}, I_D = 250 \mu\text{A}$ $I_D = 250 \mu\text{A}, \text{ Referenced to } 25 ^{\circ}\text{C}$ $V_{DS} = 24 \text{ V}, V_{GS} = 0 \text{ V}$ $V_{GS} = 20 \text{ V}, V_{DS} = 0 \text{ V}$	30	22	80	A V
OFF CHARA  BV <sub>DSS</sub> $\Delta$ BV <sub>DSS</sub> / $\Delta$ T $I_{DSS}$ $I_{GSSF}$ $I_{GSSR}$	Drain-Source Breakdown Voltage Breakdown Voltage Temp. Coefficient Zero Gate Voltage Drain Current Gate - Body Leakage, Forward Gate - Body Leakage, Reverse	$I_D$ = 250 $\mu$ A, Referenced to 25 °C $V_{DS}$ = 24 V, $V_{GS}$ = 0 V $V_{GS}$ = 20 V, $V_{DS}$ = 0 V	30	22		V
BV <sub>DSS</sub> $\Delta BV_{DSS}/\Delta T_{J}$ $I_{DSS}$ $I_{GSSF}$ $I_{GSSR}$	Drain-Source Breakdown Voltage Breakdown Voltage Temp. Coefficient Zero Gate Voltage Drain Current Gate - Body Leakage, Forward Gate - Body Leakage, Reverse	$I_D$ = 250 $\mu$ A, Referenced to 25 °C $V_{DS}$ = 24 V, $V_{GS}$ = 0 V $V_{GS}$ = 20 V, $V_{DS}$ = 0 V	30	22	1	<u> </u>
ΔBV <sub>DSS</sub> /ΔT <sub>J</sub> I <sub>DSS</sub> I <sub>GSSF</sub>	Breakdown Voltage Temp. Coefficient  Zero Gate Voltage Drain Current  Gate - Body Leakage, Forward  Gate - Body Leakage, Reverse	$I_D$ = 250 $\mu$ A, Referenced to 25 °C $V_{DS}$ = 24 V, $V_{GS}$ = 0 V $V_{GS}$ = 20 V, $V_{DS}$ = 0 V	30	22	1	<u> </u>
ΔBV <sub>DSS</sub> /ΔT <sub>J</sub> I <sub>DSS</sub> I <sub>GSSF</sub> I <sub>GSSR</sub>	Zero Gate Voltage Drain Current Gate - Body Leakage, Forward Gate - Body Leakage, Reverse	$I_D$ = 250 $\mu$ A, Referenced to 25 °C $V_{DS}$ = 24 V, $V_{GS}$ = 0 V $V_{GS}$ = 20 V, $V_{DS}$ = 0 V		22	1	mV/°C
DSS GSSF GSSR	Gate - Body Leakage, Forward Gate - Body Leakage, Reverse	V <sub>GS</sub> = 20 V, V <sub>DS</sub> = 0 V			1	
I <sub>GSSF</sub>	Gate - Body Leakage, Reverse					μΑ
	, ,	$V_{cs} = -20 \text{ V}, V_{ps} = 0 \text{ V}$			100	nA
ON CHARAC	TERISTICS (Note 2)				-100	nA
			ı			
$V_{GS(th)}$	Gate Threshold Voltage	$V_{DS} = V_{GS}, I_{D} = 250 \mu\text{A}$	1	1.5	3	V
	Gate Threshold Voltage Temp.Coefficient	I <sub>D</sub> = 250 μA, Referenced to 25 °C		-5		mV/°C
R <sub>DS(ON)</sub>	Static Drain-Source On-Resistance	$V_{GS} = 10 \text{ V}, I_{D} = 40 \text{ A}$		0.005	0.0065	Ω
		T <sub>J</sub> = 125°C		0.0072	0.0091	1
		$V_{GS} = 4.5 \text{ V}, I_{D} = 37 \text{ A}$		0.0067	0.0085	
I <sub>D(on)</sub>	On-State Drain Current	V <sub>GS</sub> = 10 V, V <sub>DS</sub> = 10 V	80			Α
g <sub>FS</sub>	Forward Transconductance	$V_{DS} = 10 \text{ V}, I_{D} = 40 \text{ A}$		86		S
DYNAMIC CH	HARACTERISTICS					
C <sub>iss</sub>	Input Capacitance	$V_{DS} = 15 \text{ V}, V_{GS} = 0 \text{ V},$ f = 1.0  MHz		3200		pF
C <sub>oss</sub>	Output Capacitance			820		pF
	Reverse Transfer Capacitance			400		pF
SWITCHING	CHARACTERISTICS (Note 1)		•			
t <sub>D(on)</sub>	Turn - On Delay Time	$V_{DD} = 10 \text{ V}, \ I_{D} = 1 \text{ A},$ $V_{GS} = 10 \text{ V}, \ R_{GEN} = 6 \Omega$		15	27	nS
t,	Turn - On Rise Time			15	27	nS
$\mathbf{t}_{D(off)}$	Turn - Off Delay Time			85	105	nS
t,	Turn - Off Fall Time			42	68	nS
$Q_g$	Total Gate Charge	$V_{DS} = 15 \text{ V}$ $I_D = 40 \text{ A}, V_{GS} = 5 \text{ V}$		35	50	nC
$Q_{gs}$	Gate-Source Charge			9		nC
$Q_{gd}$	Gate-Drain Charge			16		nC
	RCE DIODE CHARACTERISTICS		1	1	1	
l <sub>s</sub>	Maximum Continuous Drain-Source Diode Forward Current (Note 1)				80	Α
I <sub>SM</sub>	Maximum Pulsed Drain-Source Diode Forward (				240	Α
V <sub>SD</sub>	Drain-Source Diode Forward Voltage	$V_{GS} = 0 \text{ V}, I_{S} = 40 \text{ A} \text{ (Note1)}$		0.9	1.3	V
t <sub>rr</sub>	Reverse Recovery Time Reverse Recovery Current	$V_{GS} = 0 \text{ V}, I_F = 40 \text{ A}$ $dI_F/dt = 100 \text{ A/}\mu\text{s}$		32	55	ns

<sup>1.</sup> Pulse Test: Pulse Width  $\leq$  300 µs, Duty Cycle  $\leq$  2.0%.