
# (COTS) COMMERCIAL OFF-THE-SHELF SCHOTTKY CENTER-TAP RECTIFIER IN A T0-258 PACKAGE



40 Amp, 45 To 100 Volt Schottky Rectifier

#### FEATURES

- · Very Low Forward Voltage
- Fast Switching Speed
- Hermetic Metal Package, TO-258 Outline
- Standard Off-The-Shelf
- Isolated Package
- Available Screened To MIL-S-19500, TX, TXV And S Levels

#### DESCRIPTION


This product is specifically designed for use at power switching frequencies in excess of 100 kHz. The product combines two Schottky-barrier diodes in a center-tap configuration in a single package, simplifying installation, reducing heat sink hardware, and the need to obtain matched components. The device is ideally suited for Hi-Rel applications where small size and hermetically sealed package is required.


### ABSOLUTE MAXIMUM RATINGS (T<sub>C</sub> = 25° C) Per Diode

Peak Inverse Voltage
Maximum Average DC Output Current, Per Leg
Non-Repetitive Peak Surge Current (8.3 mS)
Peak Reverse Transient Current
Storage Temperature Range 55° C to + 175° C
Junction Operating Temperature Range 55° C to + 150° C
Package Thermal Resistance, Junction-to-Case

SCHEMATIC

#### PIN CONNECTION





Common cathode is standard. Glass Feedthroughs are standard.

**⊙**Omnirel

32


8 09 R0 3.2 - 1

#### ELECTRICAL CHARACTERISTICS (Per Diode)


Part No.	PIV	Maximum Forward Voltage @ $I_F = 20A^{(1)}$		Maximum Reverse Current	
		T <sub>C</sub> = 25°C	T <sub>C</sub> = 125°C	T <sub>C</sub> = 25°C	T <sub>C</sub> = 125°C
COM4213C	45	.72 V	.64 V		
COM4219C	60	.85 V	.75 V	2 m A	40mA
COM4220C	100	.90 V	.82 V		

<sup>(1)</sup> Pulse Test: Pulse Width 300 µs, Duty Cycle 2.0%.

TYPICAL FORWARD VOLTAGE




TYPICAL FORWARD VOLTAGE




 $\mathbf{V}_{\mathrm{F}} \text{ - INSTANTANEOUS VOLTAGE (VOLTS)}$ 

TYPICAL FORWARD VOLTAGE



# TYPICAL REVERSE CURRENT



## MECHANICAL OUTLINE

