

# High Performance Triple Universal Filter Building Block

#### **FEATURES**

- Up to 6th Order Filter Functions with a Single 20 Pin Surface Mount Package
- Center Frequency Range up to 35kHz
- fo×Q Product Up to 1 MHz
- Guaranteed Center Frequency and Q Accuracy Over Temperature
- Guaranteed Low Offset Voltages Over Temperature
- 90dB Dynamic Range
- Filter Operates From Single 4.7V Supply and Up to ±8V Supplies
- Low Power
- Clock Inputs T<sup>2</sup>L and CMOS Compatible

#### **APPLICATIONS**

- High Order, Wide Frequency Range Bandpass, Lowpass, Notch Filters
- Low Power Consumption, Single 5V Supply Clock Tunable Filters
- Tracking Filters

#### DESCRIPTION

The LTC1061 consists of three high performance, universal filter building blocks. Each filter building block together with an external clock and 2 to 5 resistors can produce various second order functions which are available at its three output pins. Two out of three always provide lowpass and bandpass functions while the third output pin can produce highpass or notch or allpass. The center frequency of these functions can be tuned from 0.1Hz to 35kHz and is dependent on an external clock or an external clock and a resistor ratio.

The LTC1061 can be used with single or dual supplies ranging from  $\pm 2.37V$  to  $\pm 8V$  (or 4.74V to 16V). When the filter operates with supplies of  $\pm 5V$  and above, it can handle input frequencies up to 100kHz.


The LTC1061 is compatible with the LTC1059 single universal filter and the LTC1060 dual. Higher than 6th order functions can be obtained by cascading the LTC1061 with the LTC1059 or LTC1060. Any classical filter realization (such as Butterworth, Cauer, Bessel and Chebyshev) can be obtained by the appropriate choice of the external resistors.

The LTC1061 is manufactured by using Linear Technology's enhanced LTCMOS™ silicon gate process.


LTCMOSTM is a trademark of Linear Technology Corp.

## TYPICAL APPLICATION

#### 6th Order, Clock Tunable, 0.5dB Ripple Chebyshev BP Filter




#### **Amplitude Response**



# **ABSOLUTE MAXIMUM RATINGS**

Supply Voltage	18V
Operating Temperature Range	$-40^{\circ}C \le T_{A} \le 85^{\circ}C$
Storage Temperature Range	65°C to 150°C
Lead Temperature (Soldering, 10sec)	

# PACKAGE/ORDER INFORMATION



# **ELECTRICAL CHARACTERISTICS**

(Complete Filter)  $V_S = \pm 5V$ ,  $T_A = 25$ °C,  $T^2L$  clock input level, unless otherwise specified

PARAMETER	CONDITIONS		MIN	TYP	MAX	UNITS
Center Frequency Range, fo	$\begin{array}{l} f_0 \times Q \leq 175 \text{kHz, Mode 1, V}_S = \pm 7.5 \text{V} \\ f_0 \times Q \leq 1.6 \text{MHz, Mode 1, V}_S = \pm 7.5 \text{V} \\ f_0 \times Q \leq 75 \text{kHz, Mode 3, V}_S = \pm 7.5 \text{V} \\ f_0 \times Q \leq 1 \text{MHz, Mode 3, V}_S = \pm 7.5 \text{V} \\ \text{(Note 1)} \end{array}$			0.1-35k 0.1-25k 0.1-25k 0.1-17k		Hz Hz Hz Hz
Input Frequency Range				0-200k		Hz
Clock to Center Frequency Ratio, f <sub>CLK</sub> /f <sub>o</sub> (Note 1)	Sides A, B: Mode 1, R1 = R3 = $50$ k $\Omega$ R2 = $5$ k $\Omega$ , Q = 10, f <sub>CLK</sub> = $250$ kHz Pin 7 High. Side C: Mode 3, R1 = R3 = $50$ k R2 = R4 = $5$ k, f <sub>CLK</sub> = $250$ kHz Same as Above but Pin 7 at Mid-Supplies, f <sub>CLK</sub> = $500$ kHz	•			50 ± 1.2%	
Clock to Center Frequency Ratio, Side to Side Matching		•			1.2%	
Q Accuracy (Note 1)	Sides A, B, Mode 1 50:1 or 100:1 Side C, Mode 3 f <sub>0</sub> = 5kHz, Q = 10	•		±3	5	%
f <sub>o</sub> Temperature Coefficient Q Temperature Coefficient	Mode 1, 50:1, f <sub>CLK</sub> < 300kHz Mode 1, 100:1, f <sub>CLK</sub> < 500kHz Mode 3, f <sub>CLK</sub> < 500kHz			±1 ±5 ±5		ppm/°C ppm/°C ppm/°C

### **ELECTRICAL CHARACTERISTICS**

(Complete Filter)  $V_S = \pm 5V$ ,  $T_A = 25$ °C,  $T^2L$  clock input level, unless otherwise specified

PARAMETER	CONDITIONS		MIN	TYP	MAX	UNITS
DC Offset Voltage (Note 2) Vos1 Vos2 Vos2	f <sub>CLK</sub> = 250kHz, 50:1 f <sub>CLK</sub> = 500kHz, 100:1	•		2 3 6	15 25 50	mV mV mV
V <sub>OS3</sub> V <sub>OS3</sub>	$f_{CLK} = 250 \text{kHz}, 50:1$ $f_{CLK} = 500 \text{kHz}, 100:1$			3 6	25 50	mV mV
Clock Feedthrough Max. Clock Frequency Power Supply Current	f <sub>CLK</sub> <1MHz Mode 1, Q<5, V <sub>S</sub> ≥ ±5V		6	0.4 2.5	12	mV <sub>RMS</sub> MHz mA
		•	U	•	16	mA

# **ELECTRICAL CHARACTERISTICS** (Complete Filter) $V_S = \pm 2.37V$ , $T_A = 25^{\circ}C$ unless otherwise specified

PARAMETER	CONDITIONS	MIN	TYP	MAX	UNITS
Center Frequency Range, fo	f <sub>o</sub> × Q ≤ 120kHz, Mode 1, 50:1 f <sub>o</sub> × Q ≤ 120kHz, Mode 3, 50:1			Hz Hz	
Input Frequency Range			0-20k		Hz
Clock to Center Frequency Ratio	50:1, f <sub>CLK</sub> = 250kHz, Q = 10 Sides A, B: Mode 1 Side C: Mode 3 100: 1, f <sub>CLK</sub> = 500kHz, Q = 10 Sides A, B: Mode 1 Side C: Mode 3		50±1% 100±1%		
Q Accuracy	Same as Above, 100:1 or 50:1		±3		%
Max. Clock Frequency Power Supply Current			700k 4.5	6	Hz mA

# **ELECTRICAL CHARACTERISTICS** (Internal Op Amps) T<sub>A</sub> = 25°C unless otherwise specified

PARAMETER	CONDITIONS		MiN	TYP	MAX	UNITS
Supply Voltage Range			± 2.37		±9	٧
Voltage Swings	V <sub>S</sub> = ±5V, R <sub>L</sub> = 5k (Pins 1, 2, 13, 14, 19, 20) R <sub>L</sub> = 3.5k (Pins 3, 12, 18)	•	±3.8 ±3.6	± 4.2		V
Output Short Circuit Current Source/Sink	V <sub>S</sub> = ±5V			40/3		mA
DC Open Loop Gain	$V_S = \pm 5V, R_L = 5k$			80		dB
GBW Product	V <sub>S</sub> = ±5V			3		MHz
Slew Rate	V <sub>S</sub> = ±5V			7		V/μs

The • denotes the specifications which apply over the full operating temperature range.

**Note 1:** An LTC1061S with improved Q and clock to center frequency ratio accuracy can be made available upon special request.

**Note 2:** For definition of the DC offset voltages refer to the LTC1061 data sheet. An LTC1061S with improved DC offset specifications can be made available upon special request.

