Infrared light emitting diode, top view type SIR-320ST3F

The SIR-320ST3F is a GaAs infrared light emitting diode housed in clear plastic. This device has a high luminous efficiency and a 940 nm spectrum suitable for silicon detectors. It is small and at the same time has a wide radiation angle, making it ideal for compact optical control equipment.


Applications

Optical control equipment
Light source for remote control devices

Features

- 1) Compact (φ3.1 mm).
- High efficiency, high output Po = 9.0 mW (I_F = 50 mA).
- 3) Wide radiation angle $\theta = \pm 18^{\circ}$.
- 4) Emission spectrum well suited to silicon detectors $(\lambda_P = 940 \text{ nm}).$
- 5) Good current-optical output linearity.
- 6) Long life, high reliability.
- 7) Low cost, clear epoxy resin package.

External dimensions (Units: mm)



■Absolute maximum ratings (Ta = 25°C)

Parameter	Symbol	Limits	Unit
Forward current	lF	75	mA
Reverse voltage	VR	5	V
Power dissipation	P□	100	mW
Pulse forward current	I FP*	1.0	А
Operating temperature	Topr	-25~ + 85	င
Storage temperature	Tstg	-40~ + 85	°C


^{*} Pulse width = 0.1 msec, duty ratio 1%

Sensors SIR-320ST3F

●Electrical and optical characteristics (Ta = 25°C)

Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
Optical output	Po	_	9.0	_	mW	I==50mA
Emitting strength	lE	5.6	_	_	mW/sr	I==50mA
Forward voltage	VF	_	1.2	1.5	٧	I==50mA
Reverse current	lR	_	_	10	μΑ	V _R =3V
Peak light emitting wavelength	λp	_	940	_	nm	I==50mA
Spectral line half width	Δλ	_	40	_	nm	I==50mA
Half-viewing angle	0 1/2	_	±18	_	deg	I==50mA
Response time	tr • tf	_	1.0	_	μs	I=50mA
Cut-off frequency	fc	_	1.0	_	MHz	I==50mA

Electrical and optical characteristic curves



Flg. 1 Forward current falloff




Fig. 2 Forward current vs. forward voltage




Fig. 3 Wavelength




Fig. 4 Emitting strength vs. forward current




Fig. 5 Radiant intensity vs. ambient temperature

Sensors SIR-320ST3F

Directional pattern




Fig. 6 Directional pattern




Fig. 7 Directional pattern