ISO9001: 2015		ISO14001: 2015
---------------	--	----------------

Title. TACT SWITCH

Product Model. KAN0611-0501B

Customer's Part NO.

Customer's Model:

Customer's Approval Requested.

Please return this copy as a certification of your approval.

Checked by: Date:

Approved by: Date:

APPROVE	REVIEW	PREPARE
黄自兵	李生勇	林庆杰

WENZHOU GANGYUAN ELECTRONICS CO., LTD.



CUSTOMER	CUSTOMER'S P/N	GYE'S P/N	PRODUCT	REVISION
		KAN0611-0501B	TACT SWITCH	A

1、 概述

GENERAL

1.2 适用范围

APPLICATION

此规格书适用于机械式轻触开关的相关要求

This specification is applied to the requirements for TACTILE SWITCH (MECHANICAL CONTACT)

1.3 工作温度范围

Operating Temperature Range

-40℃~85℃(在标准大气压、标准湿度条件下)

-40°C∼85°C (Normal humidity, normal air pressure)

1.4 贮藏温度范围

Storage Temperature Range

-40℃~90℃(在标准大气压、标准湿度条件下)

-40°C ~90°C (Normal humidity, normal air pressure)

1.5 测试条件

Test Conditions

在没有其它特定的条件下,应该在以下的条件下进行测试和测量:

Unless otherwise specified, tests and measurement shall be made in the following standard conditions:

常温......5℃~35℃

Normal temperature...... 5° C \sim 35 $^{\circ}$ C

标准湿度......相对湿度 25%~85%

Normal humidity....relative humidity 25%~85%

标准大气压......86Kpa~106Kpa

Normal air pressure......86Kpa~106Kpa

在制造过程中,测试和测量应该在以下的条件下进行:

If any doubt arise from the judgment, tests shall be conducted at the following conditions:

温度......20℃±2℃

Temperature $....20^{\circ}\text{C} \pm 2^{\circ}\text{C}$

相对湿度......65%±5%

Relative humidity......65%±5%

环境气压......86Kpa~106Kpa

Air pressure......86Kpa~106Kpa

APPROVE BY 黄自兵 17.10.10 CHECKED BY	李生勇 17.10.10	PRPARE BY	林庆杰 17.10.10
------------------------------------	--------------	-----------	--------------



CUSTOMER	CUSTOMER'S P/N	GYE'S P/N	PRODUCT	REVISION
		KAN0611-0501B	TACT SWITCH	A

2、 详细说明

Detailed specification

2.1 外观:应无影响、降低产品性能的缺陷;

Appearance: There should be no defects that affect the serviceability of product.

2.2 结构尺寸和安装尺寸:应符合装配图要求;

Style and dimension: shall conform to the assemble drawings.

2.3 操作形式: 有触觉反应的操作

Type of actuating: Tactile feedback.

2.4 开关结构: 单回路单输出(具体的触点结构在装配图中已绘出);

Contact arrangement: 1 pole, 1 throw

(Details of contact arrangement are given in the assembly drawings.)

2.5 开关工作额定值: DC 12V, 50mA (最大值) DC 1V, 10μA (最小值)

Ratings: DC 12V, 50mA (Max) DC 1V, 10µA (Min)

3. 电气性能:

ELECTRICAL SPECIFICATION

项目		Ť	要求						
ITEM		TI	EST CONDITIONS		REQUIREMENTS				
1 Cor	接触电阻 ntact Resistance	在以 5V 10mA的源的电路中,以一个等心 Applying a static locenter of the stem, mea 10mA or more than 1KH	≤100mΩ						
2 Insul	绝缘电阻 lation Resistance	在端子之间施加 D 间底座、盖板的电阻值 Measurement shall 500V DC potential, acros cover, for one minute.	≥100MΩ						
3 I		在端子之间施加 25 250V AC (50Hz or 60H for one minute.	无击穿、无飞弧 There should be no breakdown and flashover						
APPROVE BY	黄自兵 17.10.10								



CUSTOMER CUSTOMER'S PN GYES PN PRODUCT REVISION KAN0611-0501B TACT SWITCH A 项目 可EM TEST CONDITIONS REQUIREMENTS			INGIUAN	7 11 1 1	O VI IL			J1 1D	
项目 ITEM ITEM ITEM ITEM ITEM ITEM ITEST CONDITIONS REQUIREMENTS 核照正常使用时的力度轻按手柄中心(每秒3~4次), 在导通和断开过程中测试开关料动 Lightly striking the center of the stem at a rate encountered in normal use (3 to 4 times per second), and bounce shall be tested at "ON" and "OFF" ### ON" ### OFF ON-3ms max OFF-8ms max ON-3ms max OFF-8ms max ON-3ms max OFF-8ms max INECHANICAL SPECIFICATION #### #### ##########################	C	CUSTOMER	CUSTOMER'	S P/N GYE	'S P/N	PRODUCT	DDUCT REVISION		
TITEM TEST CONDITIONS REQUIREMENTS 核照正常使用时的力度轻按手辆中心(每秒 3~4 次), 在导通和断开过程中测试开关抖动 Lightly striking the center of the stem at a rate encountered in normal use 3 to 4 times per second), and bounce shall be tested at "ON" and "OFF" ### OScillograph ON-3ms max OFF-8ms max ON-3ms max OFF-8ms max 1 Operating Force ###################################				KAN06	11-0501B	TACT SWITC	Н А		
接底抖动 Bounce 4. 机械性能: MECHANICAL SPECIFICATION T		项目			·····································	L		要求	
接底抖动 Bounce 4. 机械性能: MECHANICAL SPECIFICATION T							R		
MECHANICAL SPECIFICATION开关垂直于操作方向放置,在开关驱动件顶端中心逐渐施力,测量开关导通所需的最大力度。 Placing the switch such that the direction of switch operation is vertical and then gradually increasing the load applied to the center of the stem, the maximum load required for the switch to come to a stop shall be measured.1.6±0.5N2最大行程 Full Travel开关垂直于操作方向放置,以一个等于 2 倍按力的静负荷施加在开关驱动件顶端中心,测量顶端移动的距离。 Placing the switch such that the direction of switch operation is vertical and then applying static load of 2 times operating force to the center of the stem; the travel distance for the switch to come to a stop shall be measured.0.25±0.1mm	4		在导通和断开注 Lightly striking use (3 to 4 time "OFF"	the center of the stens per second), and bo 开关 Switch 10KΩ	1				
B开关导通所需的最大力度。			CCIFICATION						
五十二十二十二十二十二十二十二十二十二十二十二十二十二十二十二十二十二十二十二	1	Operating	量开关导通所需 Placing the sw vertical and the the stem, the ma	量开关导通所需的最大力度。 Placing the switch such that the direction of switch operation is vertical and then gradually increasing the load applied to the center of the stem, the maximum load required for the switch to come to a stop					
APPROVE BY 黄自兵 17.10.10 CHECKED BY 李生勇 17.10.10 PRPARE BY 林庆杰 17.10.10	2	最大行程 Full Travel 开关驱动件顶端中心,测量顶端移动的距离。 Placing the switch such that the direction of switch operation is vertical and then applying static load of 2times operating force to the center of the stem; the travel distance for the switch to come to a stop						0.25±0.1mm	
	APP	PROVE BY	黄自兵 17.10.10	CHECKED BY	李生勇 17	.10.10 PRPAF	RE BY	林庆杰 17.10.10	



	UII.	NGIUAN	ALL NO VAL SI ECH ICA				ATIONS		
C	USTOMER	CUSTOMER'S	S P/N GYE	'S P/N	P	RODUCT		REVISION	
			KAN06	11-0501B	TAC	CT SWITCH	H	A	
	项目		试 验 翁	: 件			I	要求	
	ITEM		TEST COND	OITIONS			RE	QUIREMENTS	
3	回弹力 Return Force	后,测量顶端向 The sample swi operation is verti	方向放置,在开关 自由位置转换的力, tch is installed suc cal and upon depres ance, the force of the l.	of switch		0.4N.MIN			
4	停止强度 Stop Strengt	荷持续 1min。 Placing the swit vertical, and then	方向放置,从操作 ch such that the d a static load of 30N for a period of 1 mi	peration is	There	几械和电气损坏 shall be no sign of e mechanically and electrically.			
5	手柄拔出 强度 Stem Strength	的行程范围。 Placing the swit vertical, and the	方向放置,反方向 ch such that the d n the maximum fo rection of stem opera	peration is		20N.min.			
在以下设定条件下进行测量: Measurements shall be made following the test set forth below: (1) 焊接温度:245±5℃ Solder temperature: 245±5℃ (2) 浸入时间:2s±0.5s Immersion time: 2s±0.5s 对于其它步骤参考《GB 5096.6-1986》试验 12a The other steps please refer to《GB 5096.6-1986》TEST 12a						90%以上	for the edge, the should cover a		
APP	ROVE BY	黄自兵 17.10.10	CHECKED BY	李生勇 17	.10.10	PRPAR	E BY	林庆杰 17.10.10	



	- 311	1101	UAII		11111	O 11 11				110
C	USTOMER		CUSTOMER	'S P/N	GYE'	S P/N	PR	ODUCT		REVISION
					KAN061	1-0501B	TAC	T SWITCH		A
	项目				试 验	条 件	1			要求
	ITEM TEST CONDITIONS								RE	QUIREMENTS
	5、极限电气性能: ENVIRONMENTAL SPECIFICATION									
1	低温测试 Resistance t temperature	o low	标准湿度的 Following themperature are made: (1) 温质 Tem (2) 时间	(1) 温度: -30±2℃ Temperature: -30±2℃						阻: ≤200mΩ resistance: ≤200mΩ 4.1,4.2,4.3 4.1,4.2,4.3
2	高温测试 Heat resistan	ice	标准湿度的 forth below humidity co (1) 温质 tem (2) 时间	humidity conditions for 1 h before measurements are made: (1) 温度: 80±2℃ temperature:80±2℃						语: ≤200mΩ resistance: ≤200mΩ 4.1,4.2,4.3 4.1,4.2,4.3
3	根据下面的测试要求进行 5 次循环的温度周期性测试,实验后样品应放在常温及标准湿度的环境中 1 小时后做性能测试。测试期间样品应保持干燥. After 5 cycles of following conditions, the sample shall be allowed to stand under normal temperature and humidity conditions for 1 h. and measurements shall be made. During the test water drops shall be removed.							resistance: ≤200mΩ 4.1,4.2,4.3		
APP	APPROVE BY 黄自兵 17.10.10			СНЕ	ECKED BY	李生勇 1	7.10.10	PRPARE	E BY	林庆杰 17.10.10



C	CUSTOMER	CUSTOMER'	S P/N GYE	'S P/N	PRODUCT		REVISION
	KAN0611-0501B TACT SWITC						A
	项目		试 验	条 件			要求
	ITEM		TEST CON	DITIONS		RE	EQUIREMENTS
4	湿温测记 Moisturd resistanc	标准湿度的 forth below humidity con (1) 温度 tempe (2) 相对 relati (3) 时间	以下实验条件进行测环境中 1 小时后做性 the sample shall be ditions for 1 h before : 60±2℃ erature: 60±2℃ :湿度: 90%~95% we humidity:90% to 95 !: 96h : 96h	Contact 项目 3,	阻: ≤200mΩ resistance: ≤200mΩ 4.1,4.2,4.3 4.1,4.2,4.3		
5	硫化试验 Sulfuratio resistanc	标准湿度的 forth below humidity con (1) H2S H ₂ S g (2) 时间 Time (3) 温度	以下实验条件进行测环境中 1 小时后做性 the sample shall be ditions for 1 h before 气体浓度: 3ppm±1p gas concentration: 3p 1: 72h 40±2°C(90~95% erature: 40±2°C(90~	ollowing the test set al temperature and	Contact 项目 3,	阻: ≤200mΩ resistance: ≤200mΩ 4.1,4.2,4.3 4.1,4.2,4.3	
6	盐雾试验 Salt Mis	The switch (1)温度: tempe (2)盐溶液 salt so (3)时间: Time: 实验后的盐;	rature: 35℃±2℃ 克浓度: 5±1%(质量 blution: 5±1%(solids l 8h±1h	No re	上没有腐蚀斑点 markable corrosion e recognized in metal		
APP	ROVE BY	黄自兵 17.10.10	CHECKED BY	李生勇 17	10.10 PRPARI	Е ВҮ	林庆杰 17.10.10



	GA	NGYU	JAIN	AHIM	JVAL			1110	
C	CUSTOMER	Cl	USTOMER'S	P/N GYE'	S P/N	P	RODUCT		REVISION
				KAN061	1-0501B	TAC	CT SWITCH		A
	限机械性能: CNDURANCE	SPECIF	ICATION					<u> </u>	
	项目			试 验	条 件				要求
	ITEM			TEST CON	DITIONS			RE	QUIREMENTS
1	工作寿章 Operation	1 कि	Measurement s (1) DC 12V DC 12V (2) 按动速 Rate o (3) 按力: Operati (4) 平均尹	试要求进行测试: shall be made follow V, 50mA 带负载 V, 50 mA resistive lo 率: 1次/秒 of operation: 1 times/ 按力的 1.5 倍 ing Force: 1.5 times 无故障寿命: 80,000 ge fault-free life: 80	ad s s as much as C) 次			触点弹法 Contac 按力: Operatir initial va 项目 3,4	阻≤1Ω resistance≤1Ω 力≤10ms t bounce≤10ms in 初值的±30% ing Force: alue±30% i.1,4.2,4.3 i.1,4.2,4.3
2	振动 Vibra	1	根据以下给定条件进行测试: Measurement shall be made following the test set forth below: (1) 振动频率范围: 10~55~10Hz Vibration frequency range: 10 to 55 to 10Hz (2) 振幅(峰一峰): 1.5mm Amplitude: 1.5mm (3) 振动方向:包括手柄行程方向在内的三个相互垂直的方向 Direction of vibration:Three mutually perpendicular direction including the direction of stem travel (4) 测试时间:每次 2 小时 Duration: Each 2 hours.						1.1,4.2,4.3 .1,4.2,4.3
	 接条件:								
SOLD	ERING CON	DITION	<u>S:</u>						
			请按以下条件进行焊接:						
	工 工 归 拉		,	焊锡温度: ≤350℃	·温度: ≤350℃				
7.1	手工焊接 Hand solde	ring	(2) 连续焊接时间: ≤3 s						
			Pleas	se practice according	to below con	ditions:			
			` '	oldering temperature Continuous soldering					
APP	ROVE BY	黄自兵	17.10.10	CHECKED BY	李生勇 17.	.10.10	PRPARE	E BY	林庆杰 17.10.10



C	USTOMER	CUSTOMER'S P/N	GY	E'S P/N	PRODUCT	REVISION	
			KAN	0611-0501B	TACT SWITCH	A	
		项目 Items			条件 Condition		
		助焊剂附着量 Flux built-up		不附着于零部件贴装面的程度 Mounting surface should not be coated with flux			
	自动浸焊	预热温度 Preheating temperate	预热温度 Preheating temperature		印刷电路板焊接面的周围温度 100℃ max. Ambient temperature of the soldered surface of PC board. 100℃ max.		
7.2	Conditions for	预热温度时间 Preheating time			60s max.		
	Auto-dip	焊接温度 Soldering tempe	erature	260℃ max.			
		焊接浸渍时间 Continuous dipping time			5s max.		
		焊接次数	焊接次数		最多两次		
		Number of solde	Number of soldering		2 times max.		

焊接说明:

1、开关浸焊后,注意不要用溶剂清洗。

After switches were soldered, please be careful not to clean switches with solvent.

1.1 在使用烙铁的情况下,焊锡温度应在350℃以下、3秒以内。

In the case of using soldering iron, soldering conditions shall be 350°C max and 3 sec.max.

1.2 浸焊后,注意不要在顶部施加负荷。

Right after switches were soldered; please be careful not to load to on the knobs of switches.

- 2、设计中应注意的事项(Design instructions)
- 2.1 印刷基板的安装孔尺寸参见产品图。

Follow recommended P.W.B. piercing plan in outside drawing page.

- 3、注意点(Note):
- 3.1 注意不要施加超负荷的压力或晃动开关。

Please be cautions not to give excessive static load or shock to switches.

3.2 开关浸焊后,印刷基板注意不要叠放。

Please be careful not to pile up P.W.B. after switches were soldered.


3.3 保管时尤其应注意避开高湿高温和有腐蚀性气体的环境。如需要长时间保存,请不要 打开包装箱。


Preservation under high temperature and high high humidity or corrosive gas should be avoided Especially . When you need to preserve for a long period ,do not open the carton.


APPROVE BY	黄自兵 17.10.10	CHECKED BY	李生勇 17.10.10	PRPARE BY	林庆杰 17.10.10
------------	--------------	------------	--------------	-----------	--------------




CUSTOMER	CUSTOMER'S P/N	GYE'S P/N	PRODUCT	REVISION
		KAN0611-0501B	TACT SWITCH	A











General tolerance: ± 0.2 mm $H=5.0\pm 0.2$ mm

NO.	NAME	MATERIAL	QTY.	FINISHING
1	TERMINAL	Brass	1	Silver plating
2	CASE	PA66	1	Black
3	CONTACT	Phosphor bronze	1	Contact side silver plating
4	COVER	SPCC	1	Cu Sn plating
5	STEM	PA66	1	Black

APPROVE BY	黄自兵 17.10.10	CHECKED BY	李生勇 17.10.10	PRPARE BY	林庆杰 17.10.10
------------	--------------	------------	--------------	-----------	--------------