ISO9001: 2000 ISO14001: 2004

APPROVAL SPECIFICATIONS

Title. TACT SWITCH

Product Model. KAN0649

Customer's Part NO.

Customer's Model:

Customer's Approval Requested.

Please return this copy as a certification of your approval.

Checked by: Date:

Approved by: Date:

APPROVE	REVIEW	POLT
黄蜀东	关 林	曹盖

WENZHOU GANGYUAN ELECTRONICS CO., LTD.



CUSTOMER	CUSTOMER'S P/N	GYE'S P/N	PRODUCT	REVISION
		KAN0649	TACT SWITCH	Α

A. Specification & meanings

The name of the tact switch is composed by type and specification, the particular meaning of the type, specification and code is as follows.

KAN0649- □□□		
$\overline{}$	T L	Press force (refer to chart 3) Stem color (refer to chart 2)
		Product height (refer to chart 1)

1. Product height: It is denoted by three figures; For examples, "050" expresses the product which the total height is 5mm, as chart 1 shows:

Code	Product height	Code	Product height	Code	Product height
043	4.3	085	8.5		
050	5	090	9		
060	6	095	9.5		
070	7				
073	7.3 (Joint stem)				
075	7.5				
080	8				

2. Stem color: It is expressed by a figure, as chart 2 shows:

Color	Black
Code	1

3. Operating force: An English letter expresses it, unite: Newton (N),as chart 3 shows:

Operating force Code Spec		Press force	Return force	
Α	1.0	1.0±0.3	0.2min	
В	1.6	1.6±0.5	0.4min	
С	2.6	2.6±0.5	0.6min	

Examples: "KAN0649-0501B" denotes the tact switch with 6×6 base, the height is 5mm,the stem is black, the operating force is 1.6N.

APPROVE BY	黄蜀东 10.10.25	CHECKED BY	关 林 10.10.25	PRPARE BY	曹 盖 10.10.25
------------	--------------	------------	--------------	-----------	--------------



CUSTOMER	CUSTOMER'S P/N	GYE'S P/N	PRODUCT	REVISION
		KAN0649	TACT SWITCH	А

1、 概述

GENERAL

1.2 适用范围

APPLICATION

此规格书适用于机械式轻触开关的相关要求

This specification is applied to the requirements for TACTILE SWITCH (MECHANICAL CONTACT)

1.3 工作温度范围

Operating Temperature Range

- -20℃~70℃(在标准大气压、标准湿度条件下)
- -20°C ~70°C (Normal humidity, normal air pressure)
- 1.4 贮藏温度范围

Storage Temperature Range

- -30℃~80℃(在标准大气压、标准湿度条件下)
- -30° C \sim 80°C (Normal humidity, normal air pressure)
- 1.5 测试条件

Test Conditions

在没有其它特定的条件下,应该在以下的条件下进行测试和测量:

Unless otherwise specified, tests and measurement shall be made in the following standard conditions:

常温......5℃~35℃

Normal temperature......5°C ~35°C

标准湿度......相对湿度 25%~85%

Normal humidity.....relative humidity 25%~85%

标准大气压......86KPa~106Kpa

Normal air pressure......86Kpa~106Kpa

在制造过程中,测试和测量应该在以下的条件下进行:

If any doubt arise from the judgment, tests shall be conducted at the following conditions:

温度......**20**℃**±2**℃

Temperature.......20℃±2℃ 相对湿度......65%±5%

相对碰及……………………65%±5% Relative humidity…………65%±5%

环境气压......86KPa~106Kpa

Air pressure.......86KPa~106Kpa

APPROVE BY	黄蜀东 10.10.25	CHECKED BY	关 林 10.10.25	PRPARE BY	曹 盖 10.10.25
------------	--------------	------------	--------------	-----------	--------------



CUSTOMER	CUSTOMER'S P/N	GYE'S P/N	PRODUCT	REVISION
		KAN0649	TACT SWITCH	А

2、 详细说明

Detailed specification

2.1 外观:应无影响、降低产品性能的缺陷;

Appearance: There should be no defects that affect the serviceability of product.

2.2 结构尺寸和安装尺寸:应符合装配图要求;

Style and dimension: shall conform to the assemble drawings.

2.3 操作形式:有触觉反应的操作

Type of actuating: Tactile feedback.

2.4 开关结构: 单回路单输出(具体的触点结构在装配图中已绘出);

Contact arrangement: 1 pole, 1 throw

(Details of contact arrangement are given in the assembly drawings.)

2.5 开关工作额定值: DC 12V, 50mA (有效值)

Ratings: 12V DC, 50mA (effective value)

3. 电气性能:

ELECTRICAL SPECIFICATION

项	目		试 验 条 件			要求	
ITI	EM		TEST CONDITIONS			REQUIREMENTS	
1		接触电阻 act Resistance	在以 5V 10mA 的直流电源或不低于 1KHz 的交流电源的电路中,以一个等于 2 倍按力的静负荷施加于手柄中心Applying a static load of 2 times operating force to the center of the stem, measurements shall be made by 5V DC 10mA or more than 1KHZ AC small-current contact resistance meter.			≤100mΩ	
2	ı	绝缘电阻 Insulation Resistance	在端子之间施加 DC 100V /1min 的条件下,测量端子之间底座、盖板的电阻值 Measurement shall be made following application of 100V DC potential, across terminals, and across terminals and cover, for one minute.			≥100MΩ	
3	D	广质耐压 ielectric ltage proof	在端子之间施加 250V AC(50HZ 或 60HZ)/1min 250V AC (50HZ or 60HZ) shall be applied across terminals, for one minute.			无击穿、无飞弧 There should I no breakdown and flashover	be
APPROVI	E BY	黄蜀东 10.10.2	CHECKED BY	关 林 10.10.25	PRPARE BY	Y 曹 盖 10.10.2	25



(GAI	NGYUAN	APPI	ROVAL	SPECIFI	CATI	ONS
С	USTOMER	CUSTOMER'S	S P/N GY	E'S P/N	PRODUCT	Г	REVISION
			KA	N0649	TACT SWIT	СН	А
	项目 ITEM		试 验 TEST CON			RE	要求 QUIREMENTS
	械性能: IANICAL SPE	ECIFICATION					
1	按力 Operating Force	量开关导通所需 Placing the swi vertical and the center of the st	于操作方向放置,在开关驱动件顶端中心逐渐施力,测通所需的最大力度。he switch such that the direction of switch operation is and then gradually increasing the load applied to the the stem, the maximum load required for the switch to a stop shall be measured.				efer to chart 3
2	最大行程 Full Travel	开关驱动件顶端 Placing the swi vertical and the	方向放置,以一个等于 2 倍按力的静负荷施加在中心,测量顶端移动的距离。 ch such that the direction of switch operation is applying static load of 2times operating force to stem; the travel distance for the switch to come e measured.			6	0.25±0.1mm
APP	ROVE BY	黄蜀东 10.10.25	CHECKED BY	关 林 10.	10.25 PRPA	ARE BY	曹 盖 10.10.25



	GANO	GYUAN	APPROVA	_ SPE	ECIFIC	ATIC	ONS
С	USTOMER	CUSTOMER'S P/N	GYE'S P/N	Р	RODUCT		REVISION
			KAN0649	TAC	CT SWITCH		А
	项目 ITEM		试验条件 TEST CONDITIONS			RE(要求 QUIREMENTS
3	回弹力 Return Force	开关垂直于操作方向放后,测量顶端向自由位 The sample switch is operation is vertical ar to the whole travel dis free position shall be r	文置,在开关驱动件顶空 置转换的力度。 installed such that the nd upon depressing the tance, the force of the	e direction e stem in	of switch its center		fer to chart 3
4	停止强度 Stop Strength	开关垂直于操作方向放置,从操作方向向驱动件施加 30N 的静负荷持续 1min。 Placing the switch such that the direction of switch operation is vertical, and then a static load of 30N shall be applied in the direction of stem operation for a period of 1 min.		1min。 the switch such that the direction of switch operation is and then a static load of 30N shall be applied in the			
5	手柄拔出 强度 Stem Strength	的行程范围。 Placing the switch suc vertical, and then the	向放置,反方向实施最大操作力,并测量手柄 such that the direction of switch operation is the maximum force to withstand a pull applied ection of stem operation shall be measured.				20N.min.
6	在以下设定条件下进行测量: Measurements shall be made following the test set forth below: (1) 焊接温度:245±5℃ Solder temperature: 245±5℃ (2) 浸入时间:2s±0.5s Immersion time: 2s±0.5s 对于其它步骤参考《GB 5095.6—86》试验 12a The other steps please refer to《GB 5095.6-86》TEST 12a				,	90%以上 Except	for the edge, the should cover a
APP	PROVE BY 黄	专蜀东 10.10.25 CHE	CKED BY 关 林	0.10.25	PRPARE	E BY	曹 盖 10.10.25



		1101	UAN		<i>,</i>	<u> </u>	<u> </u>		7 \ 1 1 \	<u> </u>
С	USTOMER	(CUSTOMER	'S P/N	GYE'	S P/N	Pi	RODUCT		REVISION
				KAN0649 TACT SWITC				T SWITCH		Α
	项目	·			试 验	条件			I .	要求
	ITEM TEST CONDITIONS							RE	QUIREMENTS	
	5、极限电气性能: ENVIRONMENTAL SPECIFICATION									
1	低温测试 Resistance low tempera	to ature	标准湿度的 Following to normal ten measureme (1) 温度 Tem (2) 时间	Temperature : -30±2℃						阻: ≤200mΩ t resistance: Ω 4.1,4.2,4.3 4.1,4.2,4.3
2	高温测试 Heat resista	ance	标准湿度的 Following to normal ten measureme (1) 温质 ten (2) 时间	temperature:80±2℃ (2) 时间: 96h					Contac ≤200ms 项目 3,4	
3	温度周期性 Change temperati	of	样品应放在 试期间样品 After 5 cy allowed to conditions	time: 96h 根据下面的测试要求进行 5 次循环的温度周期性测试,实验后样品应放在常温及标准湿度的环境中 1 小时后做性能测试。测试期间样品应保持干燥. After 5 cycles of following conditions, the sample shall be allowed to stand under normal temperature and humidity conditions for 1 h. and measurements shall be made. During the test water drops shall be removed. Temperature Time 1 cycle 1 cycle 1 cycle 65±2℃ 2 chour) 1 cycle 65 c 1 65 c 1 65 c 1					Contac ≤200ms 项目 3,4	
APPROVE BY 黄蜀东 10.10.25 CH				ECKED BY	关 林 1	0.10.25	PRPARI	E BY	曹 盖 10.10.25	



GANGTUAN								<u> </u>
С	USTOMER	(CUSTOMER'S	P/N GY	E'S P/N	PRODUCT		REVISION
			KAN0649 TACT SWITCH					Α
	项目			试习	金 条 件			要求
	ITEM			TEST C	ONDITIONS		RE	EQUIREMENTS
4	湿温测记 Moistur resistand	е	标准湿度的环 Following the normal temp measuremer (1) 温度: tempe (2) 相对 relativ (3) 时间:	以下实验条件进行测试,实验后样品应放在常温及 环境中 1 小时后做性能测试: ne test set forth below the sample shall be left in perature and humidity conditions for 1 h before ints are made: :: 60±2℃ erature: 60±2℃ *湿度: 90%~95% ve humidity:90% to 95% !: 96h				i⊞: ≤200mΩ ct resistance: nΩ ,4.1,4.2,4.3 ,4.1,4.2,4.3
5	硫化试验 Sulfuration resistance	on	样品应按照以下实验条件进行测试,实验后样品应放在常温及标准湿度的环境中 1 小时后做性能测试: Following the test set forth below the sample shall be left in normal temperature and humidity conditions for 1 h before measurements are made: (1) H ₂ S 气体浓度: 3ppm±1ppm H ₂ S gas concentration: 3ppm±1ppm (2) 时间: 72h Time: 72h (3) 温度: 40±2℃(90~95%RH) temperature: 40±2℃(90~95%RH)					i⊞: ≤200mΩ ct resistance: nΩ ,4.1,4.2,4.3 ,4.1,4.2,4.3
6	盐雾试验 Salt Mis		在以下设定条件下进行测量: The switch shall be checked after following test: (1) 温度: 35℃±2℃ temperature: 35℃±2℃ (2) 盐溶液浓度: 5±1%(质量百分比) salt solution: 5±1%(solids by mass) (3) 时间: 8h±1h Time: 8h±1 hour 实验后的盐沉积物用水冲掉 After test, salt deposit shall be removed by running water.					上没有腐蚀斑点 markable corrosion be recognized in part.
APPROVE BY 黄蜀东 10.10.25 CHECKED				CHECKED BY	关 林 10.	10.25 PRPAR	E BY	曹 盖 10.10.25



С	USTOMER		CUSTOMER'S P/			PRODUCT			REVISION
		KAN0649 TACT SWITE				CT SWITCH		Α	
	6、极限机械性能: ENDURANCE SPECIFICATION								
	项目			试验	条件			要求	
	ITEM TEST CONDITIONS							RE	QUIREMENTS
1	工作寿f Operation		Measurement sl (1) DC 12V, DC 12V, (2) 按动速率 Rate of (3) 按力: 拉 Operating (4) 平均无故	Rate of operation: 1 times/s (3) 按力: 按力的 1.5 倍 Operating Force: Operating Force1.5double				resistar 按力: Operati initial va 项目 3,4	阻≤200mΩContact nce≤200mΩ : 初值的±30% ng Force: alue±30% 4.1,4.2,4.3 4.1,4.2,4.3
2	振动 Vibra	ition	根据以下给定条件进行测试: Measurement shall be made following the test set forth below: (1) 振动频率范围: 10~55~10Hz Vibration frequency range: 10 to 55 to 10Hz (2) 振幅(峰一峰): 1.5mm Amplitude: 1.5mm (3) 振动方向: 包括手柄行程方向在内的三个相互垂直的方向 Direction of vibration:Three mutually perpendicular direction including the direction of stem travel (4) 测试时间: 每次 2hours . Duration: Each 2hours.			z 互垂直的方 pendicular		4.1,4.2,4.3 4.1,4.2,4.3	
	接条件: ERING CON	DITIO	NS:						
SOLDERING CONDITIONS: 请按以下条件进行焊接: (1) 焊锡温度: ≤350℃ (2) 连续焊接时间: ≤3 s Please practice according to below conditions: (1) Soldering temperature: 350℃ Max. (2) Continuous soldering time: 3 s Max.									
APPROVE BY 黄蜀羽			东 10.10.25 C	CHECKED BY	关 林 10.	10.25	PRPARE	BY	曹 盖 10.10.25



	TACT SWITCH 写条件 ided conditions	A
ITEM Recomme		
温度(*C) 180 -	ided conditions	
180 -		
7.2 Conditions for reflow 120sec max.(预热 3 to 4 mi 炉内通过即	230°C	nax. 3sec max. — 时间 <u>-</u>

说明: 1.1 开关浸焊后,注意不要用溶剂清洗。


After switches were soldered, please be careful not to clean switches with solvent.


- 1.2 在使用烙铁的情况下,焊锡温度应在 380℃以下、3 秒以内。 In the case of using solding iron, solding conditions shall be 380℃ max and 3 sec.max.
- 1.3 浸焊后,注意不要在顶部施加负荷。 Right after switches were soidered; please be careful not to load to on the knobs of switches.
- 2 设计中应注意的事项(Design instructions):
- 2.1 印刷基板的安装孔尺寸参见产品图。
 Follow recommended P.W.B. piercing plan in outside drawing page.
- 3 注意点(Note):
- 3.1 注意不要施加超负荷的压力或晃动开关 Please be cautions not to give excessive static load or shock to swiches.
- 3.2 开关浸焊后,印刷基板注意不要叠放。 Please be careful not to pile up P.W.B.after switches were soldered
- 3.3 保管时尤其应注意避开高湿高温和有腐蚀性气体的环境。如需要长时间保存,请不要打开包装箱。 Preservation under high temperature and high high humidity or corrosive gas should be avoided Especially. When you need to preserve for a long period, do not open the carton.


4.000.01/E.01/	# # 40 40 0		V II 10 10 0	555455557	# * 10.10.0=
APPROVE BY	黄蜀东 10.10.25	CHECKED BY	关 林 10.10.25	PRPARE BY	曹 盖 10.10.25




CUSTOMER	CUSTOMER'S P/N GYE'S P/N		PRODUCT	REVISION
		KAN0649	TACT SWITCH	А









General tolerance: ±0.2mm

NO.	NAME	MATERIAL	NATIONALITY	QTY.	FINISHING
1	TERMINAL	Brass	China	1	Silver plating
2	CASE	FR52	USA	1	Black
3	CONTACT	Phosphor bronze	Korea	1	Contact side silver plating
4	COVER	SPCC-SD	China	1	CuSn plating
5	STEM	FR52	USA	1	
_		<u> </u>			

APPROVE BY 黄蜀东 10.10.25 CHECKED BY 关 林 10.10.25 PRPARE BY 曹 盖 10.10.25