







Features

- · Constant Voltage + Constant Current mode output
- · Circular metal housing with class I design
- · Built-in active PFC function
- · IP67 / IP65 rating for indoor or outdoor installations
- Function options: output adjustable via potentiometer; 3 in 1 dimming; DALI
- Typical lifetime>50000 hours
- 5 years warranty


Applications

- · LED bay lighting
- LED stage lighting
- · LED spot lighting

■ Description

HBG-240 series is a 240W AC/DC LED driver featuring the circular shape design. It operates from $90{\sim}305$ VAC and offers the dual modes constant voltage and constant current output models with different rated voltage between 24Vand 60V. Thanks to the high efficiency up to 93.5%, with the fanless design, the entire series is able to operate for $-40\,^{\circ}\text{C} \sim +75\,^{\circ}\text{C}$ case temperature under free air convection. The design of metal housing and IP67/IP65 ingress protection level allows this series to fit both indoor and outdoor applications. HBG-240 is equipped with various function options, such as dimming methodologies, so as to provide the optimal design flexibility for LED lighting system.

■ Model Encoding



Туре	IP Level	Function	Note
Blank	IP67	lo fixed.	In Stock
Α	IP65	Io adjustable through built-in potentiometer.	In Stock
В	IP67	3 in 1 dimming function (1~10Vdc, 10V PWM signal and resistance)	In Stock
AB	IP65	Io adjustable through built-in potentiometer with 3 in 1 dimming function	In Stock
DA	IP67	DALI control technology.	In Stock



240W Constant Voltage + Constant Current LED Driver

HBG-240 series

MODEL		HBG-240-24	HBG-240-36	HBG-240-48	HBG-240-60			
	DC VOLTAGE	24V	36V	48V	60V			
	CONSTANT CURRENT REGION Note.2	14.4 ~ 24V	21.6 ~ 36V	28.8 ~ 48V	36 ~ 60V			
	CONSTANT CURRENT REGION (for DA Type only)	16.8 ~ 24V	25.2 ~ 36V	33.6 ~ 48V	42 ~ 60V			
	RATED CURRENT	10A	6.7A	5A	4.0A			
-	RATED POWER Note.5	240W	240W	240W	240W			
	RIPPLE & NOISE (max.) Note.3	·	250mVp-p	250mVp-p	350mVp-p			
OUTPUT	THE LE GIVETOL (MAXI) NOTES	Adjustable for A/AB-Type (via built-in potentiometer)						
	CURRENT ADJ. RANGE	6 ~ 10A	4.0 ~ 6.7A	3 ~ 5A	2.4 ~ 4.0A			
	VOLTAGE TOLERANCE Note.4	±2.0%	1.0 0.171	0 0/1	12.1			
	LINE REGULATION	±0.5%						
	LOAD REGULATION	±0.5%						
	SETUP, RISE TIME Note.6							
	HOLD UP TIME (Typ.)	15ms /115VAC, 230VAC						
	VOLTAGE RANGE Note.5	90 ~ 305VAC 127 ~ 431VDC						
	FREQUENCY RANGE	47 ~ 63Hz						
		PF>0.98/115VAC, PF>0.95/230VAC, PF>0.93/277VAC@full load						
	POWER FACTOR	(Please refer to "POWER FACTOR (PF) CHARACTERISTIC" section) THD< 20%(@load≧60%/115VC,230VAC; @load≧80%/277VAC)						
	TOTAL HARMONIC DISTORTION	(Please refer to "TOTAL HARM	IONIC DISTORTION(THD)" se	ction)				
	EFFICIENCY (Typ.) Note.7	92.5%	92.5%	93%	93.5%			
	AC CURRENT (Typ.)	2.5A / 115VAC						
	INRUSH CURRENT (Typ.)	COLD START 75A(twidth=680μs measured at 50% Ipeak) at 230VAC; Per NEMA 410						
	MAX. No. of PSUs on 16A CIRCUIT BREAKER	2 units (circuit breaker of type B) / 3 units (circuit breaker of type C) at 230VAC						
	LEAKAGE CURRENT	<0.75mA/277VAC						
PROTECTION	OVER CURRENT	95 ~ 108%						
	OVER CORRENT	Constant current limiting, recovers automatically after fault condition is removed						
	SHORT CIRCUIT	Hiccup mode, recovers automatically after fault condition is removed						
	OVER VOLTAGE	27 ~ 34V	43 ~ 52V	52 ~ 63V	62 ~ 85V			
	OVERVOLIAGE	Shut down and latch off o/p voltage, re-power on to recover						
	OVER TEMPERATURE	Shut down o/p voltage, recovers automatically after temperature goes down						
	WORKING TEMP.	Tcase=-40 ~ +75°C (Please refer to "OUTPUT LOAD vs TEMPERATURE" section)						
	MAX. CASE TEMP.	Tcase=+75°C						
	WORKING HUMIDITY	20 ~ 95% RH non-condensing						
	STORAGE TEMP., HUMIDITY	-40 ~ +80°C, 10 ~ 95% RH						
	TEMP. COEFFICIENT	±0.03%/°C (0 ~ 50°C)						
	VIBRATION	10 ~ 500Hz, 5G 12min./1cycle, period for 72min. each along X, Y, Z axes						
	SAFETY STANDARDS	UL8750,CSA C22.2 No.250.13-12, ENEC EN61347-1, EN61347-2-13 independent, EN62384;GB19510.1,GB19510.14, BIS IS15885(for 48A,60A only), EAC TP TC 004, IP65 or IP67 approved						
SAFETY &	DALI STANDARDS	Compliance to IEC62386-101, 102, 207 for DA-Type only						
	WITHSTAND VOLTAGE	I/P-O/P:3.75KVAC I/P-FG:2KVAC O/P-FG:0.5KVAC						
	ISOLATION RESISTANCE	I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C / 70% RH						
	EMC EMISSION Note.9							
	EMC IMMUNITY	•						
OTHERS	MTBF	Compliance to EN61000-4-2,3,4,5,6,8,11, EN61547,light industry level (surge immunity:Line-Earth:4KV,Line-Line:2KV), EAC TP TC 0 663.8K hrs min. Telcordia SR-332 (Bellcore); 190.7Khrs min. MIL-HDBK-217F (25°C)						
	DIMENSION	φ 191.5mm *69mm (D * H)						
	PACKING	2.1Kg; 8pcs/18.3Kg/2.09CUFT						
NOTE	All parameters NOT specia Please refer to "DRIVING N	T specially mentioned are measured at 230VAC input, rated current and 25°C of ambient temperature. INVING METHODS OF LED MODULE". measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 47uf parallel capacitor.						

- 5. De-rating may be needed under low input voltages. Please refer to "STATIC CHARACTERISTIC" sections for details.

 6. Length of set up time is measured at cold first start. Turning ON/OFF the driver may lead to increase of the set up time.


 7. The DA type power supply is less efficient than the A type power supply by 1%.
- 8. The driver is considered as a component that will be operated in combination with final equipment. Since EMC performance will be affected by the complete installation, the final equipment manufacturers must re-qualify EMC Directive on the complete installation again.

 9.To fulfill requirements of the latest ErP regulation for lighting fixtures, this LED driver can only be used behind a switch without permanently
- connected to the mains.
- 10. This series meets the typical life expectancy of >50,000 hours of operation when Tcase, particularly (tc) point (or TMP, per DLC), is about 70°C or less.
- 11. Please refer to the warranty statement on MEAN WELL's website at http://www.meanwell.com 12. The ambient temperature derating of 3.5°C/1000m with fanless models and of 5°C/1000m with fan models for operating altitude higher than 2000m(6500ft).
- 13. For any application note and IP water proof function installation caution, please refer our user manual before using. https://www.meanwell.com/Upload/PDF/LED EN.pdf X Product Liability Disclaimer: For detailed information, please refer to https://www.meanwell.com/serviceDisclaimer.aspx




■ BLOCK DIAGRAM

fosc: 100KHz



■ DRIVING METHODS OF LED MODULE

X This series is able to work in either Constant Current mode (a direct drive way) or Constant Voltage mode (usually through additional DC/DC driver) to drive the LEDs.




Typical output current normalized by rated current (%)

In the constant current region, the highest voltage at the output of the driver depends on the configuration of the end systems.

Should there be any compatibility issues, please contact MEAN WELL.






※ 3 in 1 dimming function (for B/AB-Type)


DA- for DA-Type

- Output constant current level can be adjusted by applying one of the three methodologies between DIM+ and DIM-:
 1 ~ 10VDC, or 10V PWM signal or resistance.
- Direct connecting to LEDs is suggested. It is not suitable to be used with additional drivers.
- Dimming source current from power supply: $100\mu A$ (typ.)
- O Applying additive 1 ~ 10VDC




"DO NOT connect "DIM- to -V"

O Applying additive 10V PWM signal (frequency range 100Hz ~ 3KHz):





"DO NOT connect "DIM- to -V"


Applying additive resistance:



"DO NOT connect "DIM- to -V"










Note: In the case of turning the lighting fixture down to 0% brightness, please refer to the configuration as follow, or please contact MEAN WELL for other options.




Using a switch and relay can turn ON/OFF the lighting fixture.

DALI Interface (primary side; for DA-Type)


- · Apply DALI signal between DA+ and DA-.
- DALI protocol comprises 16 groups and 64 addresses.
- First step is fixed at 8% of output.









■ LIFE TIME



- (tc): Max. Case Temperature.(case temperature measured point)
- Ta: Ambient Temperature measured point




- ullet (case temperature measured point)
- Ta: Ambient Temperature measured point



- tc : Max. Case Temperature.(case temperature measured point)
- Ta: Ambient Temperature measured point




※ AB-Type



- to: Max. Case Temperature.(case temperature measured point)
- Ta: Ambient Temperature measured point

■ INSTALLATIONS



Caution

- Please inspect the appearance of the driver if the package is damaged. There should not be any cracks.
- · Please do not drop or bump the driver.
- · All screws including the suspension screw should be paired with a spring washer and locked tight.
- The entire luminaire, including the driver, should be limited to 15Kg or less.
- The luminaire should be cautiously protected from damage due to shock throughout packaging and transportation.
- · Please thoroughly follow the preceding cautionary notes to prevent the luminaire from falling, leading to injuries.