



■ Features :

- Universal AC input / Full range
- Built-in active PFC function
- High efficiency up to 90%
- Withstand 300VAC surge input for 5 seconds
- Protections: Short circuit / Overload / Over voltage
- Protections: Over temperature (optional)
- Cooling by free air convection
- 1U low profile 38mm
- Built-in remote ON-OFF control
- No load power consumption<0.5W
- All using 105°C long life electrolytic capacitors
- 5 years warranty









SPECIFICATION

MODEL		HRP-100-3.3	HRP-100-5	HRP-100-7.5	HRP-100-12	HRP-100-15	HRP-100-24	HRP-100-36	HRP-100-48
	DC VOLTAGE	3.3V	5V	7.5V	12V	15V	24V	36V	48V
ОИТРИТ	RATED CURRENT	20A	17A	13.5A	8.5A	7A	4.5A	2.9A	2.2A
	CURRENT RANGE	0 ~ 20A	0 ~ 17A	0 ~ 13.5A	0 ~ 8.5A	0 ~ 7A	0 ~ 4.5A	0 ~ 2.9A	0 ~ 2.2A
	RATED POWER	66W	85W	101.3W	102W	105W	108W	104.4W	105.6W
	RIPPLE & NOISE (max.) Note.2	80mVp-p	80mVp-p	100mVp-p	120mVp-p	150mVp-p	150mVp-p	200mVp-p	240mVp-p
	VOLTAGE ADJ. RANGE	3.1 ~ 3.8V	4.75 ~ 5.8V	7.1 ~ 9V	11.4 ~ 13.8V	14.25 ~ 18V	22.8 ~ 28.8V	34.2 ~ 39.6V	45.6 ~ 55.2\
	VOLTAGE TOLERANCE Note.3	+2.5,-3.5%	±2.5%	±2.5%	±1.5%	±1.5%	±1.5%	±1.5%	±1.5%
	LINE REGULATION	±0.5%	±0.5%	±0.5%	±0.3%	±0.3%	±0.2%	±0.2%	±0.2%
	LOAD REGULATION	±2.0%	±2.0%	±1.5%	±0.8%	±0.8%	±0.5%	±0.5%	±0.5%
	SETUP, RISE TIME	2500ms, 100ms/230VAC 2500ms, 100ms/115VAC at full load							
	HOLD UP TIME (Typ.)	50ms/230VAC 20ms/115VAC at full load							
	VOLTAGE RANGE Note.5	85 ~ 264VAC 120 ~ 370VDC							
INPUT	FREQUENCY RANGE	47 ~ 63Hz							
	POWER FACTOR (Typ.)	PF>0.95/230VAC PF>0.98/115VAC at full load							
	EFFICIENCY (Typ.)	78%	83%	84%	87.5%	88%	88.5%	89%	90%
	AC CURRENT (Typ.)	1.1A/115VAC	0.6A/230VA	C					
	INRUSH CURRENT (Typ.)	35A/115VAC 65A/230VAC							
	LEAKAGE CURRENT	<1mA/240VAC							
PROTECTION	OVERLOAD	105 ~ 135% rated output power Protection type: Constant current limiting for Vo=50 ~ 100% of rated voltage, recovers automatically after fault condition is rem							dition in none.
		3.96 ~ 4.62V	6 ~ 7V	9.4 ~ 10.9V	14.4 ~ 16.8V	18.8 ~ 21.8V	30 ~ 34.8V	41.4 ~ 48.6V	57.6 ~ 67.2
	OVER VOLTAGE					1	30 * 34.0 0	41.4 * 40.0 V	37.0 - 07.2
	OVER TEMPERATURE	Protection type: Shut down o/p voltage, re-power on to recover Shut down o/p voltage, recovers automatically after temperature goes down							
FUNCTION	REMOTE CONTROL	RC+/RC-: 0 ~ 0.8V= power on : 4 ~ 10V = power off							
FUNCTION	WORKING TEMP.	-40 ~ +60°C (Refer to "Derating Curve")							
ENVIRONMENT	WORKING TEMP. WORKING HUMIDITY	20 ~ 90% RH non-condensing							
	STORAGE TEMP., HUMIDITY	-40 ~ +85°C, 10 ~ 95% RH							
	TEMP. COEFFICIENT	±0.04%/°C (0~50°C)							
	VIBRATION	10 ~ 500Hz, 5G 10min./1cycle, 60min. each along X, Y, Z axes							
	SAFETY STANDARDS	UL62368-1,TUV EN62368-1, AS/NZS62368.1, EAC TP TC 004 approved							
	WITHSTAND VOLTAGE	I/P-O/P:3KVAC I/P-FG:2KVAC O/P-FG:0.5KVAC							
SAFETY &	ISOLATION RESISTANCE								
EMC (Note 4)	EMC EMISSION	I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C / 70% RH Compliance to EN55032 (CISPR32) Class B, EN61000-3-2,-3, EAC TP TC 020							
,//									
OTHERS	EMC IMMUNITY	Compliance to EN61000-4-2,3,4,5,6,8,11, EN55024, EN61000-6-2, heavy industry level, criteria A, EAC TP TC 020 295.7K hrs min. MIL-HDBK-217F (25°C)							
	MTBF			-217F (25 C)					
	DIMENSION	159*97*38mm (L*W*H)							
	PACKING 1. All parameters NOT specia	0.56Kg; 24pcs/		230VAC input r	ated load and Of	5°C of ambient to	emperature		
NOTE	Ripple & noise are measure Tolerance : includes set up The power supply is conside a 360mm*360mm metal playerform these EMC tests, p. Derating may be needed ui	ed at 20MHz of tolerance, line r lered a compone ate with 1mm of please refer to "E ander low input ve	bandwidth by use regulation and lo ent which will be thickness. The EMI testing of co	sing a 12" twister bad regulation. the installed into a final equipment component power check the derati	d pair-wire terminal equipment. must be re-confirsupplies." (as a ing curve for mo	inated with a 0.1 All the EMC test rmed that it still vailable on http:	uf & 47uf parallets are been exemeets EMC dires//www.meanwell	cuted by mount ectives. For guid	ance on how



