

S.Q. TUBE


Special quality pentode designed for use as wide band output tube.

| QUICK REFERENCE DATA | | |
|--------------------------|---|-----------------|
| Life test | 10 000 hours | |
| Low interface resistance | | |
| Mechanical quality | Shock and vibration resistant | |
| Base | Magnoval. Gold plated pins | |
| Heating | Indirect A.C. or D.C.; Parallel supply | |
| Heater voltage | V_f | 6.3 $V \pm 5\%$ |
| Heater current | I_f | 600 mA |
| Anode current | I_a | 50 mA |
| Mutual conductance | S | 45 mA/V |

DIMENSIONS AND CONNECTIONS

Dimensions in mm

Base: Magnoval



CHARACTERISTICS

Column I Nominal value or setting of the tube

II Range values for equipment design: Initial spread

III Range values for equipment design: End of life

| | | I | II | III | |
|------------------------------|----------------|-----|-----------|--------------------------|------------|
| Heater voltage | V_f | 6.3 | | | V |
| Heater current | I_f | 600 | | | mA |
| Anode voltage | V_a | 125 | | | V |
| Grid No.3 voltage | V_{g_3} | 0 | | | V |
| Grid No.2 voltage | V_{g_2} | 125 | | | V |
| Grid No.1 voltage | $-V_{g_1}$ | 3 | | | V |
| Anode current | I_a | 50 | | | mA |
| Grid No.2 current | I_{g_2} | 5.5 | | | mA |
| Mutual conductance | S | 45 | | | mA/V |
| Internal resistance | R_i | 20 | | | k Ω |
| Amplification factor | $\mu_{g_2g_1}$ | 30 | | | |
| Input resistance | R_{g_1} | 1 | | | k Ω |
| Frequency = 50 MHz | | | | | |
| Anode supply voltage | V_{ba} | 140 | | | V |
| Grid No.3 voltage | V_{g_3} | 0 | | | V |
| Grid No.2 supply voltage | V_{bg_2} | 140 | | | V |
| Grid No.1 supply voltage | $+V_{bg_1}$ | 12 | | | V |
| Cathode resistor | R_k | 270 | | | Ω |
| Anode current | I_a | 50 | 48 - 52 | | mA |
| Grid No.2 current | I_{g_2} | 5.5 | 4.5 - 6.5 | | mA |
| Grid No.1 to cathode voltage | $-V_{g_1k}$ | 3.0 | 2.3 - 3.7 | 1.8 | V |
| Mutual conductance | S | 45 | 38 - 52 | $\Delta S =$ max. 25% | mA/V |
| Negative grid current | $-I_g$ | | | 2 | μA |

CHARACTERISTICS (continued)As triode (grid No.2 connected to anode)

| | | I | |
|----------------------|------------|------|----------|
| Anode voltage | V_a | 125 | V |
| Grid No.1 voltage | $-V_{g_1}$ | 3 | V |
| Anode current | I_a | 55.5 | mA |
| Mutual conductance | S | 50 | mA/V |
| Internal resistance | R_i | 600 | Ω |
| Amplification factor | μ | 30 | |

CAPACITANCESPentode connected


| | | I | II | I | II | |
|---|---------------------|-------------|----------|----------------|----------|-----|
| | | With shield | | Without shield | | |
| Anode to grid No.3, grid No.2, cathode and heater | C_{a/g_3g_2} kf | 6.5 | 5.8- 7.2 | 4.0 | 3.6- 4.4 | pF |
| Grid No.1 to grid No.3, grid No.2, cathode and heater | C_{g_1/g_3g_2} kf | 18 | 15- 21 | 18 | 15- 20 | pF |
| Grid No.1 to grid No.3, grid No.2, cathode and heater | C_{g_1/g_3g_2} kf | 28 | | 28 | | pF |
| Cathode current $I_k = 55.5$ mA | | | | | | |
| Anode to grid No.1 | C_{ag_1} | 80 | max. 120 | 110 | max. 150 | mpF |



Triode connected (grid No.2 connected to anode)



| | | | | | | |
|---|------------------|------|----------|------|----------|----|
| Anode to grid No.3, cathode and heater | C_{a/g_3} kf | 10.5 | 9.4-11.6 | 7.8 | 7.0- 8.6 | pF |
| Grid No.1 to grid No.3, cathode and heater | C_{g_1/g_3} kf | 11.8 | 10-13.6 | 11.8 | 10-13.6 | pF |
| Anode to grid No.1 | C_{ag_1} | 6.2 | 5.5- 6.9 | 6.3 | 5.6- 7.0 | pF |
| Cathode to heater | C_{kf} | 6.0 | | 6.0 | | pF |



OPERATING CONDITIONS


| | | |
|--------------------------|------------|--------------|
| Anode supply voltage | V_{ba} | 140 V |
| Grid No.2 supply voltage | V_{bg2} | 140 V |
| Grid No.3 voltage | V_{g3} | 0 V |
| Grid No.1 supply voltage | $+V_{bg1}$ | 12 V |
| Cathode resistor | R_k | 270 Ω |
| Anode current | I_a | 50 mA |
| Grid No.2 current | I_{g2} | 5.5 mA |
| Mutual conductance | S | 45 mA/V |












7206714--5.ee.12



PHILIPS

Data handbook



Electronic
components
and materials

E55L

| page | sheet | date |
|-------------|--------------|-------------|
| 1 | 1 | 1968.12 |
| 2 | 2 | 1968.12 |
| 3 | 3 | 1968.12 |
| 4 | 4 | 1968.12 |
| 5 | 5 | 1968.12 |
| 6 | 6 | 1968.12 |
| 7 | 7 | 1968.12 |
| 8 | 8 | 1968.12 |
| 9 | 9 | 1968.12 |
| 10 | 10 | 1968.12 |
| 11 | FP | 2000.11.11 |