



TWIN PHOTOTUBE

Cathodes Quarter-cylindrical, caesium-coat	ed	
Cathode Window Area (Each unit)	0.31 sq. in.	
Direct Interelectrode Capacitances: Anode to Cathode (Each unit) Between Cathodes Between Anodes	1.5 µµf 1.6 µµf 0.36 µµf	
Maximum Overall Length	4"	
Maximum Diameter	1-3/16"	
Eulb	T-9	
Sase	Small 4-pin	

MAXIMUM RATINGS and CHARACTERISTICS

All values are for each unit

90 max. 50 max.	
75 70 63	µamp./lumen µamp./lumen µamp./lumen
over 10	
	90 max. 50 max. 75 70 63


greater than 2.5 µamp. 4 min. megohms For d-c currents less than 2.5 µamp. No minimum

- * Sensitivity is measured with a light input varied sinusoidally about a mean value from zero to a maximum of twice the mean. The sensitivity values shown are the ratios of the amplitude of variation in the current output to the amplitude of variation in the light input. The method of sensitivity measurement used is based on the approximation that sensitivity at 100 cycles is equal to sensitivity at cycles. The measurements were made with a 90-volt supply, a 1-megohm load, and a mean light input of 0.015 lumen. The light source was a Mazda projection lamp operated at a filament color temperature of 2870 degrees Kelvin. The effect of interelectrode capacitance was made negligible.
- Gas Amplification Factor is given as a ratio of sensitivity at maximum anode voltage to sensitivity at a voltage sufficiently low (approximately 25 volts) to eliminate gas ionization effects.






TWIN PHOTOTURE




TYPICAL CIRCUIT FOR THE 920 WITH EITHER TRANSFORMER OR RESISTANCE COUPLING FOR SOUND-ON-FILM REPRODUCTION



Notice accompanying them. Inforwithout assuming any obligations.




SPECTRAL SENSITIVITY CHARACTERISTICS



SENSITIVITY-MICROAMPERES PER MICROWATT RADIANT ENERGY



AVERAGE ANODE CHARACTERISTICS



MAY 21,1937


RCA RADIOTRON DIVISION RCA MANUFACTURING COMPANY, INC.

92C-4618R1



AVERAGE CHARACTERISTICS









AVERAGE SENSITIVITY CHARACTERISTIC

