mente m v. g. s.

— TUNG-80L —

PENTODE

MINIATURE TYPE



COATED UNIPOTENTIAL CATHODE

HEATER

12.6 VOLTS .175 AMP.

AC OR DC

ANY MOUNTING POSITION



BOTTOM VIEW
MINIATURE BUTTON
7 PIN BASE

THE 12EZ6 IS A SHARP CUTOFF PENTODE WITH A UNIPCTENTIAL CATHODE IN THE 7 PIN MINIATURE CONSTRUCTION. IT IS INTENDED FOR USE AS AN RF OR IF AMPLIFIER WHERE THE HEATER, PLATE AND SCREEN GRID POTENTIALS ARE OBTAINED DIRECTLY FROM AN AUTOMOTIVE BATTERY.

DIRECT INTERELECTRODE CAPACITANCES

GRID TO PLATE (MAX.)	.008	$\mu\mu$ f
INPUT:	7.8	$\mu\mu$ f
OUTPUT:	5.5	$\mu\mu$ f

RATINGS INTERPRETED ACCORDING TO DESIGN CENTER SYSTEM

HEATER VOLTAGE	12.6	VOLTS
MAXIMUM HEATER-CATHODE VOLTAGE	±30	VOLTS
MAXIMUM PLATE VOLTAGE	30	VOLTS
MAXIMUM GRID #2 VOLTAGE	30	VOLTS
MAXIMUM CATHODE CURRENT	10	MA.
MAXIMUM GRID #4 CIRCUIT RESISTANCE	10	MEGOHMS

TYPICAL OPERATING CONDITIONS AND CHARACTERISTICS CLASS \mathbf{A}_1 AMPLIFIER

HEATER VOLTAGE	12.6	14.0	VOLTS
HEATER CURRENT	.175	.175	AMP.
PLATE VOLTAGE	12.6	14.0	VOLTS
GRID #3 VOLTAGE ^B	0	0	VOLTS
GRID #2 VOLTAGE	12.6	14.0	VOLTS
GRID #1 VOLTAGE	-0.7	-0.8 ^D	
PLATE CURRENT	1.9	2.3	MA.
GRID #2 CURRENT	0.7	0.85	MA.
PLATE RESISTANCE	0.40	0.30	MEGOHMS
TRANSCONDUCTANCE ^C	2700	3000	μM HOS
GRID #1 VOLTAGE FOR ID=50 MMHOS	-2.6	-2.8	VOLTS
GRID #4 & GRID #3 VOLTAGE FOR G = 30 MMHOS	-2.8	-3.0	VOLTS

A THIS TUBE IS INTENDED TO BE USED IN AUTOMOTIVE SERVICE FROM A NOMINAL 12 VOLT BATTERY SOURCE. THE HEATER IS THEREFORE DESIGNED TO OPERATE OVER THE 10.0 TO 15.9 VOLTAGE RANGE ENCOUNTERED IN THIS SERVICE. THE MAXIMUM RATINGS OF THE TUBE PROVIDE FOR AN ADEQUATE SAFETY FACTOR SUCH THAT THE TUBE WILL WITHSTAND THE WIDE VARIATION IN SUPPLY VOLTAGES.

BCONNECTED TO CATHODE AT SOCKET. CFROM GRID #1 TO PLATE.

DAVERAGE BIAS DEVELOPED ACROSS A 2.2 MEGOHM GRID RESISTOR.



