







BOTTOM VIEW SMALL SHELL 8-PIN OCTAL

THE 1F6 AND 1F7GH CONSIST OF TWO DIODES AND A PENTODE IN A SINGLE BULB. THEY ARE DESIGNED FOR SERVICE AS DIODE DETECTORS, AVC RECTIFIERS AND PENTODE AMPLIFIERS. WITH THE EXCEPTION OF CAPACITANCES, THEIR ELECTRICAL CHARACTERISTICS ARE IDENTICAL.

## RATINGS

MAXIMUM PLATE VOLTAGE MAXIMUM SCREEN VOLTAGE MAXIMUM PLATE DISSIPATION MAXIMUM SCREEN DISSIPATION	180 67.5 0.4 0.05	VOLTS VOLTS WATT WATT
MINIMUM DIODE CURRENT PER PLATE WITH 10 VOLTS DC APPLIED.  MAXIMUM DIODE CURRENT PER PLATE FOR CONTINOUS	0.5	MA.
OPERATION.	0.25	MA.

CONTINUED ON NEXT PAGE

PLATE 1527 JAN. 15 1945

# TUNG-SOL -

CONTINUED FROM PRECEDING PAGE

#### DIRECT INTERELECTRODE CAPACITANCES

	IF6	IF7GH	
GRID TO PLATE A	0.007 MAX.	0.01 MAX.	μμί
INPUT: G1 TO (F+G2+G3) OUTPUT: P TO (F+G2+G3)	4.0 9.0	3.8 9.5	μμf μμf
OUTPUI: P TO (FTG2TG3)	9.0	9.9	μμι


### TYPICAL OPERATING CONDITIONS AND CHARACTERISTICS

-RF OR 1F AMPLIFIER

#### PENTODE UNIT

PLATE VOLTAGE	180	VOLTS
SCREEN VOLTAGE	67.5	VOLTS
CONTROL GRID VOLTAGE	-1.5	VOLTS
PLATE RESISTANCE (APPROX.)	1.0	ME GOHM
TRANSCONDUCTANCE	650	имноs
TRANSCONDUCTANCE FOR ECA = -12 VOLTS	20	µмноs
PLATE CURRENT	2.2	MA.
SCREEN CURRENT	0.7	MA.

A WITH SHIELD CAN



1528