# TUME-SEL

#### CATHODE RAY

THE 27SP4 IS A DIRECT-VIEW PICTURE TUBE DESIGNED FOR USE IN TELEVISION APPLICATIONS. ITS FEATURES INCLUDE:

ALUMINIZED SCREEN
UNIPOTENTIAL CATHODE
EXTERNAL CONDUCTIVE COATING
RECTANGULAR GLASS CONSTRUCTION
LOW YOUTAGE ELECTROSTATIC FOCUS

SPHERICAL FACEPLATE
MAGNETIC DEFLECTION
GREY FILTER FACEPLATE
2\* X 10 1/2\* RASTER SIZE
EXTERNAL SINGLE FIELD ION TRAP

#### ELECTRICAL DATA

| FOCUSING METHOD L                              | .OW | VOLTAGE | ELECTROSTATIC |
|--|-----|---------|---------------|
| DEFLECTING METHOD                              |     |         | MAGNETIC      |
| DEFLECTION ANGLE: (APPROX.)                    |     |         |               |
| HORIZONTAL                                     |     | 85      | DEGREES       |
| DIAGONAL                                       |     | 90      | DEGREES       |
| DIRECT INTERELECTRODE CAPACITANCES: (APPROX.)  |     |         |               |
| CATHODE TO ALL OTHER ELECTRODES                |     | 5       | ии f          |
| GRID #1 TO ALL OTHER ELECTRODES                |     | 6       | µµ f          |
| MAXIMUM EXTERNAL CONDUCTIVE COATING TO ANODE A |     | 750     | μμ f          |
| MINIMUM EXTERNAL CONDUCTIVE COATING TO ANODE A |     | 500     | uμ f          |
|  |     |         |               |

AEXTERNAL CONDUCTIVE COATING MUST BE GROUNDED.

# OPTICAL DATA

| PHOSPHOR NUMBER                                  |            | P-4     |
|--|------------|---------|
| FLUORESCENT COLOR                                |            | WHITE   |
| PHOSPHORESCENT COLOR                             |            | WHITE   |
| PERSISTENCE                                      |            | MEDIUM  |
| FACEPLATE LIGHT TRANSMISSION AT CENTER (APPROX.) | <b>6</b> 8 | PERCENT |

## MECHANICAL DATA

| 170              |   |
|------------------|---|
| 23 1/16 ± 3/8    | INCHES  |
|                  |   |
| 26 13/16         | INCHES  |
| 25 9/32 ± 3/16   | INCHES  |
| 20 7/32 ± 3/16   | INCHES  |
|                  |   |
| 24               | INCHES  |
| 18 1/2           | INCHES  |
| SMALL CAVITY CAP | J1-21   |
| L DUODECAL 6 PIN | 86-63   |
|                  | 12L   |
|                  | 23 1/16 ± 3/8<br>26 13/16<br>25 9/32 ± 3/16<br>20 7/32 ± 3/16 |

BULB CONTACT ALIGNMENT

J1-21 CONTACT ALIGNS WITH PIN POSITION #6 ± 30 DEGREES

### PIN CONNECTIONS

PIN 1 - HEATER
PIN 2 - GRID NO. 1
PIN 6 - GRID NO. 4
PIN 10 - GRID NO. 2
PIN 11 - CATHODE



PIN 12 - HEATER ANODE CAP: GRID NO. 3 GRID NO. 5

CONTINUED ON FOLLOWING PAGE

# TUNG-SOL

CONTINUED FROM PRECEDING PAGE

#### RATINGS DESIGN CENTER VALUES

| HEATER VOLTAGE                                       | 6.3      | VOLTS  |
|--|----------|--------|
| HEATER CURRENT                                       | 0.6      | AMP.   |
| MAXIMUM DC ANODE, GRID #3, GRID #5 VOLTAGE           | 20 000   | VOLTS  |
| MAXIMUM DC GRID #4 VOLTAGE (FOCUSING ELECTRODE) -500 | то +1000 | VOL TS |
| MAXIMUM DC GRID #2 VOLTAGE                           | 500      | VOLTS  |
| MAXIMUM GRID #1 VOLTAGE:                             |          |        |
| DC NEGATIVE-BIAS VALUE                               | 125      | VOLTS  |
| DC POSITIVE-BIAS VALUE                               | 0        | VOLTS  |
| POSITIVE-PEAK VALUE                                  | 2        | VOLTS  |
| MAXIMUM DC PEAK HEATER-CATHODE VOLTAGE:              |          |        |
| HEATER NEGATIVE WITH RESPECT TO CATHODE              |          |        |
| DURING WARM-UP PERIOD NOT TO EXCEED 15 SECONDS       | 410      | VOLTS  |
| AFTER EQUIPMENT WARM-UP PERIOD                       | 180      | VOLTS  |
| HEATER POSITIVE WITH RESPECT TO CATHODE              | 180      | VOL.TS |
|  |          |        |

#### TYPICAL OPERATING CONDITIONS AND CHARACTERISTICS

| DC ANODE, GRID #3, GRID #5 VOLTAGE <sup>B</sup> DC GRID #4 VOLTAGE (FOCUSING ELECTRODE) DC GRID #7 VOLTAGE | 18 000<br>-72 to +396<br>300 | VOLTS<br>VOLTS<br>VOLTS |
|--|------------------------------|-------------------------|
| DC GRID #1 VOLTAGE REQUIRED FOR CUTOFF <sup>C</sup> ION TRAP MAGNET STRENGTH (APPROX.)                     | -28 то -72<br>40             | VOLTS<br>GAUSSES        |

Berilliance and definition decrease with decreasing anode voltage. In general, anode voltage should not be less than this value.

#### CIRCUIT VALUES

MAXIMUM GRID #1 CIRCUIT RESISTANCE

1.5

MEGOHMS

 $C_{\text{VISUAL}}$  EXTINCTION OF FOCUSED RASTER. EXTINCTION OF THE STATIONARY FOCUSED SPOT WILL REQUIRE THAT THESE VALUES BE ABOUT 5 VOLTS MORE REGATIVE.