
## DIODE PENTODE

MINIATURE TYPE



COATED UNIPOTENTIAL CATHODE

HEATER
4.7 VOLTS 0.6 AMP.
AC OR DC

ANY MOUNTING POSITION



BOTTOM VIEW
MINIATURE BUTTON
9 PIN BASE
9CY

THE 5AM8 IS A DIODE PENTODE ESPECIALLY DESIGNED FOR USE AS A VIDEO DETECTOR AND IF AMPLIFIER IN 600 MA. SERIES HEATER OPERATED TELEVISION RECEIVERS. THERMAL CHARACTERISTICS OF THE HEATER ARE CONTROLLED SUCH THAT HEATER VOLTAGE SURGES DURING THE WARM-UP CYCLE ARE MINIMIZED PROVIDED IT IS USED WITH OTHER TYPES WHICH ARE SIMILARLY CONTROLLED.

## DIRECT INTERELECTRODE CAPACITANCES

PENTODE	WITH SHIELD <sup>A</sup>	WITHOUT SHIELD	
GRID #1 TO PLATE (MAX.)	0.015	0.015	ии f
INPUT	6.0	6.0	иµ f
OUTPUT	3.4	2.6	ии f
DIODE			
INPUT: P TO (H+K)	2.3	1.7	ии f
CATHODE TO (H+P)	3.0	3.0	ии f
COUPLING (DIODE PLATE TO PENTODE PLATE)	0.035	0.10	ии f
COUPLING (DIODE PLATE TO GRID #1)	0.005	0.006	µи f
COUPLING (DIODE CATHODE TO PENTODE PLATE)	0.15	0.15	µц f

ASHIELD #315-

CONTINUED ON FOLLOWING PAGE

-->INDICATES A CHANGE.

## TUNG-SOL

#### CONTINUED FROM PRECEDING PAGE

# RATINGS INTERPRETED ACCORDING TO DESIGN CENTER SYSTEM

HEATER VOLTAGE	4.7	VOLTS
MAXIMUM HEATER-CATHODE VOLTAGE:		
HEATER NEGATIVE WITH RESPECT TO CATHODE		
TOTAL DC AND PEAK	200	VOLTS
HEATER POSITIVE WITH RESPECT TO CATHODE		
DC -	100	VOLTS
TOTAL DC AND PEAK	200	VOLTS
MAXIMUM PLATE VOLTAGE	300	VOLTS
MAXIMUM PLATE DISSIPATION	2.8	WATTS
MAXIMUM GRID #2 VOLTAGE	SEE RATING	CHART
MAXIMUM GRID #2 SUPPLY VOLTAGE	300	VOLTS
MAXIMUM GRID #2 DISSIPATION	0.5	WATT
MAXIMUM POSITIVE GRID #1 VOLTAGE	0	VOLTS
MAXIMUM GRID #3 VOLTAGE	0	VOLTS
MAXIMUM GRID #1 CIRCUIT RESISTANCE:		
CATHODE BIAS	1.0	MEGOHM
FIXED BIAS	0.25	ME GOHM
MAXIMUM DIODE CURRENT FOR CONTINUOUS OPERATION	5.0	MA.
HEATER WARM-UP TIME (APPROX.) B	11.0	SECONDS

## TYPICAL OPERATING CONDITIONS AND CHARACTERISTICS

HEATER VOLTAGE	4.7	VOLTS
HEATER CURRENT	0.6	AMP.
PLATE VOLTAGE	200	VOL TS
GRID #2 VOLTAGE	150	VOLTS
GRID #3 VOLTAGE	0	VOLTS
CATHODE RESISTOR	120	OHMS
PLATE CURRENT	11.5	MA.
GRID #2 CURRENT	2.7	MA.
TRANSCONDUCTANCE	7 000	<b>⊭MH</b> OS
	0.6	MEGOHM
PLATE RESISTANCE (APPROX.)	0.6	MEGOTIM
PLATE RESISTANCE (APPROX.)  GRID #1 VOLTAGE FOR I <sub>b</sub> = 10 \(\mu\text{AMP}\).	-8	VOLTS

BHEATER WARM-UP TIME IS DEFINED AS THE TIME REQUIRED FOR THE VOLTAGE ACROSS THE HEATER TO REACH 80% OF ITS RATED VOLTAGE AFTER APPLYING 4 TIMES RATED HEATER VOLTAGE TO A CIRCUIT CONSISTING OF THE TUBE HEATER IN SERIES WITH A RESISTANCE OF VALUE 3 TIMES THE NOMINAL HEATER OPERATING RESISTANCE.

SINILAR TIPE REFERENCE: Its characteristics are identical to the GANS except for heater ratings and heater warm-up time.

 $<sup>^{</sup> extsf{C}}$  test condition only. Operating conditions must not exceed the design center rating.

